

Wistron CONFIDENTIAL

MODEL NAME : *Diaz UMA*


Project Code: *91.4AR01.001*

PCB NO : *08217-1*

Diaz Intergrate Intel GM Schematics Document
uFCPGA Mobile Merom
Intel Crestline-GM + ICH8M

REV : A00

Diaz Block Diagram of Intel GM



INDEX

Pg#	Description	DNI LIST
01	Cover Page	
02	Schematic Block Diagram	
03	INDEX	
04	Bus connection	
05	SMBUS BLOCK	
06	Power Rail	
07-08	CPU (Merom 、 Penryn)	
09-14	Crestline	
15-18	ICH8M	
19-20	DDRII SO-DIMM(533MHz 、 667MHz)	
21	Clock Generator (CK410M+LP)	
22-27	BLANK PAGE	
28	LVDS CON & Camera & DMIC	
29	RGB CON	
30	HDMI	
31	SATA(HDD & CD_ROM)	
32-34	MEDIA CARD READER / 1394 (R5C833)	
35	PCI-Express Card	
36	MINI CARD -WLAN	
37	MINI CARD -WWAN	
38	MINI CARD -WPAN	
39	EC IT8512E	
40	EC IT8301E	
41	FLASH&RTC&CapBTN&DEBUG	
42	USB PortX2	
43	TOUCH PAD & BT & CIR & LID	
44	SWITCH & LED	
45	EMC4001	
46-49	AUDIO CODEC & AMP	
50	LAN BCM5784MA0KMLG	
51	Magnetics and RJ-45	
52	POWER CONTROL SWITCH	
53	Power Button Board	
54	Power Sequence Logic	
55	XDP	
56	USB PORT , eSATA, FINGER	
57	SIM Board	
58-64	Power circuit	

Pg#	Description	DNI LIST
65	SCREW PAD	
A1	AUDIO_JACK	
A2	USB PORT & eSATA	
C1	CAPBTN	
F1	Fingerprint (AES2810)	
L1	LID Board	
S1	SIM Board	
W1	Wireless Switch Board	

Footprint Definition

Resistor	Footprint is 0402 if there is no description
Capacitor	Footprint is 0402 if there is no description
Ferrite Bead	Footprint is 0603 if there is no description

Layout Note

For all of ESD diode, they should be placed as close as possible to connectors and the signals from connectors should be routed to ESD diodes first. There is no branch or via before diodes

PCI TABLE

PCI DEVICE	IDSEL	REQ#/GNT#	PIRQ
R5C833	PCI_AD17	PCI_REQ1# PCI_GNT1#	PCI_PIRQC# PCI_PIRQD#

PCI Express TABLE

Lane 1	WLAN / Mini Card
Lane 2	WPAN / Mini Card
Lane 3	WWAN / Mini Card
Lane 4	ExpressCard
Lane 5	
Lane 6	LAN BCM5784KMLG

USB TABLE

ICH8-0 (EHCI#1)	User1 (Single port , in USB BD)
ICH8-1 (EHCI#1)	
ICH8-2 (EHCI#1)	User2 (Dual port-bottom , in I/O BD)
ICH8-3 (EHCI#1)	User3 (Dual port-top , in I/O BD)
ICH8-4 (EHCI#1)	Camera
ICH8-5 (EHCI#1)	WWAN / Mini Card
ICH8-6 (EHCI#2)	WPAN / Mini Card
ICH8-7 (EHCI#2)	ExpressCard
ICH8-8 (EHCI#2)	Note : No USB for WLAN
ICH8-9 (EHCI#2)	Finger Printer



Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title

Bus Connection

Size
A3

Document Number


Diaz-UMA


Rev




A00





Date: Tuesday, August 19, 2008

Sheet 4 of 68


















HOST



















ICH8M Internal VR Enable Strap
(Internal VR for VccSusi.05, VccSusi.5 and VccCL1.5)
ICH_INTVRMEN Low = Internal VR Disabled
High = Internal VR Enable(Default)












ICH8M LAN100SLP Strap
(Internal VR for VccLAN1.05 and VccCL1.05)
ICH_LAN100_SLP Low = Internal VR Disabled
High = Internal VR Enable(Default)




31	SATA_TX0	C648	MLCC//+10%	2	1	3900PF/50V	SATA_TX0- C
31	SATA_TX0+	C650	MLCC//+10%	2	1	3900PF/50V	SATA_TX0+ C
31	SATA_TX1	C652	MLCC//+10%	2	1	3900PF/50V	SATA_TX1- C
31	SATA_TX1+	C653	MLCC//+10%	2	1	3900PF/50V	SATA_TX1+ C

Distance between the ICH-8 M and cap on the "P" signal should be identical distance between the ICH-8 M and cap on the "N" signal for same pair.








Please these resistor
closely DIMMA, all
trace length<750 mil.

Please these resistor
closely DIMMB, all
trace length<750 mil.



BLANK PAGE FOR PAGE
NUMBER SAME AS DISCRETE

BLANK PAGE FOR PAGE
NUMBER SAME AS DISCRETE

BLANK PAGE FOR PAGE
NUMBER SAME AS DISCRETE

BLANK PAGE FOR PAGE
NUMBER SAME AS DISCRETE



Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title

BLANK PAGE

Size
A3

Document Number
Diaz-UMA

Rev
A00

Date: Tuesday, August 19, 2008Sheet 25 of 68

BLANK PAGE FOR PAGE
NUMBER SAME AS DISCRETE



Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title

BLANK PAGE

Size
A3

Document Number
Diaz-UMA


Rev
A00

Date: Tuesday, August 19, 2008



Sheet 26 of 68

BLANK PAGE FOR PAGE
NUMBER SAME AS DISCRETE

Setting R,G,B treac impedance to 50 ohm.



In addition to these 150 ohm terminations at the connector, 150 ohm terminations are also required at the Source. Route from source (GPU) at 50 ohm target impedance.




X03


For AFTE test Close to CON6607

AFTE14P-GP	T311	1	RED
AFTE14P-GP	T312	1	GREEN
AFTE14P-GP	T313	1	BLUE
AFTE14P-GP	T314	1	CRT_VCC_R
AFTE14P-GP	T315	1	DAT_DDC2
AFTE14P-GP	T316	1	JVGA_HS
AFTE14P-GP	T317	1	JVGA_VS
AFTE14P-GP	T318	1	CLK_DDC2
AFTE14P-GP	T172	1	M_ID2#
AFTE14P-GP	T173	1	M_ID2#
AFTE14P-GP	T199	1	GND

M08 USE CH501




X03



SiI1392 SDVO TX

LAYOUT RULES:


Route traces with 100 Ohm Differential Impedance
Avoid placing GND Copper or traces adjacent to TMDS Trace
Put these 4 resistors and 4 capacitors as close as possible to the TMDS output pins of the SiI1392




**Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

HDMI SiI 1392		
Size	Document Number	Rev
Custom	Diaz-UMA	A00
Date:	Tuesday, August 19, 2008	Sheet 30 of 68

SATA Connector







ODD Connector



X03.84


NO. 32








Recommended Crystal Specs from Data Sheet:

Normal Frequency : 24.576 Mhz
Frequency Tolerance : +/- 50ppm @ 25C
Driver Level : .1 mW
Load capacitance : 10pF
Equ. Resistance : 50 Ohm Max
Shunt Capacitance : 7.0pF Max




Place as close to R5C832 as possible.


IEEE1394/SD





R5C833_TQFP128
C.S R5C833 TQFP128





Place these components close to the flash memory card connector






For SD/MS Card Power









(20071005)for choke & 0ohm colayout

Express Card





MiniCard WWAN connector

MiniCard Relative Location (TOP VIEW):





CON3005
TOP SIDE
4.0H

CON3001
BOTTOM SIDE
4.0H

WLAN

WWAN


MiniCard * 2 Absolutely Location (TOP VIEW):
Upper / Right side on MB



DELL Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichin,
Taipei Hsien 221, Taiwan, R.O.C.


Title			MINI CARD - Robson	
Size	Document Number	Rev		
A3		Diaz-UMA		A00
Date:	Tuesday, August 19, 2008	Sheet	37	of 68

MiniCard WPAN connector




62.10043.441

MiniCard Relative Location (TOP VIEW):

















MiniCard * 2 Absolutely Location (TOP VIEW):
Upper / Right side on MB





DELL Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichin,
Taipei Hsien 221, Taiwan, R.O.C.

Title			MINI CARD - Robson	
Size	Document Number	Rev		
A3		Diaz-UMA		A00
Date:	Tuesday, August 19, 2008	Sheet	38	of 68






X03 For AFTE test Close to CON6616




CAPBTN CON.

Note:
+5V_ALW2 => for Capbutton PSOC and Media direct LED only.
+5V_RUN => for Capbutton LED and Photo sensor.


DEBUG



External USB PORT hookup reference. Your design may need more or less external ports and may be mapped differently .




Platforms should put in PADS for the USB chokes if they have the room. Chokes should be NOPOP.



Place ESD diodes as close as USB connector. Semtech SRV05-4 can also be used but the Philips IP42220CZ6 have a lower input C (1pf vs 3pf).


Place one 150uF cap by each USB connector



Each channel is 1A


Consult you ESD Engineer if you think you may need to add ESD Supression Components to your USB lines. Add PADS ONLY until proven diodes are really needed.


X03




For AFTE test Close to CON6610

Right Side








Touch Pad




CIR





HALL SENSOR




Power&Suspend





Sniffer LED driver circuit



Battery status




WLAN activity LED




Layout Note: C pad is used as a Provision For External Power Cycling, Must place C on top to be accessed when Keyboard is removed.

Wireless ON/OFF Connector



Hall Switch



DELL Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.

SWITCH & LED			
Title	Custom	Document Number	Rev
Date: Tuesday, August 19, 2008	Diaz-UMA	Sheet 44 of 68	A00

Pin 1
Pin 3
MLX_53398-0371

FAN CONN

For AFTE test Close to CON11

X03

Put C283 close to Guardian.

Guardian

Note:
150K input impedance on VCP1 (Pin 43)

Layout Note:
R4747 is put on BOT DIMM socket


+3.3V_SUS

Layout Note:
Place those capacitors close to EMC4001.


DELL Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title			EMC4001		
Size	Document Number	Rev			
Custom	Diaz-UMA	A00			
Date:	Tuesday, August 19, 2008	Sheet	45	of	68

Signal Inverter for Speaker Shutdown
Allow speakers to work while class driver is installed



**PLACE JUST BEFORE
+5V_MAX9789 CROSSES
MOAT**




Place C490 close
to Pin 30




NOTE: For TPA6040A, pop C487 and C486 (8492 X5R) and no pop R601 and R376. C487 and C486 value should match C494 and C493

TEMPORARY VALUES. FINAL
VALUES CHOSEN IN PT
PHASE.

NOTE: For TPA6040A,
pop C486 and no pop
R376



GAIN SETTING RESISTORS




Gain1	Gain2	Gain
0	0	6 dB
0	1	10 dB
1	0	15.6 dB
1	1	21.6 dB

ROUTE VIA TRACE BACK TO TIE POINT.

ROUTE VIA TRACE BACK TO TIE POINT.

ROUTE VIA TRACE BACK TO TIE POINT.




VDDA Range = 1.21V ~ 4.85V (SET = 1.23V).
If SET=0 V, VDDA = 4.75V




Maxim:1.8V ~ 3.6V
TI:1.8V ~ 4.5V

NOTE: MAKE SURE THERMAL PAD
(Pin21)UNDER MAX4411 IS NOT
CONNECTED TO GND



If AUD_EAPD# not be used,
pop R6932 and depop R6931.



For AFTE test Close to CON07



For AFTE test Close to CON4801



DELL Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipet Hsien 221, Taiwan, R.O.C.

1

1

2

2

3


3

4

4


5

5



		Wistron Corporation 21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.	
Title AUDIO BtoB CON			
Size A4	Document Number Diaz-UMA		Rev A00
Date: Tuesday, August 19, 2008		Sheet 49 of	68

Co-Layout BCM5787M & 5784M
Layout 5784M priority
Frist S.R BOM is 5784M





This BOM is 5784M

require S3 support wake on LAN 2007/10/05

NO.29

RJ45 should be 12G14801110KDE

EMI solution place near con10




+3.3V_LAN Source Guideline:



1. Use +3.3V_SUS if Wake-on-LAN is NOT required out of S4, S5
2. Use +3.3V_SRC if Wake-on_LAN is required out of S4, S5








VDDCIO_12_VAUX_25 MURATA/BLM18AG601SN1 600Ohm


5787M L29=bead
5784M L29=DNS
2007/10/15



NO.29










X03

For AFTE test Close to CON5301





FINGER PRINTER




X03

For AFTE test Close to CON1






X03 For AFTE test Close to CON6615



 Wistron Corporation 21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.		Title	
		SIM CARD	
Size A4	Document Number Diaz-UMA		Rev A00
Date: Tuesday, August 19, 2008		Sheet 57 of 68	


1.5Volt +/- 5%
Design Current : 2.968A
Maximum current : 4.240A
OCp point Min :5.308A(Imax*1.25)

+1.5V_RUN




54 1.5V_RUN_PWRGD << +1.5V_PG1

54 1.05V_RUN_PWRGD << +1.05V_PG2



1.05Volt +/- 5%
Design Current : 6.9307A
Maximum current : 9.901A
OCp point Min : 12.277A(Imax*1.24)

+1.05V_VCCP




DELL Wistron Corporation
 21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
 Taipei Hsien 221, Taiwan, R.O.C.

Title		POWER_I/O_1.5VS & 1.05VS	
Size	Custom	Document Number	Rev
Diaz-UMA		A00	
Date:	Tuesday, August 19, 2008	Sheet	60 of 68


1.25Volt +/- 5%
Design Current : 1.729A
Maximum current : 2.470A
OCp point Min : 3.063A(I_{max}*1.24)

+1.25V_RUN




1.8Volt +/- 5%
Design Current : 9.170A
Maximum current : 13.100A
OCp point Min : 16.349A(I_{max}*1.248)


+1.8V_SUS




0.9Volt +/- 5%
Design Current : 1.05A
Maximum current : 1.5A
OCp point Min : 3.8A
+0.9V_DDR_VTT



For debug



For power debug



BLANK PAGE FOR PAGE
NUMBER SAME AS DISCRETE

		Wistron Corporation 21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.	
Title			
BLANK PAGE			
Size	Document Number		Rev
A3	Diaz-UMA		A00
Date:	Tuesday, August 19, 2008		Sheet 62 of 68

TOTAL POWER=65W
-->3.33A (Vin=19.5V)

TABLE3 PIN NAME DIFFERENCES		
PIN	MAXIM	INTERSIL
1	GND	NC
3	REF	VREF
4	CCS	ICOMP
5	CCI	NC
6	CCV	VCOMP
7	DAC	NC
8	IINP	ICM
11	VDD	VDDSMB
14	BATSEL	NC
15	FBSA	VFB
16	FBSB	NC
17	CSIN	CSON
18	CSIP	CSOP
20	DLO	LGATE
21	LDO	VDDP
23	LX	PHASE
24	DHI	UGATE
25	BST	BOOT

"NC" means no-connect

Charge Current : 4.68A
Discharge current : 6.6A

TABLE2 MAXIM & INTERSIL BOM DIFFERENCES		
REF DES	MAXIM	INTERSIL
PR6306	8.45K, 0402, 1%	16.0K, 0402, 1%
PC6323	0.01uF	No Stuff
PC6304	0.1uF, 0402, 10V	No Stuff
PC6300	1.0uF, 0603, 10V	No Stuff
PR6329	365K, 0402, 1%	215K, 0402, 1%
PR6319	0, 0402, 5%	10, 0402, 5%
PR6328	0, 0402, 5%	10, 0402, 5%
PC6305	No Stuff	0.22uF
PC6313	No Stuff	0.22uF
PC6314	0.01uF	No Stuff
PC6322	0.1uF, 0402, 10V	No Stuff
PC6327	220pF, 0402, 50V	No Stuff
PD6301	RB751V-40	No Stuff
PC6317	3.3nF	No Stuff
PR6315	1, 0603, 1%	0, 0603, 5%
PR6321	100, 0402, 5%	0, 0402, 5%
PR6318	10K, 0402, 5%	4.7K, 0402, 5%
PC6308	0.01uF	0.01uF
PC6315	0.01uF	0.01uF
PD6300	1SS355	No stuff
PR6325	1K, 0603, 5%	No stuff


TABLE1				
ADAPTOR (W)	TRIP CURRENT (A)	PR6317	PR6305	PR6326
65	3.17	57.6K	13.0K	N/A
90	4.43	51.1K	17.8K	348
130	6.43	32.4K	20.5K	100
150	7.43	30.9K	24.9K	432
200	9.75	19.1K	28K	301
230	11.28	32.4K	6.49K	115









Note 1: PR6326 is populated if ADAPT_TRIP_SET is used to program for the next lower adaptor. ADAPT_TRIP_SET is floating for the higher adaptor, grounded for the lower adaptor.

Note 2: 24.9K at PR6326 allows the 65W adaptor setting to switch down to 45W. (now is 33.2K for 90W)

Note 3: PR6392 must be 5m ohm instead of 10m ohm for the 230W adaptor

	BATT+ IN	1	T180	AFTE14P-GP
Z4304	SMB CLK	1	T181	AFTE14P-GP
Z4305	SMB DAT	1	T182	AFTE14P-GP
Z4306	BATT PRES#	1	T183	AFTE14P-GP
	SYSPRES#	1	T184	AFTE14P-GP
	BATT VOLT1	1	T185	AFTE14P-GP
	BATT1	1	T186	AFTE14P-GP
	BATT2	1	T187	AFTE14P-GP









[X01] S03353

[X01] S01758

[X01] S03354



Version Change list for EE Circuit

Item	Page	Title	Date	Request Owner	Issue Description	Solution Description	Rev.
1	all	X00 release	10/24/2007		X00 release		X00
2	44	Switch power pull	11/30/2007	AA EE	Change main power switch and sniffer power switch power plane to +3.3V_RTC_LD0	Change +RTC_SELL to +3.3V_RTC_LD0	X01
3	30	HDMI power	11/30/2007	AA EE	Modify power diode to MOSFET for leakage current that can lower forward voltage and match HDMI 5V voltage range	Replace D4612 by Q19 and connect Q19 gate to RUN_ENABLE	X01
4	51	LAN LED	11/30/2007	AA EE	Changed LAN Jack (CON10) pin12 to +3.3V_LAN	Changed LAN Jack (CON10) pin12 to +3.3V_LAN	X01
5	35	Express Card power switch	11/30/2007	AA EE	Express Card power switch (U13) pin4 should be connected to +3.3V_RUN for the purpose of using RICOH/R5538 as 2nd source	Connect U13 pin4 to +3.3V_RUN	X01
6	18	ICH8	11/30/2007	AA EE	ICH8 pin AD11 VCCSUSDA modify to +3.3V_ALW for +3.3V_RUN to solve S5 leakage issue	Connect ICH8 pin AD11 to +3.3V_ALW	X01
7	A1,A2	Audio Board	11/30/2007	AA EE	1.AH1change to NPTH;2.ACON5 change to 12G142001113DE; 3.AU3 pin1 rename to USBP0_D+_U;4.AU3 pin3 rename to USBP0_D-_U	1.AH1change to NPTH;2.ACON5 change to 12G142001113DE; 3.AU3 pin1 rename to USBP0_D+_U;4.AU3 pin3 rename to USBP0_D-_U	X01
8	15,44	LED mask circuit	12/05/2007	AA EE	1.Delete sniffer LED mask circuit 2.modify SATA and WPAN LED circuit.	1.Delete R246,R247,Q43 2.modify SATA and WPAN LED circuit	X01
9	17	CLK_ICH_48M	12/06/2007	AA EE	To improve 48MHz clock signal integrity , pop R339, change C456 to 10pF from 4.7pF and make it stuff.	Pop R339, change C456 to 10pF from 4.7pF and make it stuff.	X01
10	29	CRT signals	12/06/2007	AA EE	Fine tune CRT signals	change C6649-C6654 to 10pF.	X01
11	65	Screw Hole	12/06/2007	AA EE	Added screw hole by NB thermal solution & ME request	Added H32, changed H24	X01
12	16,35, 50	Reset signals	12/06/2007	AA EE	To improve RESET signals integrity	1. Audio: ICH_AZ_C0DEC_RST#, R270=100 ohm 2. HDMI: ICH_AZ_HDMI_RST#, R205=100ohm 3. RICOH: PCI_RST#, R1601=100 ohm, add C6663=10pF 4. WLAN: PLTRST#, add C696=22pF 5. WWAN: PLTRST#, add C697=22pF 6. EC: PLTRST#, add R6972=220ohm	X01
13	28	+LVBVCC	12/06/2007	AA EE	Fine tune LVDS power sequence fl time	Change R17 to 470K ohm from 330K ohm	X01
14	21	PCI Clock	12/10/2007	AA EE	Fine tune PCI clock slew rate by EA	Swap net name: CLK_PCI_PCCARD & CLK_PCI_8512	X01
15	39	EC power	12/10/2007	AA EE	update EC pin12 net by vender request changed list for batter quality.	Added C3901=0.1uF, C3902=1uF, R3907=0 ohm	X01
16	21,28, 40	EMI component	12/10/2007	AA EE	modify compoment by EMI Comm Team request.	P21: add C2107, C115, C159, C172, C194 P28: add C7110-7111, C7113, C7112 (33pF), C7114(33pF) P28: remove R2804A/B, add L1 P40: add CN21, CN22, CN23, CN24, CN25, CN26, CN28	X01
17	40	Platform ID	12/10/2007	AA EE	add platform indicator circuit	add R4025-28, net name: PLATFORM_ID[0:1]	X01
18	54	Power Sequence	12/10/2007	AA EE	Flow power circuit.	Remove R73 & net name: 1.25V_RUN_PWRGD	X01
19	40,43	Connector	12/10/2007	AA EE	Changed Connector by ME request.	page 40 -> change CON4010 page 43 -> change CON3	X01
20	C1	CAPBTN I2C	12/12/2007	AA EE	Fine tune CAPBTN I2C timing.	1.Change I2C damping R (CBT_R795) from 330ohm to 100ohm 2.Add through holes CBT_H15(s01291) & CBT_H28(s03350)	X01
21	F1	FingerPrinter LDO	12/12/2007	AA EE	Fine tune LDO performance.	1.F_U3, Pin3(CE pin) connects with Pin1(Vin) 2.F_U3, Pin4(ECO pin) connects with Pin1(Vin)	X01
22	S1	SIM Screw Hole	12/12/2007	AA EE	ME update DXF	change screw hole SH2 & SH3 & SC0N1	
23	28	Digital MIC	12/13/2007	AA EE	DMIC clock EMI solution modify	1.R2802 change to 80ohm bead(follow Lanai P/N) 2.R2803 change to 47ohm 3.Mount C748 (33P)	
24	A2	Audio Board	12/14/2007	AA EE	Update eSATA connector for USB function only.	changed ACON5 = 12G142001115DE	
25	39	IT8512E	12/15/2007	AA EE	Del C3921 (IT8512E I version pop 0ohm, J version pop 0.1uF)	Del C3921	
26	40	Platform ID	12/15/2007	AA EE	Del R4025,R4027 to force PCB platform type (Intel SR)	Del R4025,R4027	
27	21,33, 39,50	XTAL	12/15/2007	AA EE	Change XTAL for better capability	(1) X4 24.576MHz change to 076010222452DE,C453 change to 22pF,C454 change to 22pF (2) X1 25MHz change to 076010222509DE, C47,C55 change to 33pF (3) X2 14.318MHz change to 07601021143CDE , (4) X5 32.768KHz change to 07601020327ADE, change C667,C654 to 15pF	
28	46-48	Audio	12/18/2007	AA EE	Modify Audio BOM	1.Unmount R4602 2.Mount R4601,Q123,R6958 3.Delete R6964,R6965,R6960,R6961,R6970,R6962,R6963,R6971 4.Add R4701,R4702,R4703,R4704,C4701,C4702	
29	50-51	LAN	12/18/2007	AA EE	Modify schematic for triple LED control & EMI solution	1.Add R5110-R5114,D5101; del T5004, add LINK_LED100# 2.Add C5110-C5117	
30	45,47	Test Point	12/18/2007	AA EE	Add test point for factory ICT team request	Add T33 in U19.23 & T34 in U8.26	
31	41	SPI Flash	12/18/2007	AA EE	Remove SPI Flash dypm RES.	Remove R310, R316, R317, R4102	

DELL		Wistron Corporation	
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.			
File			
Change list (1)			
Size	Document Number	Rev	
Custom	Diaz-UMA	A00	
Date:	Tuesday, August 19, 2008	Sheet	66 of 68

Version Change List for EE Circuit

Item	Page	Title	Date	Request Owner	Issue Description	Solution Description	Rev.
32	31	HDD/ODD Power	2007/12/18	AA EE	Modify HDD/ODD power circuit by customer request	1.unmount JP4, R3101 2.POP BOM: R5, R7, R399, R400, C13, Q2, Q3, Q56	X01
33	49, A1 A2	USB charged	2007/12/19	AA EE	Remove USB charged circuit by customer request	1.Delete AU2 2.rename USBP0_D-_U & USBP0_D+_U to USBP0_D- & USBP0_D+ 3.connect CON9, ACON1 pin36 to DGND, pin29 NC.	X01
34	39, 41 45, 50	Test Point	2007/12/19	AA EE	Add test point by ICT factory request	1.Add T151, T152, T159, T166, T178, T179 for U27 signal pin 2.Add T222, T219, T220, T221 for U2 signal pin 3.Add T148 at U15 pin14, T150 at U8 pin3	X01
35	A2	Audio Board	2007/12/20	AA EE	Modify USB differential signals.	1.Delete AL7 2.rename USBP0_D+ & USBP0_D- to AICH_USBP0+3 & AICH_USBP0-	X01
36	44	WPAN LED	2007/12/21	AA EE	Pop BOM for WPAN LED support	POP BOM: R4411(100K Ohm)	X01
37	65	Screw Hole	2007/12/25	AA EE	add screw hole for IR Blockade	Add: H32, H33	X01
38	C1	CAPBTN	2007/12/25	AA EE	update CAPBTN Circuit by customer ID modified	Swap net SNS_REWIND & SNS_PLAY, LED_REWIND# & LED_PLAY#	X01
39	F1	FingerPrint Screw	2007/12/25	AA EE	Screw hole (NPTH) modified the internal diameter to 1.7mm and the external diameter to 3mm	Modify F_H1, F_H2	X01
40	17	WPAN CTRL	2007/12/26	AA EE	Modify WPAN detect signals by different WLAN module support.	changed net USB_WPAN_DET# to R1701 & pull up to +3.3V_RUN	X01
41	13, 38	Cost Down Plan	2007/12/27	AA EE	Cost Down Plan	CE1303, CE1301 => Change to POSCAP 220U/4V De-pop => C602, C589, C590, C1302, C1312, CE7 C363 => Change 10uF/10V Y5V C1309 => Pop 0.1uF R1301 => Change to 0 ohm De-pop => CE16	X01
42	30, 42	Connector	2007/12/28	AA EE	By ME connector changed list	Changed CON6610 = 12G13141108ADE Changed CON6608 = 12G24110193RDE	X01
43	40	Board ID	2008/02/14	AA EE	Changed pcb id to X02	Changed pcb id to X02	X02
44	15	XTAL	2008/02/14	AA EE	Modify C375, C377 per XTAL report	Change C375, C377 to 3.3pF	X02
45	16	ICH8 reset signal	2008/02/14	AA EE	U14, U30, U37: power modify to +3.3V_ALW from +3.3V_RUN	U14, U30, U37: power modify to +3.3V_ALW from +3.3V_RUN	X02
46	41, C1	CapBTN	2008/02/14	AA EE	Add CapBTN IC reset signal	1. Add CBT_RESET pin, add two jumpers on the CapBtn board. 2. Sense pad modify to elliptic through hole 3. Add a reserved 10uF capacitor parallel to +5V_ALW2 on the CapBtn board	X02
47	30, 37	Comm. team solution	2008/02/14	AA Comm. Team	Add comm. team solutions	1.Pop L4606, depop RN3701 by comm. Team request 2.CMIU: Add C3051 39PF close to C6925	X02
48	47, A1	Audio	2008/02/14	AA EE	Modify ACON2, ACON3, ACON4 footprint. Change value of C492, C496 to improve AP performance	1.ACON4 PCB footprint change to pt_phone_j_6p_4hd_col_lf 2.ACON3, ACON2 footprint change to pt_phone_j_6p_4h_col_lf 3.C492 and C496 Bom change to 2.2U(116236122511310DE) from 1uF	X02
49	21	Clock	2008/02/18	AA EE	Delete reserved resistors	Delete RN1, RN2, RN3, RN5, RN6, RN7, RN8, RN9, RN10, RN11	X02
50	65	Nut	2008/02/18	AA ME	Swap PN of H23, H24 base on updated DXF	Swap PN of H23, H24	X02
51	C1	CAPBTN	2008/02/19	AA EE	LED Mute/V0/VU of power rail update	LED Mute/V0/VU are connect to +5V_ALW2 power rail	X02
52	39	EC	2008/02/19	AA EE	Support CAPBTN reset signals.	modify net_name U15.I09: CAP_EC_RESET, Delete: T3907	X02
53	F1	Finger Print	2008/02/19	AA EE	update F_X1 footprint	update F_X1 footprint: modify pin1 indication	X02
54	C1	CAPBTN	2008/02/19	AA EE	Modify level shift circuit & Hole	1.Add elliptic through holes for BT, WiFi, and HDD LEDs 2.Change CBT_C1 to PT footprint	X02
55	39	EC	2008/02/19	AA EE	Modify Chlp version.	update Chip version: 060042005012DE, option R3920, mount C3920	X02
56	47	Speaker gain	2008/02/21	AA EE	Fine tune gain	1.Unmount R374, R377 and Mount R379, R368 2.R4701, R4703 change 24.3Kohm and R4702, R4704 mount 100Kohm	X02
57	F1	Finger Print	2008/02/22	AA EE	Add Test Point by Factory Request	Add F_T14 Test Point	X02
58	46	Audio	2008/02/22	AA EE	Modify Audio solve pop issue	Modify Audio Circuit	X02
59	44	Switch LED	2008/02/25	AA EE	Modify LED color by customer request	LED1 changed to 07G015200975DE, WHITE&ORANGE	X02
60	60, 61	POWER	2008/05/7	W EE	PL6001 12.4A change to 17A ; PL6101 14.3A change to 17A; Add PC6001(1u/10V)	Modify power Circuit	X02
61	58	POWER	2008/05/7	W EE	PR5817 change location to PR5837(4.7K 0805); PC5824 change location to PC5834(1000PF/50V); PR5821 change location to PR5849(4.7K 0805); PC5834 change location to PR5835(1000PF/50V);	Modify power Circuit	X02
62	61	POWER	2008/05/7	W EE	PU6101 Pin6, PIN7 swap	Modify power Circuit	X02
63	60	POWER	2008/05/7	W EE	PQ6004(SI4430BDY) change location to PQ6000 (SI4336DY) add PR6016(DY)0R 0805; PC6025(DY) 1000PF/50V;	Modify power Circuit	X02
64	60	POWER	2008/05/7	W EE	POP PC182, POP PC186; PC58 change to 3900pF	Modify power SW Circuit	X02
65	61	POWER	2008/05/7	W EE	POP PR6330(0R), POP PR6332(0R), POP PR6318(10K), POP PR6333(0R), PR6331(0R)	Modify power Circuit	X02
66		POWER	2008/05/7	W EE	D21 GM M7B Close GAP (J2, J3, PJP5800, PJP5801, PJP5900, PJP5901, PJP5902, PJP5903, PJP6000, PJP6001, PJP6002, PJP6003, PJP6100, PJP6101, PJP6102, PJP6103, PJP6104, PJP6105, PJP6200, PJP6201, PJP6202, PJP6203, PP6300) D21 GM CAPBTN Board Close GAP(CBT_JP1, CBT_JP2) D21 GM Audio Board Close GAP(AJ1)	Close power GAP	X02
67	29	CRT	2008/05/16	W EE	Q2901, Q2902 "BSS138N" change to "2N7002"	change part X02	X02



Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

File

Change list (2)

Size

Document Number

Rev

Custom

Diaz-UMA

A00

Date: Tuesday, August 19, 2008

Sheet 67 of 68

Version Change list for EE Circuit

Item	Page	Title	Date	Request Owner	Issue Description	Solution Description	Rev.
68	60, 61	POWER	2008/06/30	W EE	PR6004 change to 7.87Kohm;PR6100 change to 249Kohm;PR6116 change to 5.1Kohm	change part	X03
69	40	Board ID	2008/06/30	W EE	Board ID change to X03=> R534"Dummy";POP "R535"	change PCB ID	X03
70	L1	Lid Board	2008/06/30	W EE	Lid Board: add HALL1 connect" 20.F0866.003"	change part	X03
71	A2	Audio Board	2008/06/30	W EE	Audio Board :ACON5 change to " PN:12G142001115DE" waiting wistron P/N	change part	X03
72	66-74	I/O Board	2008/07/04	W EE	I/O board schematic remove	Independence I/O board schematic for layout ME issue	X03
73	65	For EMI	2008/07/04	W EMI	For EMI :+CPU_PWR_SRC add EC816,EC815,EC817 0.1u/50V EMI CAP	EMI solution	X03
74	65	For EMI	2008/07/04	W EMI	For EMI :+DCIN_JACK add EC813 0.1u/50V EMI CAP	EMI solution	X03
75	65	For EMI	2008/07/04	W EMI	For EMI :+DC_IN_SS add EC811,EC812 0.1u/50V EMI CAP	EMI solution	X03
76	65	For EMI	2008/07/04	W EMI	For EMI :+PWR_SRC add EC814 0.1u/50V EMI CAP	EMI solution	X03
77	37	SIM CARD	2008/07/04	W EE	For SI : UIM_CLK add R6634 0R	For SI	X03
78	65	HOLD	2008/07/07	W ME	Cost down remove H23	remove part	X03
79		For ATE	2008/07/07	W ME	all test point change to "ZZ.PAD14.001" page 7 test point T31,42 change to "ZZ.PAD14.001" page 10 test point T127,T27,T29,T28,T126,T18,T19,T21,T25,T23,T35,T37,T40,T38,T39,T36,T20,T24,T22,T26,T41,T137,T32,T135,T128,T130,T131,T30,T1002,T1001 page 11 test point T134,T136 page 15 test point T92,T91,T93,T84,T85,T80,T90,T143,T54,T96,T71,T82,T53 page 16 test point T74,T175,T77,T89,T214,T95 page 17 test point T45,T74,T56,T139,T158,T157,T177,T176,T210,T144,T156,T49,T147,T146,T48,T47,T140,T141,T46 page 18 test point T61,T67,T70,T72,T52,T51,T73 page 32 test point T55 page 33 test point T153 page 36 test point T160,T161,T162,T163,T164,T165 page 37 test point T168,T169,T170 page 38 test point T167 page 39 test point T148,T390,T3902,T3905,T3906,T3907,T3909,T3910,T3903,T3904 page 40 test point T4001,T4005 page 41 test point T178,T179,T159,T166,T151,T152,T154 page 45 test point T33,T17,T16,T150,T13 page 50 test point T222,T229,T220,T221,T5002,T5003 page 55 test point T118,T122,T119,T125,T117,T121,T120,T124,T116,T123,T115,T113,T112,T114,T142,T149	New ATE test point change to 14 mils	X03
80		For AFTE	2008/07/07	W ME	Add AFTE test point "ZZ.AFT14.101" Page29 add AFTE test point T311,T312,T313,T314,T315,T316,T317,T318,T171,T172 Page 40 add AFTE test point T500-T529 "ZZ.AFT14.101" for Con5&CON4010 Page 42 add AFTE test point T356-T361 "ZZ.AFT14.101" for Con6610 Page 43 add AFTE test point T347,T348,T349,T350 "ZZ.AFT14.101" for Con663 Page 43 add AFTE test point T351,T352,T353 "ZZ.AFT14.101" for Con6617 Page 44 add AFTE test point T345-T346 "ZZ.AFT14.101" for Con6614 Page 45 add AFTE test point T341,T342,T343 "ZZ.AFT14.101" for Con11 Page 48 add AFTE test point T328,T329,T336 "ZZ.AFT14.101" for Con4801 Page 48 add AFTE test point T337,T338,T339,T340 change to "ZZ.AFT14.101" for Con7 Page 48 add AFTE test point T331,T330,T332,T333,T335,T334 "ZZ.AFT14.101" for Con5301 Page 56 add AFTE test point T320,T321,T322,T323 "ZZ.AFT14.101" for Con1 Page 57 add AFTE test point T188,T189,T190,T191,T192,T193 "ZZ.AFT14.101" for Con6615 Page 64 add AFTE test point T180-T187 "ZZ.AFT14.101" for PCon6400	New AFTE test point change to 14 mils	X03
81	18	Board ID	2008/07/07	W ME	Page 18 L49 change to "68.1R090.10A" ;	change bead dimension	X03
82	29	For ME	2008/07/07	W ME	page 29 connect change to wistron P/N "20.20768.015"	ME modify PCB root pin	X03
83	29	For SI	2008/07/07	W ME	Page29 L4909,L4910,L4911 CHANGE TO "68.00143.111" BLM18BA220SN1D-0P L4610,L4611 change to "63.R0033.L03" 0R DUMMY C6649,C6650,C6651;C6652;C6653;C6654	For SI issue	X03
84	31	For EE	2008/07/07	W ME	Page 31 remove J4 power GAP	Separate HDD and ODD power plane	X03
85	40	Board ID	2008/07/07	W ME	page 40 add R538(DY),R539(DY) connect to U29 Pin43 "BIB2" for next stage board ID	For board ID	X03
86	65	For ME	2008/07/07	W ME	PAGE 65 REMOVE H33,H34	IR trace issue	X03
87	15	For SI	2008/07/07	W ME	page 15 change R275 to 47R"64.47R05.6DL" for ICH_A2 CODEC_SDOUT;	For SI issue	X03
88	39	For SI	2008/07/08	W ME	R308,R308 change to 4.7K R	For SI issue	X03
89	65	For ME	2008/08/01	W ME	Page 65 H33,H34,H35 for IR Hold	IR HOLD change	A00
90	33	For SI	2008/08/01	W EE	Page 33 R545 change to 33R	For R5C833 SI Singel	A00
91	30	For SI	2008/08/01	W EE	Page 30 R3002 change to 820R	for HDMI singel	A00
92	52	For Boot	2008/08/01	W EE	Page 52 PC192 change to 0.1u	Drop	A00
93	40	For KB detect	2008/08/01	W EE	Page 40 add R106 10K and R158 20K for LED_BL_DET	add KB B/L Detect	A00
94	40	For Board ID	2008/08/01	W EE	Page 40 remove BID2 change Board_VER to 00	Board change	A00
95	54	For Boot	2008/08/01	W EE	Page 54 add R417 1KR RESET_OUT# to GND	for Boot	A00
96	16, 21 37, 57	Remove WWAN	2008/08/01	W EE	WWAN remove Page 16 DY R356 ,RP4 connect SB_WWAN_PCIE_RST# to 3.3V_RUN Page 16 DY C443,C439 for WWAN remove Page 21 DY R2118,R66 Page 37 DY CON6605,C6644,C6645,C6646,C6647,C6648,C6636,C6637,C6638,C6639,C6640,C6641,C6642,C6643,CE17,CE18 Page 57 DY CON6615	Remove WWAN	A00
97	13, 36	For Layout	2008/08/01	W EE	Page 36 Remove J3,Page 13 remove J4	Remove J3 modify for Layout	

**Wistron Corporation**
-21F, 80, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

File

Change list (3)

Size

Document Number

Rev

Custom

Diaz-UMA

A00

Date: Tuesday, August 19, 2008

Sheet 68 of 68