


**E450**


# Sandy Bridge Mobile PROCESSOR With Cougar Point-M

**June 2010**  
**Revision 0.2**



|                                                                                                 |  |                               |                          |
|-------------------------------------------------------------------------------------------------|--|-------------------------------|--------------------------|
|  <b>神舟</b> |  | <b>HASEE TECHNOLOGY INC.,</b> |                          |
| <b>Cover Page</b>                                                                               |  |                               |                          |
| Draw by<br>LIZX                                                                                 |  | Size<br>B                     | CAGE Code<br><Cage Code> |
| Thursday, May 22, 2014                                                                          |  | Scale                         | Model<br><b>E450</b>     |
|                                                                                                 |  | DWG NO                        | Rev<br>0.2               |
|                                                                                                 |  | Sheet<br>1                    | of 50                    |








|                                                                                                 |           |                               |                  |
|-------------------------------------------------------------------------------------------------|-----------|-------------------------------|------------------|
|  <b>神舟</b> |           | <b>HASEE TECHNOLOGY INC.,</b> |                  |
| <b>Block Diagram</b>                                                                            |           |                               |                  |
| Draw by<br>Thursday, May 22, 2014                                                               | Size<br>B | CAGE Code<br><Cage Code>      | DWG NO<br>E450   |
| Scale                                                                                           |           | Model<br>E450                 | Sheet<br>2 of 50 |



|                                                                                                 |        |                               |               |
|-------------------------------------------------------------------------------------------------|--------|-------------------------------|---------------|
|  <b>神舟</b> |        | <b>HASEE TECHNOLOGY INC.,</b> |               |
|                                                                                                 |        | <b>SANDYBRIDGE 1/7</b>        |               |
| Draw by                                                                                         | Size B | CAGE Code<br><Cage Code>      | DWG NO        |
| Thursday, May 22, 2014                                                                          | Scale  | Model <b>E450</b>             | Sheet 3 of 50 |



For platforms that do not implement the S3 Power Reduction circuitry:  
R25--->No stuff R23--->Stuff  
R26--->No stuff Q40--->No stuff Q65--->No stuff





**神舟**


HASEE


**HASEE TECHNOLOGY INC.,**



**SANDYBRIDGE 217**

|                        |                |                          |            |            |
|------------------------|----------------|--------------------------|------------|------------|
| Draw by<br>LIZX        | Size<br>Custom | CAGE Code<br><Cage Code> | DWG NO     | Rev<br>0.2 |
| Thursday, May 22, 2014 | Scale          | Model<br>E450            | Sheet<br>4 | of 50      |










|                                                                                       |        |                               |         |
|---------------------------------------------------------------------------------------|--------|-------------------------------|---------|
|  |        | <b>HASEE TECHNOLOGY INC.,</b> |         |
|                                                                                       |        | <b>SANDYBRIDGE 6/7</b>        |         |
| Draw by                                                                               | Size   | CAGE Code                     | DWG NO  |
|                                                                                       | Custom | <Cage Code>                   |         |
| Thursday, May 22, 2014                                                                | Scale  | Model                         | Sheet   |
|                                                                                       |        | <b>E450</b>                   | 8 of 50 |
|                                                                                       |        | Rev 0.2                       |         |





| PEG Static Lane Reversal - CFG2 is for the 16x |                                                                                                        |
|------------------------------------------------|--------------------------------------------------------------------------------------------------------|
| CFG2                                           | 1: (Default) Normal Operation; Lane # definition matches socket pin map definition<br>0: Lane Reversed |

| PCIe Port Bifurcation Straps |                                                                                                                                                                                                                                                      |
|------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| CFG[6:5]                     | 11: (Default) x16 - Device 1 functions 1 and 2 disabled<br>10: x8, x8 - Device 1 function 1 enabled ; function 2 disabled<br>01: Reserved - (Device 1 function 1 disabled ; function 2 enabled)<br>00: x8,x4,x4 - Device 1 functions 1 and 2 enabled |

| Display Port Presence Strap(EDP) |                                                                                                                                                                            |
|----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| CFG4                             | 1: (Default) Disabled; No Physical Display Port attached to Embedded Display Port<br>0: Enabled; An external Display Port device is connected to the Embedded Display Port |

| PEG DEFER TRAINING |                                                                                                         |
|--------------------|---------------------------------------------------------------------------------------------------------|
| CFG7               | 1: (Default) PEG Train immediately following xxRESETB de assertion<br>0: PEG Wait for BIOS for training |



神舟

HASEE





HASEE TECHNOLOGY INC.,

SANDYBRIDGE 7/7

|                        |        |                       |               |         |
|------------------------|--------|-----------------------|---------------|---------|
| Draw by                | Size B | CAGE Code <Cage Code> | DWG NO        | Rev 0.2 |
| Thursday, May 22, 2014 | Scale  | Model E450            | Sheet 9 of 50 |         |


D88131-001

15,23,48 SMB\_CLK\_S R209 0 SODIMMO 1 SMB\_CLK R  
15,23,48 SMB\_DATA\_S R210 0 SODIMMO 1 SMB\_DATA R





### DIMM 0

|                        |                |                          |                   |            |
|------------------------|----------------|--------------------------|-------------------|------------|
| Draw by                | Size<br>Custom | CAGE Code<br><Cage Code> | DWG NO            | Rev<br>0.2 |
| Thursday, May 22, 2014 | Scale          | Model<br><b>E450</b>     | Sheet<br>10 of 50 |            |

[illegible][illegible][illegible][illegible]









|            |          |
|------------|----------|
| CMOS SET   | RTC_RST# |
| Clear Cmos | GND      |
| KEEP CMOS  | OPEN     |

|                                             |
|---------------------------------------------|
| INTVRMEN-Integrated SUS<br>1.05V VRM Enable |
| High - Enable Internal VRs                  |



|                                           |                                                              |
|-------------------------------------------|--------------------------------------------------------------|
| R251 - Flash Descriptor Security Override |                                                              |
| HDA_SDOUT                                 | Low = Disabled (NoStuff) - Default<br>High = Enabled (Stuff) |

24 GPIO33\_CONTROL  
GPIO控制和E220相反

|                                        |                              |
|----------------------------------------|------------------------------|
| R249 - NO REBOOT                       |                              |
| Disabled when Low -- (NoStuff) DEFAULT | Enabled when HIGH -- (Stuff) |



神舟

HASEE TECHNOLOGY INC.,

PCH 1/9

Draw by

Size

CAGE Code

DWG NO

Rev

Thursday, May 22, 2014

Scale

Model

E450

Sheet


14




of 50















R345 - MPC Switch Control

MPC OFF -- (NoStuff) DEFAULT

MPC ON -- (Stuff)




4,10,11,12,13,14,15,16,17,19,20,21,23,24,25,26,31,32,33,37,38,41,44,46,48

+V3.3S

4,14,15,16,19,21,24,25,26,28,30,33,34,37,44,46,48




+V3.3A



RSVD

PCI

USB



| BBS_BIT1 | BBS_BIT0 | Boot BIOS Location |
|----------|----------|--------------------|
| 0        | 0        | LPC                |
| 0        | 1        | RESERVED           |
| 1        | 0        | -----              |
| 1        | 1        | SPI                |







神舟









**HASEE TECHNOLOGY INC.,**

**PCH 5/9--PCI,USB,NVRAM**

|                        |        |             |        |          |
|------------------------|--------|-------------|--------|----------|
| Draw by                | Size   | CAGE Code   | DWG NO | Rev      |
|                        | Custom | <Cage Code> |        | 0.2      |
| Thursday, May 22, 2014 | Scale  | Model       | E450   | Sheet    |
|                        |        |             |        | 18 of 50 |



| INTERNAL GFX |      | EXTERNAL GFX |
|--------------|------|--------------|
| STUFF        | R494 | R493         |
| UNSTUFF      | R493 | R494         |







# HASEE TECHNOLOGY INC.,

## PCH 6/9--GPIO,VSS

|                        |        |             |        |          |
|------------------------|--------|-------------|--------|----------|
| Draw by                | Size   | CAGE Code   | DWG NO | Rev      |
| Thursday, May 22, 2014 | Custom | <Cage Code> |        | 0.2      |
| Scale                  | Model  | E120        | Sheet  | 19 of 50 |





Note: C315 - STUFFED ONLY FOR CPT INTERPOSER;  
UNSTUFF FOR CPT 4.14.15.16.18.19.24.25.26.28.30.33.34.37.44.46




**HASEE TECHNOLOGY INC.,**

**PCH 8/9--POWER2**

|                        |                |                          |        |            |
|------------------------|----------------|--------------------------|--------|------------|
| Draw by                | Size<br>Custom | CAGE Code<br><Cage Code> | DWG NO | Rev<br>0.2 |
| Thursday, May 22, 2014 | Scale          | Model                    | F450   | Sheet      |



|                                                                                                 |        |                               |          |
|-------------------------------------------------------------------------------------------------|--------|-------------------------------|----------|
|  <b>神舟</b> |        | <b>HASEE TECHNOLOGY INC.,</b> |          |
|                                                                                                 |        | <b>PCH 9/9--VSS</b>           |          |
| Draw by                                                                                         | Size   | CAGE Code                     | DWG NO   |
|                                                                                                 | Custom | <Cage Code>                   |          |
| Thursday, May 22, 2014                                                                          | Scale  | Model                         | Sheet    |
|                                                                                                 |        | <b>E450</b>                   | 22 of 50 |



CPU frequency setting is 100 MHz

| FSLC | CPU    |
|------|--------|
| 0    | 133MHZ |
| 1    | 100MHZ |



# 神舟


## HASEE TECHNOLOGY INC.,


### CK505

|                        |        |             |        |          |
|------------------------|--------|-------------|--------|----------|
| Draw by                | Size   | CAGE Code   | DWG NO | Rev      |
| Thursday, May 22, 2014 | Custom | <Cage Code> |        | 0.2      |
| Scale                  | Model  | E450        | Sheet  | 23 of 50 |
















|                                                                                                 |        |                               |            |
|-------------------------------------------------------------------------------------------------|--------|-------------------------------|------------|
|  <b>神舟</b> |        | <b>HASEE TECHNOLOGY INC.,</b> |            |
| <b>MiniPCI-E 2</b>                                                                              |        |                               |            |
| Draw by                                                                                         | Size B | CAGE Code<br><Cage Code>      | DWG NO     |
| Thursday, May 22, 2014                                                                          | Scale  | Model<br><b>E450</b>          | Rev<br>0.2 |
|                                                                                                 |        | Sheet<br>26 of 50             |            |









| IT1337E-48 PIN MUX |         |        |        |
|--------------------|---------|--------|--------|
| PINS               | SM/xD   | SD/MMC | MS     |
| 05                 | SM_WPSW | SD_CMD | MS_BS  |
| 06                 | SM_RD   |        | MS_INS |
| 07                 | SM_RNB  | SD_CD  |        |
| 08                 | SM_D0   | SD_D0  | MS_D0  |
| 09                 | SM_D1   | SD_D1  | MS_D1  |
| 11                 | SM_D2   | SD_D2  | MS_D2  |
| 18                 | SM_D3   | SD_D3  | MS_D3  |
| 22                 | SM_D4   | SD_D4  | MS_D4  |
| 29                 | SM_D5   | SD_D5  | MS_D5  |
| 32                 | SM_D6   | SD_D6  | MS_D6  |
| 34                 | SM_D7   | SD_D7  | MS_D7  |
| 39                 | SM_CE   | SD_WP  |        |
| 40                 | SM_WP   | SD_CLK | MS_CLK |




\*\*\* Refer to HDMI Cost Reduced Level Shifter Design Recommendation Design Guide :Page 131 \*\*\*





|                                                                                                                     |        |                                |        |          |
|---------------------------------------------------------------------------------------------------------------------|--------|--------------------------------|--------|----------|
|  <b>HASEE TECHNOLOGY INC.,</b> |        | <b>SLEEP CONTRON/DISCHARGE</b> |        |          |
|                                                                                                                     |        |                                |        |          |
| Draw by                                                                                                             | Size   | CAGE Code                      | DWG NO | Rev      |
|                                                                                                                     | Custom | <Cage Code>                    |        | 0.2      |
| Thursday, May 22, 2014                                                                                              | Scale  | Model                          | E450   | Sheet    |
|                                                                                                                     |        |                                |        | 32 of 50 |











# 神舟

## 5V/3.3V VR




33 of 50







|                                                                                                          |        |                                                        |        |          |
|----------------------------------------------------------------------------------------------------------|--------|--------------------------------------------------------|--------|----------|
|  <b>神舟</b><br>HASEE |        | <b>HASEE TECHNOLOGY INC.,</b><br><br><b>1.05S_VCCP</b> |        |          |
|                                                                                                          |        |                                                        |        |          |
| Draw by                                                                                                  | Size   | CAGE Code                                              | DWG NO | Rev      |
|                                                                                                          | Custom | <Cage Code>                                            |        | 0.2      |
| Thursday, May 22, 2014                                                                                   | Scale  | Model                                                  | E450   | Sheet    |
|                                                                                                          |        |                                                        |        | 36 of 50 |



DNP: DO NOT POPULATE

如果data上有一个15ns低电平的毛刺，  
R131改为100R

6 VR\_SVID\_DATA

6 -VR\_SVID\_ALERT

6 VR\_SVID\_CLK

24.37 DELAY\_VR\_PWRGOOD

4.24 -H\_PROCHOT

R17 PLACE NEAR PQ5

24.37,48 ALL\_SYS\_PWRGD  
36.37 PM\_15S105SMPWRGD  
16.24 PM\_PCH\_PWRGD

6 VCCSENSE  
6 VSSSENSE




神舟

HASEE

HASEE TECHNOLOGY INC.,

CPU VR1

|                        |        |             |        |          |
|------------------------|--------|-------------|--------|----------|
| Draw by                | Size   | CAGE Code   | DWG NO | Rev      |
| Thursday, May 22, 2014 | Custom | <Cage Code> |        | 0.2      |
| Scale                  | Model  | E450        | Sheet  | 38 of 50 |



DNP: DO NOT POPULATE

If the layout of each phase to CPU is symmetric, R119, R160, R125, R164, can be removed. They are used for phase current balance adjustment.

|                                                                                       |        |                               |        |                |
|---------------------------------------------------------------------------------------|--------|-------------------------------|--------|----------------|
|  |        | <b>HASEE TECHNOLOGY INC.,</b> |        |                |
|                                                                                       |        |                               |        | <b>CPU VR2</b> |
| Draw by                                                                               | Size   | CAGE Code                     | DWG NO | Rev            |
|                                                                                       | Custom | <Cage Code>                   |        | 0.2            |
| Thursday, May 22, 2014                                                                | Scale  | Model                         | E450   | Sheet 39 of 50 |









## SATA-HDD

PACKAGE: 同E100  
sata\_C166s6-100a\_ALLTOP



## SATA-ODD


(PACKAGE:sata\_91929\_ACES)




**HASEE TECHNOLOGY INC.,**

**SATA HDD & ODD**

|                        |                |                          |                   |            |
|------------------------|----------------|--------------------------|-------------------|------------|
| Draw by                | Size<br>Custom | CAGE Code<br><Cage Code> | DWG NO            | Rev<br>0.2 |
| Thursday, May 22, 2014 | Scale          | Model<br><b>E450</b>     | Sheet<br>42 of 50 |            |






E400


Doking Keyboard.  
(DOK-6129B\_US)

For K/B CONNECTOR




Keyboard-CON

TOUCH PAD LEFT/RIGHT BUTTON




TOUCH PAD CONNECTOR




TOUCHPAD (CON15)

线序已更改同 TM-00372-027  
封装已更改同 E220  
20100629


For LID SW




For 3G SIM/UIM CARD




For BLUETOOTH




For touch screen



Debug Connector




MB & I/O-CON




PACKAGE  
ZI90-092D0-24R0\_cen  
朝向

|                        |       |                        |          |
|------------------------|-------|------------------------|----------|
|                        |       | HASEE TECHNOLOGY INC., |          |
| Board Connector        |       |                        |          |
| Draw by                | Size  | CAGE Code              | DWG NO   |
| C                      |       | <Cage Code>            |          |
| Thursday, May 22, 2014 | Scale | Model                  | Sheet    |
|                        |       | E450                   | 44 of 50 |

# DC IN-PORT



# POWER BUTTON



**HASEE TECHNOLOGY INC.,**

## DC-PORT & POWER-BUTTON

Draw by

Size  
A

CAGE Code  
<Cage Code>

DWG NO

Rev  
0.2

Thursday, May 22, 2014

Scale

Model  
**E450**


Sheet  
45 of 50

| PWRSTS | WLAN | BATT-LED | HDD  |
|--------|------|----------|------|
| LED2   | LED3 | LED1     | LED4 |

TOP Left

Right


LED




|                                                                                                 |        |                               |                   |
|-------------------------------------------------------------------------------------------------|--------|-------------------------------|-------------------|
|  <b>神舟</b> |        | <b>HASEE TECHNOLOGY INC.,</b> |                   |
| <b>LED</b>                                                                                      |        |                               |                   |
| Draw by                                                                                         | Size B | CAGE Code<br><Cage Code>      | DWG NO<br>Rev 0.2 |
| Thursday, May 22, 2014                                                                          | Scale  | Model <b>E450</b>             | Sheet 46 of 50    |

I/O & MB-CON  
GND-I/O  
GND\_CODEC-I/O


I/O & MB-CON




PACKAGE  
ZI90-092D0-24R0\_cen  
朝向




USB PORT




MIC



EARPHONE






For PCH debug with XDP, need to NO STUFF R364

```
To debug for pch:
Stuff: R858\R886\R772\R761\R866\R732
      \R895\R897\R884\R638
Unstuff: R854\R885\R857\R867\R868\R856
         R627\R697\R693\R694\R696\R278\R279
```

```
To debug for CPU:
Stuff: R885\R854\R856\R857\R867\R868\R627\R690
Unstuff:
```







Change List from Ver01 to Ver02

- 1、Page4, Pull-up R25 from +V3.3S changed to +V3.3A
- 2、Page4, R25, R22, Q65, Q67 all NoStuff  
R23 Stuff
- 3、Page7, PQ45, Q22, R58 all NoStuff  
R59 Stuff
- 4、Page14, U29、R243、R618、R785、R787、R788、C641 Deleted (SPI1 Flash Del)  
R240、R616、R784 Deleted (SPI0 series-resistor Del)
- 5、Page19, U4, C121, R487 all NoStuff
- 6、Page23, All NoStuff
- 7、Page24, C384, C385, Y5, R522, R600, R718 All NoStuff; R847, C368 Stuff  
同时 Page18, R352 Stuff  
R882 Stuff
- 8、Page28, H33\H32 change the footprint
- 9、Page33, PR152--> 220K, R842-->1M, C537-->0.1UF, C674-->0.01UF(Stuff)
- 10、Page36, C358 change and NC
- 11、Page37, C483 change and NC; R909-->Stuff
- 12、Page14, Isolate HDA SYNC from the codec during the strap:  
Add R787(Stuff), Q51, Q46, R247
- 13、Page44, J17(for bluetooth) pin6, from +V5s changed to +V3.3s
- 14、Layout J6和J14的库要更改及PCH上方邮票孔位置更改
- 15、About the Power:  
L13(2.2u)-->1u-----+V1.5  
C537(0.01u)-->0.1u-----+V5A  
C178-->33nF, R167-->2.87K, R127-->1.2K all 1%-----+VCORE  
C364-->82nF, C367-->2200pF, R177-->665, R144-->2.43K,  
R150-->220K, R172-->270, C286-->560pF, C288-->1nF, C264-->47pF-----+VGFORCE
- 16、Page34, add C641-->0.22uF, C645-->1uF  
change C647 -->33nF
- 17、Page41, add R220 and amplifier for Mic in

- Change List from Ver01 to Ver02


  - 1、Page4, Pull-up R25 from +V3.3S changed to +V3.3A
  - 2、Page4, R25, R22, Q65, Q67 all NoStuff  
R23 Stuff
  - 3、Page7, PQ45, Q22, R58 all NoStuff  
R59 Stuff
  - 4、Page14, U29, R243, R618, R785, R787, R788, C641 Deleted (SPI1 Flash Del)  
R240, R616, R784 Deleted (SPI0 series-resistor Del)
  - 5、Page19, U4, C121, R487 all NoStuff
  - 6、Page23, All NoStuff
  - 7、Page24, C384, C385, Y5, R522, R600, R718 All NoStuff; R847, C368 Stuff  
同时 Page18, R352 Stuff  
R882 Stuff
  - 8、Page28, H33\H32 change the footprint
  - 9、Page33, PR152--> 220K, R842-->1M, C537-->0.1UF, C674-->0.01UF(Stuff)
  - 10、Page36, C358 change and NC
  - 11、Page37, C483 change and NC; R909-->Stuff
  - 12、Page14, Isolate HDA SYNC from the codec during the strap:  
Add R787(Stuff), Q51, Q46, R247
  - 13、Page44, J17(for bluetooth) pin6, from +V5s changed to +V3.3s
  - 14、Layout J6和J14的库要更改及PCH上方邮票孔位置更改
  - 15、About the Power:  
L13(2.2u)-->1u-----+V1.5  
C537(0.01u)-->0.1u-----+V5A  
C178-->33nF, R167-->2.87K, R127-->1.2K all 1%-----+VCORE  
C364-->82nF, C367-->2200pF, R177-->665, R144-->2.43K,  
R150-->220K, R172-->270, C286-->560pF, C288-->1nF, C264-->47pF-----+VGFORCE
  - 16、Page34, add C641-->0.22uF, C645-->1uF  
change C647 -->33nF
  - 17、Page41, add R220 and amplifier for Mic in

|                                                                                                                                                                  |   |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------|---|
|                                                                                                                                                                  | 3 |
| <p>Change List from Ver02 to Ver03</p> <p>1、 Page35,add R670<br/>Page36,add PJP33<br/>(Vccp substitute for V1.05s)</p> <p>2、 Page41,con4 change<br/>add R725</p> |   |

- |                                                                                                                                                                  |   |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------|---|
|                                                                                                                                                                  | 3 |
| <p>Change List from Ver02 to Ver03</p> <p>1、 Page35,add R670<br/>Page36,add PJP33<br/>(Vccp substitute for V1.05s)</p> <p>2、 Page41,con4 change<br/>add R725</p> |   |

[illegible]

- [illegible]



|                                                                                                 |           |                               |                          |
|-------------------------------------------------------------------------------------------------|-----------|-------------------------------|--------------------------|
|  <b>神舟</b> |           | <b>HASEE TECHNOLOGY INC.,</b> |                          |
| <b>PWR SEQUENCE BLOCK</b>                                                                       |           |                               |                          |
| Draw by<br><b>LIZX</b>                                                                          | Size<br>B | CAGE Code<br><Cage Code>      | DWG NO<br><br>Rev<br>0.2 |
| Thursday, May 22, 2014                                                                          | Scale     | Model<br><b>E450</b>          | Sheet<br>50 of 50        |

|                                                                                                 |           |                               |                          |
|-------------------------------------------------------------------------------------------------|-----------|-------------------------------|--------------------------|
|  <b>神舟</b> |           | <b>HASEE TECHNOLOGY INC.,</b> |                          |
| <b>PWR SEQUENCE BLOCK</b>                                                                       |           |                               |                          |
| Draw by<br><b>LIZX</b>                                                                          | Size<br>B | CAGE Code<br><Cage Code>      | DWG NO<br><br>Rev<br>0.2 |
| Thursday, May 22, 2014                                                                          | Scale     | Model<br><b>E450</b>          | Sheet<br>50 of 50        |

|                                                                                                 |           |                               |                          |
|-------------------------------------------------------------------------------------------------|-----------|-------------------------------|--------------------------|
|  <b>神舟</b> |           | <b>HASEE TECHNOLOGY INC.,</b> |                          |
| <b>PWR SEQUENCE BLOCK</b>                                                                       |           |                               |                          |
| Draw by<br><b>LIZX</b>                                                                          | Size<br>B | CAGE Code<br><Cage Code>      | DWG NO<br><br>Rev<br>0.2 |
| Thursday, May 22, 2014                                                                          | Scale     | Model<br><b>E450</b>          | Sheet<br>50 of 50        |