1. ALL RESISTANCE VALUES ARE IN OHMS, 0.1 WATT +/- 5%.
2. ALL CAPACITANCE VALUES ARE IN MICROFARADS.
3. ALL CRYSTALS & OSCILLATOR VALUES ARE IN HERTZ.

REV	ZONE	ECN	DESCRIPTION OF CHANGE	CK APPD DATE	ENG APPD DATE
B		293301	PRODUCTION RELEASED	09/11/03	?

SCHEM,MLB,PB17"

09/04/2003

PAGE	CONTENTS
1	TITLE PAGE AND CONTENTS
2	SYSTEM BLOCK DIAGRAM
3	POWER BLOCK DIAGRAM
4	PCB NOTES AND HOLES
5	MPC7450 MAXBUS INTERFACE
6	MPC7450 DATA
7	CPU PLL AND CONFIGURATION STRAPS
8	INTREPID MAXBUS AND BOOT STRAPS
9	INTREPID MEMORY INTERFACE / BOOT ROM
10	DDR MEMORY MUXES
11	200PIN DDR MEMORY SODIMM CONNECTORS
12	INTREPID AGP 4X/PCI
13	INTREPID ENET/FW/UATA/EIDE INTERFACES
14	INTREPID GPIOS/SERIAL/USB INTERFACES/SSCG
15	INTREPID POWER RAILS
16	INTREPID DECOUPLING
17	CARDBUS CONTROLLER (PCI1510)
18	M10 AGP & CLOCKS
19	M10 LVDS/TMDS/VGA/GPIO & GPU VCORE
20	SIL1162 TMDS TRANSMITTER
21	M10 ANALOG, POWER, GND

PAGE	CONTENTS
22	VIDEO CONNECTORS - INVERTER, DVI, S-VIDEO DUAL-CHANNEL LVDS
23	LMU, LIGHT SENSOR, BOOTBANGER, SLEEP LED SPIDEY - KBD,TPAD,HALL EFFECT,PWR BUTTON
24	INTERNAL CONNECTORS - DVD, CARDSLOT, HARD DRIVE, LEFT USB/BLUETOOTH
25	FAN CONTROLLER, MODEM, SOUND SERIAL DEBUG (JOLLY ROGER, PWR/NMI/RESET)
26	USB 2.0
27	MARVELL GIGABIT ETHERNET PHY
28	FIREWIRE A/B PHY
29	FIREWIRE A/B CONNECTORS, PORT POWER LIMITER
30	PMU (POWER MANAGEMENT UNIT)
31	BATTERY CHARGER AND CONNECTOR
32	12.8V SYSTEM POWER SUPPLY / PMU POWER SUPPLY
33	3.3V / 5V SYSTEM POWER SUPPLIES
34	CPU CORE VOLTAGE POWER SUPPLY
35	1.5V/ 1.8V / 2.5V SYSTEM POWER SUPPLIES
36	SIGNAL CONSTRAINTS (1 OF 3) - DIGITAL/CLK
37	SIGNAL CONSTRAINTS (2 OF 3) - DIGITAL/DIFF
38	SIGNAL CONSTRAINTS (3 OF 3) - POWER NETS
39	FUNCTIONAL TEST POINTS
40	REVISION HISTORY (1 OF 1)
41-42	SIGNAL NAMES
43-44	COMPONENT LOCATIONS

BOM OPTIONS	STUFF	NO STUFF
D3_HOT		✓
D3_COLD	✓	
GPU_SS	✓	
GPU_SWITCH	✓	
SERIAL_DEBUG		✓
VCORE_OFFSET	✓	
1_8V_MAXBUS	✓	
1_5V_MAXBUS		✓
NEC_USB	✓	
INTREPID_USB		✓
BBANG		✓
NO_BBANG	✓	
ATI_MEMIO_HI	✓	
ATI_MEMIO_LO		✓
SSCG		✓
NO_SSCG	✓	
5V_HD_LOGIC	✓	
3V_HD_LOGIC		✓
EXT_TMDS	✓	
INT_TMDS		✓
NO_4XVCORE	✓	

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	BOM OPTION
051-6531	1	SCHEM,MLB,PB17 INCH	SCH1	
820-1524	1	PCBF,MLB,PB17 INCH	PCB1	

DIMENSIONS ARE IN MILLIMETERS
XX ±
X.XX ±
X.XXX ±
ANGLES °
DO NOT SCALE DRAWING
THIRD ANGLE PROJECTION

METRIC

DRAFTER | DESIGN CK
ENG APPD | MFG APPD
QA APPD | DESIGNER
RELEASE | SCALE NONE
MATERIAL/FINISH NOTED AS APPLICABLE | SIZE D

Apple Computer Inc.

NOTICE OF PROPRIETARY PROPERTY
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING
I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

TITLE
SCHEM,MLB,PB17 INCH

DRAWING NUMBER 051-6531 REV. B
SHT 1 OF 44

U44 INTREPID

J18 Ethernet Connector P.28 — 4 DATA PAIRS — U49 Ethernet PHY P.28 — G/MII 3.3V 10/100/1000 8BIT TX 8BIT RX 125MHZ

J24 FW - A Connector P.30 — 2 DATA PAIRS @ 200MHz

J22 FW - B Connector P.30 — 2 DATA PAIRS @ 400MHZ

U28 FireWire PHY P.29 — 1394 OHCI 3.3V 8BIT TX/RX 100MHZ

J11 OPTICAL DRIVE Connector P.25 — EIDE

J13 ULTRA ATA/100 Connector P.25 — UIDE

SLEEP LED P.26 — LMU

J14 TUBA (SOUND) Connector P.26 — I2S, I2C

U48/J2/J4 Fan Circuit P.26 — I2C

J25 Battery Connector P.32 — SMBUS 3.3V

Power Supply & Charger P.32-36

J19 SUTRO (PWR) Connector P.32

U36 LMU P.24 — I2C

U39 PMU P.31 — SERIAL 5V

J10 CARDBUS Connector P.18 — 33MHZ 16/32 BITS 3.3V/5V

U26 TI PCI1510 CardBus Controller P.18 — PCI BUS 32BITS 33MHZ 3.3V

J15 TRACKPAD Connector; Keyboard Connector; KB LED LIGHT SENSOR P.24

U52 USB 2.0 CONTROLLER P.27

U17 BOOT ROM 1M X 8 P.10

J3 (SHARE WITH BLUETOOTH) LEFT USB P.25 — USB 2.0

J12 RIGHT USB BACKUP BATTERY P.33 — USB 2.0 — NOT USED

J3 (SHARE WITH LEFT USB) BlueTooth P.25 — NOT USED

J9 Modem Board Connector P.26 — INTRPEID I2C

ETHERNET 10/100/1000 P.14	FIREWIRE 800 MB/S P.14	UATA 100 P.14	EIDE P.14	CARDSLOT P.14	I2S P.15	I2C P.14 P.15
USB PORT A P.15					SCCA P.15	
USB PORT B P.15					VIA/PMU P.15	
USB PORT C P.15					BOOTROM P.14	
USB PORT D P.15					PCI 32BITS 33MHZ P.13	
USB PORT E P.15						
USB PORT F P.15						
MAXBUS P.9	DDR MEMORY P.10				4X AGP P.13	

NOT USED

J5 Serial Debug Connector P.26

AGP BUS 1.5V/3.3V 32BITS 66MHZ

U43 ATI M10 64MB P.18-21 — MEMORY CH. A (INTERNAL MEM); MEMORY CH. C (INTERNAL MEM); MEMORY CH. B (INTERNAL MEM); MEMORY CH. D (INTERNAL MEM)

J21 AIRPOPT Connector P.25

J8 Inverter Connector P.22

LVDS; EDID (I2C); S-VIDEO; COMPOSITE; TMDS; RGB; (DDC TOO)

J7 LCD Panel Connector P.22 — J17 S-Video Connector P.22 — J16 DVI-I Connector P.22

MAXBUS 1.8V 167MHZ 32BIT ADDRESS 64BIT DATA

U42 APOLLO CPU (MPC7457) P.5-6 — CPU PLL Config P.7 — PMU

MEMORY BUS 2.5V 167MHZ 64BITS

U11/U12/U13/U14 2:1 DDR MUXES P.11

J20/J23 DDR SDRAM DIMM 0; DDR SDRAM DIMM 1 SO-DIMM Connector P.12

SYSTEM BLOCK DIAGRAM

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE D | DRAWING NUMBER 051-6531 | REV. B

SCALE NONE | SHT 2 OF 44

POWER SYSTEM ARCHITECTURE

AC ADAPTER IN
PG 31

INRUSH LIMITER
PG 30

+24V_PBUS

1V20_REF
U21 PG 31
>-13.44V TURNS-ON
<-13.44V SHUTS-OFF

RUN/SS
BUCK REGULATOR (LTC1625)
PG 32
VCC
AC: 12.8V
NO AC: BATTERY VOLTAGE
1625 NOT RUNNING
SHUTDOWN: RUNNING
SLEEP: RUNNING
RUN: RUNNING

+PBUS (12.8V)

BACKLIGHT INVERTER

+5V_MAIN
VCC
MAIN 2.5V/1.5V DC/DC (MAX1715)
PG 35
PGOOD
SHUTDOWN: STOPPED
SLEEP: RUNNING
RUN: RUNNING
TURNS ON OUTPUT @ 2.4V ON1/ON2

MAP31 DDR I/O
MAP31 DDR CORE
DDR POWER
+2.5V_MAIN
1_5V_2_5V_OK
+1.5V_MAIN
INTREPID CORE
AGP I/O

+PBUS

DCDC_EN
SLEEP
MAXBUS SEQUENCING

+5V_MAIN
VCC
SHDN
DC/DC (MAX1717)
PG 34
SHUTDOWN: STOPPED
SLEEP: STOPPED
RUN: RUNNING
CPU_VCORE
(+1.4V/+1.5V)

14V_PBUS

+3V_PMU LDO
PG 32
+BATT
+5V_MAIN
+3V_PMU
+4_6V_BU

RC AT 1M*0.047UF @ 24V
STARTS 2.0MSEC AFTER DCDC_EN_L BECOMES LOW

RUN/SS - 5V
TURNS ON AT >1V
<100UA ALLOWED
INTERNAL ZENER CLAMP TO 6V
MAIN 3V/5V DC/DC (LTC3707)
PG 33
VCC
STBYMD
PGOOD
SHUTDOWN: STOPPED
SLEEP: RUNNING
RUN: RUNNING
INTERNAL ZENER CLAMP TO 6V
<100UA ALLOWED
TURNS ON AT >1V
RUN/SS - 3V

+5V_MAIN
3V_5V_OK
HOLDS BOTH RUN/SS AT GND WHEN IT'S CONNECTED TO GND
TURNS CONTROL TO RUN/SS WHEN IT'S OPEN
+3.3V_MAIN

DCDC_EN_L
AFTER PMU IS UP AND RUNNING
DCDC_EN_L WILL PULL ON1/ON2 LOW IN SHUTDOWN

+5V_MAIN
+PBUS (12.8V)
VCC
EXT_VCC
DC/DC (LTC1778)
PG 20
SHUTDOWN: STOPPED
SLEEP: D3HOT/D3COLD
RUN: RUNNING
TURNS ON AS LOW AS 0.8V/TYP 1.5V
INTERNAL 1.2UA CURRENT SOURCE
RUN/SS
GPU_VCORE
+1.2V/+1.0V

DCDC_EN
SLEEP
D3_COLD
GPU_VCORE SEQUENCING
1M & 0.1UF @14V, IT TAKES ~5.88MS TO START SWITCHER
1_5V_2_5V_OK
D3_HOT
DCDC_EN_L
D3_HOT
1_5V_2_5V_OK WILL NOT PULL LOW UNTIL +5V_MAIN TURNS ON
HOWEVER, 5V SHOULD TURN ON ~2.23MS AFTER DCDC_EN_L OR PMU_POWERUP_L BECOMES '1'; MUCH LESS THAN THE RC CHARGING AT INT_VCC (5V)

+PBUS
BACKUP BATTERY
CHARGER INPUT & BOOST OUTPUT
PG 32
12.8V CHARGES BACKUP BATTERY
24V IS OUTPUT ONLY FROM BACKUP BATTERY
BACKUP BATTERY CIRCUIT CHARGES OFF +PBUS AND PREVENTS +PBUS AND +24V_PBUS FROM DROPPING BELOW 6V (UNTIL DRAINED)

RC AT 1M*0.1UF @ 24V
STARTS ~4.25MSEC AFTER DCDC_EN_L BECOMES LOW

NO INRUSH PROTECTION
WHEN ONLY BATTERY IS CONNECTED
+24V_PBUS

DC/DC (LTC3411)
PG 35
SHUTDOWN: STOPPED
SLEEP: STOPPED
RUN: RUNNING
+1.8V_MAIN
MAXBUS BROADCOM

BATTERY CHARGER (MAX1772)
PG 31
+BATT

3S 3P PRISMATIC CELLS

NO INRUSH PROTECTION
WHEN ONLY BATTERY IS CONNECTED
BATTERY VOLTAGE FEED-IN PATH
PG 31
+PBUS



POWER BLOCK DIAGRAM

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 3 OF 44	

PCB SPECS

THICKNESS : 1.2 MM / 0.047 IN
1/2 OZ CU THICKNESS: 0.7 MILS
1.0 OZ CU THICKNESS: 1.4 MILS

IMPEDANCE : 50 OHMS +/- 10%
DIELECTRIC: FR-4
LAYER COUNT: 12
SIGNAL TRACE WIDTH: 4 MILS
SIGNAL TRACE SPACING: 4 MILS
PREPREG THICKNESS: 2-3 MILS

SEE PCB CAD FILES FOR MORE SPECIFIC INFO.

BOARD STACK-UP AND CONSTRUCTION

20R10 TH VIA OR VIA IN PAD

1		SIGNAL (1/3 OZ + COPPER PLATING)
2	PREPREG (3MIL)	GROUND (1/2 OZ)
3	LAMINATE (4MIL)	SIGNAL (1/2 OZ)
4	PREPREG (3MIL)	SIGNAL (1/2 OZ)
5	LAMINATE (4MIL)	GROUND (1/2 OZ)
6	PREPREG (2MIL)	CUT POWER PLANE(1 OZ)
7	LAMINATE (3MIL)	CUT POWER PLANE(1 OZ)
8	PREPREG (2MIL)	GROUND (1/2 OZ)
9	LAMINATE (4MIL)	SIGNAL (1/2 OZ)
10	PREPREG (3MIL)	SIGNAL (1/2 OZ)
11	LAMINATE (4MIL)	GROUND (1/2 OZ)
12	PREPREG (3MIL)	SIGNAL (1/3 OZ + COPPER PLATING)

BOARD HOLES



GROUND VIAS



BOARD INFORMATION

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 4 OF 44	



PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
337S2733	1	IC,APOLLO7,1.X,1.3GHZ,1.XV CORE,85C	U43	CRITICAL	1_30_VCORE
337S2807	1	IC,APOLLO7,1.X,1.33GHZ,1.32V VCORE,85C	U43	CRITICAL	1_32_VCORE





BOOT BANGER - LMU PERORMS THIS FUNCTION IF NEEDED
SEE PAGE 22

MPC7447/BBANG

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B

SCALE	SHT	OF
NONE	6	44

CPU PLL CONFIG CIRCUITRY



STATE ENCODING	CPU_PLL_STOP_OC	CPU_VCORE_HI_OC
LOW SPEED	0	0
HIGH SPEED	0	1
PLL DISABLE	1	X

CPU FREQUENCY CONFIGURATION

APOLLO 7

MULTIPLIER (Bus-to-Core)	CORE FREQUENCY (AT BUS FREQUENCY) 167MHZ (MHZ)	133MHZ (MHZ)	CPU_PLL_CFG 4 0123 E ABCD HEX
0.0X	PLL OFF		0 1111 0F
1.0X	PLL BYPASS		0 0011 03
2.0X	333	267	0 0100 04
3.0X	500	400	0 1000 08
4.0X	667	533	0 1010 0A
5.0X	833	667	0 1011 0B
5.5X	917	733	0 1001 09
6.0X	1000	800	0 1101 0D
6.5X	1083	867	0 0101 05
7.0X	1167	933	0 0010 02
7.5X	1250	1000	0 0001 01
8.0X	1333	1067	0 1100 0C
8.5X	1417	1133	0 0110 06
9.0X	1500	1200	1 0111 17
9.5X	1583	1267	0 0111 07
10.0X	1667	1333	1 1010 1A
10.5X	1750	1400	1 1000 18
11.0X	1833	1467	1 1001 19
11.5X	1917	1533	0 0000 00
12.0X	2000	1600	1 1011 1B
12.5X	2083	1667	1 1111 1F
13.0X	2167	1733	1 0101 15
13.5X	2250	1800	0 1110 0E
14.0X	2333	1867	1 1100 1C
15.0X	2500	2000	1 0001 11
16.0X	2667	2133	1 1101 1D
17.0X	2833	2267	1 0000 10
18.0X	3000	2400	1 0010 12
20.0X	3333	2667	1 0011 13
21.0X	3500	2800	1 0100 14
24.0X	4000	3200	1 0110 16
28.0X	4667	3733	1 1110 1E

CPU CONFIGURATION

MAXBUS VSEL



DESKTOP HAD PROBLEM USING INVERTER TO INVERT HRESET_L NEED TO CHARACTERIZE

BUSTYPE SELECT

APOLLO ONLY SUPPORTS MAXBUS

SIGNAL	TIED	APPLICATION
CPU_EMODE0_L (PROCESSOR)	HIGH	60X BUS MODE
	CPU_HRESET_L	MAX BUS MODE
CPU_BUS_VSEL (PROCESSOR)	CPU_HRESET_L	2.5V INTERFACE
	LOW	1.8V INTERFACE
	CPU_HRESET_INV	1.5V INTERFACE

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 7 OF 44	

INTREPID BOOT STRAPS

BIT 32 TO 39

MAXBUS_SLEEP

NO STUFF R642 10K	NO STUFF R135 10K	NO STUFF R123 10K	NO STUFF R153 10K	NO STUFF R166 10K	NO STUFF R179 10K	NO STUFF R651 10K	NO STUFF R178 10K
CPU_DATA<32>	CPU_DATA<33>	CPU_DATA<34>	CPU_DATA<35>	CPU_DATA<36>	CPU_DATA<37>	CPU_DATA<38>	CPU_DATA<39>
R136 10K	R643 10K	R639 10K	R657 10K	R664 10K	R673 10K	R143 10K	R674 10K
DDR_TYPE 0: DDR1 1: DDR2	Analyzerclk_En_h 0: Active 1: Active low	DDR_TYPE 0: DDR1 1: DDR2	ExtPLL_SDwn_Pol 0: Active high 1: Active low	Spare	Spare	Spare	Spare

BIT 40 TO 47

MAXBUS_SLEEP

NO STUFF R122 10K	NO STUFF R142 10K	NO STUFF R164 10K	SSCG R134 10K	NO STUFF R184 10K	NO_SSCG R177 10K	NO_SSCG R152 10K	NO_SSCG R165 10K
CPU_DATA<40>	CPU_DATA<41>	CPU_DATA<42>	CPU_DATA<43>	CPU_DATA<44>	CPU_DATA<45>	CPU_DATA<46>	CPU_DATA<47>
R640 10K	R652 10K	R665 10K	NO_SSCG R644 10K	R683 10K	SSCG R675 10K	SSCG R658 10K	SSCG R666 10K
Spare	Spare	BIT2	BIT1	BIT0	Internalspreaden 1: Active	PCI1_Source Clock 0: PLL1 (NO SPREAD)	PCI0_Source Clock 0: PLL1 (NO SPREAD)

PLL4MODESEL_NXT[2:0]
000: 166.4MHZ (2.5X)
001: 149.76MHZ
010: 133.12MHZ (2.0X)
011: 99.84MHZ (1.5X)
100: 83.20MHZ

MODE A (2.5X) IS FOR STATIC OPERATION
MODE C (2.0X) IS FOR CLOCK SLEW OPERATION

BIT 48 TO 55

MAXBUS_SLEEP

SSCG R133 10K	SSCG R121 10K	NO STUFF R163 10K	NO STUFF R151 10K	NO STUFF R162 10K	NO STUFF R141 10K	NO STUFF R183 10K	NO STUFF R176 10K
CPU_DATA<48>	CPU_DATA<49>	CPU_DATA<50>	CPU_DATA<51>	CPU_DATA<52>	CPU_DATA<53>	CPU_DATA<54>	CPU_DATA<55>
NO_SSCG R645 10K	NO_SSCG R641 10K	NO STUFF R668 10K	R659 10K	R667 10K	R653 10K	NO STUFF R684 10K	R676 10K
BUF_REF_CLK_OUTEnable_h 1: Active	SetPLL4ExtSrc 1: External source	Spare	TI 1394b workaround 1: TI PHY workaround	BIT2	BIT1	BIT0	Spare

MaxBus output impedance
111: 28.6 ohm
011: 33.3 ohm
101: 40 ohm
001: 50 ohm
110: 66.6 ohm
010: 100 ohm
100: 200 ohm
000: 200 ohm

R227 4.7 1/16W MF 402 5%
+1.5V_INTREPID_PLL → +1.5V_INTREPID_PLL7
C308 0.22UF 20% 6.3V CERM 402

THE FOLLOWING STRAP BITS CAN BE CHANGED BY SOFTWARE:
1/ D47 - SELAGPSPREADCLK - SLEEP/WAKE CYCLE REQUIRED
2/ D46 - SELPCI1SPREADCLK - SLEEP/WAKE CYCLE REQUIRED
3/ D44 - PLL4MODESEL_NXT<0> - SLEEP/WAKE CYCLE REQUIRED
4/ D43 - PLL4MODESEL_NXT<1> - SLEEP/WAKE CYCLE REQUIRED
5/ D42 - PLL4MODESEL_NXT<2> - SLEEP/WAKE CYCLE REQUIRED
6/ D33 - ANALYZERCLK_EN_H - IMMEDIATE EFFECT

IF A STRAP IS NOT LISTED, THEN
IT CANNOT BE CHANGED BY SOFTWARE

VDD15A_7 (PLL6) H26
CRITICAL

U45 INTREPID-REV2.1 BGA (1 OF 9)

CPU_BR_L	E29	BR	INPUT
CPU_BG_L	E26	BG	NO BUS KEEPER
CPU_TS_L	B27	TS	NO BUS KEEPER
CPU_ADDR<0>	D24	A_0	
CPU_ADDR<1>	D25	A_1	
CPU_ADDR<2>	A27	A_2	
CPU_ADDR<3>	E24	A_3	
CPU_ADDR<4>	G23	A_4	
CPU_ADDR<5>	B26	A_5	
CPU_ADDR<6>	A26	A_6	
CPU_ADDR<7>	D23	A_7	
CPU_ADDR<8>	A25	A_8	
CPU_ADDR<9>	E23	A_9	
CPU_ADDR<10>	J22	A_10	
CPU_ADDR<11>	B25	A_11	
CPU_ADDR<12>	H22	A_12	
CPU_ADDR<13>	G22	A_13	
CPU_ADDR<14>	D22	A_14	
CPU_ADDR<15>	B24	A_15	
CPU_ADDR<16>	B23	A_16	
CPU_ADDR<17>	E22	A_17	
CPU_ADDR<18>	J21	A_18	
CPU_ADDR<19>	G21	A_19	
CPU_ADDR<20>	E21	A_20	
CPU_ADDR<21>	A24	A_21	
CPU_ADDR<22>	D21	A_22	
CPU_ADDR<23>	A23	A_23	
CPU_ADDR<24>	H20	A_24	
CPU_ADDR<25>	B22	A_25	
CPU_ADDR<26>	H21	A_26	
CPU_ADDR<27>	A22	A_27	
CPU_ADDR<28>	E20	A_28	
CPU_ADDR<29>	B21	A_29	
CPU_ADDR<30>	D20	A_30	
CPU_ADDR<31>	A21	A_31	

MAXBUS INTERFACE

CPU_CI_L	G26	CI	
CPU_GBL_L	A29	GBL	
CPU_TBST_L	A28	TBST	
CPU_TSIZ<0>	G24	TSIZ_0	
CPU_TSIZ<1>	H24	TSIZ_1	
CPU_TSIZ<2>	D26	TSIZ_2	
CPU_TT<0>	E25	TT_0	
CPU_TT<1>	G25	TT_1	
CPU_TT<2>	B28	TT_2	
CPU_TT<3>	D27	TT_3	
CPU_TT<4>	J25	TT_4	
CPU_WT_L	D28	WT	
CPU_AACK_L	B29	AACK	NO BUS KEEPER - PU
CPU_ARTRY_L	H23	ARTRY	NO BUS KEEPER - PU
CPU_HIT_L	B31	HIT	INPUT - PU
CPU_QREQ_L	A32	QREQ	INPUT - PD
CPU_QACK_L	G27	QACK	NO BUS KEEPER - ?
INT_SUSPEND_REQ_L	AK9	SUSPENDREQ	
INT_SUSPEND_ACK_L	AM8	SUSPENDACK	

FB BUFFER HAS 50 OHM OUTPUT IMPEDANCE

Vin = Intrepid Vcore (1.5V)
Vout = MaxBus rail (1.8V)

INT_CPUFB_IN	J24	CPU_FB_IN	
INT_CPUFB_OUT	H16	CPU_FB_OUT	NO BUS KEEPER - PU
SYSCLK_LA_TP	G8	ANALYZER_CLK	
CPU_CLK_EN	AH9	STOPCPUCLK	INPUT - PU
INTREPID_ACS_REF	H13	ACS_REF	NO BUS KEEPER - ?
SYSCLK_CPU_UF	J15	CPU_CLK	NO BUS KEEPER - PU
CPU_TBEN	A31	TBEN	NO BUS KEEPER - PU

INTREPID OUTPUTS HIGH BY DEFAULT

VSSA_7 (PLL6) H25

DBG	A30	CPU_DBG_L	5 8 36
DRDY	G28	CPU_DRDY_L	5 8 36
DTI_0	K25	CPU_DTI<0>	5 36
DTI_1	D29	CPU_DTI<1>	5 36
DTI_2	B30	CPU_DTI<2>	5 36
TA	E27	CPU_TA_L	5 8 36
TEA	E28	CPU_TEA_L	5 8 36

D_0	D10	CPU_DATA<0>	6 36
D_1	G12	CPU_DATA<1>	6 36
D_2	E11	CPU_DATA<2>	6 36
D_3	H11	CPU_DATA<3>	6 36
D_4	B9	CPU_DATA<4>	6 36
D_5	B8	CPU_DATA<5>	6 36
D_6	A9	CPU_DATA<6>	6 36
D_7	A8	CPU_DATA<7>	6 36
D_8	E12	CPU_DATA<8>	6 36
D_9	D11	CPU_DATA<9>	6 36
D_10	B10	CPU_DATA<10>	6 36
D_11	J13	CPU_DATA<11>	6 36
D_12	A10	CPU_DATA<12>	6 36
D_13	D12	CPU_DATA<13>	6 36
D_14	E13	CPU_DATA<14>	6 36
D_15	G13	CPU_DATA<15>	6 36
D_16	B11	CPU_DATA<16>	6 36
D_17	D13	CPU_DATA<17>	6 36
D_18	A11	CPU_DATA<18>	6 36
D_19	G14	CPU_DATA<19>	6 36
D_20	H14	CPU_DATA<20>	6 36
D_21	E14	CPU_DATA<21>	6 36
D_22	B12	CPU_DATA<22>	6 36
D_23	G15	CPU_DATA<23>	6 36
D_24	B13	CPU_DATA<24>	6 36
D_25	H15	CPU_DATA<25>	6 36
D_26	D14	CPU_DATA<26>	6 36
D_27	B14	CPU_DATA<27>	6 36
D_28	A12	CPU_DATA<28>	6 36
D_29	G16	CPU_DATA<29>	6 36
D_30	E15	CPU_DATA<30>	6 36
D_31	J16	CPU_DATA<31>	6 36
D_32	D15	CPU_DATA<32>	6 8 36
D_33	A14	CPU_DATA<33>	6 8 36
D_34	A13	CPU_DATA<34>	6 8 36
D_35	D16	CPU_DATA<35>	6 8 36
D_36	E16	CPU_DATA<36>	6 8 36
D_37	G17	CPU_DATA<37>	6 8 36
D_38	B15	CPU_DATA<38>	6 8 36
D_39	H17	CPU_DATA<39>	6 8 36
D_40	A15	CPU_DATA<40>	6 8 36
D_41	B16	CPU_DATA<41>	6 8 36
D_42	E17	CPU_DATA<42>	6 8 36
D_43	A16	CPU_DATA<43>	6 8 36
D_44	J18	CPU_DATA<44>	6 8 36
D_45	H18	CPU_DATA<45>	6 8 36
D_46	D17	CPU_DATA<46>	6 8 36
D_47	G18	CPU_DATA<47>	6 8 36
D_48	A17	CPU_DATA<48>	6 8 36
D_49	B17	CPU_DATA<49>	6 8 36
D_50	E18	CPU_DATA<50>	6 8 36
D_51	B18	CPU_DATA<51>	6 8 36
D_52	D18	CPU_DATA<52>	6 8 36
D_53	A18	CPU_DATA<53>	6 8 36
D_54	A19	CPU_DATA<54>	6 8 36
D_55	H19	CPU_DATA<55>	6 8 36
D_56	B19	CPU_DATA<56>	6 8 36
D_57	J19	CPU_DATA<57>	6 8 36
D_58	A20	CPU_DATA<58>	6 8 36
D_59	D19	CPU_DATA<59>	6 8 36
D_60	E19	CPU_DATA<60>	6 8 36
D_61	G19	CPU_DATA<61>	6 8 36
D_62	B20	CPU_DATA<62>	6 8 36
D_63	G20	CPU_DATA<63>	6 8 36

R197 511 1% 1/16W MF 402
R144 0 5% 1/16W MF 402
R137 1K 1% 1/16W MF 402

SHORT = 1" SHORTER THAN MATCHED LENGTH
LONG = 1" LONGER THAN MATCHED LENGTH

INT_CPUFB_OUT	R167 0	INT_CPUFB_OUT_SHORT	R215 0	INT_CPUFB_OUT_NORM	NO STUFF R207 0
			NO STUFF R225 0		R208 0
INT_CPUFB_IN			R226 0	INT_CPUFB_IN_NORM	NO STUFF R196 0

INT_CPUFB_OUT	NO STUFF R207 0	INT_CPUFB_LONG

MAXBUS PULL-UPS

MAXBUS_SLEEP

CPU_TS_L	RP21 10K	CPU_TA_L	RP21 10K	CPU_ARTRY_L	RP21 10K	CPU_BR_L	RP23 10K
CPU_HIT_L	RP24 10K	CPU_DRDY_L	RP23 10K	CPU_TEA_L	RP23 10K	CPU_AACK_L	RP23 10K
CPU_DBG_L	RP24 10K	CPU_BG_L	RP21 10K	CPU_QREQ_L	RP24 10K		

5% 1/16W SM1

INTREPID BOOT STRAPS

BIT 56 TO 63

MAXBUS_SLEEP

NO STUFF R140 10K	NO STUFF R161 10K	NO STUFF R175 10K	NO STUFF R132 10K	NO STUFF R131 10K	NO STUFF R150 10K	R174 10K	NO STUFF R182 10K
CPU_DATA<56>	CPU_DATA<57>	CPU_DATA<58>	CPU_DATA<59>	CPU_DATA<60>	CPU_DATA<61>	CPU_DATA<62>	CPU_DATA<63>
R654 10K	R669 10K	R677 10K	R646 10K	R647 10K	R660 10K	NO STUFF R678 10K	R685 10K
Spare	Spare	Spare	PCI1_REQ2_L / PCI1_GNT2_L 0: GPIO 1: GPIO	PCI1_REQ1_L / PCI1_GNT1_L 0: GPIO 1: GPIO	PCI1_REQ0_L / PCI1_GNT0_L 0: GPIO 1: GPIO	Firewire PHY interface 0: Legacy interface 1: B-mode interface	Processor Bus Mode 0: 60x bus (G3) 1:

Intrepid MaxBus	
NOTICE OF PROPRIETARY PROPERTY	
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING I TO MAINTAIN THE DOCUMENT IN CONFIDENCE II NOT TO REPRODUCE OR COPY IT III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART	
APPLE COMPUTER INC.	SIZE D · DRAWING NUMBER 051-6531 · REV. B SCALE NONE · SHT 8 OF 44

SERIES RESISTORS FOR CLOCK/CONTROL SIGNALS

PINS ARE SWAPABLE FOR RPAKS



MEM_VREF



CLOCKS



CS

CKE

ADDR



BA

CNTL

1MB BOOT ROM





OVERRIDE ROM MODULE
INTERCEPTS ROM CHIP SELECT

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
341S1336	1	BOOTROM,P84	U17	CRITICAL	?

PULL-DOWN RESISTORS TO ENSURE
CKE STAYS LOW AFTER INTREPID
2.5V I/O SHUTS OFF



INT - DDR/BOOTROM

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 9 OF 44	



SEL = LOW; HOST = B PORT; A PORT = 100OHM TO GND
SEL = HIGH; HOST = A PORT; B PORT = 100OHM TO GND
MEM_MUXSEL_H<0> AND MEM_MUXSEL_L<0> ARE ACTIVE LOW
MEM_MUXSEL_H<1> AND MEM_MUXSEL_L<1> ARE ACTIVE HIGH

ADDED 0 OHM RESISTORS IN CASE POLARITY IS WRONG

16BIT 2:1 DDR MUXES

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 10 OF 44	









FOR RETURN CURRENT



DDR SODIMM CONNS

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B

SCALE NONE

SHT 11 OF 44



USB2 AND CBUS REQ REMAINS ON +3V_MAIN BECAUSE THESE CHIPS ARE POWERED IN SLEEP









NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

INTREPID AGP/PCI

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 12 OF 44	


CRITICAL
U45
INTREPID-REV2.1
BGA
(5 OF 9)
UATA100
ATA_D0 V5 UIDE_DATA<0>
ATA_D1 T1 UIDE_DATA<1>
ATA_D2 U1 UIDE_DATA<2>
ATA_D3 U2 UIDE_DATA<3>
ATA_D4 V4 UIDE_DATA<4>
ATA_D5 V2 UIDE_DATA<5>
ATA_D6 W1 UIDE_DATA<6>
ATA_D7 V1 UIDE_DATA<7>
ATA_D8 W2 UIDE_DATA<8>
ATA_D9 W8 UIDE_DATA<9>
ATA_D10 W4 UIDE_DATA<10>
ATA_D11 W5 UIDE_DATA<11>
ATA_D12 Y2 UIDE_DATA<12>
ATA_D13 Y1 UIDE_DATA<13>
ATA_D14 W7 UIDE_DATA<14>
ATA_D15 Y8 UIDE_DATA<15>
ATA_A0 Y5 UIDE_ADDR<0>
ATA_A1 AB1 UIDE_ADDR<1>
ATA_A2 Y7 UIDE_ADDR<2>
ATA_VREF Y15 UIDE_REF
ATA_RST Y4 UIDE_RST_L
ATA_WR AA1 UIDE_DIOW_L
ATA_RD AA2 UIDE_DIOR_L
ATA_CHRDY AA5 UIDE_IOCHRDY
ATA_CS0 AA4 UIDE_CS0_L
ATA_CS1 AB2 UIDE_CS1_L
ATA_DMACK AC1 UIDE_DMACK_L
ATA_DMARQ AC2 UIDE_DMARQ
ATA_INTRQ AA8 UIDE_INTRQ
UDMA - STOP
UDMA - HOSTDMARDY/HSTROBE
UDMA - DEVICEDMARDY/DSTROBE
R51 82 5% 1/16W MF 402
HD_DMARQ
R92 82 5% 1/16W MF 402
HD_INTRQ
CARDSLOT
CS_CE1 AD1 CSLOT_CE1_L_SPN
CS_CE2 AB4 CSLOT_CE2_L_SPN
CS_IORD AB5 CSLOT_IORD_L_SPN
CS_IOWR AD2 CSLOT_IOWR_L_SPN
CS_OE AC4 CSLOT_OE_L_SPN
CS_WE AE1 CSLOT_WE_L_SPN
CS_WAIT AE2 CSLOT_IOWAIT_L_PU
+3V_MAIN
R52 10K 5% 1/16W MF 402
CS_WAIT IS AN INPUT
IDEDD0 AC5 EIDE_DATA<0>
IDEDD1 AD4 EIDE_DATA<1>
IDEDD2 AF1 EIDE_DATA<2>
IDEDD3 AG1 EIDE_DATA<3>
IDEDD4 AF2 EIDE_DATA<4>
IDEDD5 AH1 EIDE_DATA<5>
IDEDD6 AD5 EIDE_DATA<6>
IDEDD7 AG2 EIDE_DATA<7>
IDEDD8 AE4 EIDE_DATA<8>
IDEDD9 AE5 EIDE_DATA<9>
IDEDD10 AF4 EIDE_DATA<10>
IDEDD11 AH2 EIDE_DATA<11>
IDEDD12 AD7 EIDE_DATA<12>
IDEDD13 AG4 EIDE_DATA<13>
IDEDD14 AJ1 EIDE_DATA<14>
IDEDD15 AJ2 EIDE_DATA<15>
IDE
IDEA0 AF5 EIDE_ADDR<0>
IDEA1 AE7 EIDE_ADDR<1>
IDEA2 AK1 EIDE_ADDR<2>
IDEA3 AG5 CSLOT_ADDR3_SPN
IDEA4 AH4 CSLOT_ADDR4_SPN
IDEA5 AL1 CSLOT_ADDR5_SPN
IDEA6 AK2 CSLOT_ADDR6_SPN
IDEA7 AH5 CSLOT_ADDR7_SPN
IDEA8 AF7 CSLOT_ADDR8_SPN
IDEA9 AG7 CSLOT_ADDR9_SPN
NOT USING CARDSLOT INTERFACE
IDECHRDY AK4 EIDE_IOCHRDY
IDECS0 AB7 EIDE_CS0_L
IDECS1 AM1 EIDE_CS1_L
IDERST AJ4 EIDE_RST_L
IDEWR AM2 EIDE_WR_L
IDERD AL2 EIDE_RD_L
IDEDMACK AG8 EIDE_DMACK_L
IDEDMARQ AH7 EIDE_DMARQ
IDEINTRQ AA7 EIDE_INT
R154 1K 1% 1/16W MF 402
R630 10 5% 1/16W MF 402
ENET_PHY_TX_EN
ENET_LINK_TX_EN
CLKENET_LINK_TX
R624 10 5% 1/16W MF 402
ENET_PHY_TX_ER
ENET_LINK_TX_ER
CRITICAL
U45
INTREPID-REV2.1
BGA
(4 OF 9)
TX_CLK H9
TX_EN A7
TX_ER A5
TXD_0 H10
TXD_1 E9
TXD_2 D8
TXD_3 A6
TXD_4 B7
TXD_5 G10
TXD_6 D9
TXD_7 E10
RX_CLK J12
RX_DV C4
RX_ER D2
RXD_0 D3
RXD_1 E7
RXD_2 D6
RXD_3 B4
RXD_4 A4
RXD_5 D7
RXD_6 G9
RXD_7 E8
GBE_REFCLK L13
GTX_CLK H12
CRS E6
COL C5
MDIO B5
MDC B6
GB ETHERNET
TDI AK8
TDO AT5
TCK AP5
TMS AR5
TRSTN AN6
TEI AH10
TST_MONIN AM7
TST_MONOUT AK10
TST_PLLEN AR6
TEST
ENET_LINK_TXD<0>
ENET_LINK_TXD<1>
ENET_LINK_TXD<2>
ENET_LINK_TXD<3>
ENET_LINK_TXD<4>
ENET_LINK_TXD<5>
ENET_LINK_TXD<6>
ENET_LINK_TXD<7>
CLKENET_LINK_RX
ENET_RX_DV
ENET_RX_ER
ENET_LINK_RXD<0>
ENET_LINK_RXD<1>
ENET_LINK_RXD<2>
ENET_LINK_RXD<3>
ENET_LINK_RXD<4>
ENET_LINK_RXD<5>
ENET_LINK_RXD<6>
ENET_LINK_RXD<7>
CLKENET_LINK_GBE_REF
CLKENET_LINK_GTX
ENET_CRS
ENET_COL
ENET_MDIO
ENET_MDC
CLKENET_PHY_GTX
R124 10 5% 1/16W MF 402
JTAG_ASIC_TDI
JTAG_ENET_TDI
JTAG_ASIC_TCK
JTAG_ASIC_TMS
JTAG_ASIC_TRST_L
INT_JTAG_TEI
INT_TST_MONIN_PD
INT_TST_MONOUT_TP
INT_TST_PLLEN_PD
MISC
RESET U5 INT_RESET_L
PURESET T2 INT_PU_RESET_L
FIREWIRE
PHY_DATA0 L4 FW_LINK_DATA<0>
PHY_DATA1 M4 FW_LINK_DATA<1>
PHY_DATA2 P7 FW_LINK_DATA<2>
PHY_DATA3 N5 FW_LINK_DATA<3>
PHY_DATA4 K1 FW_LINK_DATA<4>
PHY_DATA5 K2 FW_LINK_DATA<5>
PHY_DATA6 L2 FW_LINK_DATA<6>
PHY_DATA7 N4 FW_LINK_DATA<7>
PHY_LPS M1 FW_PHY_LPS
PHY_CTL0 P5 FW_LINK_CNTL<0>
PHY_CTL1 L1 FW_LINK_CNTL<1>
PHY_LREQ M2 FW_LINK_LREQ
FWR_PCLK T7 CLKFW_LINK_PCLK
FWR_LCLK U14 CLKFW_LINK_LCLK
FW_LINKON N2 FW_LKON
FW_PINT N1 FW_PINT
R34 22 5% 1/16W MF 402
FW_PHY_LREQ
R145 22 5% 1/16W MF 402
CLKFW_PHY_LCLK
IICCLK_0 AN2 INT_I2C_CLK0
IICDATA_0 AN1 INT_I2C_DATA0
IICCLK_1 AK5 INT_I2C_CLK1
IICDATA_1 AM3 INT_I2C_DATA1
TEST PULL-UPS/DOWNS
+3V_MAIN
RP16 10K 5% 1/16W SM1
JTAG_ASIC_TDI
JTAG_ASIC_TMS
RP117 10K 5% 1/16W MF 402
JTAG_ENET_TDI
R621 10K 5% 1/16W MF 402
INT_TST_PLLEN_PD
JTAG_ASIC_TCK
R626 1K 5% 1/16W MF 402
JTAG_ASIC_TRST_L
INT_JTAG_TEI
R629 1K 5% 1/16W MF 402
INT_TST_MONIN_PD
I2C PULL-UPS
+3V_MAIN
RP12 2.2K 5% 1/16W SM1
INT_I2C_CLK0
INT_I2C_DATA0
INT_I2C_CLK1
INT_I2C_DATA1
ENET_TXD SERIES TERMINATION
RP15 22 5% 1/16W SM1
RP14 22 5% 1/16W SM1
ENET_PHY_TXD<0>
ENET_PHY_TXD<1>
ENET_PHY_TXD<2>
ENET_PHY_TXD<3>
ENET_PHY_TXD<4>
ENET_PHY_TXD<5>
ENET_PHY_TXD<6>
ENET_PHY_TXD<7>
ENET_LINK_TXD<0>
ENET_LINK_TXD<1>
ENET_LINK_TXD<2>
ENET_LINK_TXD<3>
ENET_LINK_TXD<4>
ENET_LINK_TXD<5>
ENET_LINK_TXD<6>
ENET_LINK_TXD<7>
I2C-0 (MAIN)
A0-WR A1-RD: RAM - STANDARD J20 - PG 12
A2-WR A3-RD: RAM - REVERSED J23 - PG 12
AC-WR AD-RD: N/A
AE-WR AF-RD: BOOTBANG E2PROM U37 - PG 23
84-WR 85-RD: LMU U36 - PG 23
58-WR 59-RD: N/A
6A-WR 6B-RD: N/A
D0-WR D1-RD: N/A
I2C-1 (MAIN): N/A; CLOCK SLEW SSCG U56 - PG 15
I2C-2 (SLEEP): N/A; FAN CONTROLLER U3 - PG 24; SNAPPER SOUND J12 - PG 24; N/A
PMU (SLEEP): N/A
ADDR LSB INDICATES READ ('1') OR WRITE ('0') MODES
JTG_RSTN_L | TST_TEI_H | JTG_TDO_H (I/O) | JTG_TDI_H (I/O) | TST_PLLEN_H | ANALYZER_CLK | DESCRIPTION
1 | X | X | X | X | X | JTAG MODE
0 | 0 | EXTPLL SHUTDOWN (OUTPUT) | DDR_ TPDENABLE (OUTPUT) | 0 | (OUTPUT) | NORMAL OPERATION
0 | 0 | (OUTPUT) | 0(I) | 1 | SELECTED PLL OUTPUTS | VIEW PLLS (SOFTWARE)
0 | 0 | HWPLL_ TESTSEL5 (INPUT) | 1(I) | 1 | SELECTED PLL OUTPUTS | VIEW PLLS (HARDWARE)
0 | 1 | 0(I) | 0(I) | MEMWE | SYNC/MEM DATA BYPASS | ATPG NORMAL
0 | 1 | 0(I) | 1(I) | 0 | X(I) | ATPG IDDQ
0 | 1 | 0(I) | 1(I) | 1 | X(I) | TEST TRI-STATE
0 | 1 | 1(I) | 0(I) | 0 | X(I) | FUNCTIONAL TEST WITHOUT POSTSCALAR BYPASS
0 | 1 | 1(I) | 0(I) | 1 | X(I) | FUNCTIONAL TEST WITH POSTSCALAR BYPASS
0 | 1 | 1(I) | 1(I) | X | X(I) | FUNCTIONAL TEST IDDQ
INT - ENET/FW/UATA EIDE/I2C
NOTICE OF PROPRIETARY PROPERTY
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING
I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART
APPLE COMPUTER INC.
SIZE D
DRAWING NUMBER 051-6531
REV. B
SCALE NONE
SHT 13 OF 44



HWPLL_TESTMUXSEL	SIGNAL NAME
5	MOD_BITCLK_B_H
4	MOD_CLKOUT_B_H
3	MOD_DTO_B_H
2	MOD_SYNC_B_H
1	MOD_DTI_B_H
0	JTG_TDO_H

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	BOM OPTION
116S1104	1	RES,METAL FILM,10 K OHM,5,1/16W,0402,SM	R100	NO_SSCG

PART NUMBER	ALTERNATE FOR PART NUMBER	BOM OPTION	REF DES	COMMENTS:
197S0004	197S0035		Y1	ALT FOR SIWARD



Intrepid Power

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B

SCALE	SHT	OF
NONE	15	44

INTREPID MAXBUS DECOUPLING

24 Balls
4 X 10UF (0805)
32 X 0.22UF (0402)

38 34 23 15 8 7 6 MAXBUS_SLEEP

C204 10uF 20% 6.3V CERM 805 · C348 10uF 20% 6.3V CERM 805 · C239 0.22uF 20% 6.3V CERM 402 · C240 0.22uF 20% 6.3V CERM 402 · C350 0.22uF 20% 6.3V CERM 402 · C312 0.22uF 20% 6.3V CERM 402 · C176 0.22uF 20% 6.3V CERM 402 · C288 0.22uF 20% 6.3V CERM 402 · C313 0.22uF 20% 6.3V CERM 402 · C94 0.22uF 20% 6.3V CERM 402 · C286 0.22uF 20% 6.3V CERM 402 · C158 0.22uF 20% 6.3V CERM 402

C236 10uF 20% 6.3V CERM 805 · C196 10uF 20% 6.3V CERM 805 · C174 0.22uF 20% 6.3V CERM 402 · C206 0.22uF 20% 6.3V CERM 402 · C259 0.22uF 20% 6.3V CERM 402 · C237 0.22uF 20% 6.3V CERM 402 · C238 0.22uF 20% 6.3V CERM 402 · C95 0.22uF 20% 6.3V CERM 402 · C117 0.22uF 20% 6.3V CERM 402 · C241 0.22uF 20% 6.3V CERM 402 · C260 0.22uF 20% 6.3V CERM 402 · C314 0.22uF 20% 6.3V CERM 402

C173 0.22uF 20% 6.3V CERM 402 · C171 0.22uF 20% 6.3V CERM 402 · C175 0.22uF 20% 6.3V CERM 402 · C226 0.22uF 20% 6.3V CERM 402 · C172 0.22uF 20% 6.3V CERM 402 · C207 0.22uF 20% 6.3V CERM 402 · C118 0.22uF 20% 6.3V CERM 402 · C287 0.22uF 20% 6.3V CERM 402 · C119 0.22uF 20% 6.3V CERM 402 · C349 0.22uF 20% 6.3V CERM 402

C205 0.22uF 20% 6.3V CERM 402 · C209 0.22uF 20% 6.3V CERM 402

INTREPID CORE DECOUPLING

30 Balls
4 X 10UF (0805)
29 X 0.22UF (0402)

+1_5V_MAIN

C128 10uF 20% 6.3V CERM 805 · C101 10uF 20% 6.3V CERM 805 · C147 0.22uF 20% 6.3V CERM 402 · C243 0.22uF 20% 6.3V CERM 402 · C262 0.22uF 20% 6.3V CERM 402 · C242 0.22uF 20% 6.3V CERM 402 · C227 0.22uF 20% 6.3V CERM 402 · C181 0.22uF 20% 6.3V CERM 402 · C142 0.22uF 20% 6.3V CERM 402 · C215 0.22uF 20% 6.3V CERM 402 · C278 0.22uF 20% 6.3V CERM 402 · C264 0.22uF 20% 6.3V CERM 402

C157 10uF 20% 6.3V CERM 805 · C315 10uF 20% 6.3V CERM 805 · C244 0.22uF 20% 6.3V CERM 402 · C212 0.22uF 20% 6.3V CERM 402 · C178 0.22uF 20% 6.3V CERM 402 · C179 0.22uF 20% 6.3V CERM 402 · C177 0.22uF 20% 6.3V CERM 402 · C159 0.22uF 20% 6.3V CERM 402 · C161 0.22uF 20% 6.3V CERM 402 · C162 0.22uF 20% 6.3V CERM 402 · C280 0.22uF 20% 6.3V CERM 402 · C279 0.22uF 20% 6.3V CERM 402

C144 0.22uF 20% 6.3V CERM 402 · C246 0.22uF 20% 6.3V CERM 402 · C211 0.22uF 20% 6.3V CERM 402 · C263 0.22uF 20% 6.3V CERM 402 · C180 0.22uF 20% 6.3V CERM 402 · C213 0.22uF 20% 6.3V CERM 402 · C197 0.22uF 20% 6.3V CERM 402 · C208 0.22uF 20% 6.3V CERM 402 · C214 0.22uF 20% 6.3V CERM 402

INTREPID AGP I/O DECOUPLING

21 Balls
4 X 10UF (0805)
24 X 0.22UF (0402)

38 21 19 18 15 12 +1_5V_AGP

C371 10uF 20% 6.3V CERM 805 · C231 10uF 20% 6.3V CERM 805 · C356 0.22uF 20% 6.3V CERM 402 · C297 0.22uF 20% 6.3V CERM 402 · C268 0.22uF 20% 6.3V CERM 402 · C217 0.22uF 20% 6.3V CERM 402 · C355 0.22uF 20% 6.3V CERM 402 · C267 0.22uF 20% 6.3V CERM 402 · C250 0.22uF 20% 6.3V CERM 402 · C298 0.22uF 20% 6.3V CERM 402 · C377 0.22uF 20% 6.3V CERM 402 · C216 0.22uF 20% 6.3V CERM 402

C281 10uF 20% 6.3V CERM 805 · C394 10uF 20% 6.3V CERM 805 · C228 0.22uF 20% 6.3V CERM 402 · C230 0.22uF 20% 6.3V CERM 402 · C265 0.22uF 20% 6.3V CERM 402 · C378 0.22uF 20% 6.3V CERM 402 · C357 0.22uF 20% 6.3V CERM 402 · C229 0.22uF 20% 6.3V CERM 402 · C325 0.22uF 20% 6.3V CERM 402 · C393 0.22uF 20% 6.3V CERM 402 · C324 0.22uF 20% 6.3V CERM 402 · C323 0.22uF 20% 6.3V CERM 402

C251 0.22uF 20% 6.3V CERM 402 · C266 0.22uF 20% 6.3V CERM 402 · C249 0.22uF 20% 6.3V CERM 402

INTREPID 3.3V DECOUPLING

57 Balls
4 X 10UF (0805)
72 X 0.22UF (0402)

+3V_MAIN

C164 10uF 20% 6.3V CERM 805 · C395 10uF 20% 6.3V CERM 805 · C375 0.22uF 20% 6.3V CERM 402 · C351 0.22uF 20% 6.3V CERM 402 · C53 0.22uF 20% 6.3V CERM 402 · C42 0.22uF 20% 6.3V CERM 402 · C21 0.22uF 20% 6.3V CERM 402 · C185 0.22uF 20% 6.3V CERM 402 · C31 0.22uF 20% 6.3V CERM 402 · C143 0.22uF 20% 6.3V CERM 402 · C123 0.22uF 20% 6.3V CERM 402 · C121 0.22uF 20% 6.3V CERM 402

C10 10uF 20% 6.3V CERM 805 · C9 10uF 20% 6.3V CERM 805 · C33 0.22uF 20% 6.3V CERM 402 · C184 0.22uF 20% 6.3V CERM 402 · C43 0.22uF 20% 6.3V CERM 402 · C35 0.22uF 20% 6.3V CERM 402 · C261 0.22uF 20% 6.3V CERM 402 · C60 0.22uF 20% 6.3V CERM 402 · C52 0.22uF 20% 6.3V CERM 402 · C199 0.22uF 20% 6.3V CERM 402 · C57 0.22uF 20% 6.3V CERM 402 · C19 0.22uF 20% 6.3V CERM 402

C16 0.22uF 20% 6.3V CERM 402 · C108 0.22uF 20% 6.3V CERM 402 · C55 0.22uF 20% 6.3V CERM 402 · C32 0.22uF 20% 6.3V CERM 402 · C125 0.22uF 20% 6.3V CERM 402 · C45 0.22uF 20% 6.3V CERM 402 · C76 0.22uF 20% 6.3V CERM 402 · C277 0.22uF 20% 6.3V CERM 402 · C28 0.22uF 20% 6.3V CERM 402 · C26 0.22uF 20% 6.3V CERM 402

C34 0.22uF 20% 6.3V CERM 402 · C23 0.22uF 20% 6.3V CERM 402 · C120 0.22uF 20% 6.3V CERM 402 · C146 0.22uF 20% 6.3V CERM 402 · C141 0.22uF 20% 6.3V CERM 402 · C30 0.22uF 20% 6.3V CERM 402 · C145 0.22uF 20% 6.3V CERM 402 · C96 0.22uF 20% 6.3V CERM 402 · C54 0.22uF 20% 6.3V CERM 402 · C50 0.22uF 20% 6.3V CERM 402

C75 0.22uF 20% 6.3V CERM 402 · C122 0.22uF 20% 6.3V CERM 402 · C51 0.22uF 20% 6.3V CERM 402 · C59 0.22uF 20% 6.3V CERM 402 · C163 0.22uF 20% 6.3V CERM 402 · C126 0.22uF 20% 6.3V CERM 402 · C98 0.22uF 20% 6.3V CERM 402 · C109 0.22uF 20% 6.3V CERM 402 · C56 0.22uF 20% 6.3V CERM 402 · C27 0.22uF 20% 6.3V CERM 402

C296 0.22uF 20% 6.3V CERM 402 · C248 0.22uF 20% 6.3V CERM 402 · C210 0.22uF 20% 6.3V CERM 402 · C58 0.22uF 20% 6.3V CERM 402 · C22 0.22uF 20% 6.3V CERM 402 · C20 0.22uF 20% 6.3V CERM 402 · C61 0.22uF 20% 6.3V CERM 402 · C44 0.22uF 20% 6.3V CERM 402 · C29 0.22uF 20% 6.3V CERM 402 · C24 0.22uF 20% 6.3V CERM 402

C183 0.22uF 20% 6.3V CERM 402 · C18 0.22uF 20% 6.3V CERM 402 · C49 0.22uF 20% 6.3V CERM 402 · C36 0.22uF 20% 6.3V CERM 402 · C17 0.22uF 20% 6.3V CERM 402 · C99 0.22uF 20% 6.3V CERM 402 · C396 0.22uF 20% 6.3V CERM 402 · C124 0.22uF 20% 6.3V CERM 402 · C127 0.22uF 20% 6.3V CERM 402 · C100 0.22uF 20% 6.3V CERM 402

INTREPID DDR DECOUPLING

44 Balls
4 X 10UF (0805)
51 X 0.22UF (0402)

38 15 10 9 +2_5V_INTREPID

C422 10uF 20% 6.3V CERM 805 · C417 10uF 20% 6.3V CERM 805 · C407 0.22uF 20% 6.3V CERM 402 · C391 0.22uF 20% 6.3V CERM 402 · C310 0.22uF 20% 6.3V CERM 402 · C317 0.22uF 20% 6.3V CERM 402 · C480 0.22uF 20% 6.3V CERM 402 · C390 0.22uF 20% 6.3V CERM 402 · C370 0.22uF 20% 6.3V CERM 402 · C320 0.22uF 20% 6.3V CERM 402 · C365 0.22uF 20% 6.3V CERM 402 · C366 0.22uF 20% 6.3V CERM 402

C418 10uF 20% 6.3V CERM 805 · C423 10uF 20% 6.3V CERM 805 · C367 0.22uF 20% 6.3V CERM 402 · C292 0.22uF 20% 6.3V CERM 402 · C295 0.22uF 20% 6.3V CERM 402 · C403 0.22uF 20% 6.3V CERM 402 · C291 0.22uF 20% 6.3V CERM 402 · C352 0.22uF 20% 6.3V CERM 402 · C322 0.22uF 20% 6.3V CERM 402 · C392 0.22uF 20% 6.3V CERM 402 · C385 0.22uF 20% 6.3V CERM 402 · C376 0.22uF 20% 6.3V CERM 402

C321 0.22uF 20% 6.3V CERM 402 · C318 0.22uF 20% 6.3V CERM 402 · C399 0.22uF 20% 6.3V CERM 402 · C410 0.22uF 20% 6.3V CERM 402 · C335 0.22uF 20% 6.3V CERM 402 · C369 0.22uF 20% 6.3V CERM 402 · C384 0.22uF 20% 6.3V CERM 402 · C294 0.22uF 20% 6.3V CERM 402 · C406 0.22uF 20% 6.3V CERM 402 · C405 0.22uF 20% 6.3V CERM 402

C404 0.22uF 20% 6.3V CERM 402 · C400 0.22uF 20% 6.3V CERM 402 · C386 0.22uF 20% 6.3V CERM 402 · C289 0.22uF 20% 6.3V CERM 402 · C387 0.22uF 20% 6.3V CERM 402 · C401 0.22uF 20% 6.3V CERM 402 · C354 0.22uF 20% 6.3V CERM 402 · C389 0.22uF 20% 6.3V CERM 402 · C309 0.22uF 20% 6.3V CERM 402 · C398 0.22uF 20% 6.3V CERM 402

C337 0.22uF 20% 6.3V CERM 402 · C290 0.22uF 20% 6.3V CERM 402 · C402 0.22uF 20% 6.3V CERM 402 · C397 0.22uF 20% 6.3V CERM 402 · C368 0.22uF 20% 6.3V CERM 402 · C334 0.22uF 20% 6.3V CERM 402 · C388 0.22uF 20% 6.3V CERM 402 · C293 0.22uF 20% 6.3V CERM 402 · C319 0.22uF 20% 6.3V CERM 402 · C336 0.22uF 20% 6.3V CERM 402

C316 0.22uF 20% 6.3V CERM 402

Intrepid Decoupling

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 16 OF 44	

PCI1510 PULL-UPS

+3V_MAIN

R757 10K 5% 1/16W MF 402 — CBUS_PCI_PERR_L 17

R756 10K 5% 1/16W MF 402 — CBUS_PCI_SERR_L 17

R753 10K 5% 1/16W MF 402 — CBUS_SUSPEND_PU 17

+3V_MAIN

C813 10UF 20% 6.3V CERM 805

C795 0.22UF 20% 6.3V CERM 402

C798 0.22UF 20% 6.3V CERM 402

C790 0.22UF 20% 6.3V CERM 402

C796 0.22UF 20% 6.3V CERM 402

C797 0.22UF 20% 6.3V CERM 402

C791 0.22UF 20% 6.3V CERM 402

R762 10K 5% 1/16W MF 402

+2_5V_MAIN

C789 0.22UF 20% 6.3V CERM 402

A7 C13 D5 E1 M1 N7 N11 — VCC

39 30 26 24 20 18 17 14 MAIN_RESET_L

THIS PROPERLY SHUTS DOWN
CARDBUS POWER FOR PSUEDO-D3COLD

R348 47 5% 1/16W MF 402

+3V_MAIN

+5V_MAIN

NO STUFF
R373 10K 5% 1/16W MF 402

U19
TPS2211
SSOI

NC	9		
V_12	5	AVPP	10
V_5_1	6		
V_5_2	3	AVCC0	11
V_3_1	4	AVCC1	12
V_3_2		AVCC2	13
VCCD0	1		
VCCD1	2		
VPPD0	15	CRITICAL	
VPPD1	14		
SHTDWN	16		
GND	7	OC	8 NC

+VPP_CBUS_SW 17 38

+VCC_CBUS_SW 17 38

MAKE SURE VCC AND VPP ARE WIDE PLANE/TRACES
TO MINIMIZE INDUCTANCE!

C773 0.1UF 20% 10V CERM 402

C467 0.1UF 20% 10V CERM 402

0.1UF ARE USED TO INCREASE ESD DISCHARGES OF UP TO 10KV

TPS2211_SHDN_L_PU

PCI1510_VR_EN_L

CRITICAL
U26
PCI1510GGU
BGA

CLAMP FOR PC-CARD
CLAMP FOR PCI

NC	H10	CLK_48_RSVD/NC	
	D4	VR_EN*	
	L8	VR_PORT	
	N8	AD0	39 37 26 24 12 9 PCI_AD<0>
	M7	AD1	39 37 26 24 12 9 PCI_AD<1>
	L7	AD2	39 37 26 24 12 9 PCI_AD<2>
	N6	AD3	39 37 26 24 12 9 PCI_AD<3>
	K4	AD4	39 37 26 24 12 9 PCI_AD<4>
	M6	AD5	39 37 26 24 12 9 PCI_AD<5>
	L6	AD6	39 37 26 24 12 9 PCI_AD<6>
	N5	AD7	39 37 26 24 12 9 PCI_AD<7>
	N4	AD8	39 37 26 24 12 9 PCI_AD<8>
	M2	AD9	39 37 26 24 12 9 PCI_AD<9>
	M5	AD10	39 37 26 24 12 9 PCI_AD<10>
	L4	AD11	39 37 26 24 12 9 PCI_AD<11>
	N3	AD12	39 37 26 24 12 9 PCI_AD<12>
	K5	AD13	39 37 26 24 12 9 PCI_AD<13>
	L5	AD14	39 37 26 24 12 9 PCI_AD<14>
	M4	AD15	39 37 26 24 12 9 PCI_AD<15>
	J4	AD16	39 37 26 24 12 9 PCI_AD<16>
	H1	AD17	39 37 26 24 12 9 PCI_AD<17>
	H3	AD18	39 37 26 24 12 9 PCI_AD<18>
	H2	AD19	PCI_AD<19>
	G2	AD20	39 37 26 24 12 9 PCI_AD<20>
	G4	AD21	39 37 26 24 12 PCI_AD<21>
	F1	AD22	39 37 26 24 12 9 PCI_AD<22>
	C3	AD23	39 37 26 24 12 PCI_AD<23>
	F3	AD24	39 37 26 24 12 9 PCI_AD<24>
	E2	AD25	39 37 26 24 12 9 PCI_AD<25>
	F4	AD26	39 37 26 24 12 9 PCI_AD<26>
	B1	AD27	39 37 26 24 12 9 PCI_AD<27>
	D2	AD28	39 37 26 24 12 9 PCI_AD<28>
	E4	AD29	39 37 26 24 12 9 PCI_AD<29>
	D3	AD30	39 37 26 24 12 9 PCI_AD<30>
	E3	AD31	39 37 26 24 12 9 PCI_AD<31>
	K6	C/BE0*	39 37 26 24 12 PCI_CBE<0>
	M3	C/BE1*	39 37 26 24 12 PCI_CBE<1>
	J2	C/BE2*	39 37 26 24 12 PCI_CBE<2>
	A1	C/BE3*	39 37 26 24 12 PCI_CBE<3>
	N1	PAR	39 37 26 24 12 PCI_PAR
	K1	IRDY	39 37 26 24 12 PCI_IRDY_L
	L2	SERR	17 CBUS_PCI_SERR_L
	F2	IDSEL	CBUS_PCI_IDSEL
	K3	PERR	17 CBUS_PCI_PERR_L
	J1	FRAME	39 37 26 24 12 PCI_FRAME_L
	L1	STOP	39 37 26 24 12 PCI_STOP_L
	J3	TRDY	39 37 26 24 12 PCI_TRDY_L
	K2	DEVSEL	39 37 26 24 12 PCI_DEVSEL_L
	G3	PRST	CBUS_PCI_RESET_L
	C2	REQ	12 CBUS_PCI_REQ_L
	C1	GNT	12 CBUS_PCI_GNT_L
	G1	PCLK	36 12 CLK33M_CBUS
NC	M9	SPKROUT	
NC	M8	RI_OUT/PME	
	N10	SUSPEND	17 CBUS_SUSPEND_PU
	K7	MFUNC0	14 CBUS_INT_L
	N9	MFUNC1	17 CBUS_MFUNC1_PD
	L9	MFUNC2	17 CBUS_MFUNC2_PD
	K10	MFUNC3	17 CBUS_MFUNC3_PD
	M10	MFUNC4	17 CBUS_MFUNC4_PD
	N12	MFUNC5	17 CBUS_MFUNC5_PD
	L10	MFUNC6	17 CBUS_MFUNC6_PD
	L11	GRST	
	B11	VCCCB	
	L3	VCCP	
	N13	VCCD0*	CBUS_VCCD0_L
	L12	VCCD1*	CBUS_VCCD1_L
	K9	VPPD0	CBUS_VPPD0
	M11	VPPD1	CBUS_VPPD1
	L13	CD1*/CCD1*	CBUS_DET_1_L 17 39
	B5	CD2*/CCD2*	CBUS_DET_2_L 17 39
	F12	IORD*/CAD13	CBUS_IORD_L 17
	C11	IOWR*/CAD15	CBUS_IOWR_L 17
	G10	OE*/CAD11	CBUS_OE_L 17
	H13	CE1*/CC/BE0*	CBUS_CE1_L 17
	B2	VS1*/CVS1	CBUS_VS1 17
	A9	VS2*/CVS2	CBUS_VS2 17
	D13	WE*/CGNT*	CBUS_WE_L 17
	A6	RDY/IREQ*/CINT*	CBUS_READY 17
	D8	RESET/CRST*	CBUS_RESET_L 17
	A8	REG*/CC/BE3*	CBUS_REG_L 17
	C6	BVD1/CSTSCHG/STSCHG*/RI*	CBUS_BVD1_L 17
	D6	BVD2/SPKR*/CAUDIO	CBUS_BVD2_L 17
INTEGRATED PULL-UP	A5	WP/IOIS16*/CCLKRUN*	CBUS_WP_L 17
	G13	CE2/CAD10*	CBUS_CE2_L 17
	B8	INPACK/CREQ*	CBUS_INPACK_L 17
	B6	WAIT/CSERR*	CBUS_WAIT_L 17
	C7	A0/CAD26	CBUS_ADDR<0> 17
	D7	A1/CAD25	CBUS_ADDR<1> 17
	B7	A2/CAD24	CBUS_ADDR<2> 17
	D10	A3/CAD23	CBUS_ADDR<3> 17
	B12	A4/CAD22	CBUS_ADDR<4> 17
	C8	A5/CAD21	CBUS_ADDR<5> 17
	C9	A6/CAD20	CBUS_ADDR<6> 17
	A12	A7/CAD18	CBUS_ADDR<7> 17
	E11	A8/CC/BE1*	CBUS_ADDR<8> 17
	F11	A9/CAD14	CBUS_ADDR<9> 17
	G11	A10/CAD9	CBUS_ADDR<10> 17
	G12	A11/CAD12	CBUS_ADDR<11> 17
	D9	A12/CC/BE2*	CBUS_ADDR<12> 17
	E12	A13/CPAR	CBUS_ADDR<13> 17
	D12	A14/CPERR*	CBUS_ADDR<14> 17
	C10	A15/CIRDY*	CBUS_ADDR<15> 17
	B13	A16/CCLK	CBUS_ADDR_16_UF
	F10	A17/CAD16	CBUS_ADDR<17> 17
	E13	A18/RSVD	CBUS_ADDR<18> 17
	A13	A19/CBLOCK*	CBUS_ADDR<19> 17
	E10	A20/CSTOP*	CBUS_ADDR<20> 17
	D11	A21/CDEVSEL*	CBUS_ADDR<21> 17
	C12	A22/CTRDY*	CBUS_ADDR<22> 17
	A10	A23/CFRAME*	CBUS_ADDR<23> 17
	B10	A24/CAD17	CBUS_ADDR<24> 17
	B9	A25/CAD19	CBUS_ADDR<25> 17
	A4	D0/CAD27	CBUS_DATA<0> 17
	C4	D1/CAD29	CBUS_DATA<1> 17
	A3	D2/RSVD	CBUS_DATA<2> 17
	K11	D3/CAD0	CBUS_DATA<3> 17
	K12	D4/CAD1	CBUS_DATA<4> 17
	J13	D5/CAD3	CBUS_DATA<5> 17
	J10	D6/CAD5	CBUS_DATA<6> 17
	H12	D7/CAD7	CBUS_DATA<7> 17
	C5	D8/CAD28	CBUS_DATA<8> 17
	B4	D9/CAD30	CBUS_DATA<9> 17
	B3	D10/CAD31	CBUS_DATA<10> 17
	M12	D11/CAD2	CBUS_DATA<11> 17
	J11	D12/CAD4	CBUS_DATA<12> 17
	K13	D13/CAD6	CBUS_DATA<13> 17
	J12	D14/RSVD	CBUS_DATA<14> 17
	H11	D15/CAD8	CBUS_DATA<15> 17

R750 47 5% 1/16W MF 402 — CBUS_ADDR<16> 17

R764 47 5% 1/16W MF 402 — IO_RESET_L 30 27 26 23

R766 47 5% 1/16W MF 402 — MAIN_RESET_L 39 30 26 24 20 18 17 14

RP39 10K 5% 1/32W 25V SM

CBUS_MFUNC1_PD 17
CBUS_MFUNC2_PD 17
CBUS_MFUNC3_PD 17
CBUS_MFUNC4_PD 17
CBUS_MFUNC5_PD 17
CBUS_MFUNC6_PD 17

R767 22 5% 1/16W MF 402

A2 A11 D1 F13 H4 K8 M13 N2 — GND

TI REFERENCE SCHEMATIC DID NOT HAVE BULK ON +VCC_CBUS_SW

C783 2.2UF 20% 10V CERM 805

C776 2.2UF 20% 10V CERM 805

PC CARD/CARDBUS CONNECTOR

CRITICAL
J9
QT500806-L111
M-ST-SM1

	84		81
	2	1	CBUS_DATA<3> 17
39 17 CBUS_DET_1_L	4	3	CBUS_DATA<4> 17
17 CBUS_DATA<11>	6	5	CBUS_DATA<5> 17
17 CBUS_DATA<12>	8	7	CBUS_DATA<6> 17
17 CBUS_DATA<13>	10	9	
	12	11	CBUS_DATA<7> 17
17 CBUS_DATA<14>	14	13	CBUS_CE1_L 17
17 CBUS_DATA<15>	16	15	CBUS_ADDR<10> 17
17 CBUS_CE2_L	18	17	CBUS_OE_L 17
17 CBUS_VS1	20	19	
	22	21	CBUS_ADDR<11> 17
17 CBUS_IORD_L	24	23	CBUS_ADDR<9> 17
17 CBUS_IOWR_L	26	25	CBUS_ADDR<8> 17
17 CBUS_ADDR<17>	28	27	CBUS_ADDR<13> 17
17 CBUS_ADDR<18>	30	29	
	32	31	CBUS_ADDR<14> 17
17 CBUS_ADDR<19>	34	33	CBUS_WE_L 17
17 CBUS_ADDR<20>	36	35	CBUS_READY 17
17 CBUS_ADDR<21>	38	37	+VCC_CBUS_SW 17 38
38 17 +VCC_CBUS_SW	40	39	
	42	41	+VPP_CBUS_SW 17 38
38 17 +VPP_CBUS_SW	44	43	CBUS_ADDR<16> 17
17 CBUS_ADDR<22>	46	45	CBUS_ADDR<15> 17
17 CBUS_ADDR<23>	48	47	CBUS_ADDR<12> 17
17 CBUS_ADDR<24>	50	49	
	52	51	CBUS_ADDR<7> 17
17 CBUS_ADDR<25>	54	53	CBUS_ADDR<6> 17
17 CBUS_VS2	56	55	CBUS_ADDR<5> 17
17 CBUS_RESET_L	58	57	CBUS_ADDR<4> 17
17 CBUS_WAIT_L	60	59	
	62	61	CBUS_ADDR<3> 17
17 CBUS_INPACK_L	64	63	CBUS_ADDR<2> 17
17 CBUS_REG_L	66	65	CBUS_ADDR<1> 17
17 CBUS_BVD2_L	68	67	CBUS_ADDR<0> 17
17 CBUS_BVD1_L	70	69	
	72	71	CBUS_DATA<0> 17
17 CBUS_DATA<8>	74	73	CBUS_DATA<1> 17
17 CBUS_DATA<9>	76	75	CBUS_DATA<2> 17
17 CBUS_DATA<10>	78	77	CBUS_WP_L 17
39 17 CBUS_DET_2_L	80	79	
	83	82	

CARDBUS

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 17 OF 44	

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
338S0133	1	IC,ATI,M10,NO HEATSPREADER	U44	CRITICAL	?

OMIT
CRITICAL

U44
RAGE_MOBILITY
M10-CSP64
64MB
BGA
(1 OF 6)

AGP_AD<31> AB30 AD31
AGP_AD<30> AB27 AD30
AGP_AD<29> AA29 AD29
AGP_AD<28> AB28 AD28
AGP_AD<27> AA30 AD27
AGP_AD<26> AA27 AD26
AGP_AD<25> Y30 AD25
AGP_AD<24> AA28 AD24
AGP_AD<23> W30 AD23
AGP_AD<22> W27 AD22
AGP_AD<21> V30 AD21
AGP_AD<20> V28 AD20
AGP_AD<19> V29 AD19
AGP_AD<18> V27 AD18
AGP_AD<17> U30 AD17
AGP_AD<16> U28 AD16
AGP_AD<15> R27 AD15
AGP_AD<14> R29 AD14
AGP_AD<13> P28 AD13
AGP_AD<12> P30 AD12
AGP_AD<11> P27 AD11
AGP_AD<10> P29 AD10
AGP_AD<9> N28 AD9
AGP_AD<8> N30 AD8
AGP_AD<7> M30 AD7
AGP_AD<6> M27 AD6
AGP_AD<5> M29 AD5
AGP_AD<4> L28 AD4
AGP_AD<3> L30 AD3
AGP_AD<2> L27 AD2
AGP_AD<1> L29 AD1
AGP_AD<0> K28 AD0

AGP_CBE<3> W28 CBEB3
AGP_CBE<2> U29 CBEB2
AGP_CBE<1> R30 CBEB1
AGP_CBE<0> N27 CBEB0

CLK66M_GPU_AGP AG30 PCICLK
AGP_FRAME_L U27 FRAMEB
AGP_IRDY_L T30 IRDYB
AGP_TRDY_L T28 TRDYB
AGP_STOP_L T27 STOPB
AGP_DEVSEL_L T29 DEVSELB
AGP_PAR R28 PAR
AGP_REQ_L AF29 REQB
AGP_GNT_L AF27 GNTB
AGP_INT_L AH29 INTAB
AGP_ATI_RESET_L AH30 RSTB
AGP_WBF_L AE27 WBF

AGP_ATI_VREFG AK3 VREFG
AGP_ATI_VREF D8 VREF

AD_STB0 N29 AGP_AD_STB<0>
AD_STB1 W29 AGP_AD_STB<1>
AD_STBB0 M28 AGP_AD_STB_L<0>
AD_STBB1 Y29 AGP_AD_STB_L<1>
AGP_BUSYB AG28 AGP_BUSY_L
AGPREF K30
AGPTEST K29 GPU_AGP_TEST
AGP8X_DETB U25 AGP8X_DET_PU
SUS_STAT AJ28 AGP_SUS_STAT_L_PU
ST0 AF30 AGP_ST<0>
ST1 AF28 AGP_ST<1>
ST2 AE29 AGP_ST<2>
SBA7 AC28 AGP_SBA<7>
SBA6 AB29 AGP_SBA<6>
SBA5 AC27 AGP_SBA<5>
SBA4 AC30 AGP_SBA<4>
SBA3 AD27 AGP_SBA<3>
SBA2 AD30 AGP_SBA<2>
SBA1 AE28 AGP_SBA<1>
SBA0 AD29 AGP_SBA<0>
RBFB AE30 AGP_RBF_L
STP_AGPB AG29 AGP_STP_L
SB_STB AC29 AGP_SB_STB
SB_STBS AD28 AGP_SB_STB_L
RSTB_MSK AD24 ATI_RSTB_MSK
DBI_LO Y25 ATI_DBI_LO_PU
DBI_HI Y27 ATI_DBI_HI_PU

C19 P2 B18 P4 A19 R3 A18 R4 D19 P1 G29 G27 B29 C26 A16 C11 → VSS

A10 C5 A3 G4 E2 U2 V4 AB2 AC4 B23 K2 A23 K1 B22 L2 A22 L1 → VSS

D+ AC10 GPU_THERM_DP
D- AC11 GPU_THERM_DM
+GPU_MEM 18 21 38
TEST_YCLK E8
TEST_MLCK J6 (PULL-UP to GPU_MEM_IO)
MEMTEST C8 ATI_MEMTEST
PLLTEST AC22 NC

ATI_MEMVMODE0 B7 MEMVMODE0
ATI_MEMVMODE1 B6 MEMVMODE1

INT_AGP_VREF 12 38

(PLACE C1002 CLOSE TO AGPREF PIN)

OMIT

U44
RAGE_MOBILITY
M10-CSP64
64MB
BGA
(6 OF 6)

M2 P3 A21 B19 M15 N15 P15 R15 T15 T12 T13 T14 W16 V16 U16 T16 R16 R17 R18 R19 → VSS
U6 AE15 F18 P25 → VDDCI

OMIT

U44
RAGE_MOBILITY
M10-CSP64
64MB
BGA
(2 OF 6)

B26 A26 B25 A25 C22 D21 C21 D20 C20 D22 C23 D23 A27 B27 → VSS
H2 H1 J2 J1 K4 K3 L4 M3 L3 M4 N2 N1 N4 N3 G30 G28 B30 D26 D16 B15 D11 B10 D5 B3 G3 E1 U1 V3 AB1 AC3 J30 J29 H30 H29 F30 F29 E30 E29 J28 J27 H28 H27 F28 F27 E28 E27 D30 D29 C30 C29 A30 A29 A28 B28 D28 C28 D27 C27 D25 C25 D24 C24 D18 C18 D17 C17 D15 C15 D14 C14 B17 → VSS

A17 B16 A16 B14 A14 B13 A13 D13 C13 D12 C12 D10 C10 D9 C9 B12 A12 B11 A11 B9 A9 B8 A8 C7 D7 C6 D6 C4 D4 C3 D3 A5 B5 A4 B4 A2 B2 A1 B1 E4 E3 F3 F4 H3 H4 J3 J4 C1 C2 D1 D2 F1 F2 G1 G2 R1 R2 T1 T2 V1 V2 W1 W2 T3 T4 U3 U4 W3 W4 Y3 Y4 Y1 Y2 AA1 AA2 AC1 AC2 AD1 AD2 AA3 AA4 AB3 AB4 AD3 AD4 AE3 AE4 → VSS

38 21 19 18 12 +3V_GPU
38 21 19 18 16 15 12 +1_5V_AGP
38 21 19 18 12 +3V_GPU
38 21 19 18 12 +3V_GPU
38 21 19 20 +1_8V_GPU
39 38 19 GPU_VCORE
+GPU_VCORE_VDDCI

R119 47 5% 1/16W MF 402
R127 10K 5% 1/16W MF 402
R159 20K 5% 1/16W MF 402
R172 20K 5% 1/16W MF 402
R158 0 5% 1/16W MF 402
R126 47K 5% 1/16W MF 402
R138 47K 5% 1/16W MF 402
R118 45.3 1% 1/16W MF 402

C62 0.1uF 20% 16V CERM 402
C63 0.01uF 20% 16V CERM 402
C64 0.01uF 20% 16V CERM 402
C67 10uF 20% 6.3V CERM 805
C65 0.01uF 20% 16V CERM 402
C68 0.01uF 20% 16V CERM 402
C66 0.01uF 20% 16V CERM 402
C69 0.01uF 20% 16V CERM 402

L2
60-OHM-EMI
SM

MAIN_RESET_L IS TOGGLED FOR SLEEP
24 20 17 14 MAIN_RESET_L
R53 47 5% 1/16W MF 402
R54 10K 5% 1/16W MF 402

21 19 18 12 +3V_GPU
R43 1K 1% 1/16W MF 402
R44 1K 1% 1/16W MF 402
38 21 18 +GPU_MEM
R45 1K 1% 1/16W MF 402
R46 1K 1% 1/16W MF 402
C11 0.1uF 20% 16V CERM 402
C37 10uF 20% 6.3V CERM 805
PLACE VERF_VOLTAGE DIVIDER CLOSE TO ATI M10 VREF PIN

ATI_MEMIO_LO R55 4.7K 5% 1/16W MF 402
ATI_MEMIO_HI R104 4.7K 5% 1/16W MF 402
ATI_MEMIO_HI R70 4.7K 5% 1/16W MF 402
ATI_MEMIO_LO R105 4.7K 5% 1/16W MF 402

FOR 2.5 VDDR1
MEMVMODE0=1.8V
MEMVMODE1=GND
FOR 1.8 VDDR1
MEMVMODE0=GND
MEMVMODE1=1.8V

27M OSC

(PLACE THE OSCILLATOR AND R189 AND R195 CLOSE TO ATI PIN AJ29)

+3V_SLEEP
L4
FERR-EMI-100-OHM
SM
38 +3V_ATI_OSC_SLEEP
C77 0.1uF 20% 16V CERM 402
C78 4.7uF 20% 6.3V CERM 805
NO STUFF
R188 100K 5% 1/16W MF 402
CRITICAL
VCC
G2
27.0000M
OSC SM-1
OE
OUT
GND
ATI_OSC_OE
ATI_CLK27M_OSC
(PLACE R200 CLOSE TO OSC)
GPU_SS
R200 0 5% 1/16W MF 402
ATI_CLK27M_OSC_SS 18
R189 287 1% 1/16W MF 402
ATI_CLK27M_IN 19
R195 162 1% 1/16W MF 402

S0=1;S1=M => -1.5% DOWN-SPREAD
SPREAD SPECTRUM SUPPORT

+3V_SLEEP
GPU_SS
L3
FERR-EMI-100-OHM
SM
38 +3V_ATI_SS
GPU_SS C70 10uF 20% 6.3V CERM 805
GPU_SS C71 0.1uF 20% 16V CERM 402
NO STUFF
R173 0 5% 1/16W MF 402
GPU_SS
R181 0 5% 1/16W MF 402
GPU_SS 7 CRITICAL
VDD
U47
CY25811
SOI
18 ATI_CLK27M_OSC_SS 1 XIN/CLKIN
NC 8 XOUT
SSCLK 5 ATI_SSCLK_UF
NC 6 FRSEL
CY25811_S1 3 S1
CY25811_S0 4 S0
VSS 2
GPU_SS
R201 33 5% 1/16W MF 402
ATI_SSCLK_IN 19
NO STUFF
R37 0 5% 1/16W MF 402
NO STUFF
R38 0 5% 1/16W MF 402

M10 AGP INTERFACE

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 18 OF 44	

TMDS TERMINATION

TERMINATION NETWORK SHOULD BE CONNECTED AS SHOWN
CMF LINE SHOULD BE ROUTED AS 4MIL SURFACE
TRACE SO THAT IT MAY BE CUT BETWEEN CAPS

U44 RAGE_MOBILITY M10-CSP64 64MB BGA (3 OF 6)

GPU_DVOD<0> AJ5 ZV_LCDDATA0
GPU_DVOD<1> AK5 ZV_LCDDATA1
GPU_DVOD<2> AG6 ZV_LCDDATA2
GPU_DVOD<3> AH6 ZV_LCDDATA3
GPU_DVOD<4> AJ6 ZV_LCDDATA4
GPU_DVOD<5> AK6 ZV_LCDDATA5
GPU_DVOD<6> AG7 ZV_LCDDATA6
GPU_DVOD<7> AH7 ZV_LCDDATA7
GPU_DVOD<8> AJ7 ZV_LCDDATA8
GPU_DVOD<9> AK7 ZV_LCDDATA9
GPU_DVOD<10> AG8 ZV_LCDDATA10
GPU_DVOD<11> AH8 ZV_LCDDATA11
NC AJ8 ZV_LCDDATA12
NC AK8 ZV_LCDDATA13
NC AG9 ZV_LCDDATA14
NC AH9 ZV_LCDDATA15
NC AJ9 ZV_LCDDATA16
NC AK9 ZV_LCDDATA17
NC AG10 ZV_LCDDATA18
NC AH10 ZV_LCDDATA19
ZV_LCDDATA20_PU AJ10 ZV_LCDDATA20
NC AK10 ZV_LCDDATA21
NC AG11 ZV_LCDDATA22
NC AH11 ZV_LCDDATA23

GPU_DVO_VSYNC AJ4 ZV_LCDCNTL0
GPU_DVO_HSYNC AK4 ZV_LCDCNTL1
GPU_DVOD_DE AH5 ZV_LCDCNTL2
GPU_DVO_CLKP AG5 ZV_LCDCNTL3

ATI_AGP_FBSKEW<0> AJ2 GPIO0
ATI_AGP_FBSKEW<1> AK2 GPIO1
ATI_X1CLK_SKEW<0> AK1 GPIO2
ATI_X1CLK_SKEW<1> AH3 GPIO3
ATI_BUS_CFG<0> AH2 GPIO4
ATI_BUS_CFG<1> AJ1 GPIO5
ATI_BUS_CFG<2> AF4 GPIO6
ATI_GPIO7_SPN (NO ICT TEST) AH1 GPIO7
ATI_GPIO8_PD AG3 GPIO8
ATI_GPIO9_SPN (NO ICT TEST) AF3 GPIO9
ATI_GPIO10_SPN (NO ICT TEST) AG2 GPIO10
ATI_GPIO11_SPN (NO ICT TEST) AF2 GPIO11
ATI_GPIO12_SPN (NO ICT TEST) AG1 GPIO12
ATI_GPIO13_SPN (NO ICT TEST) AF1 GPIO13
HPD_PWR_SNS_EN AE2 GPIO14
GPU_VCORE_CNTL_L AE1 GPIO15
ATI_SSCLK_IN M1 GPIO16

ATI_TMDS_DN<0> AJ13 TX0M
ATI_TMDS_DP<0> AK13 TX0P
ATI_TMDS_DN<1> AJ14 TX1M
ATI_TMDS_DP<1> AK14 TX1P
ATI_TMDS_DN<2> AJ15 TX2M
ATI_TMDS_DP<2> AK15 TX2P
ATI_TMDS_CLKN AJ12 TXCM
ATI_TMDS_CLKP AK12 TXCP

ATI_CLK27M_IN AJ29 XTALIN
NC AJ30 XTALOUT
ATI_TESTEN AH24 TESTEN
NC AJ26 SSIN

VSS B24
VSS B20
VSS A24
VSS A20
VSS B21

ROMCSB AE5 NC
R AK28 GPU_R
G AK27 GPU_G
B AK26 GPU_B
VSYNC AG27 ATI_VSYNC
V2SYNC AG25 NC
HSYNC AG26 ATI_HSYNC
H2SYNC AG24 NC
RSET AK25 ATI_RSET
R2SET AJ24 ATI_R2SET
Y_G AK23 GPU_Y
C_R AK24 GPU_C
COMP_B AK22 GPU_COMP
DIGON AE13 FP_PWR_EN
BLON AF13 INV_ON_PWM
HPD1 AF11 GPU_HPD
AUXWIN AJ27 GPU_AUXWIN

DDC1DATA AH28 GPU_DVI_DDC_DATA
DDC1CLK AH27 GPU_DVI_DDC_CLK
DDC2DATA AE12 LVDS_DDC_DATA
DDC2CLK AF12 LVDS_DDC_CLK
DDC3DATA AH26 SI_DDC_DATA
DDC3CLK AH25 SI_DDC_CLK

TXOUT_U0N AH18 LVDS_U0N
TXOUT_U0P AG18 LVDS_U0P
TXOUT_U1N AH19 LVDS_U1N
TXOUT_U1P AG19 LVDS_U1P
TXOUT_U2N AH20 LVDS_U2N
TXOUT_U2P AG20 LVDS_U2P
TXOUT_U3N AH22 LVDS_U3N_TP (NO ICT TEST)
TXOUT_U3P AG22 LVDS_U3P_TP (NO ICT TEST)
TXCLK_UN AH21 CLKLVDS_UN
TXCLK_UP AG21 CLKLVDS_UP
TXOUT_L0N AK16 LVDS_L0N
TXOUT_L0P AJ16 LVDS_L0P
TXOUT_L1N AK17 LVDS_L1N
TXOUT_L1P AJ17 LVDS_L1P
TXOUT_L2N AK18 LVDS_L2N
TXOUT_L2P AJ18 LVDS_L2P
TXOUT_L3N AK20 LVDS_L3N_TP (NO ICT TEST)
TXOUT_L3P AJ20 LVDS_L3P_TP (NO ICT TEST)
TXCLK_LN AK19 CLKLVDS_LN
TXCLK_LP AJ19 CLKLVDS_LP
SSOUT AJ25 NC

OMIT

+1.8V_GPU +3V_GPU
EXT_TMDS R228 10K 5% 1/16W MF 402
INT_TMDS R234 10K 5% 1/16W MF 402

NO STUFF +3V_GPU
R223 10K 5% 1/16W MF 402
R221 1K 5% 1/16W MF 402

R229 1K 5% 1/16W MF 402

R240 75 1% 1/16W MF 402
R246 75 1% 1/16W MF 402
R249 75 1% 1/16W MF 402

R256 715 1% 1/16W MF 402
R257 499 1% 1/16W MF 402

R245 75 1% 1/16W MF 402
R248 75 1% 1/16W MF 402
R254 75 1% 1/16W MF 402

R711 10K 5% 1/16W MF 402
R247 10K 5% 1/16W MF 402
R253 10K 5% 1/16W MF 402

+1.5V_AGP
Q77 SI3446DV TSOP
GPU_CORE_OK
+GPU_VDD15_UF
C166 1000pF 10% 25V X7R 402

L24 FERR-220-OHM 0805
+1.5V_GPU_VDD15 (500mA)

C222 0.01uF 20% 16V CERM 402
C256 0.01uF 20% 16V CERM 402
C299 0.01uF 20% 16V CERM 402
C305 0.01uF 20% 16V CERM 402
C328 10uF 20% 6.3V CERM 805
C232 0.01uF 20% 16V CERM 402
C269 0.01uF 20% 16V CERM 402
C300 0.01uF 20% 16V CERM 402
C306 0.01uF 20% 16V CERM 402

U44 RAGE_MOBILITY M10-CSP64 64MB BGA (5 OF 6)

F12 L6 T6 AB6 F17 G25 R25 AB25 VDD15
AJ3 AF25 AG4 AH4 AF5 F6 G6 H6 P6 AD26 V6 W6 AC6 AD6 AE6 F7 F10 AE10 F11 AE11 F13 F14 AE14 AF14 W26 AF15 AE17 AC25 AE18 F23 F24 AE24 F25 M25 N25 W25 V25 VDDC
OMIT
G7 G8 G9 G10 G11 G12 G13 G14 G15 G16 G17 G18 G19 G20 G21 G22 G23 G24 H7 H8 H23 H24 J7 J24 K7 K24 L7 L24 M7 M24 N7 N24 P7 P24 R7 R24 T7 T24 U7 U24 V7 V24 W7 W24 Y7 Y24 AA7 AA24 AB7 AB24 AC7 AC8 AC23 AC24 AD7 AD8 AD9 AD10 AD11 AD12 AD13 AD14 AD15 AD16 AD17 AD18 AD19 AD20 AD21 AD22 AD23 VSS

GPU VCORE - 1.2V

(PUT ALL CAPs BELOW ATI ASIC)

C167 10uF 20% 6.3V CERM 805
C219 10uF 20% 6.3V CERM 805
C252 0.22uF 20% 6.3V CERM 402
C270 0.22uF 20% 6.3V CERM 402
C301 0.22uF 20% 6.3V CERM 402
C307 0.22uF 20% 6.3V CERM 402
C329 0.22uF 20% 6.3V CERM 402
C332 0.22uF 20% 6.3V CERM 402
C186 0.22uF 20% 6.3V CERM 402
C220 0.22uF 20% 6.3V CERM 402
C253 0.22uF 20% 6.3V CERM 402
C271 0.22uF 20% 6.3V CERM 402
C302 0.22uF 20% 6.3V CERM 402
C311 0.22uF 20% 6.3V CERM 402
C330 0.22uF 20% 6.3V CERM 402
C333 0.22uF 20% 6.3V CERM 402
C187 0.22uF 20% 6.3V CERM 402
C221 0.22uF 20% 6.3V CERM 402
C254 0.22uF 20% 6.3V CERM 402
C282 0.22uF 20% 6.3V CERM 402
C303 0.22uF 20% 6.3V CERM 402
C326 0.22uF 20% 6.3V CERM 402
C331 0.22uF 20% 6.3V CERM 402
C338 0.22uF 20% 6.3V CERM 402

M10 Power Shut down Sequencing

XW21 SM
DP6 BAS16TW SOT-363
+1.8V_ATI_PVDD
+2.5V_SLEEP_NECK
+2.5V_SLEEP
XW24 SM
XW20 SM
+1.8V_PVDD_NECK
+1.5V_AGP_NECK
XW23 SM
+1.5V_AGP
GPU_VCORE_NECK
+GPU_VDD15_NECK

R258 10K 5% 1/16W MF 402
R260 10K 5% 1/16W MF 402
NO STUFF R262 10K 5% 1/16W MF 402
NO STUFF R265 10K 5% 1/16W MF 402
NO STUFF R269 10K 5% 1/16W MF 402
NO STUFF R271 10K 5% 1/16W MF 402
NO STUFF R273 10K 5% 1/16W MF 402
NO STUFF R259 10K 5% 1/16W MF 402
NO STUFF R261 10K 5% 1/16W MF 402
NO STUFF R263 10K 5% 1/16W MF 402
NO STUFF R266 10K 5% 1/16W MF 402
NO STUFF R270 10K 5% 1/16W MF 402
NO STUFF R272 10K 5% 1/16W MF 402
NO STUFF R274 10K 5% 1/16W MF 402

(GPIO0) ATI_AGP_FBSKEW<0>
(GPIO1) ATI_AGP_FBSKEW<1>
(GPIO2) ATI_X1CLK_SKEW<0>
(GPIO3) ATI_X1CLK_SKEW<1>
(GPIO4) ATI_BUS_CFG<0>
(GPIO5) ATI_BUS_CFG<1>
(GPIO6) ATI_BUS_CFG<2>

GPU VCORE SUPPLY

+PBUS

R389 1M 5% 1/16W MF 402
R430 1 5% 1/16W MF 603
R339 576K 1% 1/16W MF 402

C762 4.7UF 20% 25V CERM 1206
C766 4.7UF 20% 25V CERM 1206

Q51 SI7860DP SO-8-PWRPK CRITICAL

WHEN VCORE_CNTL HIGH => 1.2V
1.2V = 0.8V * (1 + R332 / (R331//R333))
WHEN VCORE_CNTL LOW => 1.0V
1.0V = 0.8V * (1 + R332 / R333)

+5V_MAIN
R306 100K 5% 1/16W MF 402
R316 100K 5% 1/16W MF 402
DP1 BAS16TW SOT-363
SLEEP_L_LS5
DCDC_EN
1778_SHDN_L_D3COLD
R294 10K 5% 1/16W MF 402
GPU_VCORE_PWR_SEQ
GPU_VCORE_SEQ_L
Q6 2N3904 SM
Q5 2N3904 SM
R203 33K 5% 1/16W MF 402
GPU_VCORE_SEQ

NO STUFF R388 0 5% 1/16W MF 402
NO STUFF R341 63.4K 1% 1/16W MF 402
C473 4.7UF 20% 10V CERM 1206
1778_GND
R390 0 5% 1/16W MF 402
R236 100K 5% 1/16W MF 402
C494 0.1UF 20% 25V CERM 603
C514 0.1UF 20% 25V CERM 603
R340 20K 1% 1/16W MF 402
1778_ITH_RC
C448 470PF 10% 50V CERM 402
C451 220PF 5% 25V CERM 402
R311 0 5% 1/16W MF 402
R332 0 1% 1/16W MF 402
C483 0.1UF 20% 10V CERM 402

U16 LTC1778 SSOP CRITICAL
RUN/SS ITH VRNG FCB PGOOD SGND PGND
EXT INT VIN VCC VCC
ION BOOST TG SW BG VFB PGND

D5 SM MBR0540
R416 2.2 5% 1/16W MF 603
NO STUFF C882 0.0022UF 10% 50V CERM 402
OMIT XW2 SM

Q48 SI7892DP SO-8-PWRPK CRITICAL
L30 2.1UH-11A SM
D24 SMB B340LB

C708 22uF 20% 16V CERM 1210
C721 330UF 20% 6.3V POLY SMD
C719 330UF 20% 6.3V POLY SMD
C720 330UF 20% 6.3V POLY SMD

R352 4.99K 1% 1/16W MF 402
R451 18.2K 1% 1/16W MF 402
R351 20K 1% 1/16W MF 402
R804 1.82K 1% 1/16W MF 402
C902 0.1UF 20% 16V CERM 402
R307 100K 5% 1/16W MF 402
R410 10K 5% 1/16W MF 402
C515 0.1UF 20% 16V CERM 402
Q80 2N7002DW SOT-363
Q80 2N7002DW SOT-363

HIGH_VCORE_DIV
HIGH_VCORE
VCORE_CNTL_RC
GPU_VCORE_CNTL

M10 CORE PWR/LVDS/TMDS

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 19 OF 44	

SIL1162 DVI TRANSMITTER



NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B

SCALE	SHT
NONE	20 OF 44

GPU PLL - 1.8V

U55 MM1571J (100mA MAX) SOT-25A CRITICAL
(Total PVDD = 66mA)
+2_5V_GPU → VIN; VOUT → +1_8V_ATI_PVDD; GPU_CORE_OK; CONT; NOISE; ATI_PVDD_BYP; GND
C889 1UF 10% 6.3V CERM 603
C379 0.01uF 20% 16V CERM 402
C380 10uF 20% 6.3V CERM 805

L65 FERR-220-OHM 0402 — +1_8V_GPU_PLL
C438 10uF 20% 6.3V CERM 805
C865 0.1uF 20% 10V CERM 402
C716 0.01uF 20% 16V CERM 402 (21mA)

L66 FERR-220-OHM 0402 — +1_8V_GPU_AVDD (AVDD+VDDDI=75mA)
C415 10uF 20% 6.3V CERM 805
C437 0.01uF 20% 16V CERM 402
C870 0.01uF 20% 16V CERM 402

L58 FERR-220-OHM 0402 — +2_5V_GPU_A2VDD (140mA)
C360 10uF 20% 6.3V CERM 805
C364 0.01uF 20% 16V CERM 402
C374 0.01uF 20% 16V CERM 402

L55 FERR-220-OHM 0402 — +1_8V_GPU_AVDDQ (2mA)
C339 10uF 20% 6.3V CERM 805
C363 0.01uF 20% 16V CERM 402

L56 FERR-220-OHM 0402 — +1_8V_GPU_VDDDI (AVDD+VDDDI=75mA)
C358 10uF 20% 6.3V CERM 805
C361 0.01uF 20% 16V CERM 402
C372 0.01uF 20% 16V CERM 402

L57 FERR-220-OHM 0402 — +GPU_MCLK
C359 10uF 20% 6.3V CERM 805
C362 0.01uF 20% 16V CERM 402
C373 0.01uF 20% 16V CERM 402

+1_5V_SLEEP → R722 0 5% 1/10W FF 805 → +1_5V_AGP
1.5V

+1_8V_SLEEP → R284 0 5% 1/16W FF 805 → +1_8V_GPU
1.8V

+1_8V_SLEEP → R729 0 5% 1/4W FF 1210 → ATI_MEMIO_LO
+2_5V_SLEEP → R728 0 5% 1/4W FF 1210 → ATI_MEMIO_HI → +GPU_MEM
1.8V 2.5V

+2_5V_SLEEP → R721 0 5% 1/10W FF 805 → +2_5V_GPU
2.5V

+3V_SLEEP → R299 0 5% 1/10W FF 805 → +3V_GPU
3.3V

AGP 4X I/O - 1.5V

+1_5V_AGP_GPU
L59 FERR-10-OHM-500MA SM
C381 0.1uF 20% 10V CERM 402
C420 0.1uF 20% 10V CERM 402
C446 0.1uF 20% 10V CERM 402
C543 0.1uF 20% 10V CERM 402
C871 10uF 20% 6.3V CERM 805 (20mA)
C382 0.01uF 20% 16V CERM 402
C421 0.01uF 20% 16V CERM 402
C447 0.01uF 20% 16V CERM 402
C671 0.01uF 20% 16V CERM 402

MEMORY CORE - 2.5V

+GPU_MEM
L63 FERR-220-OHM 0805 — +GPU_MEMCORE (1800mA)
C383 0.1uF 20% 10V CERM 402
C425 0.1uF 20% 10V CERM 402
C866 0.1uF 20% 10V CERM 402
C672 0.1uF 20% 10V CERM 402
C715 10uF 20% 6.3V CERM 805
C408 0.01uF 20% 16V CERM 402
C426 0.01uF 20% 16V CERM 402
C450 0.01uF 20% 16V CERM 402
C701 0.01uF 20% 16V CERM 402

LVDS PLL - 1.8V

+1_8V_ATI_PVDD
L61 FERR-220-OHM 0402 — +1_8V_GPU_PNLPLL (40mA)
C409 10uF 20% 6.3V CERM 805
C428 0.01uF 20% 16V CERM 402
C867 0.01uF 20% 16V CERM 402
EXT_TMDS R279 0 5% 1/16W MF 603 → +1_8V_GPU_TP_PLL
C877 10uF 20% 6.3V CERM 805
C878 0.01uF 20% 16V CERM 402

MEMORY PLL - 1.8V

+1_8V_ATI_PVDD
L62 FERR-220-OHM 0402 — +1_8V_GPU_MEMPLL
C411 10uF 20% 6.3V CERM 805
C429 0.01uF 20% 16V CERM 402

LVDS - 2.5V

+2_5V_GPU
L64 FERR-10-OHM-500MA SM — +2_5V_GPU_PNLTO (350mA)
C412 10uF 20% 6.3V CERM 805
C434 0.01uF 20% 16V CERM 402
C868 0.01uF 20% 16V CERM 402

LVDS/TMDS - 1.8V

+1_8V_GPU
L60 FERR-220-OHM 0402 — +1_8V_GPU_PNLTO (180mA)
C413 10uF 20% 6.3V CERM 805
C435 0.1uF 20% 10V CERM 402
C864 0.1uF 20% 10V CERM 402
C704 0.1uF 20% 10V CERM 402
C414 0.1uF 20% 10V CERM 402
C436 0.01uF 20% 16V CERM 402
C869 0.01uF 20% 16V CERM 402

GPU POWER SOURCES - 1.5V, 1.8V, 2.5V & 3.3V

U44 RAGE_MOBILITY M10-CSP64 64MB BGA (4 OF 6) OMIT

AK29 PVDD	AK30 PVSS	F5	AA5
AF23 AVDD0	AF22 AVSSQ	G5	AB5
AF24 AVDD1	AJ22 A2VSSQ	H5	AC5
AE21 A2VDD0	AE22 AVSSN0	J5	AD5
AF21 A2VDD1	AE23 AVSSN1	K5	G26
AJ23 A2VDDQ	AE19 A2VSSN0	L5	K6
AH23 VDD1DI	AE20 A2VSSN1	M5	R6
AF20 VDD2DI	AG23 VSS1DI	N5	Y6
F19 VDDRH0	AF19 VSS2DI	P5	AA6
N6 VDDRH1	F20 VSSRH0	R5	F8
K25	M6 VSSRH1	T5	F9
L25		U5	F15
T25		V5	F16
Y28		W5	F21
K27		Y5	F22
AA25			H25
K26			J25
L26			J26
M26			
N26			
P26			
R26 VDDP			
T26			
U26			
V26			
Y26			
AA26			
AB26			
AC26			

E5	AF6 VDDR4	AJ21 LPVSS	AE16 LVDDR_18
E6	AE7	AJ11 TPVSS	AF16 LVDDR_18
E12	AF7	A7 MPVSS	AG16 LVDDR_25
E13	AE8	AH16 LVSSR0	AF17 LVDDR_25
E18 VDDM	AF8	AG17 LVSSR1	AG12 TXVDDR0
E19	AE9	AH17 LVSSR2	AG13 TXVDDR1
E20	AF9	AF18 LVSSR3	AG14 TXVDDR2
E26	AF10 VDDR3	AH12 DVOVMODE	AG15 TXVDDR3
F26	AD25	AH13 TXVSSR1	
E7	AE25	AH14 TXVSSR2	
H26	AE26	AH15 TXVSSR3	
E9	AF26		
E10			
E11			
E14			
E15			
E16 VDDR1			
E17			
E21			
E22			
E23			
E24			
E25			

M10 SHUT DOWN POWER SEQUENCING

+2_5V_SLEEP → OMIT XW27 SM → +2_5V_SLEEP_NECK2 → DP7 BAS16TW SOT-363 → +3V_SLEEP_NECK → OMIT XW30 SM → +3V_SLEEP
+1_8V_SLEEP → OMIT XW28 SM → +1_8V_SLEEP_NECK → DP7 BAS16TW SOT-363
+1_5V_SLEEP → OMIT XW29 SM → +1_5V_SLEEP_NECK → DP7 BAS16TW SOT-363

U54 INT_TMDS MM1571J (1200mA) SOT-25A CRITICAL
INT_TMDS GPU_CORE_OK; +2_5V_GPU → VIN; VOUT → +1_8V_ATI_TPVDD; CONT; NOISE; ATI_TPVDD_BYP; GND
C879 1UF 10% 6.3V CERM 603
C880 0.01uF 10% 16V CERM 402
L69 FERR-220-OHM 0402 — +1_8V_GPU_TP_PLL

MEMORY I/O

+GPU_MEM
L67 FERR-220-OHM 0805 (1200mA) — +GPU_MEM_IO_FLT
C872 10uF 20% 6.3V CERM 805
C875 0.1uF 20% 10V CERM 402
C850 0.1uF 20% 10V CERM 402
C855 0.1uF 20% 10V CERM 402
C860 0.1uF 20% 10V CERM 402
C873 0.1uF 20% 10V CERM 402
C876 0.1uF 20% 10V CERM 402
C851 0.1uF 20% 10V CERM 402
C856 0.1uF 20% 10V CERM 402
C861 0.1uF 20% 10V CERM 402
C874 0.1uF 20% 10V CERM 402
C847 0.1uF 20% 10V CERM 402
C852 0.1uF 20% 10V CERM 402
C857 0.1uF 20% 10V CERM 402
C862 0.01uF 20% 16V CERM 402

3.3V IO SUPPLY

(Max Current varies, depends on usage)

+1_8V_DVO_F
C304 10uF 20% 6.3V CERM 805
C327 0.1uF 20% 10V CERM 402
C647 0.1uF 20% 10V CERM 402

INT_TMDS R268 0 5% 1/16W MF 603

+3V_GPU_FLT
L68 FERR-10-OHM-500MA SM — +3V_GPU
C722 10uF 20% 6.3V CERM 805
C848 0.1uF 20% 10V CERM 402
C853 0.1uF 20% 10V CERM 402
C858 0.1uF 20% 10V CERM 402
C863 0.1uF 20% 10V CERM 402
C725 0.1uF 20% 10V CERM 402
C849 0.1uF 20% 10V CERM 402
C854 0.1uF 20% 10V CERM 402
C859 0.1uF 20% 10V CERM 402

EXT_TMDS R255 0 5% 1/16W MF 402 → +1_8V_GPU
ATI_DVODMODE → INT_TMDS R251 0 5% 1/16W MF 402

EXT_TMDS
L16 FERR-10-OHM-500MA SM — +1_8V_GPU

M10 POWER

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 21 OF 44	

EXTERNAL VIDEO (DVI) INTERFACE

ANALOG FILTERING PLACE CLOSE TO CONNECTOR

FL2 CRITICAL LCFILTER SM-220MHZ — GPU_B → VGA_B
FL1 CRITICAL LCFILTER SM-220MHZ — GPU_G → VGA_G
FL3 CRITICAL LCFILTER SM-220MHZ — GPU_R → VGA_R
C685 3.3PF 0.25% 50V CERM 402
C676 3.3PF 0.25% 50V CERM 402
C684 3.3PF 0.25% 50V CERM 402

+3V_MAIN
CRITICAL U56 74AHC1G32 SM — ATI_HSYNC → VGA_HSYNC_BUF
R718 33 5% 1/16W MF 402 → VGA_HSYNC
CRITICAL U57 74AHC1G32 SM — ATI_VSYNC → VGA_VSYNC_BUF
R714 33 5% 1/16W MF 402 → VGA_VSYNC
VGA VSYNC BUFFERS

DVI DDC CURRENT LIMIT
(55mA requirement per DVI spec)
+5V_SLEEP → F1 0.5AMP-13.2V SM → +5V_DDC_SLEEP_UF → L23 400-OHM-EMI SM-1 → +5V_DDC_SLEEP
Isolation required for DVI power switch
D21 SM MBR0530 — DDC_CLK_ISO

CRITICAL J14 QH1112 F-RT-TH
TMDS_CONN_DN<0> → TMDS_CONN_DN<2>
TMDS_CONN_DN<1> → TMDS_CONN_DN<1>
TMDS_CONN_DP<0> → TMDS_CONN_DP<2>
TMDS_CONN_DP<1> → TMDS_CONN_DP<1>
(TMDS_DN<5>) → (TMDS_DN<4>)
(TMDS_DP<5>) → (TMDS_DP<4>)
(TMDS_DN<3>)
(TMDS_DP<3>)
DVI_DDC_CLK_UF
(+5V_DDC_SLEEP)
DVI_DDC_DATA_UF
TMDS_CONN_CLKP
TMDS_CONN_CLKN
VGA_VSYNC
DVI_HPD_UF
VGA_B
VGA_R
VGA_HSYNC
VGA_G

R661 4.7K 5% 1/16W MF 402 → DDC_CLK_ISO
R655 4.7K 5% 1/16W MF 402 → DDC_CLK_ISO
R670 100 5% 1/16W MF 402 → DVI_DDC_CLK
R649 100 5% 1/16W MF 402 → DVI_DDC_DATA
R650 100 5% 1/16W MF 402 → DVI_HPD
C706 100pF 5% 50V CERM 402
C669 100pF 5% 50V CERM 402
C1 100pF 5% 50V CERM 402
C710 0.01UF 20% 50V CERM 603
R706 0 5% 1/16W MF 402 — PLACE NEAR 3, 11 & 19
R1 0 5% 1/16W MF 402 — PLACE NEAR C5A & C5B
CHGND1

NOTE: Pulldown for DVI_HPD provided by DVI power switch interface
NOTE: DVI_HPD SHARES Q68 WITH ALS BECAUSE OF BOARD REAL ESTATE

3V LEVEL SHIFTERS
+3V_SLEEP
Q38 2N7002DW SOT-363 — DVI_DDC_CLK → GPU_DVI_DDC_CLK
Q38 2N7002DW SOT-363 — DVI_DDC_DATA → GPU_DVI_DDC_DATA
Q35 2N7002DW SOT-363 — DVI_HPD → GPU_HPD
R662 10K 5% 1/16W MF 402
R671 10K 5% 1/16W MF 402
R694 100K 5% 1/16W MF 402

Power key detect path when system is shutdown or asleep.. DDC_CLK is isolated from NV17M DURING SHUTDOWN. WHEN power key on remote device is pressed, +5V_will be driven into DDC_CLK. Since host rails will be low, TP0610 will turn on, driving SOFT_PWR_ON_L low. As host rails rise, TP0610 will turn off, as will remote device path into DDC_CLK. Isolation will be disabled as well.

DVI POWER SWITCH
Q40 TP0610 SM — DVI_DDC_CLK_UF → DVI_TURN_ON
R690 680 5% 1/16W MF 402
R691 10K 5% 1/16W MF 402 — DVI_TURN_ON_BASE
Q42 2N3904 SM — SOFT_PWR_ON_L
R688 330 5% 1/16W MF 402 — Pulldown prevents 3904 from turning on when DVI monitor has active, self-powered DDC clock pullup.
+5V_DDC_SLEEP

Power key detect path when system is running. HPD normally driven to 3.3V. When power key on remote device pressed, HPD will be driven to 5V. COMPARATOR ENABLED BY NV17MAP GPIO.

+3V_SLEEP
R680 68.1K 1% 1/16W MF 402
C696 0.1UF 20% 10V CERM 402
HPD_4V_REF
CRITICAL U46 LMC7211 SM — HPD_PWR_SW
R663 10K 1% 1/16W MF 402 — DVI_HPD_UF → DVI_HPD_DIV
R686 10K 1% 1/16W MF 402
R681 100K 1% 1/16W MF 402
Q41 2N7002DW SOT-363 — HPD_ON
R703 330 5% 1/16W MF 402
+PBUS
Q45 TP0610 SM
R696 100K 5% 1/16W MF 402
R704 100K 5% 1/16W MF 402
COMP_ENABLE
COMP_DISABLE
HPD_ON_RC
R700 20K 5% 1/16W MF 402 — HPD_BASE
Q44 2N3904 SM
C703 47UF 20% 6.3V CERM 1210
R705 68K 5% 1/16W MF 402
NEED PULL-DOWN BECAUSE THIS SIGNAL IS TRISTATED INITIALLY
HPD_PWR_SNS_EN
Q41 2N7002DW SOT-363
R213 100K 5% 1/16W MF 402

TMDS FILTERING PLACE CLOSE TO CONNECTOR

CRITICAL L72 90-OHM-200MA SM — TMDS_DN<0> → TMDS_CONN_DN<0>; TMDS_DP<0> → TMDS_CONN_DP<0>
CRITICAL L21 165-OHM SM — TMDS_CLKP → TMDS_CONN_CLKP; TMDS_CLKN → TMDS_CONN_CLKN
CRITICAL L73 90-OHM-200MA SM — TMDS_DN<1> → TMDS_CONN_DN<1>; TMDS_DP<1> → TMDS_CONN_DP<1>
CRITICAL L74 90-OHM-200MA SM — TMDS_DN<2> → TMDS_CONN_DN<2>; TMDS_DP<2> → TMDS_CONN_DP<2>

S-VIDEO/COMP OUT INTERFACE

Place GND shorts at graphics controller

XW12 SM — GPU_TV_GND1
L26 FERR-10-OHM-500MA SM — TV_GND1
C712 0.01UF 20% 50V CERM 603
L25 3.3UH 0603 — GPU_Y
C702 560PF 10% 50V CERM 402
C707 560PF 10% 50V CERM 402
L29 3.3UH 0603 — GPU_C
C718 560PF 10% 50V CERM 402
C724 560PF 10% 50V CERM 402
L27 3.3UH 0603 — GPU_COMP
C714 560PF 10% 50V CERM 402
C713 560PF 10% 50V CERM 402
CRITICAL J15 MINIDIN RT-TH MH1177 — TV_C, TV_Y, TV_COMP
XW13 SM — GPU_TV_GND2
L28 FERR-10-OHM-500MA SM — TV_GND2
C717 0.01UF 20% 50V CERM 603
CHGND1

Place GND shorts at graphics controller

LCD INTERFACE

LVDS INTERFACE

100K pull-ups are for no-panel case (development) Panel has 2K pull-ups

C416 0.001UF 20% 50V CERM 402 — CHGND4
CRITICAL J6 G-501973 F-RT-SM 34
+3V_SLEEP
R342 100K 5% 1/16W MF 402
R320 100K 5% 1/16W MF 402
+3V_LCD — (LVDS DDC POWER) — NC
LVDS_DDC_CLK
LVDS_DDC_DATA
NO STUFF
C449 0.001UF 20% 50V CERM 402
C452 0.001UF 20% 50V CERM 402
CHGND4
LVDS_L0N
LVDS_L0P
LVDS_L1N
LVDS_L1P
LVDS_L2N
LVDS_L2P
CLKLVDS_LN
CLKLVDS_LP
LVDS_U0N
LVDS_U0P
LVDS_U1N
LVDS_U1P
LVDS_U2N
LVDS_U2P
CLKLVDS_UN
CLKLVDS_UP
C500 0.001UF 20% 50V CERM 402
CHGND4

LCD POWER SWITCHES

+3V_MAIN
R400 100K 5% 1/16W MF 402
C484 2200pF 5% 50V CERM 603
R391 100K 5% 1/16W MF 402 — LCD_DIGON_L, LCD_PWREN_L
SI3443DV TSOP Q11
+3V_LCD_SW
L6 FERR-250-OHM SM
C474 0.001UF 20% 50V CERM 402
CHGND4
Q8 2N7002 SM — FP_PWR_EN
CHGND1

INVERTER INTERFACE

+PBUS
L33 FERR-1K-OHM-EMI SM — +12_8V_INV
+5V_MAIN
Q7 FDG6324L SC70-6 — +5V_INV_UF_SW
L32 400-OHM-EMI SM-1 — +5V_INV_SW
R317 100K 5% 1/16W MF 402 — FP_PWR_EN_1
C440 10UF 20% 6.3V CERM 805
C746 0.001UF 20% 50V CERM 402
CRITICAL J7 SM-2MT
Q7 FDG6324L SC70-6 — FP_PWR_EN
C749 0.001UF 20% 50V CERM 402
L31 400-OHM-EMI SM-1 — BRIGHT_PWM
C739 0.001UF 20% 50V CERM 402
CHGND2
+3V_PMU
C552 0.1UF 20% 10V CERM 402
74LVC32 TSSOP U24 — INV_ON_PWM → BRIGHT_PWM_UF
INVERTER EXPECTS ACTIVE HIGH SIGNAL
SHARES LOGIC WITH KB RESET SIGNALS (PG 28)
R724 0 5% 1/16W MF 402
C744 0.01UF 20% 50V CERM 603
CHGND2

VIDEO CONNECTORS

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.
SIZE D | DRAWING NUMBER 051-6531 | REV. B
SCALE NONE | SHT 22 OF 44

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
341S1194	1	IC,LMU,P84	U52	CRITICAL	?

MLB - ALS SENSOR



LMU



PART NUMBER	ALTERNATE FOR PART NUMBER	BOM OPTION	REF DES	COMMENTS:
197S0008	197S0040		Y4	ALT FOR SIWARD

BOOT BANGER E2PROM



SLEEP LED



SPIDEY FLEX



KEYBOARD PULLUPS



KB LED DRIVER









BOOT BANGING SIGNAL DEFINITION

1/ BBANG_HRESET_L (OPEN COLLECTOR OUTPUT - 10K PULLUP ON MLB)
2/ PMU_HRESET_L (3V INPUT INTO LMU)
3/ BBANG_JTAG_TCK (REGULAR OUTPUT)
4/ JTAG_CPU_TMS (OPEN COLLECTOR OUTPUT - 470OHM PULLUP ON MLB)
5/ JTAG_CPU_TDI (OPEN COLLECTOR OUTPUT - 470OHM PULLUP ON MLB)
6/ JTAG_CPU_TRST_L (OPEN COLLECTOR OUTPUT - 470OHM PULLUP ON MLB)

LMU PULL-DOWNS



LMU/BOOTBANGER/SPIDEY

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 23 OF 44	

HARD DRIVE INTERFACE (UATA100)

EIDE SERIES TERMINATION

PLACE TERMINATORS NEAR INTREPID



WIRELESS INTERFACE



OPTICAL DRIVE INTERFACE (EIDE)



PLACE SERIES R CLOSE TO INTERPID



PLACE PULLUP RESISTORS CLOSE TO INTREPID



IOCHRDY - UATA100 REQUIRES PULL-UP TO 3.3V



ANY SEQUENCING REQUIREMENT BETWEEN +5V_HD_SLEEP AND +3V_SLEEP?

BLUETOOTH/LEFT-SIDE USB



INTERNAL I/O CONNECTORS

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 24 OF 44	

SOUND BOARD (SOUSAPHONE)

AUDIO - SNAPPER
SND - INTREPID

L77 FERR-220-OHM 0402 — SND_SYNC (39 14) ↔ SND_SYNC_F (25)
L80 FERR-220-OHM 0402 — SND_CLKOUT (36 14 39) ↔ SND_CLKOUT_F (25)
L81 FERR-220-OHM 0402 — INT_AUDIO_TO_SND (39 14) ↔ INT_AUDIO_TO_SND_F (25)
L82 FERR-220-OHM 0402 — SND_TO_AUDIO (39 14) ↔ SND_TO_AUDIO_F (25)
L76 FERR-220-OHM 0402 — SND_AMP_MUTE (25 39) ↔ SND_AMP_MUTE_F (25)
L78 FERR-220-OHM 0402 — SND_HW_RESET_L (14 39) ↔ SND_HW_RESET_L_F (25)
L79 FERR-220-OHM 0402 — SND_SCLK (32 34 38) ↔ SND_SCLK_F (25)

C895 0.01UF 20% 16V CERM 402 NO STUFF
C899 0.01UF 20% 16V CERM 402 NO STUFF
C896 0.01UF 20% 16V CERM 402 NO STUFF
C897 0.01UF 20% 16V CERM 402 NO STUFF
C898 0.01UF 20% 16V CERM 402 NO STUFF
C900 0.01UF 20% 16V CERM 402 NO STUFF
C901 0.01UF 20% 16V CERM 402 NO STUFF

+3V_MAIN
+5V_MAIN

J12 CRITICAL
QT510306-L111 F-ST-SM1

INT_AUDIO_TO_SND_F (25)	1	2	SND_TO_AUDIO_F (25)
	3	4	SND_HP_SENSE_L (14 39)
INT_I2C_CLK2 (39 25 14)	5	6	SND_LIN_SENSE_L (14 39)
SND_SCLK_F (25)	7	8	
	9	10	SND_AMP_MUTE_F (25)
SND_CLKOUT_F (25)	11	12	SLEEP (23 30 33 35 39)
SND_SYNC_F (25)	13	14	
INT_I2C_DATA2 (39 25 14)	15	16	SND_HW_RESET_L_F (25)
SLEEP_LED (39 23)	17	18	
	19	20	
	21	22	SND_HP_MUTE_INV (25 39)
	23	24	
	25	26	
	27	28	
	29	30	

XW9 SM — 1 ↔ 2 (38 SND_AGND)

+5V_MAIN
RP44 100K 5% 1/16W SM1 — 2 / 7
SND_AMP_MUTE (39 25)
026 2N7002DW SOT-363 — D 6, S 1, G 2
SND_AMP_MUTE_L (14)
AMP_CONTROL (25)
RP44 100K 5% 1/16W SM1 — 5 / 4
026 2N7002DW SOT-363 — D 3, S 5, G 4
INT_PU_RESET_L (13 30)

+3V_MAIN
RP44 100K 5% 1/16W SM1 — 1 / 8
R689 100K 5% 1/16W MF 402 — 2
SND_HP_MUTE_INV (39 25)
031 2N7002DW SOT-363 — D 6, S 1, G 2
SND_HP_MUTE
031 2N7002DW SOT-363 — D 3, S 4, G 5
SND_HP_MUTE_L (14)
AMP_CONTROL (25)
RP44 100K 5% 1/16W SM1 — 6 / 3

PLACE XW9 CLOSE TO 5V SWITCHER (U27)
PLACE CAPS AS CLOSE TO THERMISTORS AS POSSIBLE
PLACE IN BETWEEN 3/5/1.5/2.5V PWR SUPPLY

CAPS FOR EMI EXPERIMENTATION ONLY

FAN INTERFACE

MAIN1
C681 0.001UF 20% 50V CERM 402
Q66 2N3904 SM
SUPPLY_M_DP (25) / SUPPLY_M_DM (25)

PLACE CLOSE TO CPU
MAIN2
C668 0.001UF 20% 50V CERM 402
Q39 2N3904 SM
CPU_M_DP (25) / CPU_M_DM (25)

PLACE UNDERNEATH UPPER RAM
ALTERNATE1
C678 0.001UF 20% 50V CERM 402 NO STUFF
Q47 2N3904 SM NO STUFF
THERM1_A_DP (37 25) / THERM1_A_DM (37 25)

PLACE CLOSE TO BATTERY CHARGER/VCORE
ALTERNATE2
C651 0.001UF 20% 50V CERM 402 NO STUFF
Q62 2N3904 SM NO STUFF
THERM2_A_DP (37 25) / THERM2_A_DM (37 25)

KEEP STUFFING RESISTORS CLOSE TO ADT7460 CONTROLLER

CPU_M_DP (25)	R719 0 5% 1/16W MF 402	THERM1_DP (25 37)
CPU_M_DM (25)	R725 0 5% 1/16W MF 402	THERM1_DM (25 37)
SUPPLY_M_DP (25)	R713 0 5% 1/16W MF 402	THERM2_DP (25 37)
SUPPLY_M_DM (25)	R716 0 5% 1/16W MF 402	THERM2_DM (25 37)

KEEP STUFFING RESISTORS CLOSE TO ADT7460 CONTROLLER

THERM1_A_DP (37 25)	R723 0 5% 1/16W MF 402 NO STUFF	THERM1_DP (25 37)
THERM1_A_DM (37 25)	R726 0 5% 1/16W MF 402 NO STUFF	THERM1_DM (25 37)
THERM2_A_DP (37 25)	R710 0 5% 1/16W MF 402 NO STUFF	THERM2_DP (25 37)
THERM2_A_DM (37 25)	R717 0 5% 1/16W MF 402 NO STUFF	THERM2_DM (25 37)

MODEM

SUPPORTS BOTH THE LAST DASH AND Q52 SOFT MODEM

+5V_MAIN
C767 10UF 20% 6.3V CERM 805
C513 0.1UF 20% 16V CERM 402 NO STUFF
R405 10K 5% 1/16W MF 402

+3V_MAIN
C478 0.1UF 20% 16V CERM 402 NO STUFF
C469 10UF 20% 6.3V CERM 805

J8 CRITICAL
QT510166-L010 F-ST-SM1

MOD_DTO (39 14)	1	2	MOD_SYNC (14 39)
MOD_CLKOUT (39 14)	3	4	INT_MOD_DTI (14 39)
	5	6	MOD_BITCLK (14 39)
COMM_RESET_L (39 14)	7	8	
COMM_SHUTDOWN (39 14)	9	10	MODEM_USB_DM (14 37 39)
INT_I2C_CLK2 (39 25 14)	11	12	MODEM_USB_DP (14 37 39)
INT_I2C_DATA2 (39 25 14)	13	14	COMM_RING_DET_L (14 30 39)
	15	16	

FAN CONTROLLER

+3V_MAIN
R814 10 5% 1/16W MF 402
ADT7460_VCC
C904 1UF 20% 10V CERM 603
C711 0.1UF 20% 10V CERM 402

U3 ADT7460 QSOP

ADT7460_VCORE_MON (9)	14	+2.5V/ SMBALERT#	PWM1/ XTO (15) ADT7460_FAN1_PWM
INT_I2C_DATA1 (39 14 13)	16	SDA	TACH1 (6) FANL_TACH (25 39)
INT_I2C_CLK1 (39 14 13)	1	SCL	PWM2/ SMBALERT# (5) ADT7460_FAN2_PWM
THERM1_DP (37 25)	13	D1+	TACH2 (7) FANR_TACH (25)
THERM1_DM (37 25)	12	D1-	CRITICAL PWM3/ ADR ENABLE# (8) ADT7460_ADR_EN_L
THERM2_DP (37 25)	11	D2+	TACH3 (4) NC
THERM2_DM (37 25)	10	D2-	TACH4/ ADR SELECT/ THERM# (9) ADT7460_THERM (25)
			GND (2)

R42 10K 5% 1/16W MF 402
R692 10K 5% 1/16W MF 402 — +5V_SLEEP
R695 10K 5% 1/16W MF 402

Q78 2N7002DW SOT-363 — D 6, S 3, G 2 — FANL_PWM (25 39)
Q78 2N7002DW SOT-363 — D 1, S 4, G 5 — FANR_PWM (25 39)

C688 0.001UF 20% 50V CERM 402 NO STUFF
C690 0.001UF 20% 50V CERM 402 NO STUFF
C846 0.001UF 20% 50V CERM 402 NO STUFF
C905 0.001UF 20% 50V CERM 402 NO STUFF

THERM ISOLATION

+3V_MAIN
R811 100K 5% 1/16W MF 402
+3V_PMU_AVCC (30 38)
R812 100K 5% 1/16W MF 402
THERM_L_OC (30)
R813 100K 5% 1/16W MF 402
THERM_INV
Q87 2N7002DW SOT-363 — D 6, S 5, G 2 — ADT7460_THERM (25)
Q87 2N7002DW SOT-363 — D 3, S 4, G 5
C903 0.1UF 20% 10V CERM 402

LEFT FAN (CPU)

+5V_SLEEP
R679 10K 5% 1/16W MF 402
FANL_TACH (39 25)
FANL_GND (39 38)
Q37 SI3446DV TSOP
CRITICAL J4 SM-2MT
PLACE CLOSE TO CONNECTOR
C134 4.7UF 20% 10V CERM 1206
FANL_PWM (39 25)

SERIAL DEBUG INTERFACE

+5V_MAIN
SERIAL_DEBUG CRITICAL J16 M-ST-5087 SM

COMM_TXD_L (39 14)	1	10	COMM_DTR_L (14 39)
COMM_TRXC (39 14)	2	9	COMM_RTS_L (14 39)
	3	8	
COMM_GPIO_L (39 14)	4	7	COMM_RXD (14 39)
	5	6	

DEBUG POWER BUTTON

R527 0 5% 1/16W MF 603 NO STUFF
PWR_BUTTON_L (39 23)

DEBUG JUMPERS

+5V_SLEEP
R293 10K 5% 1/16W MF 402
R295 10K 5% 1/16W MF 402
FANL_PWM (25 39)
FANR_PWM (25 39)

R537 0 5% 1/16W MF 603 NO STUFF
PMU_NMI_BUTTON_L (30)
R553 0 5% 1/16W MF 603 NO STUFF
PMU_RESET_BUTTON_L (39)

RIGHT FAN (GPU)

+5V_SLEEP
R623 10K 5% 1/16W MF 402
J2 CRITICAL SM-2MT
FANR_GND (39 38)
FANR_TACH (25)
Q36 SI3446DV TSOP
PLACE CLOSE TO CONNECTOR
C135 4.7UF 20% 10V CERM 1206
FANR_PWM (39 25)

FAN/MODEM/SOUND/SLEEP LED/DEBUG

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 25 OF 44	

PART NUMBER	ALTERNATE FOR PART NUMBER	BOM OPTION	REF DES	COMMENTS:
197S0608	197S0038	NEC_USB	Y5	ALT FOR SIWARD

Y7 LOAD CAPACITANCE IS 16PF

SERR_L AND PERR_L
HAS DEDICATED PULL-UP
FOR BOTH CBUS AND USB2

Series Rpaks required to
facilitate NAND-tree testing

Low/Full/High Speed (External)

Low/Full/High Speed (External)

NEED PULL-UP RESISTORS IN CASE USB 1.0 IS USED FOR PORT POWER

PLACE NEAR J3

SUTRO CONNECTOR

PLACE NEAR J12

BUBBA CONNECTOR

INTREPID USB CONSTRAINTS

USB 2.0

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 26 OF 44	

Ethernet routing priority:
1. Decoupling caps
2. TX SERIES TERMINATION - LOCATE NEAR LINK
3. RX SERIES TERMINATION - LOCATE NEAR PHY

All differential signals should be close, parallel, matched lengths, with minimum via count, and short if possible

Must maintain 50-ohms trace impedance on all MDI pairs and all RJ45 pairs

Sandwich each RJ54 pair between chassis grounds

+3V_MAIN

NO STUFF R333 0 5% 1/16W MF 402

3405_MODE

C442 10uF 20% 6.3V CERM 805

U14 LTC3405 SOT23-6 CRITICAL
VIN, RUN, MODE, GND, SW, VFB

LTC3405_SW

CRITICAL L5 3.3uH SM1

R319 0 5% 1/16W MF 402

R334 665K 1% 1/16W MF 402 R2A

C471 22pF 5% 50V CERM 402

R361 49.9K 1% 1/16W MF 402 R2B

3405_VFB

+1_0V_MARVELL

C486 10uF 20% 6.3V CERM 805

VOUT = 0.8V*(1+R2EQV/R1)
R2EQV = R2A||R2B

R362 182K 1% 1/16W MF 402 R1

PLACE ALL SERIES RES CLOSE TO PHY

R370 0 5% 1/16W MF 402 — CLKENET_LINK_TX / CLKENET_PHY_TX

R353 0 5% 1/16W MF 402 — CLKENET_LINK_RX / CLKENET_PHY_RX

R344 0 5% 1/16W MF 402 — CLKENET_LINK_GBE_REF / CLKENET_PHY_GBE_REF

CRITICAL U49 88E1111 BCC

TX_CLK, RX_CLK, 125CLK

TXD0, TXD1, TXD2, TXD3, TXD4, TXD5, TXD6, TXD7

TX_EN, TX_ER, GTX_CLK

RXD0, RXD1, RXD2, RXD3, RXD4, RXD5, RXD6, RXD7

RX_DV, RX_ER, CRS, COL, MDC, MDIO

INT-/INT+, RESET, COMA

S_IN+, S_IN-, S_OUT+, S_OUT-, S_CLK+, S_CLK-, HSDAC+, HSDAC-

XTAL1, XTAL2, VSSC

CTRL10, DVDD, VDDO, VDDOH, VDDOX, AVDD

MDI0+, MDI0-, MDI1+, MDI1-, MDI2+, MDI2-, MDI3+, MDI3-

LED_LINK10, LED_LINK100, LED_LINK1000, LED_DUPLEX, LED_RX, LED_TX

CONFIG0 (000), CONFIG1 (000), CONFIG2 (111), CONFIG3 (110), CONFIG4 (111), CONFIG5 (101), CONFIG6 (000)

SEE CONFIG TABLES (BELOW)

TDI, TDO, TCK, TMS, TRST, RSET, SEL_OSC, SEL_2.5V, GND

C492 C511 C517 C502 C465 C475 0.1UF/0.01UF 20% 10V CERM 402

PLACE CAPS (IN ORDER) ON PINS 1, 6, 10/15, 57/62, 67/71, 85

C464 C472 C453 C503 C501 C496 0.1UF/0.01UF/10uF

PLACE CAPS (IN ORDER) ON PINS 5, 21/26, 48/52, 66/72, 88, 96

+2_5V_MARVELL

C497 C504 C487 C476 C754 0.1UF/0.01UF/10uF

PLACE CAPS (IN ORDER) ON PINS 32/35, 36/40, 45 & 78

+2_5V_MARVELL_AVDD

L34 FERR-EMI-600-OHM SM

+2_5V_MAIN

R465 0 5% 1/16W MF 603

PLACE CLOSE TO ETHERNET CONNECTOR

NO STUFF R438 0 5% 1/16W FF 805 — CHGND1

C488 C466 C506 C520 0.1UF

PLACE CAPS AT TRANSFORMER PINS 1, 4, 7 & 10

CRITICAL J17 RJ45 RT-TH

RJ45_DP<0>, RJ45_C0_PD, RJ45_DN<0>, RJ45_DP<1>, RJ45_C1_PD, RJ45_DN<1>, RJ45_DP<2>, RJ45_C2_PD, RJ45_DN<2>, RJ45_DP<3>, RJ45_C3_PD, RJ45_DN<3>

Short shielded RJ-45

CHGND1

CRITICAL T1 XFR-ENET-1000BT SM

R735 R733 R382 R347 75 5% 1/16W MF 402

ENET_CTAP_CHGND

C457 100pF 10% 3KV CERM 1808 — CHGND1

R346 R372 R404 R413 49.9 1% 1/16W MF 402

R355 R381 R406 R428 49.9 1% 1/16W MF 402 — MDI0_PD, MDI1_PD, MDI2_PD, MDI3_PD

C454 C477 C493 C505 0.01UF 20% 10V CERM 402

PLACE RESISTORS CLOSE TO PHY

PLACES PHY IN "COMA" MODE WHEN ASLEEP ON BATTERY (SAVES POWER)

D1 1N914 SOT23

Q15 2N7002DW SOT-363 (×2)

C755 2.2uF 20% 10V CERM 805

R371 10K, R345 10K, R354 1.5K, R343 1K 5% 1/16W MF 402

PUT CRYSTAL CIRCUIT CLOSE TO PHY

NO STUFF R435 20K 5% 1/16W MF 402

R427 0 5% 1/16W MF 402

CRITICAL Y3 25.0000M 8X4.5MM-SM

C555 C491 33pF 5% 50V CERM 402

Y3'S LOAD CAPACITANCE IS 20PF

NO STUFF R393 R403 49.9 1% 1/16W MF 402

R335 10K 5% 1/16W MF 402

R380 4.99K 1% 1/16W MF 402

PART NUMBER	ALTERNATE FOR PART NUMBER	BOM OPTION	REF DES	COMMENTS:
197S0703	197S0037	ALTERNATE	Y3	
197S0603	197S0037	ALTERNATE	Y3	ALT FOR SIWARD

CONFIG DEFINITIONS	
PIN	BIT[2:0]
VDDO	111
LED_LINK10	110
LED_LINK100	101
LED_LINK1000	100
LED_DUPLEX	011
LED_RX	010
LED_TX	001
VSS	000

CONFIG INPUTS			
PIN	BIT[2]	BIT[1]	BIT[0]
CONFIG<0>	PHYADR[2]	PHYADR[1]	PHYADR[0]
CONFIG<1>	ENA_PAUSE	PHYADR[4]	PHYADR[3]
CONFIG<2>	ANEG[3]	ANEG[2]	ANEG[1]
CONFIG<3>	ANEG[0]	ENA_XC	DIS_125
CONFIG<4>	MODE[2]	MODE[1]	MODE[0]
CONFIG<5>	DIS_FC	DIS_SLEEP	MODE[3]
CONFIG<6>	SEL_BDT	INT_POL	75/50 OHM

MARVELL 88E1111

10/100/1000 ETHERNET

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 27 OF 44	

PART NUMBER	ALTERNATE FOR PART NUMBER	BOM OPTION	REF DES	COMMENTS:
197S0052	197S0011	?	G1	SIWARD ALT FOR FW OSC

DSX STRAP OPTIONS

0 -> BILINGUAL PORT

1 -> A-ONLY PORT

PLACE NEAR PHY

PLACE NEAR PHY

CAPACITOR IN CONJUCTION WITH INTERNAL PULLUP PROVIDES RESET PULSE WHEN PHY FIRST RECEIVES POWER

FIREWIRE

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 28 OF 44	

PORT POWER SWITCH

ENABLES PORT POWER WHEN MACHINE IS RUNNING OR WHEN ASLEEP ON AC

STATE	PMU_POWER_UP_L	POWER_UP	DCDC_EN	AC_IN	LTC4210_ON
SHUTDOWN (AC)	1	0	0	1	OFF
SLEEP (AC)	1	0	1	1	ON
RUN (AC)	0	1	1	1	ON
SHUTDOWN (BATT)	1	0	0	0	OFF
SLEEP (BATT)	1	0	1	0	OFF (PULL-DOWN RESISTOR)
RUN (BATT)	0	1	1	0	ON
	2.99V	+3V_PMU	+4_6V_BU	+3V_PMU	







PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	BOM OPTION
341S1008	1	IC,PMU,V81B	U33	

CPU_VCORE_HI_OC/PMU_AP should have a pulldown for coming out of reset. MLB will have a pull-up to +3V_MAIN or +3V_SLEEP, which will act as our pulldown since both are off during PMU reset.



UNDERVOLTAGE RESET CIRCUIT



Keep crystal subcircuit close to PMU.
Y6'S LOAD CAPACITANCE IS 12PF

PART NUMBER	ALTERNATE FOR PART NUMBER	BOM OPTION	REF DES	COMMENTS:
197S0704	197S0041		Y6	ALT CRYSTAL SIZE
197S0604	197S0041		Y6	ALT FOR SIWARD

PMU KEYBOARD RESET CIRCUIT



Q11 ADAPTER DETECTION SCHEME

CASE	ADAPTER	PIN VOLT	ID VOLT RANGE	SYSTEM STATUS
1	Q11 (65W)	2.007V- 2.066V	1.65V- 2.31V	RECOGNIZES AS Q11 FULL FUNCTIONS
2	A29 (45W)	2.558V- 2.661V	2.31V- 2.97V	RECOGNIZES AS A29 LIMITED FUNCTIONS
3	AIRLINE	0.589V- 0.663V	0.33V- 0.99V	FULL FUNCTIONS NO BATTERY CHARGING
4	HOOPER	3.19V- 3.28V	2.97V- 3.30V	RECOGNIZES AS HOOPER LIMITED FUNCTIONS

Keep crystal subcircuit close to PMU.



Y7'S LOAD CAPACITANCE IS 12.5PF



A29 DETECT CIRCUIT



PMU

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 30 OF 44	

DC POWER INPUT

(POWER JACK, ETC. ON SEPARATE BOARD)

CRITICAL

J18
87438-0833
M-RT-SM

CHARGE_LED_L
+ADAPTER
ADAPTER_DET

NO STUFF
C757 0.1UF 20% 50V CERM 805

PLACE CLOSE TO DC INPUT

R396 20K 1% 1/16W MF 402

DC INRUSH LIMITER

Q013 SI4435DY SOI
Q016 SI4435DY SOI

+ADAPTER_SW
+ADAPTER_SENSE
AC_ENABLE_GATE
AC_ENABLE_L

R414 330K 5% 1/16W MF 402
C458 0.1UF 20% 50V CERM 805
R374 470K 5% 1/16W MF 402
R474 47K 5% 1/16W MF 402
R499 68K 5% 1/16W MF 402
C592 0.1UF 20% 50V CERM 805
BCKFD_PROT_GATE
BCKFD_PROT_EN_L
Q021 2N7002DW SOT-363

+3V_PMU
+24V_PBUS

R395 102K 1% 1/16W MF 402
R364 102K 1% 1/16W MF 402
C468 0.01UF 20% 16V CERM 402
R363 10K 5% 1/16W MF 402
1V20_REF
U15 LMC7211 SM CRITICAL
AC_IN
AC_DIV
R394 1M 5% 1/16W MF 402
AC_IN_L
Q010 2N7002DW SOT-363
R375 10K 1% 1/16W MF 402
R365 57.6K 1% 1/16W MF 402
R383 470K 5% 1/16W MF 402

GREATER THAN 13.5V DETECT

PLACE U23 NEXT TO R460

U23 SENSE VOLTAGE DROP ACROSS R460

U23 MAX4172 TSSOP CRITICAL
RS+ RS- PG NC1 NC2 OUT GND
MAX4172_OUT
CURRENT_THRESHOLD
R454 2.21K 0.1% 1/10W MF 603
C572 0.01UF 20% 50V CERM 603
C883 0.1UF 10% 50V X7R 603-1

R460 0.025 1% 1W MF 2512
R488 4.7 5% 1/16W MF 402
R498 4.7 5% 1/16W MF 402
1772_CSSP
1772_CSSN
C578 0.47UF 20% 50V CERM 1206
C579 0.47UF 20% 50V CERM 1206

IF A29 ADAPTER USED, ADJUST CURRENT SETTING

1MSEC INTEGRATION TIME

R742 1K 1% 1/16W MF 402
C771 0.1UF 20% 10V CERM 402
IAC_RC_COMP
R747 42.2K 0.1% 1/16W FF 603
C772 0.1UF 20% 10V CERM 402
U50 LMC7111 SOT23-5 CRITICAL
IAC_FB
R466 10K 1% 1/10W MF 402
DP4 BAS16TW SOT-363
LTC1625_ITH
R358 150 1% 1/16W MF 402
1625_COMP
ADAPTER_I_REG

PLACE R358 CLOSE TO LTC1625
ROUTE LTC1625_ITH CAREFULLY

R738 42.2K 0.1% 1/10W FF 603
R734 82.5K 0.1% 1/10W FF 603
R739 51.1K 0.1% 1/16W FF 603
IF ADAPTER IS OVER 18V, ADJUST CURRENT SETTING
A29_CURRENT_ADJ
R748 100K 5% 1/16W MF 402
OVER_18V_ADJ
Q020 2N7002DW SOT-363
AC_GTR_18V
C775 1UF 20% 10V CERM 603
Q065 2N7002DW SOT-363
1772_ACOK_L
A29_DETECT

BATTERY SWITCH-OVER CIRCUIT

+BATT
F4 5AMP-125V SM-2
F3 5AMP-125V SM-2
+24V_PBUS
+PBUS
+BATT_24V_FUSE
+BATT_14V_FUSE
CRITICAL
Q024 SI4435DY SOI
Q076 SUD45P03 TO-252
R490 47K 5% 1/16W MF 402
R746 47K 5% 1/16W MF 402
BATT_24V_GATE
BATT_14V_GATE
R512 10K 5% 1/16W MF 402
R744 10K 5% 1/16W MF 402
BATT_24PBUS_EN
BATT_14PBUS_EN
DP4 BAS16TW SOT-363
Q021 2N7002DW SOT-363
AC_IN_L_RC
R489 158K 1% 1/16W MF 402
C593 10UF 20% 6.3V CERM 805

WHEN AC IS IN, P-CHANNEL FETS ARE QUICKLY (DIODE) TURNED OFF
WHEN AC IS NOT PLUGGED, P-CHANNEL FETS ARE ON
RC TIME IS 480K*10UF @ +3V_PMU

SWITCHER VOLTAGE CONTROL

PMU SELECTS BETWEEN TWO VOLTAGES

R567 27.4K 1% 1/16W MF 402
R558 10K 1% 1/16W MF 402
R548 10K 1% 1/16W MF 402
R560 4.12K 1% 1/16W MF 402
R565 48.7K 1% 1/16W MF 402
R566 1K 1% 1/16W MF 402
R561 100K 5% 1/16W MF 402
BATTV_HIGH
BATTV_LOW
Q027 2N7002DW SOT-363
R580 5.23K 1% 1/16W MF 402
Q029 2N7002DW SOT-363
BATT_LOW_L
PMU_CHARGE_V

SWITCHER CURRENT CONTROL

CHARGE DISABLED BY PMU OR INPUT VOLTAGE <18V
CHARGE THROTTLED BY LOW BATTERY VOLTAGE

OD OUTPUT LOW - WHEN AC GREATER THAN 18V

R754 100K 1% 1/16W MF 402
D9 1N914 SOT23
R755 12.7K 1% 1/16W MF 402
C600 1UF 20% 50V CERM1 1210

U31 MAX1772 QSOP CRITICAL
CSSP CSSN DCIN ACIN ACOK RFIN VCTL ICTL ICHG IINP CCV CCI CCS REF CELLS LDO DLOV BST DHI LX DLO PGND CSIP CSIN BATT GND

1772_DCIN
1772_ACIN
1772_ACOK_L
(+3V_PMU)
1772_VCTL
1772_ICTL
1772_ICHG
1772_IINP
1772_CCV
1772_CCI
1772_CCS
1772_CELLS
1772_DLOV
1772_BST
1772_DHI
1772_LX
1772_DLO
(GND)
1772_CSIP
1772_CSIN
REF = 4.096V
REF_CLS

R542 1K 1% 1/16W MF 402
R526 1K 1% 1/16W MF 402
C622 0.01UF 20% 16V CERM 402
C616 0.01UF 20% 16V CERM 402
C652 1UF 20% 10V CERM 603
C817 0.1UF 20% 25V CERM 603
C802 0.1UF 20% 25V CERM 603
1772_CCV_RC
1772_REF
R497 1K 1% 1/16W MF 402
C621 0.1UF 20% 10V CERM 402
C630 1UF 20% 10V CERM 603
R487 10K 1% 1/16W MF 402
R473 4.12K 1% 1/16W MF 402
1772_CLS
R559 100K 5% 1/16W MF 402
NO STUFF C906 0.0022UF 10% 50V CERM 402
XW19

R571 33 5% 1/8W FF 1206
D10 1N914 SOT23
1772_LDO
1772_BST_ESR
R549 100K 5% 1/16W MF 402
C624 0.1UF 20% 25V CERM 603
R774 4.7 5% 1/16W MF 603
C608 0.1UF 20% 50V CERM 805

Q63 IRF7805 SM CRITICAL
Q64 IRF7811W SO-8 CRITICAL
C547 2.2UF 20% 6.3V CERM 1812
C562 2.2UF 20% 6.3V CERM 1812
C563 2.2UF 20% 6.3V CERM 1812
C557 2.2UF 20% 6.3V CERM 1812
C564 2.2UF 20% 6.3V CERM 1812
L42 10uH SM1 CRITICAL
D30 MBRS140T3
+BATT_RSNS
R763 0.05 1% 1W MF 2512
R543 1 5% 1/16W MF 603
R511 1 5% 1/16W MF 603
C619 4.7UF 20% 25V CERM 1206
C632 4.7UF 20% 25V CERM 1206
C631 4.7UF 20% 25V CERM 1206
C633 4.7UF 20% 25V CERM 1206
C617 4.7UF 20% 25V CERM 1206
C618 4.7UF 20% 25V CERM 1206
+BATT_24V_FUSE
C824 33UF 20% 25V ELEC SM1

V_{BATT} = CELLS X (4.096 + (0.4096 * V_{VCTL} / V_{REFIN}))

For 4.15V cells, VCTL = 0.123 REFIN

For 4.20V cells, VCTL = 0.245 REFIN

I_{CHG} = (0.2048/R_{62}) * (V_{ICTL} / V_{REFIN})

+3V_PMU
Q030 2N7002DW SOT-363
CHARGE_DISABLE
PMU_CHRG_BATT_0

+3V_PMU
U38 LMC7211 SM CRITICAL
BATT_LOW
BATT_DIV
1V65_REF
R588 100K 1% 1/16W MF 402
R579 499K 1% 1/16W MF 402
R599 100K 1% 1/16W MF 402
R570 100K 1% 1/16W MF 402
C658 0.047UF 10% 16V CERM 402
C615 0.1UF 20% 10V CERM 402

R749 6.34K 1% 1/16W MF 402
A29_CLS_ADJ
Q065 2N7002DW SOT-363
A29_DETECT

BATTERY CONNECTOR

CRITICAL
J25
87438-0833
M-RT-SM

+BATT_VSNS
+BATT_POS
(BATT_IN_PD)
BATT_CLK
BATT_DATA
PMU_BATT_DET_L
BATT_NEG

L9 FERR-EMI-100-OHM SM
L53 FERR-50-OHM SM
L10 FERR-EMI-100-OHM SM
L8 FERR-EMI-100-OHM SM
L12 FERR-50-OHM SM
PMU_SMB_CLK
PMU_SMB_DATA

BATTERY CHARGER

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 31 OF 44	

12.8V PBUS SUPPLY



BACKUP BATTERY / USB CONNECTOR



PMU SUPPLY



12.8V REGULATOR

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.	SIZE	DRAWING NUMBER	REV.
	D	051-6531	B
	SCALE: NONE	SHT 32 OF 44	

3.3V/5V MAIN SUPPLY



3.3V/5V REGULATOR

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 33 OF 44	

VCORE POWER SEQUENCING

CPU core follows CPU I/O voltage
(approx. 7ms delay)

1.175V -> 1.025V 1.30V -> 1.10V

+5V_MAIN

MAXBUS_SLEEP

CPU_VCORE_PWR_SEQ

CPU_VCORE_SEQ_L

CPU_VCORE_SEQ

R408 100K 5% 1/16W MF 402
R398 100K 5% 1/16W MF 402
R356 100K 1% 1/16W MF 402
R267 10K 5% 1/16W MF 402
R318 0 5% 1/16W MF 402

DP2 BAS16TW SOT-363
Q12 2N3904 SM
Q017 2N3904 SM

SLEEP_L_LS5
DCDC_EN

DP2 BAS16TW SOT-363
DP2 BAS16TW SOT-363

CPU_VCORE_HI_OC

R297 470K 5% 1/16W MF 402
R314 470K 5% 1/16W MF 402 NO STUFF
R328 0 5% 1/16W MF 402
R324 0 5% 1/16W MF 402 NO STUFF
R304 470K 5% 1/16W MF 402
R329 0 5% 1/16W MF 402
R325 0 5% 1/16W MF 402
R322 10K 5% 1/16W MF 402 NO STUFF

R303 0 5% 1/16W MF 402 NO STUFF <D4>
R313 470K 5% 1/16W MF 402 <D3>
R327 470K 5% 1/16W MF 402 NO STUFF <D2>
R323 470K 5% 1/16W MF 402 <D1>
R301 470K 5% 1/16W MF 402 <D4>
R305 0 5% 1/16W MF 402 NO STUFF <D3>
R330 470K 5% 1/16W MF 402 NO STUFF <D2>
R326 0 5% 1/16W MF 402 NO STUFF <D1>
R302 1K 5% 1/16W MF 402

VCC U11 PI3B3257 QSOP STR_VER-2 CRITICAL
A1 B1 A2 B2 A3 B3 A4 B4 SEL OE
Y1 Y2 Y3 Y4 GND

VCORE_SLOW<1>
VCORE_SLOW<2>
VCORE_SLOW<3>
VCORE_SLOW<4>
VCORE_FAST<1>
VCORE_FAST<2>
VCORE_FAST<3>
VCORE_FAST<4>
VCORE_MUX_SEL
VCORE_MUX_EN

C439 0.1UF 20% 16V CERM 402

VCORE_VID<1>
VCORE_VID<2>
VCORE_VID<3>
VCORE_VID<4>

R288 0 5% 1/16W MF 402 NO_4XVCORE
R289 0 5% 1/16W MF 402 NO_4XVCORE
R290 0 5% 1/16W MF 402 NO_4XVCORE
R292 0 5% 1/16W MF 402 NO_4XVCORE

SEL = 0; Y1=A1
SEL = 1; Y1=B1

Keep trace fat (40-100 mils) and short!!

CPU_VCORE_SLEEP

C2 10UF 20% 6.3V CERM 805
C689 10UF 20% 6.3V CERM 805
C5 10UF 20% 6.3V CERM 805
C699 10UF 20% 6.3V CERM 805
C234 10UF 20% 6.3V CERM 805
C682 10UF 20% 6.3V CERM 805
C674 10UF 20% 6.3V CERM 805
C274 10UF 20% 6.3V CERM 805
C7 10UF 20% 6.3V CERM 805
C680 10UF 20% 6.3V CERM 805
C693 10UF 20% 6.3V CERM 805
C13 10UF 20% 6.3V CERM 805
C116 10UF 20% 6.3V CERM 805
C6 10UF 20% 6.3V CERM 805
C695 10UF 20% 6.3V CERM 805
C679 10UF 20% 6.3V CERM 805
C285 10UF 20% 6.3V CERM 805
C4 10UF 20% 6.3V CERM 805
C3 10UF 20% 6.3V CERM 805
C687 10UF 20% 6.3V CERM 805

+PBUS

C427 8.2UF 20% 16V TANT CASE-D CRITICAL
C431 8.2UF 20% 16V TANT CASE-D CRITICAL
C443 8.2UF 20% 16V TANT CASE-D CRITICAL
C430 8.2UF 20% 16V TANT CASE-D CRITICAL
C432 8.2UF 20% 16V TANT CASE-D CRITICAL
C441 8.2UF 20% 16V TANT CASE-D CRITICAL
C444 8.2UF 20% 16V TANT CASE-D CRITICAL
C445 8.2UF 20% 16V TANT CASE-D CRITICAL

+5V_MAIN

VCORE_VCC

PLACE C423 CLOSE TO PINS 15 & 13!

C498 1UF 20% 10V CERM 603
D2 SM MBR0530

R349 20 5% 1/16W MF 402
VCORE_BOOST

R407 0 5% 1/16W MF 402
C507 1UF 20% 10V CERM 603

R397 27.4K 1% 1/16W MF 402

VCC U20 MAX1717 QSOP VDD

SKP/SDN
FBS
ILIM
GNDS
A/B
REF
TON
CC
D0
D1
D2
D3
D4
V+
BST
DH
LX
DL
GND
FB
TIME
VGATE

VCORE_SHDN_L
(VCORE_SNS)
VCORE_ILIM
(VCORE_GNDSNS)
MAX1717_AB_SEL
VCORE_REF
VCORE_TON
VCORE_CC
MIN_LINE_WIDTH=10
VCORE_VPLUS
VCORE_BST
VCORE_DH
VCORE_LX
VCORE_DL
VCORE_GND
VCORE_FB
VCORE_TIME
VCORE_VGATE

R429 2.2 5% 1/16W MF 603
C518 0.1UF 20% 25V CERM 603

NO STUFF C455 0.0047uF 10% 25V CERM 402

Q50 SI7860DP SO-8-PWRPK CRITICAL
Q49 SI7860DP SO-8-PWRPK CRITICAL

Q54 IRF7832 SO-8 CRITICAL
Q55 IRF7832 SO-8 CRITICAL
Q53 IRF7832 SO-8 CRITICAL

Keep trace fat and short!!

L36 1.2UH-18.3A SM1 CRITICAL

XW15 SM
CPU_VCORE_SLEEP_F

Keep trace fat and short!!

R331 0.001 1% 1W MF 2512 CRITICAL

CPU_VCORE_SLEEP

C728 220UF 20% 2V TANT 7343 CRITICAL
C734 220UF 20% 2V TANT 7343 CRITICAL
C733 220UF 20% 2V TANT 7343 CRITICAL
C732 220UF 20% 2V TANT 7343 CRITICAL
C885 220UF 20% 2V TANT 7343 CRITICAL
C731 220UF 20% 2V TANT 7343 CRITICAL
C730 220UF 20% 2V TANT 7343 CRITICAL
C729 220UF 20% 2V TANT 7343 CRITICAL
C884 220UF 20% 2V TANT 7343 CRITICAL

D25 BS40C SM CRITICAL
R732 2.2 5% NO STUFF 1/4W MF 1210
CPU_VCORE_SNUB
C764 0.0022uF 10% 50V CERM 603 NO STUFF

NO STUFF R384 0 5% 1/16W MF 402
CPU_VCORE_HI_OC

R366 0 5% 1/16W MF 402
INT_GPIO1_PU

NO STUFF R337 470K 5% 1/16W MF 402 <D0>

VCORE_VID<0>
VCORE_VID<1>
VCORE_VID<2>
VCORE_VID<3>
VCORE_VID<4>

MAX1717 VID CAN TAKE 3.3V TO 5.5V INPUTS

R336 470K 5% 1/16W MF 402
C529 0.01UF 20% 16V CERM 402
R448 66.5K 1% 1/16W MF 402
R385 12.7K 1% 1/16W MF 402
C459 1UF 20% 10V CERM 603
C512 220PF 5% 25V CERM 402

XW5 SM
R415 100 5% 1/16W MF 402
XW7 SM
R434 390K 5% 1/16W MF 402
C521 0.001UF 20% 50V CERM 402

Connect MAX1717 GND pin 13 to GND at bottom-side FET

VCORE_GNDA

+5V_MAIN

R805 100K 5% 1/16W MF 402 VCORE_SEL_OFF_PU

R809 1.5K 1% 1/16W MF 402
VCORE_SEL_ON

NO STUFF R806 0 5% 1/16W MF 402
MAX1717_AB_SEL

R807 0 5% 1/16W MF 402 AB_SEL_LOW

Q086 2N7002DW SOT-363
Q086 2N7002DW SOT-363

NO STUFF R808 100K 5% 1/16W MF 402

VCORE_OFFSET

R376 162K 1% 1/16W MF 603 R2

OMIT R321 3.01K 1% 1/16W MF 402 R1

VCORE_GNDDIV

NOTE: R310 (R2) NO STUFFED FOR NO OFFSET CASE

GROUND SENSE VOLTAGE DIVIDER

This allows for an offset to the ground sense to adjust the output voltage.
VREF = 2.0V, HENCE VOFFSET = 2.0V * (R1/(R1+R2)) AND VCORE = VDAC + VOFFSET.

ROUTE AS DIFFERENTIAL PAIR

PLACE THIS SHORT AT PIN OF 1000uF CAP CLOSEST TO CPU
XW3 SM
VCORE_GNDSNS
VCORE_SNS

NO STUFF R315 2.05K 1% 1/16W MF 402
VCORE_GNDDIV
NO STUFF R312 100 1% 1/16W MF 402
VCORE_GNDSNS

FMAX CONNECTOR

CRITICAL
NO STUFF
J5 M-ST-SM-52465-1217

VCORE_GNDDIV_TEST
VCORE_GNDSNS_TEST
+3V_PMU_RESET
SOFT_PWR_ON_L
NC (RFU)

VCORE_VID<0>
VCORE_VID<1>
VCORE_VID<2>
VCORE_VID<3>
VCORE_VID<4>

OUTPUT VOLTAGE

V_{DAC} D4=0	V_{DAC} D4=1	D3	D2	D1	D0
2.00	1.275	0	0	0	0
1.95	1.250	0	0	0	1
1.90	1.225	0	0	1	0
1.85	1.200	0	0	1	1
1.80	1.175	0	1	0	0
1.75	1.150	0	1	0	1
1.70	1.125	0	1	1	0
1.65	1.100	0	1	1	1
1.60	1.075	1	0	0	0
1.55	1.050	1	0	0	1
1.50	1.025	1	0	1	0
1.45	1.000	1	0	1	1
1.40	0.975	1	1	0	0
1.35	0.950	1	1	0	1
1.30	0.925	1	1	1	0
NO CPU	NO CPU	1	1	1	1

FOR V-STEP:

D<4..0>	A/B_ = Hi/Fast	A/B_ = Lo/Slow
<= 1K PU	1	0
>= 100K PU	1	1
>= 100K PD	0	1
<= 1K PD	0	0

When A/B_ is high (fast): D4-D0 read as-is
When A/B_ is low (slow): <=1K-ohm -> 0
>=100K-ohm -> 1

If all pull-ups are >=100K and all pull-downs are <=1K, $V_A = V_B$.

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
114S4023	1	RESISTOR	R321	?	1_30_VCORE
114S6343	1	RESISTOR	R321	?	1_32_VCORE

VCORE SUPPLY

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE D | DRAWING NUMBER 051-6531 | REV. B
SCALE NONE | SHT 34 OF 44

1.5V/2.5V SWITCHER

+1_5V_SLEEP LOADS

1) AGP I/O - IF USING D3COLD
2) MAXBUS I/O - IF 1.5V INTERFACE

+1_5V_MAIN LOADS

1) INTREPID CORE
2) AGP I/O IF USING D3HOT

+2_5V_SLEEP LOADS

1) FBCORE/FBIO IF USING D3COLD
2) INTREPID MEMORY I/O

+2_5V_MAIN LOADS

1) MAP31 - FBCORE/FBIO IF USING D3HOT
2) GIGABIT ETHERNET - AVDDL
3) DDR SODIMMS - CORE/IO
4) DDR MUXES
5) CLOCK SLEWING I/O
6) PCI1510 CORE

THERE'S 100K PULL-UP ON PG 31 ALREADY

DIODE PROVIDE PROVIDE QUICK SHUT-DOWN
POWER DOWN DELAY 1.5MS TO 3.5MS

CHANGE R424 BACK TO 10K, 1%, AND STUFF 5.11K FOR 1.5V OPERATION
CONNECTING 1_5V_FB TO GND, FORCES 1.8V OUTPUT

1.8V SWITCHER

+1_8V_MAIN LOADS

1) INTREPID PLLS

+1_8V_SLEEP LOADS

1) MPC7450 - MAXBUS I/O - IF 1.8V INTERFACE
2) CPU JTAG & MaxBus Pull-ups
3) CPU PLL Config Straps
4) OPTIONAL VIDEO MEMORY (M10 PRO ONLY)

CONTINUOUS MODE

BURST MODE
NO STUFF

1.5V/1.8V/2.5V SUPPLIES

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 35 OF 44	

DIGITAL SIGNALS

GROUP	SIG_NAME		MAX_VIAS	MAX_EXPOSED_LENGTH	STUB_LENGTH	NET_SPACING_TYPE	NO_TEST	PULSE_PARAM	
MAXBUS	CPU_AACK_L				250.0000	10 MIL SPACING			5 8
	CPU_ADDR<0..31>		5		250			83 MHZ	5 8
	CPU_ARTRY_L				250.0000	10 MIL SPACING			5 8
	CPU_BG_L				250.0000	10 MIL SPACING			5 8
	CPU_BR_L				250.0000	10 MIL SPACING			5 8
	CPU_CI_L		5		250.0000				5 8
	CPU_DATA<0..31>		5		250			83 MHZ	6 8
	CPU_DATA<32..63>		5		250			83 MHZ	6 8
	CPU_DBG_L		5		250.0000	10 MIL SPACING			5 8
	CPU_DTI<0..2>		5		250				5 8
	CPU_DRDY_L_UF					10 MIL SPACING			
	CPU_DRDY_L				250.0000	10 MIL SPACING			5 8
	CPU_GBL_L		5		250.0000				5 8
	CPU_HIT_L				250.0000	10 MIL SPACING			5 8
	CPU_QACK_L		5		250.0000	10 MIL SPACING			5 8
	CPU_QREQ_L				250.0000	10 MIL SPACING			5 8
	CPU_TA_L				250.0000	10 MIL SPACING			5 8
	CPU_TBST_L		5		250.0000	10 MIL SPACING			5 8
	CPU_TEA_L				250.0000				5 8
	CPU_TS_L				250.0000	10 MIL SPACING			5 8
	CPU_TSIZ<0..2>		5		250				5 8
	CPU_TT<0..4>		5		250				5 8
	CPU_WT_L		5		250.0000				5 8
GROUP 0	MEM_DATA<7..0>		4		200			167 MHZ	9 10
	RAM_DATA_A<7..0>		4		200			167 MHZ	10 11
	RAM_DATA_B<7..0>		4		200			167 MHZ	10 11
	MEM_DQS<0>	TOTAL LENGTH CONTROLLED BY SPREADSHEET			200				9 10
	RAM_DQS_A<0>		4		200				10 11
	RAM_DQS_B<0>		4		200				10 11
	MEM_DQM<0>		4		200				9 10
	RAM_DQM_A<0>		4		200				10 11
	RAM_DQM_B<0>		4		200				10 11
GROUP 1	MEM_DATA<15..8>		4		200			167 MHZ	9 10
	RAM_DATA_A<15..8>		4		200			167 MHZ	10 11
	RAM_DATA_B<15..8>		4		200			167 MHZ	10 11
	MEM_DQS<1>	TOTAL LENGTH CONTROLLED BY SPREADSHEET	4		200				9 10
	RAM_DQS_A<1>		4		200				10 11
	RAM_DQS_B<1>		4		200				10 11
	MEM_DQM<1>				200				9 10
	RAM_DQM_A<1>		4		200				10 11
	RAM_DQM_B<1>		4		200				10 11
GROUP 2/3	MEM_DATA<31..16>		4		200			167 MHZ	9 10
	RAM_DATA_A<31..16>		4		200			167 MHZ	10 11
	RAM_DATA_B<31..16>		4		200			167 MHZ	10 11
	MEM_DQS<3..2>	TOTAL LENGTH CONTROLLED BY SPREADSHEET	4		200			167 MHZ	9 10
DDR RAM	RAM_DQS_A<3..2>		4		200			167 MHZ	10 11
	RAM_DQS_B<3..2>		4		200			167 MHZ	10 11
	MEM_DQM<3..2>		4		200			167 MHZ	9 10
	RAM_DQM_A<3..2>		4		200			167 MHZ	10 11
	RAM_DQM_B<3..2>		4		200			167 MHZ	10 11
GROUP 4/5	MEM_DATA<47..32>		4		200			167 MHZ	9 10
	RAM_DATA_A<47..32>		4		200			167 MHZ	10 11
	RAM_DATA_B<47..32>		4		200			167 MHZ	10 11
	MEM_DQS<5..4>	TOTAL LENGTH CONTROLLED BY SPREADSHEET	4		200			167 MHZ	9 10
	RAM_DQS_A<5..4>		4		200			167 MHZ	10 11
	RAM_DQS_B<5..4>		4		200			167 MHZ	10 11
	MEM_DQM<5..4>		4		200			167 MHZ	9 10
	RAM_DQM_A<5..4>		4		200			167 MHZ	10 11
	RAM_DQM_B<5..4>		4		200			167 MHZ	10 11
GROUP 6	MEM_DATA<55..48>		4		200			167 MHZ	9 10
	RAM_DATA_A<55..48>		4		200			167 MHZ	10 11
	RAM_DATA_B<55..48>		4		200			167 MHZ	10 11
	MEM_DQS<6>	TOTAL LENGTH CONTROLLED BY SPREADSHEET	4		200				9 10
	RAM_DQS_A<6>				200				10 11
	RAM_DQS_B<6>		4		200				10 11
	MEM_DQM<6>				200				9 10
	RAM_DQM_A<6>		4		200				10 11
	RAM_DQM_B<6>		4		200				10 11
GROUP 7	MEM_DATA<63..56>		4		200			167 MHZ	9 10
	RAM_DATA_A<63..56>		4		200			167 MHZ	10 11
	RAM_DATA_B<63..56>		4		200			167 MHZ	10 11
	MEM_DQS<7>	TOTAL LENGTH CONTROLLED BY SPREADSHEET	4		200				9 10
	RAM_DQS_A<7>				200				10 11
	RAM_DQS_B<7>				200				10 11
	MEM_DQM<7>		4		200				9 10
	RAM_DQM_A<7>		4		200				10 11
	RAM_DQM_B<7>		4		200				10 11
ADDR	MEM_ADDR<12..0>		4					83 MHZ	9
	RAM_ADDR<12..0>		6		200				9 11
CONTROL	MEM_BA<1..0>		4						9
	RAM_BA<1..0>		6		200				9 11
	MEM_CS_L<3..0>		4						9
	RAM_CS_L<3..0>		6		200				9 11
	MEM_CKE<3..0>		4						9
	RAM_CKE<3..0>		6		200				9 11
	MEM_RAS_L		4						9
	RAM_RAS_L				200.0000				9 11
	MEM_CAS_L		4						9
	RAM_CAS_L				200.0000				9 11
	MEM_WE_L		4						9
	RAM_WE_L				200.0000				9 11
	MEM_MUXSEL_H<1..0>		3						9 10
	MEM_MUXSEL_L<1..0>		3						9 10
	RAM_MUXSEL_H		5						10
	RAM_MUXSEL_L		5						10

CLOCK LINE CONSTRAINTS

GROUP	SIG_NAME			MAX VIAS	MAX EXPOSED LENGTH	STUB_LENGTH	NET_SPACING_TYPE	PULSE PARAM	
INTREPID CLOCKS	SYSCLK_CPU_UF						10 MIL SPACING		8
	SYSCLK_CPU			4		200.0000	10 MIL SPACING		5 8
	INT_CPUFB_OUT			3			10 MIL SPACING		8
	INT_CPUFB_OUT_SHORT			3			10 MIL SPACING		8
	INT_CPUFB_OUT_NORM			3			10 MIL SPACING		8
	INT_CPUFB_IN_NORM			3			10 MIL SPACING		8
	INT_CPUFB_LONG			3			10 MIL SPACING		8
	INT_CPUFB_IN					200.0000	10 MIL SPACING		8
	SYSCLK_DDRCLK_A0_UF			3		200.0000	10 MIL SPACING		9
	SYSCLK_DDRCLK_A0_L_UF			3		200.0000	10 MIL SPACING		9
	SYSCLK_DDRCLK_A1_UF			3		200.0000	10 MIL SPACING		9
	SYSCLK_DDRCLK_A1_L_UF			3		200.0000	10 MIL SPACING		9
	SYSCLK_DDRCLK_B0_UF			3		200.0000	10 MIL SPACING		9
	SYSCLK_DDRCLK_B0_L_UF			3		200.0000	10 MIL SPACING		9
	SYSCLK_DDRCLK_B1_UF			3		200.0000	10 MIL SPACING		9
	SYSCLK_DDRCLK_B1_L_UF			3		200.0000	10 MIL SPACING		9
	SYSCLK_DDRCLK_A0	DDRCLK_A0		3		200.0000	10 MIL SPACING		9 11
	SYSCLK_DDRCLK_A0_L	DDRCLK_A0				200.0000	10 MIL SPACING		9 11
	SYSCLK_DDRCLK_A1	DDRCLK_A1		3		200.0000	10 MIL SPACING		9 11
	SYSCLK_DDRCLK_A1_L	DDRCLK_A1				200.0000	10 MIL SPACING		9 11
	SYSCLK_DDRCLK_B0	DDRCLK_B0		3		200.0000	10 MIL SPACING		9 11
	SYSCLK_DDRCLK_B0_L	DDRCLK_B0		3		200.0000	10 MIL SPACING		9 11
	SYSCLK_DDRCLK_B1	DDRCLK_B1		3		200.0000	10 MIL SPACING		9 11
	SYSCLK_DDRCLK_B1_L	DDRCLK_B1		3		200.0000	10 MIL SPACING		9 11
	INT_REF_CLK_OUT			3		200.0000	10 MIL SPACING		14
	INT_REF_CLK_IN					200.0000	10 MIL SPACING		14
	CLK66M_GPU_AGP_UF					200.0000	10 MIL SPACING		12
	CLK66M_GPU_AGP			4		200.0000	10 MIL SPACING		12 18
	INT_AGP_FB_OUT					200.0000	10 MIL SPACING		12
	INT_AGP_FB_IN			4		200.0000	10 MIL SPACING		12
	CLK33M_CBUS_UF					200.0000	10 MIL SPACING		12
	CLK33M_CBUS		SHOULD BE AT MOST 4 VIAS FOR CLK	6		200.0000	10 MIL SPACING		12 17
	CLK33M_AIRPORT_UF					200.0000	10 MIL SPACING		12
	CLK33M_AIRPORT		SHOULD BE AT MOST 4 VIAS FOR CLK	6		200.0000	10 MIL SPACING		12 24 39
	CLK33M_USB2_UF					200.0000	10 MIL SPACING		12
	CLK33M_USB2		SHOULD BE AT MOST 4 VIAS FOR CLK	6		200.0000	10 MIL SPACING		12 26
	INT_PCI_FB_OUT					200.0000	10 MIL SPACING		12
	INT_PCI_FB_IN			3		200.0000	10 MIL SPACING		12
MAP31	GPU_CLK27M_OUT						10 MIL SPACING		
	GPU_CLK27M_UF						10 MIL SPACING		
	GPU_SSCLK_UF						10 MIL SPACING		
	GPU_SSCLK_IN						10 MIL SPACING		
	GPU_FBCLK0						10 MIL SPACING		
	GPU_FBCLK0_L						10 MIL SPACING		
	GPU_FBCLK1						10 MIL SPACING		
	GPU_FBCLK1_L						10 MIL SPACING		
	GPU_DVO_CLKP						10 MIL SPACING		19 20
CRYSTALS	CLK27M_GPU_XOUT						10 MIL SPACING		
	CLK27M_XTAL_IN						10 MIL SPACING		
	CLK27M_GPU_XIN						10 MIL SPACING		
	CLK18M_INT_XIN						10 MIL SPACING		14
	CLK18M_INT_XOUT						10 MIL SPACING		14
	CLK18M_XTAL_IN						10 MIL SPACING		14
	CLK18M_INT_EXT						10 MIL SPACING		14
	CLK25M_ENET_XIN						10 MIL SPACING		27
	CLK25M_ENET_XOUT						10 MIL SPACING		27
	NEC_XT1						10 MIL SPACING		26
	NEC_XT2		THERE'S ANOTHER 280MIL LEG				10 MIL SPACING		26
SOUND	SND_SCLK			7		200.0000	10 MIL SPACING		14 25 39
	SND_CLKOUT					200.0000	10 MIL SPACING		14 25 39
ETHERNET MARVELL	CLKENET_PHY_RX					200.0000			27
	CLKENET_LINK_RX			3		200.0000	10 MIL SPACING		13 27
	CLKENET_PHY_GBE_REF					200.0000			27
	CLKENET_LINK_GBE_REF			3		200.0000	10 MIL SPACING		13 27
	CLKENET_PHY_TX					200.0000			27
	CLKENET_LINK_TX			5		200.0000	10 MIL SPACING		13 27
	CLKENET_LINK_GTX					200.0000			13
	CLKENET_PHY_GTX			3		200.0000	10 MIL SPACING		13 27
FIREWIRE	CLKFW_PHY_PCLK					200.0000			28
	CLKFW_LINK_PCLK			3		200.0000	10 MIL SPACING		13 28
	CLKFW_PHY_LCLK			3		200.0000	10 MIL SPACING		13 28
	CLKFW_LINK_LCLK					200.0000			13
	FW_XI					200.0000	10 MIL SPACING		28
	FW_OSC					200.0000	10 MIL SPACING		28

SIGNAL CONSTRAINTS - PAGE 1

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE D | DRAWING NUMBER 051-6531 | REV. B

SCALE NONE | SHT 36 OF 44

Digital Signals (cont'd)

GROUP	SIG_NAME	DELAY_RULE	MAX_VIAS	MAX_EXPOSED_LENGTH	STUB_LENGTH	NET_SPACING_TYPE	NO_TEST	PULSE_PARAM	
AGP	AGP_AD<15..0>		5	100				66 MHZ	12 18
AGP BYTES 0-1	AGP_CBE<1..0>		5	100				66 MHZ	12 18
	AGP_AD_STB<0>		4	100		8 MIL SPACING			12 18
	AGP_AD_STB_L<0>		4	100		8 MIL SPACING			12 18
AGP BYTES 2-3	AGP_AD<31..16>		5	100				66 MHZ	12 18
	AGP_CBE<3..2>		5	100				66 MHZ	12 18
	AGP_AD_STB<1>		4	100		8 MIL SPACING			12 18
	AGP_AD_STB_L<1>			100		8 MIL SPACING			12 18
AGP SIDEBAND	AGP_SBA<7..0>		5	100				66 MHZ	12 18
	AGP_SB_STB			100.0000		8 MIL SPACING			12 18
	AGP_SB_STB_L		4	100.0000		8 MIL SPACING			12 18
AGP CONTROL	AGP_FRAME_L			250.0000					12 18
	AGP_IRDY_L			250.0000					12 18
	AGP_TRDY_L		6	250.0000					12 18
	AGP_DEVSEL_L			250.0000					12 18
	AGP_STOP_L		6	250.0000					12 18
	AGP_PAR		6	250.0000					12 18
	AGP_REQ_L			285.0000					12 18
	AGP_GNT_L			250.0000					12 18
	AGP_RBF_L			250.0000					12 18
DVO	GPU_DVOD<0..11>		5	250					19 20
	GPU_DVO_HSYNC								19 20
	GPU_DVO_VSYNC								19 20
PCI	PCI_AD<31..0>					MIN_DAISY_CHAIN		33 MHZ	9 12 17 24 26 39
	PCI_CBE<3..0>					MIN_DAISY_CHAIN		33 MHZ	12 17 24 26 39
	PCI_FRAME_L					MIN_DAISY_CHAIN			12 17 24 26 39
	PCI_IRDY_L					MIN_DAISY_CHAIN			12 17 24 26 39
	PCI_TRDY_L					MIN_DAISY_CHAIN			12 17 24 26 39
	PCI_DEVSEL_L					MIN_DAISY_CHAIN			12 17 24 26 39
	PCI_STOP_L					MIN_DAISY_CHAIN			12 17 24 26 39
	PCI_PAR					MIN_DAISY_CHAIN			12 17 24 26 39
ULTRA ATA-100	UIDE_DATA<15..8>			NEED TO MATCH DELAY TO 250	200			100 MHZ	13 24
	UIDE_DATA<7>				200				13 24
	UIDE_DATA<6..0>				200			100 MHZ	13 24
	UIDE_ADDR<2..0>				200			100 MHZ	13 24
	UIDE_RST_L				200.0000				13 24
	UIDE_DIOW_L				200.0000				13 24
	UIDE_DIOR_L			10 MIL SPACING	200.0000				13 24
	UIDE_DMACK_L				200.0000				13 24
	UIDE_CS0_L				200.0000				13 24
	UIDE_CS1_L				200.0000				13 24
	UIDE_DMARQ				200.0000				13
	UIDE_IOCHRDY			10 MIL SPACING	200.0000				13 24
	UIDE_INTRQ				200.0000				13
	HD_DATA<15..0>		5	TOTAL UIDE+HD SKEW <500MIL	200			100 MHZ	24
	HD_ADDR<2..0>		5		200			100 MHZ	24
	HD_RESET_L		5		200.0000				24
	HD_DIOW_L		5		200.0000				24
	HD_DIOR_L		5	10 MIL SPACING	200.0000				24
	HD_DMACK_L		5		200.0000				24
	HD_CS0_L		5		200.0000				24
	HD_CS1_L		5		200.0000				24
	HD_DMARQ				200.0000				13 24
	HD_IOCHRDY		5	10 MIL SPACING	200.0000				24
	HD_INTRQ		5						13 24
EIDE INTREPID	EIDE_DATA<15..0>							33 MHZ	13 24
	EIDE_ADDR<2..0>							33 MHZ	13 24
	EIDE_CS0_L								13 24
	EIDE_CS1_L								13 24
	EIDE_RD_L								13 24
	EIDE_WR_L								13 24
	EIDE_IOCHRDY								13 24
	EIDE_INT								13 24
	EIDE_RST_L								13 24
	EIDE_DMACK_L								13 24
	EIDE_DMARQ								13 24
OPTICAL	EIDE_OPTICAL_DATA<15..0>							33 MHZ	24 39
	EIDE_OPTICAL_ADDR<2..0>							33 MHZ	24 39
	EIDE_OPTICAL_CS0_L								24 39
	EIDE_OPTICAL_CS1_L								24 39
	EIDE_OPTICAL_RD_L								24 39
	EIDE_OPTICAL_WR_L								24 39
	EIDE_OPTICAL_IOCHRDY								24 39
	EIDE_OPTICAL_INT								24 39
	EIDE_OPTICAL_RST_L								24 39
	EIDE_OPTICAL_DMAACK_L								24 39
	EIDE_OPTICAL_DMA_RQ								24 39
ETHERNET MII	ENET_LINK_RXD<7..0>		5						13 27
	ENET_RX_DV								13 27
	ENET_RX_ER								13 27
	ENET_PHY_TXD<7..0>		5						13 27
	ENET_LINK_TXD<7..0>								13
	ENET_PHY_TX_ER		5						13 27
	ENET_LINK_TX_ER								13
	ENET_PHY_TX_EN		5						13 27
	ENET_LINK_TX_EN								13
	ENET_MDIO								13 27
	ENET_MDC								13 27
	ENET_COL								13 27
	ENET_CRS								13 27
FIREWIRE MII	FW_LINK_DATA<7..0>		5						13 28
	FW_PHY_DATA<7..0>		5						28
	FW_LINK_CNTL<1..0>								13 28
	FW_PHY_CNTL<1..0>								28
	FW_LINK_LREQ								13
	FW_PHY_LREQ								13 28
	FW_PINT								13 28

Differential Signals

GROUP	SIG_NAME	DIFFERENTIAL_PAIR		MAX_EXPOSED_LENGTH	NET_SPACING_TYPE	MAX_VIAS	
ETHERNET	MDI_M<0>	ENET_MDI0					27
	MDI_P<0>	ENET_MDI0					27
	MDI_M<1>	ENET_MDI1		SPACING DELETED BECAUSE			27
	MDI_P<1>	ENET_MDI1		OF PHYSICAL CONSTRAINTS			27
	MDI_M<2>	ENET_MDI2		AROUND MARVELL PHY			27
	MDI_P<2>	ENET_MDI2					27
	MDI_M<3>	ENET_MDI3					27
	MDI_P<3>	ENET_MDI3					27
	RJ45_DN<0>	RJ45_DP0			10 MIL SPACING		27 39
	RJ45_DP<0>	RJ45_DP0			10 MIL SPACING		27 39
	RJ45_DN<1>	RJ45_DP1			10 MIL SPACING		27 39
	RJ45_DP<1>	RJ45_DP1			10 MIL SPACING		27 39
	RJ45_DN<2>	RJ45_DP2			10 MIL SPACING		27 39
	RJ45_DP<2>	RJ45_DP2			10 MIL SPACING		27 39
	RJ45_DN<3>	RJ45_DP3			10 MIL SPACING		27 39
	RJ45_DP<3>	RJ45_DP3			10 MIL SPACING		27 39
FIREWIRE	FW_TPA0N	FW_TPA0			MIN_LINE_WIDTH=3.4 10 MIL SPACING		28 29
	FW_TPA0P	FW_TPA0			MIN_LINE_WIDTH=3.4 10 MIL SPACING		28 29
	FW_TPB0N	FW_TPB0			MIN_LINE_WIDTH=3.4 10 MIL SPACING		28 29
	FW_TPB0P	FW_TPB0			MIN_LINE_WIDTH=3.4 10 MIL SPACING		28 29
	FW_TPI0N	FW_TPI0			MIN_LINE_WIDTH=3.4 10 MIL SPACING		
	FW_TPI0P	FW_TPI0			MIN_LINE_WIDTH=3.4 10 MIL SPACING		
	FW_TPO0N	FW_TPO0			MIN_LINE_WIDTH=3.4 10 MIL SPACING		
	FW_TPO0P	FW_TPO0			MIN_LINE_WIDTH=3.4 10 MIL SPACING		
	FW_TPA1N	FW_TPA1		500.0000	MIN_LINE_WIDTH=3.4 10 MIL SPACING		28 29
	FW_TPA1P	FW_TPA1		500.0000	MIN_LINE_WIDTH=3.4 10 MIL SPACING		28 29
	FW_TPB1N	FW_TPB1		500.0000	MIN_LINE_WIDTH=3.4 10 MIL SPACING		28 29
	FW_TPB1P	FW_TPB1		500.0000	MIN_LINE_WIDTH=3.4 10 MIL SPACING		28 29
	FW_TPI1N	FW_TPI1			MIN_LINE_WIDTH=3.4 10 MIL SPACING		29 39
	FW_TPI1P	FW_TPI1			MIN_LINE_WIDTH=3.4 10 MIL SPACING		29 39
	FW_TPO1N	FW_TPO1			MIN_LINE_WIDTH=3.4 10 MIL SPACING		29 39
	FW_TPO1P	FW_TPO1			MIN_LINE_WIDTH=3.4 10 MIL SPACING		29 39
LVDS LOWER	CLKLVDS_LN	CLKLVDS_L			10 MIL SPACING	4	19 22 39
	CLKLVDS_LP	CLKLVDS_L			10 MIL SPACING	4	19 22 39
	LVDS_L0N	LVDS_L0			10 MIL SPACING		19 22 39
	LVDS_L0P	LVDS_L0			10 MIL SPACING		19 22 39
	LVDS_L1N	LVDS_L1			10 MIL SPACING		19 22 39
	LVDS_L1P	LVDS_L1			10 MIL SPACING		19 22 39
	LVDS_L2N	LVDS_L2			10 MIL SPACING		19 22 39
	LVDS_L2P	LVDS_L2			10 MIL SPACING		19 22 39
UPPER	CLKLVDS_UN	CLKLVDS_U			10 MIL SPACING	4	19 22 39
	CLKLVDS_UP	CLKLVDS_U			10 MIL SPACING	4	19 22 39
	LVDS_U0N	LVDS_U0			10 MIL SPACING		19 22 39
	LVDS_U0P	LVDS_U0			10 MIL SPACING		19 22 39
	LVDS_U1N	LVDS_U1			10 MIL SPACING		19 22 39
	LVDS_U1P	LVDS_U1			10 MIL SPACING		19 22 39
	LVDS_U2N	LVDS_U2			10 MIL SPACING		19 22 39
	LVDS_U2P	LVDS_U2			10 MIL SPACING		19 22 39
TMDS	TMDS_CONN_CLKN	CLKCONN_TMDS			10 MIL SPACING	4	22 39
	TMDS_CONN_CLKP	CLKCONN_TMDS			10 MIL SPACING	4	22 39
	TMDS_CLKN	CLKTMDS			10 MIL SPACING	4	20 22
	TMDS_CLKP	CLKTMDS			10 MIL SPACING	4	20 22
	TMDS_DN<0>	TMDS_D0			10 MIL SPACING		20 22 39
	TMDS_DP<0>	TMDS_D0			10 MIL SPACING		20 22 39
	TMDS_DN<1>	TMDS_D1			10 MIL SPACING		20 22 39
	TMDS_DP<1>	TMDS_D1			10 MIL SPACING		20 22 39
	TMDS_DN<2>	TMDS_D2			10 MIL SPACING		20 22 39
	TMDS_DP<2>	TMDS_D2			10 MIL SPACING		20 22 39
USB	NEC_USB_DAM	NEC_USB_DA		MIN_LINE_WIDTH=5	10 MIL SPACING		26
	NEC_USB_DAP	NEC_USB_DA		MIN_LINE_WIDTH=5	10 MIL SPACING		26
	USB_DEM	USB_DE			5 MIL SPACING		14
	USB_DEP	USB_DE			5 MIL SPACING		14
	NEC_USB_DBM	NEC_USB_DB		MIN_LINE_WIDTH=5	10 MIL SPACING		26
	NEC_USB_DBP	NEC_USB_DB		MIN_LINE_WIDTH=5	10 MIL SPACING		26
	USB_DFM	USB_DF			5 MIL SPACING		14
	USB_DFP	USB_DF			5 MIL SPACING		14
	BT_USB_DM	BT_USB_D			5 MIL SPACING		14 24 39
	BT_USB_DP	BT_USB_D			5 MIL SPACING		14 24 39
	NEC_USB_RSDM1	NEC_USB_RSD1		MIN_LINE_WIDTH=5	10 MIL SPACING		26
	NEC_USB_RSDP1	NEC_USB_RSD1		MIN_LINE_WIDTH=5	10 MIL SPACING		26
	NEC_USB_RSDM2	NEC_USB_RSD2		MIN_LINE_WIDTH=5	10 MIL SPACING		26
	NEC_USB_RSDP2	NEC_USB_RSD2		MIN_LINE_WIDTH=5	10 MIL SPACING		26
	MODEM_USB_DM	MODEM_USB_D			5 MIL SPACING		14 25 39
	MODEM_USB_DP	MODEM_USB_D			5 MIL SPACING		14 25 39
	LEFT_USB_DM	LEFT_USB		MIN_LINE_WIDTH=5	10 MIL SPACING		24 26 39
	LEFT_USB_DP	LEFT_USB		MIN_LINE_WIDTH=5	10 MIL SPACING		24 26 39
	RIGHT_USB_DM	RIGHT_USB		MIN_LINE_WIDTH=5	10 MIL SPACING		26 32 39
	RIGHT_USB_DP	RIGHT_USB		MIN_LINE_WIDTH=5	10 MIL SPACING		26 32 39
POWER SUPPLIES	1772_CSSN	1772_CSS					31
	1772_CSSP	1772_CSS					31
	1772_CSIN	1772_CSI					31
	1772_CSIP	1772_CSI					31
	3V_SNSM	3V_SNS					33
	3V_SNSP	3V_SNS					33
	5V_SNSM	5V_SNS					33
	5V_SNSP	5V_SNS					33
THERMOSTAT	THERM1_DM	THERM1					25
	THERM1_DP	THERM1					25
	THERM2_DM	THERM2					25
	THERM2_DP	THERM2					25
	THERM1_M_DM	THERM1_MAIN					
	THERM1_M_DP	THERM1_MAIN					
	THERM2_M_DM	THERM2_MAIN					
	THERM2_M_DP	THERM2_MAIN					
	THERM1_A_DM	THERM1_ALT					25
	THERM1_A_DP	THERM1_ALT					25
	THERM2_A_DM	THERM2_ALT					25
	THERM2_A_DP	THERM2_ALT					25

INTERNAL LAYER

ER = 4.3 (DIELECTRIC CONSTANT)
W = 4MIL (TRACE WIDTH)
B = 12.2MIL (DIST BETW 2 GND PLANES)
T = 0.7MIL (TRACE THICKNESS)
S = 10MIL (SEPERATION OF DIFF TRACES)
ZSINGLE = 51.57OHM
ZDIFF = 99.80HM

FOR FIREWIRE

ER = 4.3 (DIELECTRIC CONSTANT)
W = 3.4MIL (TRACE WIDTH)
B = 12.2MIL (DIST BETW 2 GND PLANES)
T = 0.7MIL (TRACE THICKNESS)
S = 10MIL (SEPERATION OF DIFF TRACES)
ZSINGLE = 53.37OHM
ZDIFF = 107.17OHM

INTERNAL LAYER (USB1.1/USB 2.0)

ER = 4.3 (DIELECTRIC CONSTANT)
W = 4MIL(USB 1.1)/ 5MIL(USB 2.0) (TRACE WIDTH)
B = 12.2MIL (DIST BETW 2 GND PLANES)
T = 0.7MIL (TRACE THICKNESS)
S = 5MIL (USB 1.1) (SEPERATION OF DIFF TRACES)
S = 10MIL (USB 2.0) (SEPERATION OF DIFF TRACES)
ZSINGLE = 51.5OHM (USB 1.1)/ 46.2OHM (USB 2.0)
ZDIFF = 89.3OHM (USB 1.1)/ 89.4OHM (USB 2.0)

SIGNAL CONSTRAINTS - PAGE 2

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE D | DRAWING NUMBER 051-6531 | REV. B
SCALE NONE | SHT 37 OF 44

POWER NET CONSTRAINTS

GROUP	SIG_NAME	VOLTAGE	MIN_LINE_WIDTH	MIN_NECK_WIDTH	
MAIN/SLEEP	+24V_PBUS	VOLTAGE=24V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	39
	+BATT	VOLTAGE=12.6V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	+PBUS	VOLTAGE=12.8V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	39
	+5V_MAIN	VOLTAGE=5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	+5V_SLEEP	VOLTAGE=5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	+3V_MAIN	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	+3V_SLEEP	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=6	
	+3V_PMU	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	39
	+2_5V_MAIN	VOLTAGE=2.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	+2_5V_SLEEP	VOLTAGE=2.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	+1_8V_MAIN	VOLTAGE=1.8V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=6	39
	+1_8V_SLEEP	VOLTAGE=1.8V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	+1_5V_MAIN	VOLTAGE=1.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	+1_5V_SLEEP	VOLTAGE=1.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	+1_5V_LDO	VOLTAGE=1.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	35
	+1_5V_SLEEP_VIN	VOLTAGE=1.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	35
ADAPTER	+ADAPTER	VOLTAGE=24V	MIN_LINE_WIDTH=50	MIN_NECK_WIDTH=10	31 32
	+ADAPTER_SW	VOLTAGE=24V	MIN_LINE_WIDTH=50	MIN_NECK_WIDTH=10	31
	+ADAPTER_SENSE	VOLTAGE=24V	MIN_LINE_WIDTH=50	MIN_NECK_WIDTH=10	31
BATTERY CHARGER	+BATT_POS	VOLTAGE=16.8V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	31 39
	BATT_NEG	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	31 39
	1772_DCIN	VOLTAGE=24V	MIN_LINE_WIDTH=10		31
	1772_LX	VOLTAGE=12.6V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	31
	+BATT_14V_FUSE	VOLTAGE=12.6V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	31
	+BATT_24V_FUSE	VOLTAGE=12.6V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	31
	+BATT_RSNS	VOLTAGE=12.6V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	31
	+BATT_VSNS	VOLTAGE=12.6V	MIN_LINE_WIDTH=10	MIN_NECK_WIDTH=10	31
	1772_LDO	VOLTAGE=5.4V	MIN_LINE_WIDTH=10		31
	1772_DLOV	VOLTAGE=5.4V	MIN_LINE_WIDTH=10		31
	1772_GND	VOLTAGE=0V	MIN_LINE_WIDTH=10		31
PMU	+ADAPTER_ILIM	VOLTAGE=24V	MIN_LINE_WIDTH=10		32
	+ADAPTER_OR_BATT	VOLTAGE=24V	MIN_LINE_WIDTH=10		32
	+4_85V_RAW	VOLTAGE=4.85V	MIN_LINE_WIDTH=10		30 32
	+4_6V_BU	VOLTAGE=4.6V	MIN_LINE_WIDTH=10		32 33
	+4_85V_ESR	VOLTAGE=4.85V	MIN_LINE_WIDTH=10		32
	+3V_PMU_ESR	VOLTAGE=3.3V	MIN_LINE_WIDTH=10		32
	+3V_PMU_AVCC	VOLTAGE=3.3V	MIN_LINE_WIDTH=10		25 30
MISC HD	+5V_HD_SLEEP	VOLTAGE=5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	24 33
	+HD_LOGIC_SLEEP	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	24
TRACKPAD	+5V_TPAD_SLEEP	VOLTAGE=5V	MIN_LINE_WIDTH=10		23 39
HALL EFFECT	+3V_HALL_EFFECT	VOLTAGE=3.3V	MIN_LINE_WIDTH=10		23 39
VIDEO	+12_8V_INV	VOLTAGE=12.8V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	22 39
	+5V_INV_UF_SW	VOLTAGE=5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	22
	+5V_INV_SW	VOLTAGE=5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	22 39
	+5V_DDC_SLEEP	VOLTAGE=5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	22 39
	+5V_DDC_SLEEP_UF	VOLTAGE=5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	22
	+3V_LCD	VOLTAGE=3.3V	MIN_LINE_WIDTH=12	MIN_NECK_WIDTH=10	22
	+3V_LCD_SW	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	22
	GPU_TV_GND1	VOLTAGE=0V	MIN_LINE_WIDTH=25		22
	GPU_TV_GND2	VOLTAGE=0V	MIN_LINE_WIDTH=25		22
	TV_GND1	VOLTAGE=0V	MIN_LINE_WIDTH=25		22 39
	TV_GND2	VOLTAGE=0V	MIN_LINE_WIDTH=25		22 39
KB LED	KBD_LED1_OUT	VOLTAGE=0V	MIN_LINE_WIDTH=10		23 39
	KBD_LED2_OUT	VOLTAGE=0V	MIN_LINE_WIDTH=10		23 39
FAN GND	FANL_GND	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	25 39
	FANR_GND	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	25 39
SOUND	+5V_SOUND_SLEEP	VOLTAGE=5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	SND_AGND	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=15	25

I/O AREA	GND	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=6	
	CHGND1	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=12	CHGND1
INVERTER	CHGND2	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=12	CHGND2
TRACKPAD	CHGND3	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=12	CHGND3
LVDS	CHGND4	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=12	CHGND4 39
I/O AREA	CHGND5	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=12	CHGND5
I/O AREA	CHGND6	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=12	CHGND6
	ENET_CTAP_CHGND	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=12	27

GROUP	SIG_NAME	VOLTAGE	MIN_LINE_WIDTH	MIN_NECK_WIDTH	
CPU	CPU_VCORE_SLEEP	VOLTAGE=1.4V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	5 34 39
	CPU_AVDD	VOLTAGE=1.4V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	5
DDR RAM	MAXBUS_SLEEP	VOLTAGE=1.8V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	5 7 8 15 16 23 34
INTREPID	DDR_VREF	VOLTAGE=1.25V	MIN_LINE_WIDTH=10		11
	+2_5V_INTREPID	VOLTAGE=2.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	9 10 15 16
	+3V_INTREPID_USB	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	14
PLLS	+1_5V_INTREPID_PLL	VOLTAGE=1.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	8 12 14
	+1_5V_INTREPID_PLL1	VOLTAGE=1.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=6	14
	+1_5V_INTREPID_PLL2	VOLTAGE=1.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=6	14
	+1_5V_INTREPID_PLL3	VOLTAGE=1.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=6	14
	+1_5V_INTREPID_PLL4	VOLTAGE=1.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=5	14
	+1_5V_INTREPID_PLL5	VOLTAGE=1.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=5	12
	+1_5V_INTREPID_PLL6	VOLTAGE=1.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=6	12
	+1_5V_INTREPID_PLL7	VOLTAGE=1.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=6	8
	+1_5V_INTREPID_PLL8	VOLTAGE=1.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=6	14
REFERENCE	INT_MEM_VREF	VOLTAGE=1.25V	MIN_LINE_WIDTH=10		9
	INT_AGP_VREF	VOLTAGE=1.25V	MIN_LINE_WIDTH=10		12 18
	INT_MEM_REF_H	VOLTAGE=0V	MIN_LINE_WIDTH=10		9
	UIDE_REF	VOLTAGE=0V	MIN_LINE_WIDTH=8		13
CARDBUS	+VCC_CBUS_SW	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	17
	+VPP_CBUS_SW	VOLTAGE=5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	17
ATI M10	GPU_VCORE	VOLTAGE=1.2V	MIN_LINE_WIDTH=30	MIN_NECK_WIDTH=10	18 19 39
	+GPU_MEM	VOLTAGE=2.5V	MIN_LINE_WIDTH=30	MIN_NECK_WIDTH=10	18 21
	+3V_GPU	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	12 18 19 21
	+3V_GPU_FLT	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=8	21
	+1_5V_AGP	VOLTAGE=1.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	12 15 16 18 19 21
	GPU_MEM_IO	VOLTAGE=2.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	
	GPU_MEM_IO_FLT	VOLTAGE=2.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	21
	+GPU_MEMCORE	VOLTAGE=2.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	21
	+1_8V_GPU	VOLTAGE=1.8V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	18 19 20 21
	+2_5V_GPU_PNLIO	VOLTAGE=2.5V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	21
	+1_8V_ATI_PVDD	VOLTAGE=1.8V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	19 21
	+1_5V_AGP_GPU	VOLTAGE=1.5V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	21
	+1_5V_GPU_VDD15	VOLTAGE=1.5V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	19
	+1_8V_GPU_PLL	VOLTAGE=1.8V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	21
1581	+1_8V_GPU_VDDDI	VOLTAGE=1.8V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	21
1582	GPU_VCORE_VDDCI	VOLTAGE=1.2V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	18
1583	+2_5V_GPU_A2VDD	VOLTAGE=2.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	21
1584	+1_8V_GPU_AVDD	VOLTAGE=1.8V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	21
1585	+1_8V_GPU_PNLPLL	VOLTAGE=1.8V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	21
1586	+1_8V_GPU_PNLIO	VOLTAGE=1.8V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	21
1587	+GPU_MCLK	VOLTAGE=2.5V	MIN_LINE_WIDTH=10	MIN_NECK_WIDTH=10	21
1588	+1_8V_GPU_AVDDQ	VOLTAGE=1.8V	MIN_LINE_WIDTH=10	MIN_NECK_WIDTH=10	21
1644	+1_8V_GPU_MEMPLL	VOLTAGE=1.8V	MIN_LINE_WIDTH=10	MIN_NECK_WIDTH=10	21
1646	+3V_ATI_OSC_SLEEP	VOLTAGE=3.3V	MIN_LINE_WIDTH=10	MIN_NECK_WIDTH=10	18
1589	+3V_ATI_SS	VOLTAGE=3.3V	MIN_LINE_WIDTH=10	MIN_NECK_WIDTH=10	18
1642	+GPU_VDD15_UF	VOLTAGE=1.5V	MIN_LINE_WIDTH=20		19
1643	+2_5V_SLEEP_NECK1	VOLTAGE=1.8V	MIN_LINE_WIDTH=10		19
1647	+3V_SLEEP_NECK	VOLTAGE=1.8V	MIN_LINE_WIDTH=10		21
1645	+1_5V_AGP_NECK	VOLTAGE=1.8V	MIN_LINE_WIDTH=10		19
1648	+1_8V_PVDD_NECK	VOLTAGE=2.5V	MIN_LINE_WIDTH=10		19
1649	GPU_VCORE_NECK	VOLTAGE=1.8V	MIN_LINE_WIDTH=10		19
1650	+GPU_VDD15_NECK	VOLTAGE=1.8V	MIN_LINE_WIDTH=10		19
1651	+2_5V_SLEEP_NECK2	VOLTAGE=3.3V	MIN_LINE_WIDTH=10		21
1652	+1_8V_SLEEP_NECK	VOLTAGE=3.3V	MIN_LINE_WIDTH=10		21
1653	+1_5V_SLEEP_NECK	VOLTAGE=1.5V	MIN_LINE_WIDTH=10		21
1654	+2_5V_GPU	VOLTAGE=2.5V	MIN_LINE_WIDTH=10	MIN_NECK_WIDTH=10	21
SILICON IMIAGE	+3V_SI_PLLVCC	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=8	20
	+3V_SI_AVCC	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=8	20
	+3V_SI_VCC	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=8	20
88E1111	+2_5V_MARVELL	VOLTAGE=2.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	27
	+2_5V_MARVELL_AVDD	VOLTAGE=2.5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=8	27
	+1_0V_MARVELL	VOLTAGE=1.0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=8	27
	LTC3405_SW	VOLTAGE=1.0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=8	27
	LM2594_IN	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
FW	+3V_FW_ESD_ILIM	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	29
	+3V_FW_ESD	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	29
	+FW_FUSE	VOLTAGE=12.8V	MIN_LINE_WIDTH=100	MIN_NECK_WIDTH=12	29
	+FW_SW	VOLTAGE=12.8V	MIN_LINE_WIDTH=100	MIN_NECK_WIDTH=12	29
	+FW_PWR_OR	VOLTAGE=33V	MIN_LINE_WIDTH=100	MIN_NECK_WIDTH=12	28 29
	+FW_VP0	VOLTAGE=33V	MIN_LINE_WIDTH=100	MIN_NECK_WIDTH=12	29
	+FW_PWR_PORTA	VOLTAGE=33V	MIN_LINE_WIDTH=100	MIN_NECK_WIDTH=12	29
	+FW_VP1	VOLTAGE=33V	MIN_LINE_WIDTH=100	MIN_NECK_WIDTH=12	29
	+3V_FW	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28 29
	+3V_FW_UF	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	+3V_FW_AVDD_PORT2	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	+3V_FW_AVDD_PORT1	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=6	28
	+3V_FW_AVDD_PORT0	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	+3V_FW_AVDD	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	+1_95V_FW_DVDD	VOLTAGE=1.95V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	+1_95V_FW_DVDD_RX0	VOLTAGE=1.95V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	+1_95V_FW_DVDD_TX0	VOLTAGE=1.95V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	+1_95V_FW_DVDD_PORT1	VOLTAGE=1.95V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	+1_95V_FW_PLLVDD	VOLTAGE=1.95V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	+1_95V_FW_PLL400VDD	VOLTAGE=1.95V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	+1_95V_FW_PLL500VDD	VOLTAGE=1.95V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	28
	FW_VGND0	VOLTAGE=0V	MIN_LINE_WIDTH=100	MIN_NECK_WIDTH=12	29
	FW_VGND1	VOLTAGE=0V	MIN_LINE_WIDTH=100	MIN_NECK_WIDTH=12	29
	FW_TPO0R	VOLTAGE=0V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	29 39
USB 2.0	NEC_AVDD	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	26
	+3V_NEC_VDD	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	26
INTREPID SSCG	+3V_CG_PLL_MAIN	VOLTAGE=3.3V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=8	14
	+2_5V_CG_MAIN	VOLTAGE=2.5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=8	14

GROUP	SIG_NAME	VOLTAGE	MIN_LINE_WIDTH	MIN_NECK_WIDTH	
LTC1625 14V SWITCHER	1625_VIN	VOLTAGE=24V	MIN_LINE_WIDTH=10		32
	1625_VSW	VOLTAGE=12.8V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	32
	1625_EXTVCC	VOLTAGE=5V	MIN_LINE_WIDTH=10		32
	1625_INTVCC	VOLTAGE=5V	MIN_LINE_WIDTH=10		32
	1625_SGND	VOLTAGE=0V	MIN_LINE_WIDTH=10		32
	1V20_REF	VOLTAGE=1.2V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	31 32
LTC3707 5V SWITCHER	3707_INTVCC	VOLTAGE=5V	MIN_LINE_WIDTH=10	MIN_NECK_WIDTH=10	33
	5V_SW	VOLTAGE=5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	33
	5V_RSNS	VOLTAGE=5V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	33
3V SWITCHER	3V_SW	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	33
	3V_RSNS	VOLTAGE=3.3V	MIN_LINE_WIDTH=25	MIN_NECK_WIDTH=10	33
	3707_SGND	VOLTAGE=0V	MIN_LINE_WIDTH=10		33
MAX1715 2.5V SWITCHER	2_5V_LX	VOLTAGE=2.5V	MIN_LINE_WIDTH=50	MIN_NECK_WIDTH=10	35
	2_5V_BST	VOLTAGE=5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	35
	2_5V_BOOST	VOLTAGE=5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	35
	2_5V_DH	VOLTAGE=2.5V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	35
	2_5V_DL	VOLTAGE=2.5V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	35
1.5V SWITCHER	1_5V_FB	VOLTAGE=1.5V	MIN_LINE_WIDTH=8		35
	1_5V_LX	VOLTAGE=1.5V	MIN_LINE_WIDTH=50	MIN_NECK_WIDTH=10	35
	1_5V_BST	VOLTAGE=5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	35
	1_5V_BOOST	VOLTAGE=5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	35
	1_5V_DH	VOLTAGE=1.5V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	35
	1_5V_DL	VOLTAGE=1.5V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	35
CONTROL	1_5V_ILIM		MIN_LINE_WIDTH=8		35
	2_5V_ILIM		MIN_LINE_WIDTH=8		35
	MAX1715_TON		MIN_LINE_WIDTH=8		35
	MAX1715_SKIP		MIN_LINE_WIDTH=8		35
	MAX1715_REF	VOLTAGE=2.0V	MIN_LINE_WIDTH=8		35
	MAX1715_VCC	VOLTAGE=5V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	35
	MAX1715_GND	VOLTAGE=0V	MIN_LINE_WIDTH=30	MIN_NECK_WIDTH=10	35
MAX1717	VCORE_VCC	VOLTAGE=5V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	34
	VCORE_LX	VOLTAGE=1.4V	MIN_LINE_WIDTH=200	MIN_NECK_WIDTH=10	34
	VCORE_DH		MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	34
	VCORE_DL		MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	34
	VCORE_BOOST	VOLTAGE=5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	34
	VCORE_BST	VOLTAGE=5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	34
	VCORE_ILIM		MIN_LINE_WIDTH=8		34
	VCORE_REF		MIN_LINE_WIDTH=8		34
	VCORE_TON	VOLTAGE=5V	MIN_LINE_WIDTH=8		34
	VCORE_CC		MIN_LINE_WIDTH=8		34
	VCORE_FB	VOLTAGE=1.4V	MIN_LINE_WIDTH=8		34 39
	VCORE_TIME		MIN_LINE_WIDTH=8		34
	VCORE_VGATE		MIN_LINE_WIDTH=8		14 34
	VCORE_GND	VOLTAGE=0V	MIN_LINE_WIDTH=30		34
	VCORE_GNDSNS	VOLTAGE=0V	MIN_LINE_WIDTH=8		34
	VCORE_SNS	VOLTAGE=1.4V	MIN_LINE_WIDTH=8		34
	VCORE_GNDDIV	VOLTAGE=0V	MIN_LINE_WIDTH=8		34
LTC1778	1778_VIN	VOLTAGE=14V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	19
	1778_VCC	VOLTAGE=5V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	19
	1778_GND	VOLTAGE=0V	MIN_LINE_WIDTH=30	MIN_NECK_WIDTH=10	19
	1778_BST	VOLTAGE=5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	19
	1778_BST_RC	VOLTAGE=5V	MIN_LINE_WIDTH=15	MIN_NECK_WIDTH=10	19
	1778_TG		MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	19
	1778_BG		MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	19
	GPU_VCORE_SW	VOLTAGE=1.2V	MIN_LINE_WIDTH=50	MIN_NECK_WIDTH=10	19
	1778_ION		MIN_LINE_WIDTH=8		19
	1778_ITH		MIN_LINE_WIDTH=8		19
	1778_ITH_RC		MIN_LINE_WIDTH=8		19
	1_5V_2_5V_OK		MIN_LINE_WIDTH=8		35
	1778_VFB		MIN_LINE_WIDTH=8		19 39
	1778_FCB		MIN_LINE_WIDTH=8		19
	1778_VRNG		MIN_LINE_WIDTH=8		19
LTC3411	LTC3411_VCC	VOLTAGE=3.3V	MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	
	LTC3411_GND	VOLTAGE=0V	MIN_LINE_WIDTH=30	MIN_NECK_WIDTH=10	
	1_8V_SW	VOLTAGE=1.8V	MIN_LINE_WIDTH=30	MIN_NECK_WIDTH=10	35
	1_8V_VFB		MIN_LINE_WIDTH=8		
	LTC3411_ITH_RC		MIN_LINE_WIDTH=8		
	LTC3411_ITH		MIN_LINE_WIDTH=8		
	LTC3411_SYNC		MIN_LINE_WIDTH=8		
	LTC3411_SHDN		MIN_LINE_WIDTH=8		
LTC1962 INT PLLS	LTC1962_INT_VIN		MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	14
	LTC1962_L3_VIN		MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	
	LTC1962_L3_VOUT		MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	
	LTC1962_1V5_VIN		MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	
	LTC1962_1V5_VOUT		MIN_LINE_WIDTH=20	MIN_NECK_WIDTH=10	

SIGNAL CONSTRAINTS - PAGE 3

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 38 OF 44	

FUNCTIONAL TEST POINTS

FUNC_TEST=YES JTAG_ASIC_TMS 13 27
FUNC_TEST=YES JTAG_ASIC_TDI 13
FUNC_TEST=YES JTAG_ASIC_TDO_TP 27
FUNC_TEST=YES JTAG_ASIC_TCK 13 27
FUNC_TEST=YES JTAG_ASIC_TRST_L 13 27
FUNC_TEST=YES CPU_CHKSTP_OUT_L 5
FUNC_TEST=YES CPU_SRESET_L 5
FUNC_TEST=YES CPU_HRESET_L 5 7 23
FUNC_TEST=YES JTAG_CPU_TMS 5 23
FUNC_TEST=YES JTAG_CPU_TDI 5 23
FUNC_TEST=YES JTAG_CPU_TDO_TP 5
FUNC_TEST=YES JTAG_CPU_TCK 5 23
FUNC_TEST=YES JTAG_CPU_TRST_L 5 23 39

FUNC_TEST=YES TMDS_CONN_CLKP 22 37
FUNC_TEST=YES VGA_R 22
FUNC_TEST=YES VGA_G 22
FUNC_TEST=YES VGA_B 22
FUNC_TEST=YES VGA_VSYNC 22
FUNC_TEST=YES VGA_HSYNC 22
FUNC_TEST=YES DVI_DDC_CLK_UF 22
FUNC_TEST=YES DVI_DDC_DATA_UF 22
FUNC_TEST=YES DVI_HPD_UF 22
FUNC_TEST=YES LVDS_L0N 19 22 37
FUNC_TEST=YES LVDS_L0P 19 22 37
FUNC_TEST=YES LVDS_L1N 19 22 37
FUNC_TEST=YES LVDS_L1P 19 22 37
FUNC_TEST=YES LVDS_L2N 19 22 37
FUNC_TEST=YES LVDS_L2P 19 22 37
FUNC_TEST=YES CLKLVDS_LN 19 22 37
FUNC_TEST=YES CLKLVDS_LP 19 22 37
FUNC_TEST=YES LVDS_U0N 19 22 37
FUNC_TEST=YES LVDS_U0P 19 22 37
FUNC_TEST=YES LVDS_U1N 19 22 37
FUNC_TEST=YES LVDS_U1P 19 22 37
FUNC_TEST=YES LVDS_U2N 19 22 37
FUNC_TEST=YES LVDS_U2P 19 22 37
FUNC_TEST=YES CLKLVDS_UN 19 22 37
FUNC_TEST=YES CLKLVDS_UP 19 22 37
FUNC_TEST=YES LVDS_DDC_CLK 19 22
FUNC_TEST=YES LVDS_DDC_DATA 19 22
FUNC_TEST=YES BRIGHT_PWM 22
FUNC_TEST=YES TV_GND1 22 38
FUNC_TEST=YES TV_GND2 22 38

FUNC_TEST=YES TV_C 22
FUNC_TEST=YES TV_Y 22
FUNC_TEST=YES TV_COMP 22
FUNC_TEST=YES SND_TO_AUDIO 14 25
FUNC_TEST=YES SND_SYNC 14 25
FUNC_TEST=YES SND_CLKOUT 14 25 36

FUNC_TEST=YES INT_AUDIO_TO_SND 14 25
FUNC_TEST=YES SND_SCLK 14 25 36
FUNC_TEST=YES SND_HW_RESET_L 14 25
FUNC_TEST=YES SND_HP_SENSE_L 14 25
FUNC_TEST=YES SND_LIN_SENSE_L 14 25
FUNC_TEST=YES INT_I2C_DATA2 14 25
FUNC_TEST=YES INT_I2C_CLK2 14 25
T290 FUNC_TEST=YES CHGND4 38
T290 FUNC_TEST=YES SLEEP_LED 23 25

FUNC_TEST=YES INT_I2C_CLK0 11 13 23
FUNC_TEST=YES INT_I2C_DATA0 11 13 23
FUNC_TEST=YES INT_I2C_CLK1 13 14 25
FUNC_TEST=YES INT_I2C_DATA1 13 14 25
FUNC_TEST=YES CBUS_DET_1_L 17
FUNC_TEST=YES CBUS_DET_2_L 17
FUNC_TEST=YES TMDS_DN<0> 20 22 37
FUNC_TEST=YES TMDS_DP<0> 20 22 37
FUNC_TEST=YES TMDS_DN<1> 20 22 37
FUNC_TEST=YES TMDS_DP<1> 20 22 37
FUNC_TEST=YES TMDS_DN<2> 20 22 37
FUNC_TEST=YES TMDS_DP<2> 20 22 37
FUNC_TEST=YES TMDS_CONN_CLKN 22 37

FUNC_TEST=YES BT_USB_DM 14 24 37
FUNC_TEST=YES BT_USB_DP 14 24 37
FUNC_TEST=YES MODEM_USB_DM 14 25 37
FUNC_TEST=YES MODEM_USB_DP 14 25 37
FUNC_TEST=YES PCI_AD<0> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<1> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<2> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<3> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<4> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<5> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<6> 9 12 17 24 26 37

FUNC_TEST=YES PCI_AD<7> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<8> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<9> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<10> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<11> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<12> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<13> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<14> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<15> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<16> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<17> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<18> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<19> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<20> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<21> 12 17 24 26 37
FUNC_TEST=YES PCI_AD<22> 12 17 24 26 37
FUNC_TEST=YES PCI_AD<23> 12 17 24 26 37
FUNC_TEST=YES PCI_AD<24> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<25> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<26> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<27> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<28> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<29> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<30> 9 12 17 24 26 37
FUNC_TEST=YES PCI_AD<31> 9 12 17 24 26 37
FUNC_TEST=YES PCI_FRAME_L 12 17 24 26 37
FUNC_TEST=YES PCI_TRDY_L 12 17 24 26 37
FUNC_TEST=YES PCI_IRDY_L 12 17 24 26 37
FUNC_TEST=YES PCI_DEVSEL_L 12 17 24 26 37
FUNC_TEST=YES PCI_STOP_L 12 17 24 26 37

FUNC_TEST=YES PCI_PAR 12 17 24 26 37
FUNC_TEST=YES PCI_CBE<0> 12 17 24 26 37
FUNC_TEST=YES PCI_CBE<1> 12 17 24 26 37
FUNC_TEST=YES PCI_CBE<2> 12 17 24 26 37
FUNC_TEST=YES PCI_CBE<3> 12 17 24 26 37
FUNC_TEST=YES AIRPORT_PCI_REQ_L 12 24
FUNC_TEST=YES AIRPORT_PCI_GNT_L 12 24
FUNC_TEST=YES AIRPORT_PCI_INT_L 14 24
FUNC_TEST=YES EIDE_OPTICAL_DATA<0> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<1> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<2> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<3> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<4> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<5> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<6> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<7> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<8> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<9> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<10> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<11> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<12> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<13> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<14> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DATA<15> 24 37
FUNC_TEST=YES EIDE_OPTICAL_DMA_RQ 24 37
FUNC_TEST=YES EIDE_OPTICAL_RD_L 24 37
FUNC_TEST=YES EIDE_OPTICAL_DMAACK_L 24 37
FUNC_TEST=YES EIDE_OPTICAL_ADDR<0> 24 37
FUNC_TEST=YES EIDE_OPTICAL_ADDR<1> 24 37
FUNC_TEST=YES EIDE_OPTICAL_ADDR<2> 24 37
T291 FUNC_TEST=YES SND_AMP_MUTE 25
T292 FUNC_TEST=YES SND_HP_MUTE_INV 25

FUNC_TEST=YES EIDE_OPTICAL_CS0_L 24 37
FUNC_TEST=YES EIDE_OPTICAL_CS1_L 24 37
FUNC_TEST=YES EIDE_OPTICAL_RST_L 24 37
FUNC_TEST=YES EIDE_OPTICAL_WR_L 24 37
FUNC_TEST=YES EIDE_OPTICAL_IOCHRDY 24 37
FUNC_TEST=YES EIDE_OPTICAL_INT 24 37
FUNC_TEST=YES TPAD_F_TXD 23
FUNC_TEST=YES TPAD_F_RXD 23
FUNC_TEST=YES LID_CLOSED_L 23
FUNC_TEST=YES COMM_RESET_L 14 25
FUNC_TEST=YES COMM_SHUTDOWN 14 25
FUNC_TEST=YES COMM_RING_DET_L 14 25 30
FUNC_TEST=YES KBD_ID 23 30
FUNC_TEST=YES +5V_TPAD_SLEEP 23 38
FUNC_TEST=YES +3V_HALL_EFFECT 23 38
FUNC_TEST=YES KBD_CAPSLOCK_LED 23
FUNC_TEST=YES KBD_FUNCTION_L 23 30
FUNC_TEST=YES KBD_CONTROL_L 23 30
FUNC_TEST=YES KBD_COMMAND_L 23 30
FUNC_TEST=YES KBD_OPTION_L 23 30
FUNC_TEST=YES KBD_SHIFT_L 23 30
FUNC_TEST=YES KBD_X<0> 23 30
FUNC_TEST=YES KBD_X<1> 23 30
FUNC_TEST=YES KBD_X<2> 23 30
FUNC_TEST=YES KBD_X<3> 23 30
FUNC_TEST=YES KBD_X<4> 23 30
FUNC_TEST=YES KBD_X<5> 23 30
FUNC_TEST=YES KBD_X<6> 23 30
FUNC_TEST=YES KBD_X<7> 23 30
FUNC_TEST=YES KBD_X<8> 23 30
T289 FUNC_TEST=YES SRCLK_TP 26
T288 FUNC_TEST=YES SRMOD_TP 26
T290 FUNC_TEST=YES TEB_TP 26
T290 FUNC_TEST=YES TEST_TP 26

FUNC_TEST=YES KBD_X<9> 23 30
FUNC_TEST=YES KBD_Y<0> 23 30
FUNC_TEST=YES KBD_Y<1> 23 30
FUNC_TEST=YES KBD_Y<2> 23 30
FUNC_TEST=YES KBD_Y<3> 23 30
FUNC_TEST=YES KBD_Y<4> 23 30
FUNC_TEST=YES KBD_Y<5> 23 30
FUNC_TEST=YES KBD_Y<6> 23 30
FUNC_TEST=YES KBD_Y<7> 23 30
FUNC_TEST=YES KBD_NUMLOCK_LED 23
FUNC_TEST=YES +BATT_POS 31 38
FUNC_TEST=YES BATT_CLK 31
FUNC_TEST=YES BATT_DATA 31
FUNC_TEST=YES BATT_NEG 31 38
FUNC_TEST=YES PMU_BATT_DET_L 30 31
FUNC_TEST=YES FANR_GND 25 38
FUNC_TEST=YES FANL_GND 25 38
FUNC_TEST=YES FANL_TACH 25
T271 FUNC_TEST=YES FANR_PWM 25
T272 FUNC_TEST=YES FANL_PWM 25
FUNC_TEST=YES RJ45_DP<0> 27 37
FUNC_TEST=YES RJ45_DN<0> 27 37
FUNC_TEST=YES RJ45_DP<1> 27 37
FUNC_TEST=YES RJ45_DN<1> 27 37
FUNC_TEST=YES RJ45_DP<2> 27 37
FUNC_TEST=YES RJ45_DN<2> 27 37
FUNC_TEST=YES RJ45_DP<3> 27 37
FUNC_TEST=YES RJ45_DN<3> 27 37
FUNC_TEST=YES FW_TPO0R 29 38
T281 FUNC_TEST=YES VCORE_VID0
T282 FUNC_TEST=YES VCORE_VID1
T283 FUNC_TEST=YES VCORE_VID2
T284 FUNC_TEST=YES VCORE_VID3
T285 FUNC_TEST=YES VCORE_VID4

FUNC_TEST=YES FW_TPO1P 29 37
FUNC_TEST=YES FW_TPO1N 29 37
FUNC_TEST=YES FW_TPI1P 29 37
FUNC_TEST=YES FW_TPI1N 29 37
FUNC_TEST=YES CHARGE_LED_L 30 31
FUNC_TEST=YES ADAPTER_DET 30 31
FUNC_TEST=YES SUTRO_ALS_GAIN_SW 23 24
FUNC_TEST=YES SUTRO_ALS_OUT 23 24
FUNC_TEST=YES KBD_LED1_OUT 23 38
FUNC_TEST=YES KBD_LED2_OUT 23 38
FUNC_TEST=YES COMM_TXD_L 14 25
FUNC_TEST=YES COMM_TRXC 14 25
FUNC_TEST=YES COMM_GPIO_L 14 25
FUNC_TEST=YES COMM_DTR_L 14 25
FUNC_TEST=YES COMM_RTS_L 14 25
FUNC_TEST=YES COMM_RXD 14 25
FUNC_TEST=YES PMU_KB_RESET_L 30
FUNC_TEST=YES PWR_BUTTON_L 23 25
FUNC_TEST=YES +PBUS 38
FUNC_TEST=YES +24V_PBUS 38
FUNC_TEST=YES GPU_VCORE 18 19 38
FUNC_TEST=YES CPU_VCORE_SLEEP 5 34 38
FUNC_TEST=YES VCORE_FB 34 38
FUNC_TEST=YES +1_8V_MAIN 38
FUNC_TEST=YES +3V_PMU 38
FUNC_TEST=YES +5V_DDC_SLEEP 22 38
FUNC_TEST=YES +12_8V_INV 22 38
T286 FUNC_TEST=YES VCORE_MUX_EN 34

FUNC_TEST=YES +5V_INV_SW 22 38
FUNC_TEST=YES LEFT_USB_DM 24 26 37
FUNC_TEST=YES LEFT_USB_DP 24 26 37
FUNC_TEST=YES RIGHT_USB_DM 26 32 37
FUNC_TEST=YES RIGHT_USB_DP 26 32 37
FUNC_TEST=YES NEC_LEFT_USB_PWREN 24 26
FUNC_TEST=YES NEC_LEFT_USB_OVERCURRENT 24 26
FUNC_TEST=YES NEC_RIGHT_USB_PWREN 26 32
FUNC_TEST=YES NEC_RIGHT_USB_OVERCURRENT 26 32
FUNC_TEST=YES DCDC_EN 19 29 32 33 34
FUNC_TEST=YES BBANG_HRESET_L 23
FUNC_TEST=YES MAIN_RESET_L 14 17 18 20 24 26 30
FUNC_TEST=YES RF_DISABLE_L_SPN 24
FUNC_TEST=YES AIRPORT_CLKRUN_L 24
FUNC_TEST=YES ROM_RW_L 9 12 24
FUNC_TEST=YES ROM_ONBOARD_CS_L 9 24
FUNC_TEST=YES ROM_CS_L 9 12 24
FUNC_TEST=YES CLK33M_AIRPORT 12 24 36
FUNC_TEST=YES AIRPORT_IDSEL 24
FUNC_TEST=YES ROM_OE_L 9 12 24
FUNC_TEST=YES INT_MOD_DTI 14 25
T274 FUNC_TEST=YES JTAG_CPU_TRST_L 5 23 39
FUNC_TEST=YES MOD_BITCLK 14 25
T276 FUNC_TEST=YES MOD_CLKOUT 14 25
T277 FUNC_TEST=YES MOD_DTO 14 25
T278 FUNC_TEST=YES MOD_SYNC 14 25
T279 FUNC_TEST=YES SLEEP 23 25 30 33 35
T280 FUNC_TEST=YES 1778_VFB 19 38

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE D | DRAWING NUMBER 051-6531 | REV. B

SCALE NONE | SHT 39 OF 44

REVISION HISTORY

REV 0.01 - 03/06/2003

3/3
1) Initial check-in of Enterprise schematic after conversion to Concept 14.2

3/10
2) added 8 new 10uF vcore caps
3) added jumpers at 1.5V, 1.8V, 2.5V, 3.3V, 5V, and PBUS supply outputs
4) added 8 more 0.1uF vcore byapass caps

3/11
5) removed dedicated boot banger circuit (U5400,U5200,RP46,U9,U1000)
6) updated firewire to phy to rev A prt number
7) changed cpu PLL config to 1083/833
8) changed reset to U56 (clock slewing chip) to MAIN_RESET_L
9) changed C550 to 138S0536 to limit AVL
10) changed Vcore stuffing options to 1.4V/1.025V using analog mux to support slewing
11) changed stuffing to set Vcore offset to 0mV by default
12) changed comments to eliminate references to L3 in power supply section

3/18
13) changed stuffing options for GPU PCI ID to 0x319
14) changed R164 (DAC1RSET) to 107 ohm pulldown
15) added 10K pulldown to U43 pin A21
16) changed fan controller to ADT7460

3/19
17) added pads for 0.1uF cap from +Adapter to digital gnd for EMC
18) added pads for 0 ohm between chassis and digital gnd near ENET connector for EMC
19) corrected path to correct for last checkin
20) removed BOM table for MAP31
21) REMOVED ALL RELATIVE_PROPAGATION_DELAY AND PROPAGATION_DELAY PROPERTIES TO PRERPARE FOR CONSTRAINT BACK ANNOTATION
22) changed CHGND on R616 to CHGND1
23) ***BOARD RENUMBERED***

3/28
24) integrated M10 pages from Q16 schematic and renumbered them

4/10
25) updated physical constraints for M10 power nets
26) added DP7 for M10 power sequencing
27) added RP27,RP28,RP32, and RP57 for TMDS series termination
28) update PLL CFG high 0010 1.25GHz
low 1011 833MHz
29) update sscg/nosscg stuffing option on intrepid boot straps
30) removed D31 between +Batt and 24V_Pbus
31) add Vcore DAC resistors (R288,R289,R290,R292) for no mux case
32) change intrepid PLL LDO stuffing back to 1.8V main
33) change C640 and C646 to 0.01uF (Apple # 132S1047) for FW check config
34) change I2C pullups (R29 and R102) to 1K
35) changed bootrom part number to 341S1255

4/18
36) changed C756 to 128S0025 (Sanyo only 6.3V 330uF)
37) add pads for 90 ohm chokes to FWB path close to connector (route through the pads)
38) changed Vcore inductor (L36) to molded core part (152S0125)
39) changed Pbus inductor (L37) to molded core part (152S0126)
40) added seperate 1_8V_GPU_TPVDD filter and LDO (U54)

4/21
41) replace disctrete LCL with single chip LCL filters (155S0154) for VGA (L ,L , and L)
42) add 165 ohm chokes on TMDS data pairs at connector (L ,L , and L)
43) move BS1 to bottom side
44) move CPU thermal sensor (Q39) to input 1 on fan controller and power supply sensor (Q66) to input 2
45) added trace from Vcore to fan controller ADC input
46) added FET inverters (Q78) to PWM outputs of fan controller (U3) to prevent spinup at boot
47) added FET (Q79) for +3V_Sleep for M10 power sequencing

4/27
48) changed TMDS data chokes to 90 ohm (155S0128)
49) changed C762 and C766 to 4.7uF 1206 caps
50) changed TMDS data chokes to 90 ohms (155S0128)
51) changed C762 and C766 to 4.7uF 1206
52) changed Q51 to Si7860DP (376S0119)
53) changed Q48 to Si7892DP (376S0120)
54) changed D24 to B340LB (371S0132)
55) changed L30 to 2.2uH Tokin inductor (152S0139)
56) added Q58, R307, and C515 for GPU Vcore control inverter
57) changed R416 to 2.2ohms
58) changed R364 to 102K
59) added 0.1uF 50V C883 to RS- of Max4172 (NO stuff)
60) changed D18 to 1N914
61) changed L38 and L41 to 4.7uH (152S0137)
62) added Q81, R308, R309, and R310 for power sequencing (no stuff)
63) changed Q49 and Q50 to Si7860DP (376S0119)
64) changed L36 to 1.2uH 18.3A (152S0125)
65) added R331 1mohm sense resistor to CPU Vcore
66) added C885 and C884 , 1000uF CPU Vcore outpur caps
67) added Q82, R607, R455, R417, and C886 for 1.5V sleep sequencing
68) added Q83 and 100K R608 for 1.8V sequencing
69) added 15.4K R616 and 10K R672 for 2.5V switcher feedback divider
70) changed pinout of sound connector for sousaphone
71) removed Q44 (5V sound sleep fet)
72) changed Q31 to invert headphone Mute to sousaphone

4/28
73) changed CPU_VCORE_SLEEP location back to across bypass caps to correct after adding reference resistor
74) changed D5 to schottky diode (MBR0540)
75) fixed unnamed net (LTC3411_SHDN_SEQ)
76) changed drain/source polarity of Q76 (FET from +BATT to Pbus)

4/28
77) moved XW15 to connect to CPU_VCORE_SLEEP_UF (before positioning resistor)
78) changed Fan control nets to FanL and FanR from Fan1 and Fan2
79) SWAPPED CONNECTIONS SO THAT OUTPUT 1 FROM FAN CONTROLLER CONNECTS TO LEFT FAN (CPU) AND FAN 2 CONNECTS TO THE RIGHT FAN (GPU)
80) updated power constraints with new fan net names

4/28
81) change Q58 on pg19 to Q80 to consolidate parts
82) CHANGED U55 TO MM1571J FOR COST SAVINGS
83) changed L72,L73,L74 to 90 ohm ferrites
84) added 10K pullup to +5V_MAIN to SND_HP_MUTE
85) repinout Sousaphone connector
86) remore redundant pullups on FANL_TACH and FANR_TACH
87) added TP to all NC on NEC USB2 part for NAND tree testing
88) added NEC_USB bomoption to 0 ohm resistor on NEC_AVSS_F

4/30
89) repinout Sousaphone connector (J12)
90) no stuff R322 to eliminate 3V_sleep pump up
91) updated various text notes with correct reference designators

5/1
92) change L30 to 152S0139 (Tokin CPI-1050-2R2) 11A
93) remove FANR_TACH functional test point
94) add CHGND4 and SLEEP_LED functional test points
95) swap INT_AUDIO_TO_SND and SND_TO_AUDIO on Sousaphone connector (J12)
*** rev 01 released for EVT ***

5/6
96) remove NO STUFF on R477 (set 5V and 3.3V switcher in pulse skipping mode)
97) change R337 to 470K and remove No Stuff and no stuff R336 to change Vcore DAC to 1.35V/1.15V
98) change R321 to 499ohm to set 5mV Vcore offset
99) change L72,L73,L74 to 155S0165 (D part for EVT only)
*** rev 02 released for EVT ***

5/7
100) no stuff Q79 to disable 3V_SLEEP sequencing to work around wake from sleep bug with M10
101) added BOM table to define correct part number for M10 without heatspreader (338S0133)
*** rev 03 released for EVT ***

5/22
102) fixed NO STUFF BOM option for R291
103) add NO STUFF to R223 to correct startup level of GPU_VCORE_CNTL
104) add NO STUFF to R300 to complete 3V sequecing on wake from sleep fix
105) changed R376 to 158K and R321 to 2.74K to set CPU_VCORE offset to 35mV
*** rev 04 released for EVT ***

5/19/03
106) changed both AGP_NV_INT_L and AGP_ATI_INT_L to AGP_INT_L
107) removed redundant 3V_GPU pullup R687 (Intrepid side AGP_INT_L pullup)
108) added R699,R701,R707,R708 as 10k pulldowns to Intrepid USB ports A and C when NEC_USB is stuffed
109) changed SND_HP_MUTE_INV gate/inversion FETS to pullup to +3V_MAIN
110) added R711 as pullup to +3V_GPU on AUXWIN signal from M10 (U44)
111) added R698 as 0 ohm jumper between FW_PHY_PD and Intrepid
112) added U56, U57, R718,R714 for VGA Hsync and VGA Vsync buffering
113) changed L72,L73,L74 to 155S0164 (new high speed part)
114) added NO STUFF BOM option to R223 to correct for sense of GPU_VCORE_CNTL
115) added NO STUFF BOM option to R300 to avoid sleep wake problem

6/3/03
116) Intgrated new 1.8V switcher (LTC3412)(U58)(353S0650) and inductor (L75- 152S0142)
117) changed 2.5V_SLEEP FET (U48) and 1.8V_SLEEP FET (U6) to higher current part (Si6467BDQ - 376S0161)
118) added 10K pulldown (R720) on FW_PHY_PD_INT for when R698 is removed
119) changed R728 and R729 to 1210 0ohm resistors to support switching the entire memory bus between 1.8V and 2.5V
120) added R721 as jumper between +2_5V_SLEEP and +2_5V_GPU

6/4/03
121) NO STUFF R631 to remove MAIN_RESET_L from clock slewing chip
122) changed FWB connector to new part with extra ground tabs (514S0059)

6/5/03
123) changed I2C 0 and 1 pullups (RP12) to 2.2K to improve rise/fall times (sensor check config errors)
124) added CRITICAL flag to new 1.8V switcher (U58), inductor (L75), 1.8V sleep FET (U6), and 2.5V sleep FET (48)
125) removed gnd caps (C651 and C647) on I2S clock at sound connector (J12)
126) added LC filter on SND_SYNC for EMI (L77 and C895)
127) added LC filter on SND_CLKOUT for EMI (80 and C899)
128) added LC filter on INT_AUDIO_TO_SND for EMI (L81 and C896)
129) added LC filter on SND_TO_AUDIO for EMI (L82 and C897)
130) added LC filter on SND_AMP_MUTE for EMI (L76 and C898)
131) added LC filter on SND_HW_RESET_L for EMI (L78 and C900)
132) added LC filter on SND_SCLK for EMI (L79 and C901)
133) added C902 and R804 to prevent latch-up condition in GPU Vcore circuit when using powermiser
134) removed R331 (CPU Vcore positioning resistor)
135) changed C728,C729,C730,C731,C732,C733,C734,C884,C885 to 220uF Rubycon caps (128S0024)
136) add Vcore offset change circuit to modify offset in low (Q86,R805,R806,R807,R808,R809)
137) changed Q83 into dual (2N7002DW) and added R810 to invert 3V_5V_ON before switching RUN/SS

6/6/03
138) rotated J26 (FW B connector)
139) changed D29 to B340B (3A part - 371S0159)

6/9/03
140) modified Vcore offset select circuit with Takashi's changes - changed Gnd reference to VCORE_GND_SNS
141) added double inverter to buffer THERM_L_OC (added Q87,R811,R812)
142) removed redundant pullup on THERM_L_OC (R780)

6/9/03
143) added cap on gate of the second FET in Q87 for possible turn on delay (C903)
144) changed inner shield of FWB connector J26 to connect to chassis gnd
145) changed R336 and R325 to 0 ohm to set Vcore VID to 1.3V/1.15V
146) changed R321 to 2.49K to set Vcore offset to +25mV
147) added 10 ohm resistor (R814) and 1uF cap (C904) to filter power to ADT7460 (Gary Leo)

6/10/03
148) changed R612 to 10K to prevent UIDE DMACK from floating
149) changed C80,C88,C81,C89,C82,C102,C79,C87 to NO STUFF (TMDS common-mode termination)
150) changed R205,R218,R211,R219,R210,R220,R204,R214 to 162 ohm 1% (TMDS common-mode termination)
151) changed RP27,RP32,RP28,RP57 to 10ohm (TMDS series termination)
*** released for EVT2 6/10/03 ***

6/13/03
152) fixed NO STUFF on R291
153) removed NO STUFF from C80,C88,C81,C89,C82,C102,C79,C87 (TMDS common-mode termination)
154) removed NO STUFF from R638 (pullup on slewing chip FSEL)
155) removed NO STUFF from C903 (cap on input to second part of THERM_OC_L buffer)
156) CHANGED R321 TO 1K FOR VCORE OFFSET OF 12MV (VCORE = 1.30V -30MV/+100MV)
*** released for EVT2 6/13/03 ***

6/18/03
157) changed R228 to pullup to 1.8V for DVO interface conpatibility
158) added R234 and INT_TMDS option to maintain internal TMDS capability
159) changed L30 to 3 pin symbol
160) added U5 to use as external TMDS transmitter (DVI)
161) added R41 to create +3V_GPU_SI power for SIL1162 (U5)
162) added L14, C130, C132, and C165 for 3V AVCC filtering for SIL1162 (U5)
163) added L13, C14, C129, C131, C133 for 3V PVCC filtering for SIL1162 (U5)
164) added L15, C255, C233, C218 for 3V Vcc filtering for SIL1162 (U5)
165) added R235 and R237 as options for MAIN_RESET_L to U5
166) added R231. R232, and C284 for Vref for U5
167) added R66, R99, R202, R212, R222, R224, R88, R110, R223 as straps for U5
168) added RP58, RP59, RP60, RP61 for series termination of SIL1162 TMDS output
169) added L16, C304, C327, C647 for filtering GPU VDDR4
170) added R255 and R251 to strap GPU_DVODMODE correctly for 1.8V DVO
171) added R268 to connect L16 to +3V_GPU_FLT when not using SIL1162
172) added C681, C668, C678, C651 to filter the thermal sensor diff pairs

6/19/03
173) changed GPU_MEM_IO to +GPU_MEM to connect ATI Vref to correct memory voltage
174) swapped TMDS CLKN and CLKP on RP57 and RP58 for layout
175) swapped DN<0> and DP<0> on RP27 for layout
176) corrected un-named nets in TMDS common-mode filters
177) added physical constriants for new Silicon Image power rails
178) CHANGED C728,C731,C734,C733,C730,C732,C729,C885,C885 TO 128S0022 (124S0024 WILL BE DELETED AS A DUPLICATE IN THE LIBRARY)

6/23/03
179) NO STUFF'ed C895,C899,C896,C897,C898,C900, and C901 to fix no sound problem
180) changed C890 to 100pF for improved transient response (Takashi)
181) Removed bypass traces on FWB chokes and stuffed L70 and L71
182) CHANGED R491 TO 52.3K 1%, R475 TO 127K 1%, AND R476 TO 4.7M 5% IN A29 ADAPTER DETECT CIRCUIT DIVIDERS TO REDUCE SHUTDOWN CURRENT
183) added R331 as CPU Vcore sense resistor (1 mohm 1% 2512)
184) No STUFF'ed C651 and C678
185) added C688,C690,C846,C905 for thermal pair filtering at fan controller
186) added C906 to prevent shoot-thru on Q64 (currently NO STUFF'ed)
187) added C907 to prevent shoot-thru on Q68 (currently NO STUFF'ed)
188) changed R517 to 100K
189) changed GND reference for input side of Q86 to digital GND (the other FET in Q856 remains on VCORE_GNDSNS

6/24/03
190) added C908 to prevent gate shoot-thru on Q56
191) added R279 to power TMDS PLL from LVDS filter when using external TMDS transmitter
192) changed R325 to 470K to set the low Vcore to 1.10V
193) stuffed Vcore offset switch (R807,R805,R809,Q86)
194) changed R809 to 1.5K 1% to set low Vcore offset to 10mV
195) changed R321 to 3.01K 1% to set high Vcore offset to 30mV

6/25/03
196) rotated L70 and L71 for layout (PCB symbol problem)
197) changed Q53,Q54,Q55 to IRF7832 (376S0148) for better thermal performance
198) NO STUFF'ed C908 (Q56 gate shoot-thru cap)
*** released for DVT 6/26/03 ***

7/2/03
199) CHANGED J9 (CARDBUS) TO 516S0141 (NEW PIN PLATING SPEC)
200) CHANGED J20 (AIRPORT) TO 516S0142 (NEW PIN PLATING SPEC)
201) CHANGED J10 (OPTICAL DRIVE) TO 516S0140 (NEW PIN PLATING SPEC)
202) CHANGED J13 (HARD DRIVE) TO 516S0140 (NEW PIN PLATING SPEC)
203) CHANGED J12 (SOUND) TO 516S0144 (NEW PIN PLATING SPEC)
204) CHANGED J8 (MODEM) TO 516S0143 (NEW PIN PLATING SPEC)
205) ADDED BOM TABLE TO PUT 0 OHM 402 ON L77,L80,L81,L82,L76,L78,L79

7/9/03
207) CORRECTED C889 TO CONNECT TO INPUT (PIN 1) OF U55
208) REMOVED POWER JUMPERS XW25,XW17,XW16,XW10,XW14,XW18
209) CHANGED 197S0035 TO PRIMARY AND 197S0004 AS ALTERNATE FOR Y1 (INTREPID)
210) CHANGED 197S0037 TO PRIMARY AND 197S0603 AS ALTERNATE FOR Y3 (ETHERNET)
211) CHANGED 197S0038 TO PRIMARY AND 197S0608 AS ALTERNATE FOR Y5 (NEC USB2)
212) CHANGED 197S0040 TO PRIMARY AND 197S0008 AS ALTERNATE FOR Y4 (LMU)
213) CHANGED 197S0041 TO PRIMARY AND 197S0604 AS ALTERNATE FOR Y6 (PMU)

7/22/03
214) ADDED 1_32V_VCORE AND 1_30V_VCORE BOM OPTIONS FOR 2 DIFFERENT CPU VCORE SPECS
215) UPDATED CAP MATERIAL TYPES
216) CHANGED FROM 715 PIN TO 667 PIN SYMBOL FOR U44 (M10)

7/28/03
217) CHANGED TMDS TERMINATION FROM 2X 162 TO 2X 49.9 OHMS PER PAIR
218) CHANGED 126S0036 FROM ALT TO PRIMARY, REPLACING 126S0035 FOR CPU VCORE INPUT CAPS
*** RELEASED FOR PRODUCTION 7/28/03 ***

8/4/03
219) CHANGED R99 TO NO STUFF TO FIX I2C ADDRESS OF SIL1162 TMDS TRANSMITTER
220) CHANGED R321 TO 4.02K 1% FOR 1_30_VCORE (40MV OFFSET) AND TO 6.34K 1% FOR 1_32_VCORE (60MV OFFSET)
221) CHANGED R304 TO 470K AND R329 AND R325 TO 0 OHM TO CHANGE LOW VID TO 1.05V ON VCORE
222) CHANGED C611 TO 2200PF, C610 TO 100PF, AND R519 TO 12.7K 1% TO INCREASE IMMUNITY TO 3.3V PGOOD SIGNAL DROPOUT
223) NO STUFF C590 TO INCREASE IMMUNITY TO 3.3V PGOOD SIGNAL DROPOUT
224) CHANGED C583 TO 2200PF, C576 TO 100PF, AND R481 TO 15.0K 1% TO INCREASE IMMUNITY TO 3.3V PGOOD SIGNAL DROPOUT
225) NO STUFF C566 TO INCREASE IMMUNITY TO 3.3V PGOOD SIGNAL DROPOUT

9/4/03
228) ADDED 197S0052 AS ALTERNATE FOR G1 (98 MHZ FW OSCILLATOR)
229) CHANGED C728-C734,C884,C885 TO 128S0022 TO REMOVE DUPLICATE PART NUMBER
230) CHANGED C883 TO 132S0100 TO CORRECT FOR USE OF OEM PART NUMBER

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 40 OF 44	


*** Signal Cross-Reference for the entire design ***
+1.0V_MARVELL 27D2< 38D3>
+1.5V_AGP 12C5< 12D1< 12D4< 15D6< 16C8< 18C6< 18D6< 19A8< 19B4< 19D5< 21B8< 21D6< 38C3>
+1.5V_AGP_GPU 21C5< 38C3>
+1.5V_AGP_HCK 19B4< 38B3>
+1.5V_GPU_VDD15 19D3< 38C3>
+1.5V_INTREPID_PLL 8D6< 12D4< 12D8< 14D6< 38D3>
+1.5V_INTREPID_PLL1 14C3< 38D3>
+1.5V_INTREPID_PLL2 14D3< 38D3>
+1.5V_INTREPID_PLL3 14D3< 38D3>
+1.5V_INTREPID_PLL4 14D3< 38D3>
+1.5V_INTREPID_PLL5 12D3< 38D3>
+1.5V_INTREPID_PLL6 12D6< 38D3>
+1.5V_INTREPID_PLL7 8D5< 38D3>
+1.5V_INTREPID_PLL8 14D3< 38D3>
+1.5V_LDO 35D6< 38D6>
+1.5V_MAIN 38D6>
+1.5V_SLEEP 38D6>
+1.5V_SLEEP_NECK 21A3< 38B3>
+1.5V_SLEEP_VIN 35D8< 38D6>
+1.8V_ATI_PVDD 19C5< 21B6< 21B6< 21D6< 38C3>
+1.8V_ATI_TPVDD 21D2<>
+1.8V_DVO_F 21B2<
+1.8V_GPU 18A7< 19D6< 20A5< 21A2< 21A6< 21B1< 21B6< 21C8< 21D6< 21D8< 38C3>
+1.8V_GPU_AVDD 21D5< 38C3>
+1.8V_GPU_AVDDQ 21C5< 21D7< 38C3>
+1.8V_GPU_MEMPLL 21B5< 38C3>
+1.8V_GPU_PLL 21D5< 38C3>
+1.8V_GPU_PNLIO 21A5< 38C3>
+1.8V_GPU_PNLPLL 21B5< 38C3>
+1.8V_GPU_TP_PLL 21D1<
+1.8V_GPU_VDDCI 21C7< 21D4< 38C3>
+1.8V_MAIN 28D6< 39A2>
+1.8V_MAIN_LX_F 35A4<>
+1.8V_PVDD_NECK 19B5<> 38B3>
+1.8V_SLEEP 38D6>
+1.8V_SLEEP_NECK 21A3<> 38B3>
+1.95V_FW_DVDD 28C4< 28C7<> 28D5< 38A3>
+1.95V_FW_DVDD_PORT1 28D6< 38A3>
+1.95V_FW_DVDD_RX0 28C5< 38A3>
+1.95V_FW_DVDD_TX0 28D4< 38A3>
+1.95V_FW_PLL400VDD 28D5< 38A3>
+1.95V_FW_PLL500VDD 28D5< 38A3>
+1.95V_FW_PLLVDD 28D5< 28D7<> 38A3>
+2.5V_CG_MAIN 14C6< 38A3>
+2.5V_GPU 21A7< 21B6< 21D3< 21D7< 21D8< 22D4< 38B3>
+2.5V_GPU_A2VDD 21D4< 21D7< 38C3>
+2.5V_INTREPID 8A8< 16D3< 16D5< 16D7< 18D8< 15D7< 16B8< 38D3>
+2.5V_MAIN 38C3>
+2.5V_MARVELL 27B8< 27C4<> 38B3>
+2.5V_MARVELL_AVDD 27C4< 38B3>
+2.5V_SLEEP 38D6>
+2.5V_SLEEP_NECK1 19C4<> 38B3>
+2.5V_SLEEP_NECK2 21A3<> 38B3>
+3V_ATI_OSC_SLEEP 18D2< 38C3>
+3V_ATI_SS 18B2< 38C3>
+3V_CG_PLL_MAIN 14C6< 38A3>
+3V_FW 28A3< 28D7<> 29D5< 38A3>
+3V_FW_AVDD 28C6< 38D3>
+3V_FW_AVDD_PORT0 28C6< 38A3>
+3V_FW_AVDD_PORT1 28C6< 38A3>
+3V_FW_AVDD_PORT2 28D6< 38A3>
+3V_FW_ESD 29B3<> 29D2<> 38B3>
+3V_FW_ESD_ILIM 29D4< 38B3>
+3V_FW_LP 29D7<> 38A3>
+3V_GPU 12D1< 18B8< 18C5< 18C7< 18D6< 19C4< 19C5< 19C7< 19D7< 21A6< 21B1< 38C3>
+3V_GPU_FLT 21B2< 38C3>
+3V_GPU_SI 20C8< 20C8< 20D8<
+3V_HALL_EFFECT 23C6<> 38B6> 39C4>
+3V_INTREPID_USB 14C4< 38D3>
+3V_LCD 22B4<> 38B6>
+3V_LCD_SW 22A4<> 38B6>
+3V_MAIN 38D6>
+3V_NEC_VDD 26D7< 26D7< 38A3>
+3V_PMU 38D6>
+3V_PMU_AVCC 25A4< 30B6< 30D5<> 38C6>
+3V_PMU_ESR 32A2< 38C6>
+3V_PMU_RESET 30A2< 34A3<>
+3V_SI_AVCC 20C7< 38B3>
+3V_SI_PLLVCC 20C7< 38B3>
+3V_SI_VCC 20C6< 38B3>
+3V_SLEEP 38D6>
+3V_SLEEP_NECK 21A3<> 38B3>
+3V_SLP_OK_L 33B4<>
+3V_SLP_ON 33A5<>
+4.0V_BU 32A3<> 33B6< 38C6>
+4.85V_ESR 32A4< 38C6>
+4.85V_HAW 28D2< 38A4<> 38C6>
+5V_DDC_SLEEP 22D3<> 22D5<> 38B6> 39A2>
+5V_DDC_SLEEP_UF 22D6< 38B6>
+5V_HD_SLEEP 24D1<> 33A7<> 38C6>
+5V_INV_SW 22B2<> 38B6> 39D1>
+5V_INV_UF_SW 22B2<> 38B6>
+5V_MAIN 38D6>
+5V_SLEEP 38D6>
+5V_SOUND_SLEEP 38D6>
+5V_TPAD_SLEEP 23C7<> 38B6> 39C4>
+12_8V_INV 22B1<> 38B6> 39A2>
+24V_PBUS 38D6> 38D7>
+ADAPTER 31D8<> 32B7< 38D6>
+ADAPTER_ILIM 32B6<> 38C6>
+ADAPTER_OR_BATT 32A6<> 38C6>
+ADAPTER_SENSE 31D5<> 38C6>
+ADAPTER_SW 31D6<> 38C6>
+BATT 38D6>
+BATT_14V_FUSE 31D1<> 38C6>
+BATT_24V_FUSE 31B2<> 38C6>
+BATT_POS 31A4<> 38C6> 39C3>
+BATT_RSNS 31B2< 38C6>
+BATT_VSNS 31A4< 38C6>
+FW_FUSE 29D7<> 38A3>
+FW_PWR_OR 28D6<> 29D5<> 38A3>
+FW_PWR_PORTA 29C5< 38A3>
+FW_SW 29D5<> 38A3>
+FW_VP0 29C7<> 38A3>
+FW_VP1 29A3<> 38A3>
+GPU_MCLK 21C7< 21D4< 38C3>
+GPU_MEM 18A6<> 18B6< 21B4< 21B7< 21C6< 21C8< 21D6< 38C3>
+GPU_MEMCORE 21C5< 38C3>
+GPU_VDD1S_NECK 19B5<> 38B3>
+GPU_VDD1S_UF 19B5<> 19D4<> 38C3>
+HD_LOGIC_SLEEP 24D2<> 38C6>
+PBUS 38D6> 39B2>
+VCC_CBUS_SW 17B1<> 17D2<> 38D3>
+VPP_CBUS_SW 17B1<> 17B2<> 17D2<> 38C3>
1V20_REF 31C7< 32C6< 38D1>
1V65_REF 31A5< 38A3>
1_5V_2_5V_OK 35C5> 38B1>
1_5V_BOOST 35C6<> 38C1>
1_5V_BST 35C5> 38C1>
1_5V_DH 35C5> 38C1>
1_5V_DL 35B5<> 38C1>
1_5V_FB 35B5< 35B7< 38C1>
1_5V_ILIM 35C5> 38C1>
1_5V_LX 35B5< 38C1>
1_5V_SLEEP_EN_L 35C7<> 35D7<>
1_5V_SLEEP_PWRELL 35A2<> 38C1>
1_8V_SW 35A5<> 38A1>
1_8V_VFB 38A1>
2_5V_BOOST 35C4< 38D1>
2_5V_BST 35C4< 38D1>
2_5V_DH 35C4< 38D1>
2_5V_DL 35B4< 38D1>
2_5V_ILIM 35C5> 38C1>
2_5V_LX 35B4< 38D1>
2_5V_SLEEP_PWREN_L 35C2<>
2_34V_REF 30A4<
3V_5V_OK 33B3<> 35A8<> 35D6<
3V_5V_OK_INV 35A8<>
3V_B6 33C4<>
3V_BOOST 33C4<>
3V_BOOST_ESR 33D3<>
3V_ITH 33C4<>
3V_ITH_RC 33C3<
3V_PMU_VTAP 32B3<
3V_RSNS 33D2< 38D1>
3V_RUNSS 33C4<
3V_SLEEP_PWREN_L 33A3<>
3V_SNSM 33C4< 37A2>
3V_SNSP 33C4< 38D1>
3V_TG 33D4<>
3V_VOSNS 33C5<>
5V_BG 33C5<>
5V_BOOST 33C5<>
5V_BOOST_ESR 33D6<>
5V_HD_PWREN 33A8<>
5V_ITH 33C5<>
5V_ITH_RC 33D6<
5V_RSNS 33D7< 38D1>
5V_RUNSS 33C5<
5V_SLEEP_PWREN 33A8<>
5V_SNSM 33C5< 37A2>
5V_SNSP 33C5< 38D1>
5V_SW 33C5> 38D1>
5V_TG 33C5<>
5V_VOSNS 33C5< 38D6>
1625_BG 32C5<>
1625_BST 32C5<
1625_BST_ESR 32C5<
1625_COMP 31D2< 32C6<
1625_DIV 32C8<
1625_ENABLE 32D7<>
1625_ENABLE_L 32D6<>
1625_EXTVCC 31D5<> 38D1>
1625_FCB 32C6<
1625_INTVCC 32C5<> 38D1>
1625_RUNSS 32C6<
1625_SGND 32B7<> 38D1>
1625_TG 32C5<
1625_VFB 32B5<>
1625_VIN 32C6< 38D1>
1625_VSW 32C5< 38D1>
1772_ACIN 31B5<
1772_ACOK_L 31B5<> 31C4<>
1772_BST 31B4<>
1772_BST_ESR 31C3<
1772_CCI 31B5<>
1772_CCS 31B5<
1772_CCV 31B5<>
1772_CCV_RC 31B5<
1772_CELLS 31B4<
1772_CLS 31A4<>
1772_CSIN 31B4<> 37A2>
1772_CSIP 31B4<> 37A2>
1772_CSSN 31C5< 37A2>
1772_CSSP 31C5< 37A2>
1772_DCIN 31B5< 38C6>
1772_DHI 31B4<>
1772_DLO 31B4<>
1772_DNI 31B4< 38C6>
1772_DN_CH0 31B4< 38C6> 39D4<
1772_DN_CH1 31B4< 39D4<
1772_ICHG 31B5<>
1772_ICTL 31B5<>
1772_IINP 31B5<
1772_LDO 31C4<> 38C6>
1772_LX 31A4< 38C6>
1772_REF 31B5<>
1772_VCTL 31B5<
1778_BG 19A5<> 38B1>
1778_BST 19A5<> 38B1>
1778_BST_RC 19A4<> 38B1>
1778_FCB 19A5< 38B1>
1778_ION 19A5< 38B1>
1778_ION_ESR 19A5< 38B1>
1778_ITH 19A7< 38B1>
1778_ITH_RC 19A7< 38B1>
1778_SHDN_L 19A6<
1778_SHDN_L_D3COLD 19A7<>
1778_TG 19A5<> 38B1>
1778_VCC 19A5<> 38B1>
1778_VFB 19A2< 19A5< 38B1> 39A1>
1778_VIN 19A5< 38B1>
1778_VRNG 19A5< 38B1>
3400_MODE 27D5<
3405_VFB 27D4<>
3407_FSET 33C5<
3707_INTVCC 33D4<> 38D1>
3707_SGND 33B5<> 38D1>
3707_STBY 33C5<>
A29_CLS_ADJ 31A5<>
A29_CURRENT_ADJ 31C4<>
A29_DETECT 30A2< 31A5<> 31C4<>
A29_DET 30A3<
AB_SEL_LOW 34A6<>
AC_DIV 32B6<
AC_ENABLE_GATE 31D6<>
AC_ENABLE_L 31C6<>
AC_GTR_18V 31C4<>
AC_IN 27B8<> 29C7< 30B3< 31C5<> 31C7<>
AC_IN_FW_CNTL 29C7<>
AC_IN_L 31C2<> 31C6<>
AC_IN_L_RC 31C2<>
ADAPTER_DET 30A4< 31D8<> 39C2>
ADAPTER_I_REG 31D3<>
ADT7468_ADR_EN_L 25B3<>
ADT7468_FAN1_PWM 25B3<>
ADT7468_FAN2_PWM 25B3<>
ADT7468_THERM 25A5<> 25B3<>
ADT7468_VCC 25C4<>
ADT7468_VCORE_MON 5C8<> 25B4<>
AGPBUSY_DET_PU 18C4<>
AGP_AD<0> 12D2<> 18C7<>
AGP_AD<15..0> 37D5>
AGP_AD<1> 12C2<> 18C7<>
AGP_AD<2> 12C2<> 18C7<>
AGP_AD<3> 12C2<> 18C7<>
AGP_AD<4> 12C2<> 18C7<>
AGP_AD<5> 12C2<> 18C7<>
AGP_AD<6> 12C2<> 18C7<>
AGP_AD<7> 12C2<> 18C7<>
AGP_AD<8> 12C2<> 18C7<>
AGP_AD<9> 12C2<> 18C7<>
AGP_AD<10> 12C2<> 18C7<>
AGP_AD<11> 12C2<> 18C7<>
AGP_AD<12> 12C2<> 18C7<>
AGP_AD<13> 12C2<> 18C7<>
AGP_AD<14> 12C2<> 18C7<>
AGP_AD<15> 12C2<> 18C7<>
AGP_AD<16> 12C2<> 18C7<>
AGP_AD<31..16> 37D5>
AGP_AD<17> 12C2<> 18C7<>
AGP_AD<18> 12C2<> 18C7<>
AGP_AD<19> 12C2<> 18C7<>
AGP_AD<20> 12C2<> 18C7<>
AGP_AD<21> 12C2<> 18C7<>
AGP_AD<22> 12C2<> 18C7<>
AGP_AD<23> 12C2<> 18C7<>
AGP_AD<24> 12C2<> 18C7<>
AGP_AD<25> 12C2<> 18D7<>
AGP_AD<26> 12C2<> 18D7<>
AGP_AD<27> 12B2<> 18D7<>
AGP_AD<28> 12B2<> 18D7<>
AGP_AD<29> 12B2<> 18D7<>
AGP_AD<30> 12B2<> 18D7<>
AGP_AD<31> 12B2<> 18D7<>
AGP_AD_STB<0> 12A2<> 12B2< 18D6<> 37D5>
AGP_AD_STB<1> 12A2<> 12B2< 18D6<> 37D5>
AGP_AD_STB_L<0> 12A2<> 12B2< 18D6<> 37D5>
AGP_AD_STB_L<1> 12A2<> 12A2< 18D6<> 37D5>
AGP_ATI_RESET_L 18B7<
AGP_ATI_VREF 18B7<
AGP_ATI_VREFG 18B7<
AGP_BUSY_L 12C4<> 12D2< 18D6>
AGP_CBE<0> 12B2<> 18B7<>
AGP_CBE<1..0> 37D5>
AGP_CBE<1> 12B2<> 18B7<>
AGP_CBE<2> 12B2<> 18B7<>
AGP_CBE<3..2> 37D5>
AGP_CBE<3> 12B2<> 18C7<>
AGP_DEVSEL_L 12B2<> 12C2< 18B7<> 37D5>
AGP_FRAME_L 12B2<> 12C2< 18B7<> 37D5>
AGP_GNT_L 12C2< 12D2> 18B7< 37D5>
AGP_INT_L 14B5<> 18B7<>
AGP_IRDY_L 12B2<> 12C2< 18B7<> 37D5>
AGP_PAR 12B2<> 18B7> 37D5>
AGP_PIPE_L 12A2<> 12B2<>
AGP_RBF_L 12A2<> 12C2< 18C6> 37D5>
AGP_REQ_L 12C2< 12D2> 18B7<> 37D5>
AGP_SBA<0> 12B2< 18C6>
AGP_SBA<7..0> 37D5>
AGP_SBA<1> 12B2<> 18C6>
AGP_SBA<2> 12B2<> 18C6>
AGP_SBA<3> 12B2<> 18C6>
AGP_SBA<4> 12B2<> 18C6>
AGP_SBA<5> 12B2<> 18C6>
AGP_SBA<6> 12B2<> 18C6>
AGP_SBA<7> 12B2<> 18C6>
AGP_SB_STB 12B2<> 12B2< 18C6<> 37D5>
AGP_SB_STB_L 12A2<> 12A2< 18C6<> 37D5>
AGP_ST<0> 12A2<> 18C6>
AGP_ST<1> 12A2<> 18C6>
AGP_ST<2> 12A2<> 18C6>
AGP_STOP_L 12B2<> 12C2< 18B7<> 37D5>
AGP_STP_L 18C6<
AGP_SUS_STAT_L_PU 18C6<
AGP_TRDY_L 12B2<> 12C2< 18B7<> 37D5>
AGP_WBF_L 12A4<> 12B2< 18B7>
AIRPORT_CLKRUN_L 14A5< 38B1>
AIRPORT_IDSEL 24C5<> 39B1>
AIRPORT_PCI_GNT_L 14B5< 24C6<> 39C4>
AIRPORT_PCI_INT_L 14B5< 14D7< 24D5<> 39C4>
AIRPORT_PCI_REQ_L 12A7< 12D7<> 24D6<> 39C4>
AIRPORT_PME_L_TP 24D5<> 39C4>
AMP_CONTROL 25C5<> 25D5<>
ATI_AGP_FBSKEW<0> 19C2< 19C7<>
ATI_AGP_FBSKEW<1> 19C2< 19C7<>
ATI_BUS_CFG<0> 19B2< 19C7<>
ATI_BUS_CFG<1> 19B2< 19C7<>
ATI_BUS_CFG<2> 19B2< 19C7<>
ATI_CLK27M_IN 18C1< 19B7<
ATI_CLK27M_OSC 18D2<
ATI_CLK27M_OSC_SS 18B2< 18D1<
ATI_DBI_HI_PU 18C6<>
ATI_DBI_LO_PU 18C6<>
ATI_DVODMODE 21A3<
ATI_GPIO7_SPN 19C7<>
ATI_GPIO8_PD 19C7<>
ATI_GPIO9_SPN 19C7<>
ATI_GPIO10_SPN 19C7<>
ATI_GPIO11_SPN 19C7<>
ATI_GPIO12_SPN 19C7<>
ATI_GPIO13_SPN 19C7<>
ATI_HSYNC 19D5<> 22C8<
ATI_MEMTEST 18A6<>
ATI_MEMVMODE0 18A7<
ATI_MEMVMODE1 18A7<
ATI_OSC_OE 18C1<>
ATI_PVDD_BYP 21D6<>
ATI_RZSET 19D6<>
ATI_RSET 19D6<>
ATI_RSTB_MSK 18C6<>
ATI_SSCLK_IN 18B4< 19B7<>
ATI_SSCLK_UF 18B1<>
ATI_TESTEN 19B7<
ATI_TMDS_CLKN 19B7> 20B4<
ATI_TMDS_CLKP 19B7> 20B4<
ATI_TMDS_DN<0> 19B7> 20B4<
ATI_TMDS_DN<1> 19B7> 20A4<
ATI_TMDS_DN<2> 19B7> 20A4<
ATI_TMDS_DP<0> 19B7> 20B4<
ATI_TMDS_DP<1> 19B7> 20A4<
ATI_TMDS_DP<2> 19B7> 20A4<
ATI_TPVDD_BYP 21C6<>
ATI_VSYNC 19D5<> 22C8<
ATI_X1CLK_SKEW<0> 19B2< 19C7<>
ATI_X1CLK_SKEW<1> 19B2< 19C7<>
BATTV_HIGH 31B7<>
BATTV_LOW 31B6<>
BATT_14PBUS_EN 31C1<>
BATT_24PBUS_GATE 31C3<>
BATT_24PBUS_EN 31C2<>
BATT_24V_GATE 31C1<>
BATT_CLK 31A4<> 39C3>
BATT_DATA 31A4<> 39C3>
BATT_DIV 31A5<
BATT_LOW 31A6<>
BATT_LOW_L 31B6<>
BATT_NEG 31A4< 38C6> 39C3>
BBANG_HRESET_L 23A4< 23C4<> 39C1>
BBANG_JTAG_TCK 23B3< 23C4<>
BBANG_TCK_EN 23B3<>
BCKFD_PROT_EN_L 31C6<>
BCKFD_PROT_GATE 31D6<>
BRIGHT_PWM 22A1<> 39A7>
BRIGHT_PWM_UF 22A2<>
BT_USB_DM 14B1< 24B2<> 37B2> 39B6>
BT_USB_DP 14C1< 24B2<> 37B2> 39B6>
CAPSLOCK_LED_L 23B6< 39C7<
CBUS_ADDR<0> 17B1<> 17B4>
CBUS_ADDR<1> 17B1<> 17B4>
CBUS_ADDR<2> 17B1<> 17B4>
CBUS_ADDR<3> 17B1<> 17B4>
CBUS_ADDR<4> 17B1<> 17B4>
CBUS_ADDR<5> 17B1<> 17B4>
CBUS_ADDR<6> 17B1<> 17B4>
CBUS_ADDR<7> 17B1<> 17B4>
CBUS_ADDR<8> 17B1<> 17B4>
CBUS_ADDR<9> 17B1<> 17B4>
CBUS_ADDR<10> 17B4> 17C1<>
CBUS_ADDR<11> 17B1<> 17B4>
CBUS_ADDR<12> 17B1<> 17B4>
CBUS_ADDR<13> 17B1<> 17B4>
CBUS_ADDR<14> 17B1<> 17B4>
CBUS_ADDR<15> 17B1<> 17B4>
CBUS_ADDR<16> 17B1<> 17B4>
CBUS_ADDR<17> 17B1<> 17B4>
CBUS_ADDR<18> 17B2<> 17B4>
CBUS_ADDR<19> 17B2<> 17B4>
CBUS_ADDR<20> 17B2<> 17B4>
CBUS_ADDR<21> 17B2<> 17B4>
CBUS_ADDR<22> 17A4> 17B2>
CBUS_ADDR<23> 17A4> 17B2>
CBUS_ADDR<24> 17A4> 17B2>
CBUS_ADDR<25> 17A4> 17B2>
CBUS_ADDR_16_UF 17B5<>
CBUS_BVDS_L 17B2> 17C4<
CBUS_BVD2_L 17B2> 17C4<
CBUS_CE1_L 17C1<> 17C4>
CBUS_CE2_L 17B4< 17C2>
CBUS_DATA<0> 17A1< 17A4>
CBUS_DATA<1> 17A1< 17A4>
CBUS_DATA<2> 17A1< 17A4>
CBUS_DATA<3> 17A4< 17C1<>
CBUS_DATA<4> 17A4< 17C1<>
CBUS_DATA<5> 17A4< 17C1<>
CBUS_DATA<6> 17A4< 17C1<>
CBUS_DATA<7> 17A4< 17C1<>
CBUS_DATA<8> 17A2< 17A4>
CBUS_DATA<9> 17A2< 17A4>
CBUS_DATA<10> 17A2< 17A4>
CBUS_DATA<11> 17A4< 17C2>
CBUS_DATA<12> 17A4< 17C2>
CBUS_DATA<13> 17A4< 17C2>
CBUS_DATA<14> 17A4< 17C2>
CBUS_DATA<15> 17A4< 17C2>
CBUS_DET_1_L 17C2> 17C4< 39B8>
CBUS_DET_2_L 17A2> 17C4< 39B8>
CBUS_INPACK_L 17B2> 17B4<
CBUS_INT_L 14B5> 14B7< 17A7<>
CBUS_IOWR_L 17B2> 17C4>
CBUS_IOWR_L 17B2> 17C4>
CBUS_MFUNC1_PD 17A7< 17C1>
CBUS_MFUNC2_PD 17A7< 17A7<>
CBUS_MFUNC3_PD 17A7< 17A7<>
CBUS_MFUNC4_PD 17A7< 17A7<>
CBUS_MFUNC5_PD 17A7< 17A7<>
CBUS_MFUNC6_PD 17A7< 17A7<>
CBUS_OE_L 17C1> 17C4>
CBUS_PCI_GNT_L 12D7< 17A7<
CBUS_PCI_IDSEL 17A7<>
CBUS_PCI_PERR_L 17B7> 17D7<
CBUS_PCI_REQ_L 12A7< 12D7<> 17A7>
CBUS_PCI_RESET_L 17A7<
CBUS_PCI_SERR_L 17B7> 17D7<
CBUS_READY 17B1> 17C4<
CBUS_RESET_L 17B4< 17C4>
CBUS_SUSPEND_PU 17A7< 17D7<
CBUS_VCCD0_L 17C4<>
CBUS_VCCD1_L 17C4<>
CBUS_VPPD0 17C4<>
CBUS_VPPD1 17C5<>
CBUS_VS1 17B2> 17C4<>
CBUS_VS2 17B2> 17C4<>
CBUS_WAIT_L 17B2> 17B4<
CBUS_WE_L 17B1> 17C4>
CBUS_WP_L 17A1> 17B4<
CG_ADDRSEL 14B7<
CG_CLKOUT 14B6<> 14C5<>
CG_FSEL 14B7< 14C5<>
CG_LOCK 14B7<>
CG_RESET_L 14B7<
CHARGE_DISABLE 31A7<>
CHARGE_LED_L 30C6<> 30D7< 31D8<> 39D2>
CHGND1 38A6>
CHGND2 38A6>
CHGND3 38A6>
CHGND4 38A6> 39B6>
CHGND5 38A6>
CHGND6 38A6>
CLK10M_PMU_XIN 30B6<
CLK10M_PMU_XOUT 30B6<
CLK10M_PMU_XOUT_UF 30B7<
CLK18M_INT_EXT 14A6<> 36B1>
CLK18M_INT_XIN 14A5< 36B1>
CLK18M_INT_XOUT 14A5<> 36B1>
CLK18M_XTAL_IN 27A7<
CLK25M_ENET_XIN 27A7< 36B1>
CLK25M_ENET_XOUT 27A7<> 36B1>
CLK25M_XTAL_IN 27A7<
CLK27M_GPU_XIN 36B1>
CLK27M_GPU_XOUT 36B1>
CLK27M_XTAL_IN 36B1>
CLK32K_PMU_XIN 30B3<>
CLK32K_PMU_XOUT 30B3<>
CLK32K_PMU_XOUT_UF 30B2<>
CLK33M_AIRPORT 12D8< 24D5<> 36C1> 39B1>
CLK33M_AIRPORT_UF 12C7<> 36C1>
CLK33M_CBUS 12D8< 17A7< 36C1>
CLK33M_CBUS_UF 12C7<> 36C1>
CLK33M_USB2 12C8< 26B7< 36C1>
CLK33M_USB2_UF 12C7<> 36C1>
CLK66M_AGP_15V_TP 12C4>
CLK66M_GPU_AGP 12C8< 18B7< 36C1>
CLK66M_GPU_AGP_UF 12C7<> 36C1>
CLKENET_LINK_GTX 13C5<> 36A1>
CLKENET_LINK_RX 13D5< 27C8< 36B1>
CLKENET_LINK_TX 13D5< 27D8< 36A1>
CLKENET_PHY_GBE_REF 27C7<> 36B1>
CLKENET_PHY_GTX 13D6< 27C7< 36A1>
CLKENET_PHY_RX 27C7<> 36B1>
CLKENET_PHY_TX 27D7<> 36B1>
CLKFW_PLL_CLK 13C3<> 28B3< 36A1>
CLKFW_PHY_LCLK 28B4< 28C3< 36A1>
CLKFW_PHY_PCLK 28B4> 28C3< 36A1>
CLKLVDS_LN 19B5> 22A4<> 37C2> 39B7>
CLKLVDS_LP 19B5> 22A4<> 37C2> 39B7>
CLKLVDS_UN 19B5> 22A4<> 37C2> 39B7>
CLKLVDS_UP 19B5> 22A4<> 37C2> 39A7>
COMM_DTR_L 14C2> 25D1<> 39B2>
COMM_GPIO_L 14C2<> 25D2<> 39C2>
COMM_RESET_L 14C2<> 25C4<> 39C4>
COMM_RING_DET_L 14B5> 14C7< 25C3<> 30C6<> 39C4>
COMM_RTS_L 14C2> 25D1<> 39B2>
COMM_TXD 14C2<> 25D1<> 39B2>
COMM_SHUTDOWN 14C5> 25C4<> 39C4>
COMM_TXVC 14C2<> 25D2<> 39C2>
COMM_TXD_L 14C2<> 25D2<> 39C2>
COMP_DISABLE 22C2<>
COMP_ENABLE 22C1<>
COMP_RC 32C6<
CPU_AACK_L 5A7< 8B6<> 8C2< 36D5>
CPU_ADDR<0> 5C7> 8D6<>
CPU_ADDR<0..31> 36D5>
CPU_ADDR<1> 5C7> 8D6<>
CPU_ADDR<2> 5C7> 8D6<>
CPU_ADDR<3> 5C7> 8D6<>
CPU_ADDR<4> 5C7> 8C6<>
CPU_ADDR<5> 5C7> 8C6<>
CPU_ADDR<6> 5C7> 8C6<>
CPU_ADDR<7> 5C7> 8C6<>
CPU_ADDR<8> 5C7> 8C6<>
CPU_ADDR<9> 5C7> 8C6<>
CPU_ADDR<10> 5B7> 8C6<>
CPU_ADDR<11> 5B7> 8C6<>
CPU_ADDR<12> 5B7> 8C6<>
CPU_ADDR<13> 5B7> 8C6<>
CPU_ADDR<14> 5B7> 8C6<>
CPU_ADDR<15> 5B7> 8C6<>
CPU_ADDR<16> 5B7> 8C6<>
CPU_ADDR<17> 5B7> 8C6<>
CPU_ADDR<18> 5B7> 8C6<>
CPU_ADDR<19> 5B7> 8C6<>
CPU_ADDR<20> 5B7> 8C6<>
CPU_ADDR<21> 5B7> 8C6<>
CPU_ADDR<22> 5B7> 8C6<>
CPU_ADDR<23> 5B7> 8C6<>
CPU_ADDR<24> 5B7> 8C6<>
CPU_ADDR<25> 5B7> 8C6<>
CPU_ADDR<26> 5B7> 8C6<>
CPU_ADDR<27> 5B7> 8C6<>
CPU_ADDR<28> 5B7> 8C6<>
CPU_ADDR<29> 5B7> 8C6<>
CPU_ADDR<30> 5B7> 8C6<>
CPU_ADDR<31> 5B7> 8B6<>
CPU_ADDR_HI_OE 5B7> 8C6<>
CPU_ADDR_HI_PU 5B7> 8C6<>
CPU_ADDR_PU 5B7> 8C6<>
CPU_ADS_L 5A7< 8B6<> 8C2< 36D5>
CPU_ATTN_L 5C7> 8D6<>
CPU_BG_L 5C7< 8C2< 8D6<> 36D5>
CPU_BR_L 5C7> 8D2< 8D6<> 36D5>
CPU_BUS_VSEL 5C3< 7A6<
CPU_CHKSTP_OUT_L 5B3<> 5C2< 39D8>
CPU_CHKS_L 5A3< 5D2<
CPU_CI_L 5A7> 8B6<> 36D5>
CPU_CLKOUT_SPN 5C3>
CPU_CLK_EN 8A6< 30C4>
CPU_DATA<0> 6D8<> 8D4<>
CPU_DATA<0..31> 36D5>
CPU_DATA<1> 6D8<> 8D4<>
CPU_DATA<2> 6D8<> 8D4<>
CPU_DATA<3> 6D8<> 8D4<>
CPU_DATA<4> 6D8<> 8D4<>
CPU_DATA<5> 6D8<> 8D4<>
CPU_DATA<6> 6D8<> 8D4<>
CPU_DATA<7> 6D8<> 8D4<>
CPU_DATA<8> 6D8<> 8D4<>
CPU_DATA<9> 6C8<> 8D4<>
CPU_DATA<10> 6C8<> 8D4<>
CPU_DATA<11> 6C8<> 8D4<>
CPU_DATA<12> 6C8<> 8C4<>
CPU_DATA<13> 6C8<> 8C4<>
CPU_DATA<14> 6C8<> 8C4<>
CPU_DATA<15> 6C8<> 8C4<>
CPU_DATA<16> 6C8<> 8C4<>
CPU_DATA<17> 6C8<> 8C4<>
CPU_DATA<18> 6C8<> 8C4<>
CPU_DATA<19> 6C8<> 8C4<>
CPU_DATA<20> 6C8<> 8C4<>
CPU_DATA<21> 6C8<> 8C4<>
CPU_DATA<22> 6C8<> 8C4<>
CPU_DATA<23> 6C8<> 8C4<>
CPU_DATA<24> 6C8<> 8C4<>
CPU_DATA<25> 6C8<> 8C4<>
CPU_DATA<26> 6C8<> 8C4<>
CPU_DATA<27> 6C8<> 8C4<>
CPU_DATA<28> 6C8<> 8C4<>
CPU_DATA<29> 6C8<> 8C4<>
CPU_DATA<30> 6C8<> 8C4<>
CPU_DATA<31> 6C8<> 8C4<>
CPU_DATA<32> 6C8<> 8C4<> 8D6<>
CPU_DATA<32..63> 36D5>
CPU_DATA<33> 6C8<> 8C4<> 8D8<>
CPU_DATA<34> 6C8<> 8C4<> 8D8<>
CPU_DATA<35> 6C8<> 8C4<> 8D8<>
CPU_DATA<36> 6C8<> 8C4<> 8D8<>
CPU_DATA<37> 6B8<> 8C4<> 8D8<>
CPU_DATA<38> 6B8<> 8C4<> 8D8<>
CPU_DATA<39> 6B8<> 8C4<> 8D8<>
CPU_DATA<40> 6B8<> 8B4<> 8C8<>
CPU_DATA<41> 6B8<> 8B4<> 8C8<>
CPU_DATA<42> 6B8<> 8B4<> 8C8<>
CPU_DATA<43> 6B8<> 8B4<> 8C8<>
CPU_DATA<44> 6B8<> 8B4<> 8C8<>
CPU_DATA<45> 6B8<> 8B4<> 8B8<>
CPU_DATA<46> 6B8<> 8B4<> 8B8<>
CPU_DATA<47> 6B8<> 8B4<> 8B8<>
CPU_DATA<48> 6B8<> 8A8< 8B4<>
CPU_DATA<49> 6B8<> 8A8< 8B4<>
CPU_DATA<50> 6B8<> 8A8< 8B4<>
CPU_DATA<51> 6B8<> 8A8< 8B4<>
CPU_DATA<52> 6B8<> 8A8< 8B4<>
CPU_DATA<53> 6B8<> 8A8< 8B4<>
CPU_DATA<54> 6B8<> 8A8< 8B4<>
CPU_DATA<55> 6B8<> 8A8< 8B4<>
CPU_DATA<56> 6B8<> 8B3< 8B4<>
CPU_DATA<57> 6B8<> 8B3< 8B4<>
CPU_DATA<58> 6B8<> 8B3< 8B4<>
CPU_DATA<59> 6B8<> 8B3< 8B4<>
CPU_DATA<60> 6B8<> 8B3< 8B4<>
CPU_DATA<61> 6B8<> 8B3< 8B4<>
CPU_DATA<62> 6A8<> 8B3< 8B4<>
CPU_DATA<63> 6A8<> 8B3< 8B4<>
CPU_DBG_L 5C3> 8A4<> 8C2< 36D5>
CPU_DRDY_L 5C3> 8A4< 8C2< 36D5>
CPU_DRDY_L_UF 36D5>
CPU_DTI<0> 5C3< 8A4<>
CPU_DTI<0..2> 36D5>
CPU_DTI<1> 5C3< 8A4<>
CPU_DTI<2> 5C3< 8A4<>
CPU_EDTI 5B2< 5C3<
CPU_EMODE0_L 5A3< 7A4<
CPU_EMODE1_L 5A5< 5C2<
CPU_GBL_L 5A7< 8B6<> 36D5>
CPU_HIT_L 5A7< 8B6< 8D2< 36D5>
CPU_HRESET_INV 7A7<>
CPU_HRESET_L 5B3< 5C2< 7A5< 7A8< 23A2<> 39C8>
CPU_L1TSCLK 5B2< 5B3<
CPU_L2TSCLK 5B3< 5C2<
CPU_LSSD_MODE 5B3< 5C2<
CPU_M_CH 5B2< 5D2<
CPU_M_DM 25A8< 25B6<
CPU_M_DP 25B6< 25B8<
CPU_PLL_CFG<0> 5C3< 7D3<
CPU_PLL_CFG<1> 5C3< 7D3<
CPU_PLL_CFG<2> 5C3< 7D3<
CPU_PLL_CFG<3> 5C3< 7D3<
CPU_PLL_CFG<4> 5C3< 7D3<>
CPU_PLL_CFGEXT 7D4<>
CPU_PLL_FS00 7C4<>
CPU_PLL_FS01 7C4<>
CPU_PLL_FS10 7C4<
CPU_PLL_STOP_BASE 7C7<
CPU_PLL_STOP_DC 7C4<> 7C8<> 30B6<>
CPU_PMONIN_L 5A3< 5C2<
CPU_PULLDOWN 5A< 5A3< 5A3< 5C7<>
CPU_PULLUP 5A3< 5C2<
CPU_QACK_L 5B3< 8B6<> 36D5>
CPU_QREQ_L 5B3< 8B6< 8C2

```
PCI_IRDY_L      12B7< 12C7<> 17B7<> 24C6<> 26B7<>
                37C5> 39A5>
PCI_PAR         12C7<> 17B7<> 24C5<> 26B7<> 37C5>
                39D4>
PCI_STOP_L      12A7< 12C7<> 17B7<> 24C5<> 26B7<>
                37C5> 39A5>
PCI_TRDY_L      12B7< 12C7<> 17A7<> 24C5<> 26B7<>
                37C5> 39A5>
PLL_STOP_L      7C4<> 7C8<>
PMU_ACK_L       14C2< 30C4<>
PMU_AC_DET      30A4<> 30B4<>
PMU_AC_IN       30B4<>
PMU_BATT0_DET_L 30B4<>
PMU_BATT1_DET_L_PU  30B4<> 30D2<
PMU_BATT_DET_L  30B3> 30D2< 31A4<> 39C3>
PMU_BYTE        30B6< 30C7<
PMU_CAPSLOCK_LED_L  30C6<>
PMU_CHARGE_V    30C4<> 31B8<>
PMU_CHRG_BATT_B 30C4<> 31A8<>
PMU_CLK         14C2<> 30C4<>
PMU_CNVSS       30B6< 30C7<
PMU_CPU_HRESET_L  23A4< 23C4<> 30C4<>
PMU_EPM         30D2< 30D4<>
PMU_FROM_INT    14C2<> 30C4<>
PMU_I2C_CLK     30B4<> 30C2<
PMU_I2C_DATA    30B4<> 30C2<
PMU_INT_L       14B5<> 14B7< 30B6<>
PMU_INT_NMI     14B5<> 14B7< 30D4<>
PMU_KB_RESET_IN1  30A7<>
PMU_KB_RESET_IN2  30A7<>
PMU_KB_RESET_L    30A6> 30B7< 39B2>
PMU_LID_CLOSED_L  23A8< 23C4<> 30B2< 30C4<>
PMU_NMI_BUTTON_L  25C1< 30C2< 30C4<>
PMU_NMI_L       30C2< 30C4<>
PMU_NUMLOCK_LED_L  30C6<>
PMU_OOPS        30B2< 30B4<>
PMU_PME_L       14B5<> 26B8< 30B2< 30C4<>
PMU_POWERUP_OK  30B4<> 30D2<
PMU_POWER_UP_L  29C7<> 30C6<> 30D7< 33B8<
PMU_REQ_L       14B7< 14C2> 30C4<>
PMU_RESET_BUTTON_L  25B1< 30C4<> 30D2<
PMU_RESET_L     30B6<>
PMU_SLEEP_LED   23C4<>
PMU_SLEEP_LED_L  23C2<> 30C4<>
PMU_SMB_CLK     30B4<> 30C2< 31A3<
PMU_SMB_DATA    30B4<> 30C2< 31A2<
PMU_TO_INT      14C2<> 30C4<>
POWER_UP        29C7<>
POWER_VALID     30B2< 30C4<>
PWR_BUTTON_L    23A7<> 25C2< 39B2>
RAM_ADDR<0>     9B4< 11B5<> 11B6<>
RAM_ADDR<12..0>  36A5>
RAM_ADDR<1>     9B4< 11B3<> 11B8<>
RAM_ADDR<2>     9B4< 11B5<> 11B6<>
RAM_ADDR<3>     9B4< 11B3<> 11B8<>
RAM_ADDR<4>     9B4< 11B5<> 11B6<>
RAM_ADDR<5>     9B4< 11B3<> 11B8<>
RAM_ADDR<6>     9B4< 11B5<> 11B6<>
RAM_ADDR<7>     9B4< 11B3<> 11B8<>
RAM_ADDR<8>     9B4< 11B5<> 11B6<>
RAM_ADDR<9>     9A4< 11B3<> 11B8<>
RAM_ADDR<10>    9A4< 11B5<> 11B6<>
RAM_ADDR<11>    9A4< 11B5<> 11B6<>
RAM_ADDR<12>    9A4< 11B3<> 11B8<>
RAM_BA<0>       9A4< 11B3<> 11B8<>
RAM_BA<1..0>    36A5>
RAM_BA<1>       9A4< 11B5<> 11B6<>
RAM_CAS_L       9A4< 11B5<> 11B6<> 36A5>
RAM_CKE<0>      9A3< 9C4< 11B6<>
RAM_CKE<3..0>   36A5>
RAM_CKE<1>      9A3< 9C4< 11B8<>
RAM_CKE<2>      9A3< 9C4< 11C5<>
RAM_CKE<3>      9A3< 9C4< 11C3<>
RAM_CS_L<0>     9C4< 11B8<>
RAM_CS_L<3..0>  36A5>
RAM_CS_L<1>     9C4< 11B6<>
RAM_CS_L<2>     9C4< 11B3<>
RAM_CS_L<3>     9C4< 11B5<>
RAM_DATA_A<0>   10C6<> 11D8<>
RAM_DATA_A<7..0>  36C5>
RAM_DATA_A<1>   10C8<> 11D8<>
RAM_DATA_A<2>   10C6<> 11D8<>
RAM_DATA_A<3>   10B8<> 11D8<>
RAM_DATA_A<4>   10B8<> 11D6<>
RAM_DATA_A<5>   10B8<> 11D6<>
RAM_DATA_A<6>   10B8<> 11D6<>
RAM_DATA_A<7>   10B8<> 11D6<>
RAM_DATA_A<8>   10B8<> 11D8<>
RAM_DATA_A<15..8>  36C5>
RAM_DATA_A<9>   10C7<> 11D8<>
RAM_DATA_A<10>  10C7<> 11D8<>
RAM_DATA_A<11>  10C7<> 11D8<>
RAM_DATA_A<12>  10C7<> 11D6<>
RAM_DATA_A<13>  10C7<> 11D6<>
RAM_DATA_A<14>  10C7<> 11D6<>
RAM_DATA_A<15>  10C7<> 11D6<>
RAM_DATA_A<16>  10C6<> 11D8<>
RAM_DATA_A<31..16>  36B5>
RAM_DATA_A<17>  10C6<> 11C8<>
RAM_DATA_A<18>  10C6<> 11C3<>
RAM_DATA_A<19>  10C6<> 11C3<>
RAM_DATA_A<20>  10C6<> 11D5<>
RAM_DATA_A<21>  10C6<> 11C5<>
RAM_DATA_A<22>  10C6<> 11C5<>
RAM_DATA_A<23>  10C6<> 11C5<>
RAM_DATA_A<24>  10C6<> 11C3<>
RAM_DATA_A<25>  10C6<> 11C3<>
RAM_DATA_A<26>  10C6<> 11C3<>
RAM_DATA_A<27>  10C6<> 11C5<>
RAM_DATA_A<28>  10C6<> 11C5<>
RAM_DATA_A<29>  10C6<> 11C5<>
RAM_DATA_A<30>  10C6<> 11C5<>
RAM_DATA_A<31>  10C6<> 11C5<>
RAM_DATA_A<32>  10C4<> 11B8<>
RAM_DATA_A<47..32>  36B5>
RAM_DATA_A<33>  10C4<> 11B8<>
RAM_DATA_A<34>  10C4<> 11B8<>
RAM_DATA_A<35>  10C4<> 11B8<>
RAM_DATA_A<36>  10B4<> 11B6<>
RAM_DATA_A<37>  10B4<> 11B6<>
RAM_DATA_A<38>  10B4<> 11B6<>
RAM_DATA_A<39>  10B4<> 11B6<>
RAM_DATA_A<40>  10B4<> 11B8<>
RAM_DATA_A<41>  10D3<> 11B8<>
RAM_DATA_A<42>  10C3<> 11A8<>
RAM_DATA_A<43>  10C3<> 11A8<>
RAM_DATA_A<44>  10C3<> 11B6<>
RAM_DATA_A<45>  10C3<> 11B6<>
RAM_DATA_A<46>  10C3<> 11A6<>
RAM_DATA_A<47>  10C3<> 11A6<>
RAM_DATA_A<48>  10C2<> 11A8<>
RAM_DATA_A<55..48>  36B5>
RAM_DATA_A<49>  10C2<> 11A8<>
RAM_DATA_A<50>  10C2<> 11A8<>
RAM_DATA_A<51>  10C2<> 11A8<>
RAM_DATA_A<52>  10B2<> 11A6<>
RAM_DATA_A<53>  10B2<> 11A6<>
RAM_DATA_A<54>  10B2<> 11A6<>
RAM_DATA_A<55>  10B2<> 11A6<>
RAM_DATA_A<56>  10B2<> 11A8<>
RAM_DATA_A<63..56>  36A5>
RAM_DATA_A<57>  10D1<> 11A8<>
RAM_DATA_A<58>  10C1<> 11A8<>
RAM_DATA_A<59>  10C1<> 11A8<>
RAM_DATA_A<60>  10C1<> 11A6<>
RAM_DATA_A<61>  10C1<> 11A6<>
RAM_DATA_A<62>  10C1<> 11A6<>
RAM_DATA_A<63>  10C1<> 11A6<>
RAM_DATA_B<0>   10C8<> 11D3<>
RAM_DATA_B<7..0>  36C5>
RAM_DATA_B<1>   10C8<> 11D3<>
RAM_DATA_B<2>   10C8<> 11D3<>
RAM_DATA_B<3>   10C8<> 11D3<>
RAM_DATA_B<4>   10C8<> 11D5<>
RAM_DATA_B<5>   10C8<> 11D5<>
RAM_DATA_B<6>   10C8<> 11D5<>
RAM_DATA_B<7>   10C8<> 11D5<>
RAM_DATA_B<8>   10C8<> 11D3<>
RAM_DATA_B<15..8>  36C5>
RAM_DATA_B<9>   10C9<> 11D3<>
RAM_DATA_B<10>  10C8<> 11D3<>
RAM_DATA_B<11>  10C8<> 11D3<>
RAM_DATA_B<12>  10C8<> 11D5<>
RAM_DATA_B<13>  10C8<> 11D5<>
RAM_DATA_B<14>  10C8<> 11D5<>
RAM_DATA_B<15>  10C8<> 11D5<>
RAM_DATA_B<16>  10C6<> 11D3<>
RAM_DATA_B<31..16>  36B5>
RAM_DATA_B<17>  10C6<> 11C3<>
RAM_DATA_B<18>  10C6<> 11C3<>
RAM_DATA_B<19>  10C6<> 11C3<>
RAM_DATA_B<20>  10C6<> 11D5<>
RAM_DATA_B<21>  10C6<> 11C5<>
RAM_DATA_B<22>  10C6<> 11C5<>
RAM_DATA_B<23>  10C6<> 11C5<>
RAM_DATA_B<24>  10C6<> 11C3<>
RAM_DATA_B<25>  10C6<> 11C3<>
RAM_DATA_B<26>  10C6<> 11C3<>
RAM_DATA_B<27>  10C6<> 11C3<>
RAM_DATA_B<28>  10C6<> 11C5<>
RAM_DATA_B<29>  10C6<> 11C5<>
RAM_DATA_B<30>  10C6<> 11C5<>
RAM_DATA_B<31>  10C6<> 11C5<>
RAM_DATA_B<32>  10B4<> 11B3<>
RAM_DATA_B<47..32>  36B5>
RAM_DATA_B<33>  10C4<> 11B3<>
RAM_DATA_B<34>  10C4<> 11B3<>
RAM_DATA_B<35>  10C4<> 11B3<>
RAM_DATA_B<36>  10C4<> 11B5<>
RAM_DATA_B<37>  10C4<> 11B5<>
RAM_DATA_B<38>  10C4<> 11B5<>
RAM_DATA_B<39>  10C4<> 11B5<>
RAM_DATA_B<40>  10C4<> 11B3<>
RAM_DATA_B<41>  10C4<> 11B3<>
RAM_DATA_B<42>  10C4<> 11A3<>
RAM_DATA_B<43>  10C4<> 11A3<>
RAM_DATA_B<44>  10C4<> 11B5<>
RAM_DATA_B<45>  10C4<> 11B5<>
RAM_DATA_B<46>  10C4<> 11A5<>
RAM_DATA_B<47>  10C4<> 11A5<>
RAM_DATA_B<48>  10D2<> 11A3<>
RAM_DATA_B<55..48>  36B5>
RAM_DATA_B<49>  10C2<> 11A3<>
RAM_DATA_B<50>  10C2<> 11A3<>
RAM_DATA_B<51>  10C2<> 11A3<>
RAM_DATA_B<52>  10C2<> 11A5<>
RAM_DATA_B<53>  10C2<> 11A5<>
RAM_DATA_B<54>  10C2<> 11A5<>
RAM_DATA_B<55>  10C2<> 11A5<>
RAM_DATA_B<56>  10C2<> 11A3<>
RAM_DATA_B<63..56>  36A5>
RAM_DATA_B<57>  10C2<> 11A3<>
RAM_DATA_B<58>  10C2<> 11A3<>
RAM_DATA_B<59>  10C2<> 11A3<>
RAM_DATA_B<60>  10C2<> 11A5<>
RAM_DATA_B<61>  10C2<> 11A5<>
RAM_DATA_B<62>  10C2<> 11A5<>
RAM_DATA_B<63>  10C2<> 11A5<>
RAM_DQM_A<0>    10B8<> 11D6<> 36C5>
RAM_DQM_A<1>    10C7<> 11D6<> 36C5>
RAM_DQM_A<2>    10B6<> 11C6<>
RAM_DQM_A<3..2>  36B5>
RAM_DQM_A<3>    10C5<> 11C6<>
RAM_DQM_A<4>    10B4<> 11B6<>
RAM_DQM_A<5..4>  36B5>
RAM_DQM_A<5>    10C3<> 11A6<>
RAM_DQM_A<6>    10B2<> 11A6<> 36B5>
RAM_DQM_A<7>    10C1<> 11A6<> 36A5>
RAM_DQM_B<0>    10C8<> 11D5<> 36C5>
RAM_DQM_B<1>    10C8<> 11D5<> 36C5>
RAM_DQM_B<2>    10C6<> 11C5<>
RAM_DQM_B<3..2>  36B5>
RAM_DQM_B<3>    10C6<> 11C5<>
RAM_DQM_B<4>    10C4<> 11B5<>
RAM_DQM_B<5..4>  36B5>
RAM_DQM_B<5>    10C4<> 11B5<>
RAM_DQM_B<6>    10C2<> 11A5<> 36B5>
RAM_DQM_B<7>    10C2<> 11A5<> 36A5>
RAM_DQS_A<0>    10B8<> 11D8<> 36C5>
RAM_DQS_A<1>    10C7<> 11D8<> 36C5>
RAM_DQS_A<2>    10B6<> 11C8<>
RAM_DQS_A<3..2>  36B5>
RAM_DQS_A<3>    10C5<> 11C8<>
RAM_DQS_A<4>    10B4<> 11B8<>
RAM_DQS_A<5..4>  36B5>
RAM_DQS_A<5>    10C3<> 11A8<>
RAM_DQS_A<6>    10B2<> 11A8<> 36B5>
RAM_DQS_A<7>    10C1<> 11A8<> 36A5>
RAM_DQS_B<0>    10C8<> 11D3<> 36C5>
RAM_DQS_B<1>    10C8<> 11D3<> 36C5>
RAM_DQS_B<2>    10C6<> 11C3<>
RAM_DQS_B<3..2>  36B5>
RAM_DQS_B<3>    10C6<> 11C3<>
RAM_DQS_B<4>    10C4<> 11B3<>
RAM_DQS_B<5..4>  36B5>
RAM_DQS_B<5>    10C4<> 11B3<>
RAM_DQS_B<6>    10C2<> 11A3<> 36B5>
RAM_DQS_B<7>    10C2<> 11A3<> 36A5>
RAM_MUXSEL_H    10A3< 10A5< 10B1<> 10B3<> 36A5>
RAM_MUXSEL_L    10A3< 10A5< 10B5<> 10B7<> 36A5>
RAM_RAS_L       9A4< 11B5<> 11B6<> 36A5>
RAM_WE_L        9A4< 11B3<> 11B8<> 36A5>
RF_DISABLE_L_SPN  24D6<> 39C1>
RIGHT_USB_DM    26A3< 32A7<> 37A2> 39D1>
RIGHT_USB_DP    26A3< 32A7<> 37A2> 39D1>
RJ45_CD_PD      27B2<>
RJ45_C1_PD      27B2<>
RJ45_C2_PD      27B2<>
RJ45_C3_PD      27B2<>
RJ45_DN<0>      27B2<> 37D2> 39B3>
RJ45_DN<1>      27B2<> 37D2> 39B3>
RJ45_DN<2>      27B2<> 37D2> 39A3>
RJ45_DN<3>      27B2<> 37D2> 39A3>
RJ45_DP<0>      27B2<> 37D2> 39B3>
RJ45_DP<1>      27B2<> 37D2> 39B3>
RJ45_DP<2>      27B2<> 37D2> 39A3>
RJ45_DP<3>      27B2<> 37D2> 39A3>
ROM_CS_L        9B3< 12A5< 24B6<> 39B1>
ROM_OE_L        9B3< 12A5< 24C5<> 39B1>
ROM_ONBOARD_CS_L  9B3< 24C6<> 39B1>
ROM_RW_L        9B3< 12A5< 24C6<> 39B1>
ROM_WP_L        9B3<
RSDM3_TP        26C5>
RSDM4_TP        26C5>
RSDM5_TP        26C5>
RSDP3_TP        26C5>
RSDP4_TP        26C5>
RSDP5_TP        26C5>
RUN_OR_AC       29C6<>
SI_A2           20B7<
SI_DDC_CLK      19C5<> 20B7<
SI_DDC_DATA     19C5<> 20B7<
SI_EDGE         20B7<
SI_MSEN         20B5<>
SI_PD           20B7<
SI_RST          20B7<
SI_TMDS_CLKN    20B5<> 20C4<
SI_TMDS_CLKP    20B5<> 20C4<
SI_TMDS_DN<0>   20B5<> 20C4<
SI_TMDS_DN<1>   20B5<> 20C4<
SI_TMDS_DN<2>   20A5<> 20B4<
SI_TMDS_DP<0>   20B5<> 20C4<
SI_TMDS_DP<1>   20B5<> 20C4<
SI_TMDS_DP<2>   20A5<> 20B4<
SI_VREF         20A5< 20A7<
SLEEP           23C4<> 25C6<> 30B6<> 30D7< 33A4<
                33A6< 33B3< 33B6<> 35B3< 35D2< 39A1>
SLEEP_LED       23C1< 25C7<> 39B6>
SLEEP_LED_I     23D1<
SLEEP_LED_L     23D2<
SLEEP_LED_SW_L  23C2<>
SLEEP_LED_UF    23C1<
SLEEP_LS5       33A5<> 33A8<
SLEEP_LS5_EN_L  33A5<>
SLEEP_L_LS5     19A7<> 27A8<> 33A5<> 34C8<> 35C8<
SLEEP_L_LS5_EN_L  33A6<>
SLEEP_L_LS5_INV  35A3< 35C2< 35C8<>
SLEEP_L_LS5_NET  33B3<> 35C8<>
SLEEP_NET       33A3<>
SLEEP_NET_INV   33A3<>
SMC_TP          26B5<
SND_AGND        25C7<> 38B6>
SND_AMP_MUTE    25C8< 25D6<> 39A4>
SND_AMP_MUTE_F  25C7< 25D6<>
SND_AMP_MUTE_L  14C5<> 25D5<>
SND_CLKOUT      14B1< 25D8< 36B1> 39D6>
SND_CLKOUT_F    25C7<> 25D7<
SND_HP_MUTE     25C5<>
SND_HP_MUTE_INV  25C5<> 25C6<> 39A4>
SND_HP_MUTE_L   14C5<> 25C4<>
SND_HP_SENSE_L  14B5<> 25D6<> 39C6>
SND_HW_RESET_L  14A7< 14B5<> 25C8< 39C6>
SND_HW_RESET_L_F  25C6<> 25C7<
SND_LIN_SENSE_L  14B5<> 25D6<> 39C6>
SND_SCLK        14B1< 25C8< 36B1> 39C6>
SND_SCLK_F      25C7< 25D7<>
SND_SYNC        14B1< 25D8< 39D6>
SND_SYNC_F      25C7<> 25D7<
SND_TO_AUDIO    14B1< 25D8< 39D6>
SND_TO_AUDIO_F  25D6<> 25D7<
SOFT_PWR_ON_L   22D1< 23A8< 30A8< 30C6<> 30D7<
                34A3<>
SRCLK_TP        26A5> 39A4>
SRMOD_TP        26A5< 39A4>
ST7_ICP_SEL_PD  23A2< 23D6<
ST7_KBD_LED_OUT  23A4< 23C4<>
ST7_OSC1        23D5<
ST7_OSC2        23D5<>
ST7_PB6_PD      23B2< 23C4<>
ST7_RESET_L     23D5<>
ST7_SENSOR4_SCK_PD  23B2< 23D4<>
ST7_SENSOR4_SDA_PD  23B2< 23D4<>
ST7_SENSORS_SCK_PU  23B2< 23D4<>
ST7_SENSORS_SDA_PU  23B2< 23D4<>
ST7_SLEEP_LED_H  23C2<> 23C4<>
ST7_XTAL_IN     23C5<
STOP_AGP_L      12D2< 12D4<>
SUPPLY_M_DM     25B6< 25B8<
SUPPLY_M_MP     25B6< 25B8<
SUTRO_ALS_GAIN_SW  23C4<> 24B2<> 39C2>
SUTRO_ALS_OUT   23C4<> 24B2<> 39C2>
SYSCLK_CPU      5C3> 8A6< 36D1>
SYSCLK_CPU_UF   8A6<> 36D1>
SYSCLK_DDRCLK_A0  9D4< 11D8<> 36D1>
SYSCLK_DDRCLK_A0_L  9D4< 11D8<> 36D1>
SYSCLK_DDRCLK_A0_L_UF  9B6<> 9D5< 36D1>
SYSCLK_DDRCLK_A0_UF  9B6<> 9D5< 36D1>
SYSCLK_DDRCLK_A1  9D4< 11A6<> 36D1>
SYSCLK_DDRCLK_A1_L  9D4< 11A6<> 36D1>
SYSCLK_DDRCLK_A1_L_UF  9B6<> 9D5< 36D1>
SYSCLK_DDRCLK_A1_UF  9B6<> 9D5< 36D1>
SYSCLK_DDRCLK_B0  9D4< 11D3<> 36D1>
SYSCLK_DDRCLK_B0_L  9D4< 11D3<> 36C1>
SYSCLK_DDRCLK_B0_L_UF  9B6<> 9C5< 36D1>
SYSCLK_DDRCLK_B0_UF  9B6<> 9D5< 36D1>
SYSCLK_DDRCLK_B1  9D4< 11A5<> 36C1>
SYSCLK_DDRCLK_B1_L  9D4< 11A5<> 36C1>
SYSCLK_DDRCLK_B1_L_UF  9B6<> 9D5< 36D1>
SYSCLK_DDRCLK_B1_UF  9B6<> 9D5< 36D1>
SYSCLK_LA_TP    8A6<>
SYSTEM_CLK_EN   14A5< 14B7< 30C4<>
TEB_TP          26A5< 39A4>
TEST_TP         26A5< 39A4>
THERM1_A_DM     25A6< 25A8< 37A2>
THERM1_A_DP     25A6< 25A8< 37A2>
THERM1_DM       25A5< 25B5< 25B5<> 37A2>
THERM1_DP       25A5< 25B5< 25B5<> 37A2>
THERM1_M_DM     37A2>
THERM1_M_DP     37A2>
THERM2_A_DM     25A6< 25A8< 37A2>
THERM2_A_DP     25A6< 25A8< 37A2>
THERM2_DM       25A5< 25B5< 25B5<> 37A2>
THERM2_DP       25A5< 25B5< 25B5<> 37A2>
THERM2_M_DM     37A2>
THERM2_M_DP     37A2>
THERM_INV       25A5<>
THERM_L_OC      25A4<> 30B4<>
TMDS_CLKN       20B3< 20C1< 20C3< 22B7<> 37B2>
TMDS_CLKP       20B3< 20C2< 20C3< 22C7<> 37B2>
TMDS_CLK_CMF    20C1<
TMDS_CONN_CLKN  22B6<> 22C7<> 37B2> 39A8>
TMDS_CONN_CLKP  22C6<> 22C7<> 37B2> 39D7>
TMDS_CONN_DN<0>  22C7<> 22D6<>
TMDS_CONN_DN<1>  22B7<> 22D5<>
TMDS_CONN_DN<2>  22B6<> 22D5<>
TMDS_CONN_DP<0>  22B7<> 22D6<>
TMDS_CONN_DP<1>  22B7<> 22D5<>
TMDS_CONN_DP<2>  22B6<> 22D5<>
TMDS_D0_CMF     20B1<
TMDS_D1_CMF     20B1<
TMDS_D2_CMF     20A1<
TMDS_DN<0>      20B1< 20B3< 20C3< 22C8<> 37B2>
                39B8>
TMDS_DN<1>      20A3< 20B1< 20C3< 22B8<> 37B2>
                39A8>
TMDS_DN<2>      20A1< 20A3< 20B3< 22B7<> 37B2>
                39A8>
TMDS_DP<0>      20B2< 20B3< 20C3< 22B8<> 37B2>
                39A8>
TMDS_DP<1>      20A3< 20B2< 20C3< 22B8<> 37B2>
                39A8>
TMDS_DP<2>      20A2< 20A3< 20B3< 22B7<> 37B2>
                39A8>
TPAD_F_RXD      23A7<> 39C4>
TPAD_F_TXD      23A7<> 39C4>
TPAD_RXD        23A8< 30C2< 30C4<>
TPAD_TXD        23A8< 30B2< 30C4<>
TPS2211_SHDN_L_PU  17C4<
TV_C            22A6<> 39D6>
TV_COMP         22A6<> 39D6>
TV_GND1         22B6<> 38B6> 39A7>
TV_GND2         22A6<> 38B6> 39A7>
TV_Y            22A6<> 39D6>
UIDE_ADDR<0>    13D7<> 24C4<
UIDE_ADDR<2..0>  37C5>
UIDE_ADDR<1>    13D7<> 24C4<
UIDE_ADDR<2>    13D7<> 24B4<
UIDE_CS0_L      13C7<> 24C4< 37C5>
UIDE_CS1_L      13C7<> 24B4< 37C5>
UIDE_DATA<0>    13D7<> 24D4<
UIDE_DATA<6..0>  37C5>
UIDE_DATA<1>    13D7<> 24D4<
UIDE_DATA<2>    13D7<> 24D4<
UIDE_DATA<3>    13D7<> 24D4<
UIDE_DATA<4>    13D7<> 24C4<
UIDE_DATA<5>    13D7<> 24C4<
UIDE_DATA<6>    13D7<> 24C4<
UIDE_DATA<7>    13D7<> 24C4< 37C5>
UIDE_DATA<8>    13D7<> 24C4<
UIDE_DATA<15..8>  37C5>
UIDE_DATA<9>    13D7<> 24C4<
UIDE_DATA<10>   13D7<> 24C4<
UIDE_DATA<11>   13D7<> 24D4<
UIDE_DATA<12>   13D7<> 24B4<
UIDE_DATA<13>   13D7<> 24B4<
UIDE_DATA<14>   13D7<> 24C4<
UIDE_DATA<15>   13D7<> 24B4<
UIDE_DIOR_L     13C7<> 24A4< 37C5>
UIDE_DIOW_L     13C7<> 24A4< 37C5>
UIDE_DMACK_L    13C7<> 24A4< 37C5>
UIDE_DMARQ      13C7<> 37C5>
UIDE_INTRQ      13C7< 37C5>
UIDE_IOCHRDY    13C7< 24A4< 37C5>
UIDE_REF        13C7<> 38D3>
UIDE_RST_L      13C7<> 24A4< 37C5>
USB2_PCI_GNT_L  12C7<> 26B7<
USB2_PCI_INT_L  14B5<> 14C7< 26A8<
USB2_PCI_REQ_L  12A7< 12D7<> 26B7>
USB_D1M         14C1< 26A5> 26B4<
USB_D1P         14C1< 26A4< 26A5>
USB_D2M         14D1< 26A4< 26A5>
USB_D2P         14D1< 26A4< 26A5>
USB_DAM         14B2<> 14D2< 26A5>
USB_DAP         14B2<> 14D2< 26A5>
USB_DBM         14B2<> 14D2<
USB_DBP         14B2<> 14D2<
USB_DCM         14B2<> 14C2< 26A5>
USB_DCP         14B2<> 14C2< 26A5>
USB_DDM         14B2<> 14C2<
USB_DDP         14B2<> 14C2<
USB_DEM         14B2< 14B2<> 37B2>
USB_DEP         14B2<> 14C2< 37B2>
USB_DFM         14B2< 14B2<> 37B2>
USB_DFP         14B2< 14B2<> 37B2>
USB_OC_AB_L     14B2< 14C7<
USB_OC_CD_L     14B2< 14C7<
USB_OC_EF_L     14B2< 14D7<
USB_PWREN_AB_L  14B2<> 14C7<
USB_PWREN_CD_L  14B2<> 14C7<
USB_PWREN_EF_L  14B2<> 14D7<
VCORE_BOOST     34C4<> 38C1>
VCORE_BST       34C5<> 38C1>
VCORE_CC        34B6<> 38B1>
VCORE_CNTL_RC   19A3<>
VCORE_DH        34B5<> 38C1>
VCORE_DL        34B5<> 38C1>
VCORE_FAST<1>   34D3< 34D5<
VCORE_FAST<2>   34D3< 34D5<
VCORE_FAST<3>   34D3< 34D5<
VCORE_FAST<4>   34D3< 34D5<
VCORE_FB        34B5< 38B1> 39A2>
VCORE_GND       34B5<> 38B1>
VCORE_GNDA      34B6<>
VCORE_GNDDIV    34A4< 34B5< 38B1>
VCORE_GNDDIV_TEST  34A3<>
VCORE_GNDGNS    34A2<> 34A4< 38B1>
VCORE_GNDSNS_TEST  34A3<>
VCORE_ILIM      34C6<> 38C1>
VCORE_LX        34B5<> 38C1>
VCORE_MUX_EN    34D5<> 39A2>
VCORE_MUX_SEL   34D5<>
VCORE_REF       34B6<> 38C1>
VCORE_SEL_OFF_PU  34B6<>
VCORE_SEL_ON    34B6<>
VCORE_SHDN_L    34C6<>
VCORE_SLOW<1>   34D6<
VCORE_SLOW<2>   34D6<
VCORE_SLOW<3>   34D6<
VCORE_SLOW<4>   34D6<
VCORE_SNS       34A1<> 38B1>
VCORE_TIME      34B4<> 38B1>
VCORE_TON       34B6< 38C1>
VCORE_VCC       34C6< 38C1>
VCORE_VGATE     14B5< 14B7< 34B4> 38B1>
VCORE_VID0      39A3>
VCORE_VID1      39A3>
VCORE_VID2      39A3>
VCORE_VID3      39A3>
VCORE_VID4      39A3>
VCORE_VID<0>    34A2<> 34B8<
VCORE_VID<1>    34A2<> 34B8< 34D4<>
VCORE_VID<2>    34A2<> 34B8< 34D4<>
VCORE_VID<3>    34A2<> 34B8< 34D4<>
VCORE_VID<4>    34A2<> 34B8< 34D4<>
VGA_B           22C6<> 22D7< 39D7>
VGA_G           22C5<> 22D7< 39D7>
VGA_HSYNC       22C6<> 22C7< 39D7>
VGA_HSYNC_BUF   22C8<>
VGA_R           22C5<> 22D7< 39D7>
VGA_VSYNC       22C5<> 22C7< 39D7>
VGA_VSYNC_BUF   22C8<>
ZV_LCDDATA20_PU  19C7<>
```


NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE COMPUTER INC.

SIZE	DRAWING NUMBER	REV.
D	051-6531	B
SCALE: NONE	SHT 42 OF 44	

*** Part Cross-Reference for the entire design ***

BS1 PCB_STANDOFF 4
C1 CAP 22
C2 CAP 34
C3 CAP 34
C4 CAP 34
C5 CAP 34
C6 CAP 34
C7 CAP 34
C8 CAP 5
C9 CAP 16
C10 CAP 16
C11 CAP 18
C12 CAP 5
C13 CAP 34
C14 CAP 20
C15 CAP 14
C16 CAP 16
C17 CAP 16
C18 CAP 16
C19 CAP 16
C20 CAP 16
C21 CAP 16
C22 CAP 16
C23 CAP 16
C24 CAP 16
C25 CAP 5
C26 CAP 16
C27 CAP 16
C28 CAP 16
C29 CAP 16
C30 CAP 16
C31 CAP 16
C32 CAP 16
C33 CAP 16
C34 CAP 16
C35 CAP 16
C36 CAP 16
C37 CAP 18
C38 CAP 5
C39 CAP 5
C40 CAP 5
C41 CAP 5
C42 CAP 16
C43 CAP 16
C44 CAP 16
C45 CAP 16
C46 CAP 5
C47 CAP 5
C48 CAP 5
C49 CAP 16
C50 CAP 16
C51 CAP 16
C52 CAP 16
C53 CAP 16
C54 CAP 16
C55 CAP 16
C56 CAP 16
C57 CAP 16
C58 CAP 16
C59 CAP 16
C60 CAP 16
C61 CAP 16
C62 CAP 18
C63 CAP 18
C64 CAP 18
C65 CAP 18
C66 CAP 18
C67 CAP 18
C68 CAP 18
C69 CAP 18
C70 CAP 18
C71 CAP 18
C72 CAP 5
C73 CAP 5
C74 CAP 5
C75 CAP 16
C76 CAP 16
C77 CAP 18
C78 CAP 18
C79 CAP 20
C80 CAP 20
C81 CAP 20
C82 CAP 20
C83 CAP 12
C84 CAP 14
C85 CAP 14
C86 CAP 24
C87 CAP 20
C88 CAP 20
C89 CAP 5
C90 CAP 5
C91 CAP 5
C92 CAP 5
C93 CAP 35
C94 CAP 16
C95 CAP 16
C96 CAP 16
C97 CAP 14
C98 CAP 16
C99 CAP 16
C100 CAP 16
C101 CAP 16
C102 CAP 20
C103 CAP 5
C104 CAP 5
C105 CAP 5
C106 CAP 5
C107 CAP 5
C108 CAP 16
C109 CAP 16
C110 CAP 5
C111 CAP 5
C112 CAP 5
C113 CAP 5
C114 CAP 5
C115 CAP 5
C116 CAP 34
C117 CAP 16
C118 CAP 16
C119 CAP 16
C120 CAP 16
C121 CAP 16
C122 CAP 16
C123 CAP 16
C124 CAP 16
C125 CAP 16
C126 CAP 16
C127 CAP 16
C128 CAP 16
C129 CAP 20
C130 CAP 20
C131 CAP 20
C132 CAP 20
C133 CAP 20
C134 CAP 25
C135 CAP 25
C136 CAP 5
C137 CAP 5
C138 CAP 5
C139 CAP 5
C140 CAP 14
C141 CAP 16
C142 CAP 16
C143 CAP 16
C144 CAP 16
C145 CAP 16
C146 CAP 16
C147 CAP 16
C148 CAP 14
C149 CAP 5
C150 CAP 5
C151 CAP 5
C152 CAP 5
C153 CAP 5
C154 CAP 5
C155 CAP 5
C156 CAP 5
C157 CAP 16
C158 CAP 16
C159 CAP 16
C160 CAP 12
C161 CAP 16
C162 CAP 16
C163 CAP 16
C164 CAP 16
C165 CAP 20
C166 CAP 19
C167 CAP 19
C168 CAP 5
C169 CAP 5
C170 CAP 5
C171 CAP 16
C172 CAP 16
C173 CAP 16
C174 CAP 16
C175 CAP 16
C176 CAP 16
C177 CAP 16
C178 CAP 16
C179 CAP 16
C180 CAP 16
C181 CAP 16
C182 CAP 14
C183 CAP 16
C184 CAP 16
C185 CAP 16
C186 CAP 19
C187 CAP 20
C188 CAP 5
C189 CAP 5
C190 CAP 5
C191 CAP 5
C192 CAP 5
C193 CAP 5
C194 CAP 5
C195 CAP 5
C196 CAP 16
C197 CAP 16
C198 CAP 14
C199 CAP 16
C200 CAP 14
C201 CAP 5
C202 CAP 5
C203 CAP 5
C204 CAP 5
C205 CAP 16
C206 CAP 16
C207 CAP 16
C208 CAP 10
C209 CAP 16
C210 CAP 16
C211 CAP 16
C212 CAP 16
C213 CAP 16
C214 CAP 16
C215 CAP 16
C216 CAP 16
C217 CAP 16
C218 CAP 20
C219 CAP 19
C220 CAP 19
C221 CAP 19
C222 CAP 19
C223 CAP 5
C224 CAP 5
C225 CAP 5
C226 CAP 16
C227 CAP 16
C228 CAP 16
C229 CAP 16
C230 CAP 16
C231 CAP 16
C232 CAP 19
C233 CAP 20
C234 CAP 34
C235 CAP 35
C236 CAP 16
C237 CAP 16
C238 CAP 16
C239 CAP 16
C240 CAP 16
C241 CAP 16
C242 CAP 16
C243 CAP 16
C244 CAP 16
C245 CAP 9
C246 CAP 16
C247 CAP 12
C248 CAP 16
C249 CAP 16
C250 CAP 16
C251 CAP 16
C252 CAP 19
C253 CAP 19
C254 CAP 19
C255 CAP 20
C256 CAP 19
C257 CAP 5
C258 CAP 5
C259 CAP 16
C260 CAP 16
C261 CAP 16
C262 CAP 16
C263 CAP 16
C264 CAP 16
C265 CAP 16
C266 CAP 16
C267 CAP 16
C268 CAP 16
C269 CAP 19
C270 CAP 19
C271 CAP 19
C272 CAP 5
C273 CAP 5
C274 CAP 34
C275 CAP 5
C276 CAP 35
C277 CAP 16
C278 CAP 16
C279 CAP 16
C280 CAP 16
C281 CAP 34
C282 CAP 19
C284 CAP 20
C285 CAP 34
C286 CAP 16
C287 CAP 16
C288 CAP 16
C289 CAP 16
C290 CAP 16
C291 CAP 16
C292 CAP 16
C293 CAP 16
C294 CAP 16
C295 CAP 16
C296 CAP 16
C297 CAP 16
C298 CAP 16
C299 CAP 19
C300 CAP 19
C301 CAP 19
C302 CAP 19
C303 CAP 19
C304 CAP 21
C305 CAP 19
C306 CAP 19
C307 CAP 19
C308 CAP 8
C309 CAP 16
C310 CAP 16
C311 CAP 19
C312 CAP 16
C313 CAP 16
C314 CAP 16
C315 CAP 16
C316 CAP 16
C317 CAP 16
C318 CAP 16
C319 CAP 20
C320 CAP 16
C321 CAP 16
C322 CAP 16
C323 CAP 16
C324 CAP 16
C325 CAP 16
C326 CAP 19
C327 CAP 21
C328 CAP 19
C329 CAP 19
C330 CAP 19
C331 CAP 19
C332 CAP 19
C333 CAP 19
C334 CAP 16
C335 CAP 16
C336 CAP 16
C337 CAP 16
C338 CAP 19
C339 CAP 21
C340 CAP 5
C341 CAP 5
C342 CAP 5
C343 CAP 5
C344 CAP 5
C345 CAP 5
C346 CAP 5
C347 CAP 5
C348 CAP 16
C349 CAP 16
C350 CAP 16
C351 CAP 16
C352 CAP 16
C353 CAP 14
C354 CAP 16
C355 CAP 16
C356 CAP 16
C357 CAP 16
C358 CAP 21
C359 CAP 21
C360 CAP 21
C361 CAP 21
C362 CAP 21
C363 CAP 21
C364 CAP 21
C365 CAP 16
C366 CAP 16
C367 CAP 16
C368 CAP 16
C369 CAP 16
C370 CAP 16
C371 CAP 16
C372 CAP 21
C373 CAP 21
C374 CAP 21
C375 CAP 16
C376 CAP 16
C377 CAP 16
C378 CAP 16
C379 CAP 21
C380 CAP 21
C381 CAP 21
C382 CAP 21
C383 CAP 21
C384 CAP 16
C385 CAP 16
C386 CAP 16
C387 CAP 16
C388 CAP 16
C389 CAP 16
C390 CAP 16
C391 CAP 16
C392 CAP 16
C393 CAP 16
C394 CAP 16
C395 CAP 16
C396 CAP 16
C397 CAP 16
C398 CAP 16
C399 CAP 16
C400 CAP 16
C401 CAP 16
C402 CAP 16
C403 CAP 16
C404 CAP 16
C405 CAP 16
C406 CAP 16
C407 CAP 16
C408 CAP 21
C409 CAP 21
C410 CAP 16
C411 CAP 21
C412 CAP 21
C413 CAP 21
C414 CAP 21
C415 CAP 21
C416 CAP 22
C417 CAP 16
C418 CAP 16
C419 CAP 14
C420 CAP 21
C421 CAP 21
C422 CAP 16
C423 CAP 16
C424 CAP 14
C425 CAP 21
C426 CAP 21
C427 CAP_P 34
C428 CAP 21
C429 CAP 21
C430 CAP_P 34
C431 CAP_P 34
C432 CAP_P 34
C433 CAP 14
C434 CAP 21
C435 CAP 21
C436 CAP 21
C437 CAP 21
C438 CAP 21
C439 CAP 34
C440 CAP 22
C441 CAP_P 34
C442 CAP_P 27
C443 CAP_P 34
C444 CAP_P 34
C445 CAP_P 34
C446 CAP 21
C447 CAP 21
C448 CAP 19
C449 CAP 22
C450 CAP 21
C451 CAP 19
C452 CAP 22
C453 CAP 27
C454 CAP 27
C455 CAP 34
C456 CAP 33
C457 CAP 27
C458 CAP 31
C459 CAP 34
C460 CAP 9
C461 CAP 32
C462 CAP 32
C463 CAP 32
C464 CAP 27
C465 CAP 27
C466 CAP 27
C467 CAP 17
C468 CAP 31
C469 CAP 25
C470 CAP 9
C471 CAP 27
C472 CAP 27
C473 CAP 19
C474 CAP 22
C475 CAP 27
C476 CAP 27
C477 CAP 27
C478 CAP 25
C479 CAP 9
C480 CAP 16
C481 CAP 11
C482 CAP 11
C483 CAP 19
C484 CAP 22
C485 CAP 32
C486 CAP 27
C487 CAP 27
C488 CAP 27
C489 CAP 11
C490 CAP 11
C491 CAP 27
C492 CAP 27
C493 CAP 27
C494 CAP 19
C495 CAP 32
C496 CAP 27
C497 CAP 27
C498 CAP 34
C499 CAP 35
C500 CAP 22
C501 CAP 27
C502 CAP 27
C503 CAP 27
C504 CAP 27
C505 CAP 27
C506 CAP 27
C507 CAP 34
C508 CAP 33
C509 CAP 32
C510 CAP 32
C511 CAP 27
C512 CAP 34
C513 CAP 25
C514 CAP 19
C515 CAP 19
C516 CAP 33
C517 CAP 27
C518 CAP 34
C519 CAP 35
C520 CAP 27
C521 CAP 34
C522 CAP 11
C523 CAP 11
C524 CAP 11
C525 CAP 11
C526 CAP 11
C527 CAP 11
C528 CAP 29
C529 CAP 34
C530 CAP 11
C531 CAP 35
C532 CAP 33
C533 CAP 33
C534 CAP 33
C535 CAP 32
C536 CAP 32
C537 CAP 32
C538 CAP 28
C539 CAP 28
C540 CAP 28
C541 CAP 28
C542 CAP 11
C543 CAP 21
C544 CAP 35
C545 CAP 33
C546 CAP 28
C547 CAP 31
C548 CAP 11
C549 CAP 11
C550 CAP 11
C551 CAP 11
C552 CAP 22
C553 CAP 32
C554 CAP 32
C555 CAP 27
C556 CAP 29
C557 CAP 31
C558 CAP 30
C559 CAP 35
C560 CAP 33
C561 CAP 28
C562 CAP 31
C563 CAP 31
C564 CAP 31
C565 CAP 11
C566 CAP 33
C567 CAP 33
C568 CAP 32
C569 CAP 32
C570 CAP 28
C571 CAP 28
C572 CAP 31
C573 CAP 11
C574 CAP 30
C575 CAP 35
C576 CAP 33
C577 CAP 28
C578 CAP 31
C579 CAP 31
C580 CAP 35
C581 CAP 35
C582 CAP 35
C583 CAP 33
C584 CAP 32
C585 CAP 32
C586 CAP 28
C587 CAP 28
C588 CAP 29
C589 CAP 11
C590 CAP 33
C591 CAP 28
C592 CAP 31
C593 CAP 31
C594 CAP 11
C595 CAP 11
C596 CAP 11
C597 CAP 11
C598 CAP 33
C599 CAP 32
C600 CAP 31
C601 CAP 11
C602 CAP 11
C603 CAP 35
C604 CAP 32
C605 CAP 28
C606 CAP 29
C607 CAP 29
C608 CAP 31
C609 CAP 33
C610 CAP 33
C611 CAP 33
C612 CAP 33
C613 CAP 32
C614 CAP 28
C615 CAP 31
C616 CAP 31
C617 CAP 31
C618 CAP 31
C619 CAP 31
C620 CAP 33
C621 CAP 31
C622 CAP 31
C623 CAP 33
C624 CAP 31
C625 CAP 32
C626 CAP 32
C627 CAP 28
C628 CAP 28
C629 CAP 28
C630 CAP 31
C631 CAP 31
C632 CAP 31
C633 CAP 31
C634 CAP 28
C635 CAP 28
C636 CAP 23
C637 CAP 23
C638 CAP 23
C639 CAP 33
C640 CAP 28
C641 CAP 28
C642 CAP 28
C643 CAP 30
C644 CAP 32
C645 CAP 28
C646 CAP 28
C647 CAP 21
C648 CAP 23
C649 CAP 26
C650 CAP 28
C651 CAP 25
C652 CAP 31
C653 CAP 28
C654 CAP 23
C655 CAP 23
C656 CAP 23
C657 CAP 26
C658 CAP 31
C659 CAP 33
C660 CAP 23
C661 CAP 26
C662 CAP 33
C663 CAP 23
C664 CAP 30
C665 CAP 26
C666 CAP 30
C667 CAP 26
C668 CAP 25
C669 CAP 22
C670 CAP 23
C671 CAP 21
C672 CAP 21
C673 CAP 23
C674 CAP 34
C675 CAP 23
C676 CAP 22
C677 CAP 35
C678 CAP 25
C679 CAP 34
C680 CAP 34
C681 CAP 25
C682 CAP 34
C683 CAP 35
C684 CAP 22
C685 CAP 22
C686 CAP 14
C687 CAP 34
C688 CAP 25
C689 CAP 34
C690 CAP 25
C691 CAP 14
C692 CAP 14
C693 CAP 34
C694 CAP_P 33
C695 CAP 34
C696 CAP 22
C697 CAP 33
C698 CAP 14
C699 CAP 34
C700 CAP 33
C701 CAP 21
C702 CAP 22
C703 CAP 22
C704 CAP 21
C705 CAP 35
C706 CAP 22
C707 CAP 22
C708 CAP 19
C709 CAP 35
C710 CAP 22
C711 CAP 25
C712 CAP 22
C713 CAP 22
C714 CAP 22
C715 CAP 21
C716 CAP 21
C717 CAP 22
C718 CAP 22
C719 CAP_P 19
C720 CAP_P 19
C721 CAP_P 19
C722 CAP 21
C723 CAP 35
C724 CAP 22
C725 CAP 21
C726 CAP 35
C727 CAP 10
C728 CAP_P 34
C729 CAP_P 34
C730 CAP_P 34
C731 CAP_P 34
C732 CAP_P 34
C733 CAP_P 34
C734 CAP_P 34
C735 CAP 10
C736 CAP 10
C737 CAP 10
C738 CAP 10
C739 CAP 22
C740 CAP 35
C741 CAP 10
C742 CAP 10
C743 CAP 10
C744 CAP 22
C745 CAP_P 35
C746 CAP 22
C747 CAP 10
C748 CAP 10
C749 CAP 22
C750 CAP_P 32
C751 CAP_P 35
C752 CAP 10
C753 CAP 10
C754 CAP 27
C755 CAP 27
C756 CAP_P 33
C757 CAP 31
C758 CAP_P 32
C759 CAP 33
C760 CAP 33
C761 CAP 11
C762 CAP 19
C763 CAP 33
C764 CAP 34
C765 CAP_P 32
C766 CAP 19
C767 CAP 25
C768 CAP 34
C769 CAP_P 32
C770 CAP 33
C771 CAP 31
C772 CAP 31
C773 CAP 17
C774 CAP 29
C775 CAP 31
C776 CAP 17
C777 CAP 28
C778 CAP 28
C779 CAP 33
C780 CAP_P 35
C781 CAP 35
C782 CAP_P 35
C783 CAP 17
C784 CAP 29
C785 CAP 33
C786 CAP 29
C787 CAP 32
C788 CAP_P 35
C789 CAP 17
C790 CAP 17
C791 CAP 17
C792 CAP 29
C793 CAP_P 32
C794 CAP_P 32
C795 CAP 17
C796 CAP 17
C797 CAP 17
C798 CAP 17
C799 CAP_P 32
C800 CAP 33
C801 CAP 32
C802 CAP 31
C803 CAP 29
C804 CAP 28
C805 CAP 29
C806 CAP 33
C807 CAP 29
C808 CAP 28
C809 CAP 35
C810 CAP 28
C811 CAP 33
C812 CAP 30
C813 CAP 17
C814 CAP 23
C815 CAP 23
C816 CAP 23
C817 CAP 31
C818 CAP_P 28
C819 CAP_P 32
C820 CAP_P 32
C821 CAP_P 32
C822 CAP_P 32
C823 CAP_P 33
C824 CAP_P 31
C825 CAP_P 33
C826 CAP 33
C827 CAP 30
C828 CAP 23
C829 CAP 26
C830 CAP 26
C831 CAP 30
C832 CAP 30
C833 CAP 26
C834 CAP 26
C835 CAP 30
C836 CAP 26
C837 CAP 26
C838 CAP 26
C839 CAP 26
C840 CAP 26
C841 CAP 26
C842 CAP 26
C843 CAP 26
C844 CAP 22
C845 CAP 26
C846 CAP 25
C847 CAP 21
C848 CAP 21
C849 CAP 21
C850 CAP 21
C851 CAP 21
C852 CAP 21
C853 CAP 21
C854 CAP 21
C855 CAP 21
C856 CAP 21
C857 CAP 21
C858 CAP 21
C859 CAP 21
C860 CAP 21
C861 CAP 21
C862 CAP 21
C863 CAP 21
C864 CAP 21
C865 CAP 21
C866 CAP 21
C867 CAP 21
C868 CAP 21
C869 CAP 21
C870 CAP 21
C871 CAP 21
C872 CAP 21
C873 CAP 21
C874 CAP 21
C875 CAP 21
C876 CAP 21
C877 CAP 21
C878 CAP 21
C879 CAP 21
C880 CAP 21
C881 CAP 21
C882 CAP 19
C883 CAP 31
C884 CAP_P 34
C885 CAP_P 34
C886 CAP 35
C887 CAP 35
C888 CAP 35
C889 CAP 21
C890 CAP 35
C891 CAP 35
C892 CAP 35
C893 CAP 35
C894 CAP 35
C895 CAP 25
C896 CAP 25
C897 CAP 25
C898 CAP 25
C899 CAP 25
C900 CAP 25
C901 CAP 25
C902 CAP 19
C903 CAP 25
C904 CAP 25
C905 CAP 25
C906 CAP 31
C907 CAP 35
C908 CAP 35
D1 DIODE 27
D2 DIODE_SCHOT 34
D3 DIODE_SCHOT 32
D4 DIODE 32
D5 DIODE_SCHOT 19
D6 DIODE_SCHOT 33
D7 DIODE_SCHOT 32
D8 ZENER 29
D9 DIODE 31
D10 DIODE 31
D11 DIODE_SCHOT 32
D12 DIODE_DUAL_6P 29
D13 DIODE_SCHOT 33
D14 DIODE_SCHOT_3P2 28
D15 DIODE_DUAL_6P 29
D16 DIODE 33
D17 DIODE_SCHOT 32
D18 DIODE 32
D19 DIODE_SCHOT 32
D20 DIODE_SCHOT 28
D21 DIODE_SCHOT 22
D22 DIODE_SCHOT 33
D23 DIODE_SCHOT 35
D24 DIODE_SCHOT 19
D25 DIODE 34
D26 DIODE_DUAL_6P 29
D27 DIODE_SCHOT 32
D28 DIODE_DUAL_6P 29
D29 DIODE_SCHOT 29
D30 DIODE_SCHOT 31
D33 DIODE_SCHOT 35
D34 DIODE_SCHOT 33
DP1 DPAK3P 19
DP2 DPAK3P 34
DP3 DPAK3P 35
DP4 DPAK3P 31
DP5 DPAK3P 29
DP6 DPAK3P 19
DP7 DPAK3P 21
F1 FUSE 22
F2 FUSE 29
F3 FUSE 31
F4 FUSE 31
F5 FUSE 29
FL1 FILTER_LC 22
FL2 FILTER_LC 22
FL3 FILTER_LC 22
G1 OSC 28
G2 OSC 18
J1 CON_F1ST_S2MT_SM 14
J2 CON_3RTSM_125 25
J3 CON_F14RT_S2MT_SM 24
J4 CON_3RTSM_125 25
J5 CON_12 34
J6 CON_F30RT_S2MT_SM 22
J7 CON_4RT_WRIB 22
J8 CON_F16ST_D_SMA 25
J9 CON_M80ST_D4MT_SM 17
J10 CON_M50SM_SMM 24
J11 CON_F14RT_S2MT_SM 32
J12 CON_F30ST_D_SM 25
J13 CON_M50SM_SMM 24
J14 CON_F30RT_T6MT_TH1 22
J15 CON_F5RT_MINIDIN_TH 22
J16 CON_10STSM_5087 25
J17 CON_RJ45_SHORT_4MT_TH 27
J18 CON_M8RT_S_SM 31
J19 CON_F200RT_DDRDIMM_SM1 11
J20 CON_F80ST_D4MT_SM 24
J22 CON_F200RT_DDRDIMM_SM2 11
J23 CON_F6RT_S4MT_TH1 29
J24 CON_F40RT_S2MT_SM 23
J25 CON_M8RT_S_SM 31
J26 CON_F9RT_1394B_S6MT_SMA 29
L1 IND 14
L2 IND 18
L3 IND 18
L4 IND 18
L5 IND 27
L6 IND 22
L7 IND 28
L8 IND 31
L9 IND 31
L10 IND 31
L11 IND 23
L12 IND 31
L13 IND 20
L14 IND 20
L15 IND 20
L16 IND 21
L18 IND 14
L21 FILTER_4P 22
L22 IND 14
L23 IND 22
L24 IND 19
L25 IND 22
L26 IND 22
L27 IND 22
L28 IND 22
L29 IND 22
L30 IND_3P 19
L31 IND 22
L32 IND 22
L33 IND 22
L34 IND 27
L35 IND 35
L36 IND_3P 34
L37 IND_3P 32
L38 IND 33
L39 IND 29
L40 IND 29
L41 IND 33
L42 IND 31
L43 FILTER_4P 29
L44 FILTER_4P 29
L45 IND 35
L46 IND 23
L47 IND 23
L48 IND 23
L49 IND 23
L50 IND 29
L51 IND 28
L52 IND 23
L53 IND 31
L54 IND 26
L55 IND 21
L56 IND 21
L57 IND 21
L58 IND 21
L59 IND 21
L60 IND 21
L61 IND 21
L62 IND 21
L63 IND 21
L64 IND 21
L65 IND 21
L66 IND 21
L67 IND 21
L68 IND 21
L69 IND 21
L70 FILTER_4P 29
L71 FILTER_4P 29
L72 FILTER_4P 22
L73 FILTER_4P 22
L74 FILTER_4P 22
L75 IND 35
L76 IND 25
L77 IND 25
L78 IND 25
L79 IND 25
L80 IND 25
L81 IND 25
L82 IND 25
P01 PHOTODIODE_2P 23
Q1 TRA_2N7002DW 7
Q2 TRA_2N7002DW 7
Q3 TRA_2N7002 7
Q4 TRA_2N3904 7
Q5 TRA_2N3904 19
Q6 TRA_2N3904 19
Q7 TRA_FDG6324L 22
Q8 TRA_2N7002 22
Q9 TRA_2N7002DW 33
Q10 TRA_2N7002DW 31
Q11 TRA_SI3443DV 22
Q12 TRA_2N3904 34
Q13 TRA_SI4435DY 31
Q14 TRA_FDG6324L 32
Q15 TRA_2N7002DW 27
Q16 TRA_SI4435DY 31
Q17 TRA_2N3904 34
Q18 TRA_2N7002 35
Q20 TRA_2N7002DW 31
Q21 TRA_2N7002DW 31
Q22 TRA_2N7002 30
Q23 TRA_2N7002DW 33
Q24 TRA_SI4435DY 31
Q25 TRA_2N7002DW 29 33
Q26 TRA_2N7002DW 25
Q27 TRA_2N7002DW 31
Q28 TRA_SI3443DV 33
Q29 TRA_2N7002DW 31
Q30 TRA_2N7002DW 31
Q31 TRA_2N7002DW 25
Q32 TRA_SI3443DV 33
Q33 TRA_2N3906 23
Q35 TRA_2N7002DW 22 23
Q36 TRA_SI3446DV 25
Q37 TRA_SI3446DV 25
Q38 TRA_2N7002DW 22
Q39 TRA_2N3904 25
Q40 TRA_TP0610 22
Q41 TRA_2N7002DW 22
Q42 TRA_2N3904 22
Q43 TRA_SI3443DV 33
Q44 TRA_2N3904 22
Q45 TRA_TP0610 22
Q46 TRA_SI3446DV 35
Q47 TRA_2N3904 25
Q48 TRA_SI7892DP 19
Q49 TRA_SI7860DP 34
Q50 TRA_SI7860DP 34
Q51 TRA_SI7860DP 19
Q52 TRA_SI4888DY 33
Q53 TRA_IRF7832 34
Q54 TRA_IRF7832 34
Q55 TRA_IRF7832 34
Q56 TRA_IRF7811W 35
Q57 TRA_IRF7805 35
Q58 TRA_2N7002DW 29
Q59 TRA_IRF7805 32
Q60 TRA_IRF7811W 32
Q61 TRA_SI4888DY 33
Q62 TRA_2N3904 25
Q63 TRA_IRF7805 31
Q64 TRA_IRF7811W 31
Q65 TRA_2N7002DW 31
Q66 TRA_2N3904 25
Q67 TRA_NDS9407 29
Q68 TRA_IRF7811W 35
Q69 TRA_IRF7805 35
Q71 TRA_SI4888DY 33
Q72 TRA_SI4888DY 33
Q73 TRA_2N3906 23
Q74 TRA_2N3906 23
Q75 TRA_2N7002DW 23
Q76 TRA_SUD45P03 31
Q77 TRA_SI3446DV 19
Q78 TRA_2N7002DW 25
Q79 TRA_2N7002DW 33
Q80 TRA_2N7002DW 19
Q81 TRA_2N7002DW 33
Q82 TRA_2N7002DW 35
Q83 TRA_2N7002DW 35
Q84 TRA_SI6467BDQ 35
Q85 TRA_SI6467BDQ 35
Q86 TRA_2N7002DW 24
Q87 TRA_2N7002DW 25
R1 RES 22
R2 RES 7
R3 RES 7
R4 RES 7
R5 RES 7
R6 RES 23
R7 RES 14
R8 RES 24
R9 RES 7
R10 RES 7
R11 RES 7
R12 RES 7
R13 RES 7
R14 RES 7
R15 RES 7
R16 RES 7
R17 RES 7
R18 RES 7
R19 RES 7
R20 RES 7
R21 RES 7
R22 RES 7
R23 RES 7
R24 RES 7
R25 RES 7
R26 RES 7
R27 RES 7
R28 RES 14
R29 RES 14
R30 RES 24
R31 RES 24
R32 RES 24
R33 RES 7
R34 RES 13
R35 RES 24
R36 RES 24
R37 RES 18
R38 RES 18
R39 RES 23
R40 RES 23
R41 RES 20
R42 RES 25
R43 RES 18
R44 RES 18
R45 RES 18
R46 RES 18
R47 RES 7
R48 RES 7
R49 RES 14
R50 RES 14
R51 RES 13
R52 RES 13
R53 RES 18
R54 RES 18
R55 RES 18
R56 RES 26
R57 RES 5
R58 RES 5
R59 RES 5
R60 RES 5
R61 RES 5
R62 RES 23
R63 RES 24
R64 RES 24
R65 RES 5
R66 RES 20
R67 RES 14
R68 RES 24
R69 RES 24
R70 RES 18
R71 RES 24
R72 RES 5
R73 RES 5
R74 RES 24
R75 RES 24
R76 RES 24
R77 RES 12
R78 RES 26
R79 RES 5
R80 RES 14
R81 RES 24
R82 RES 12
R83 RES 26
R84 RES 26
R85 RES 5
R86 RES 5
R87 RES 5
R88 RES 20
R89 RES 14
R90 RES 14
R91 RES 14
R92 RES 13
R93 RES 24
R94 RES 24
R95 RES 24
R96 RES 26
R97 RES 5
R98 RES 5
R99 RES 20
R100 RES 14
R101 RES 24
R102 RES 14
R103 RES 12
R104 RES 18
R105 RES 18
R106 RES 5
R107 RES 5
R108 RES 5
R109 RES 5
R110 RES 20
R111 RES 14
R112 RES 12
R113 RES 14
R114 RES 14
R115 RES 14
R116 RES 24
R117 RES 13
R118 RES 18
R119 RES 18
R120 RES 5
R121 RES 8
R122 RES 8
R123 RES 8
R124 RES 13
R125 RES 14
R126 RES 18
R127 RES 18
R128 RES 5
R129 RES 5
R130 RES 5
R131 RES 8
R132 RES 8
R133 RES 8
R134 RES 8
R135 RES 8
R136 RES 8
R137 RES 8
R138 RES 18
R139 RES 5
R140 RES 8
R141 RES 8
R142 RES 8
R143 RES 8
R144 RES 8
R145 RES 13
R146 RES 12
R147 RES 12
R148 RES 5
R149 RES 7
R150 RES 8
R151 RES 8
R152 RES 8
R153 RES 8
R154 RES 13
R155 RES 14
R156 RES 14
R157 RES 12
R158 RES 18
R159 RES 18
R160 RES 5
R161 RES 8
R162 RES 8
R163 RES 8
R164 RES 8
R165 RES 8
R166 RES 8
R167 RES 8
R168 RES 14
R169 RES 12
R170 RES 12
R171 RES 12
R172 RES 18
R173 RES 18
R174 RES 8
R175 RES 8
R176 RES 8
R177 RES 8
R178 RES 8
R179 RES 8
R180 RES 12
R181 RES 18
R182 RES 8
R183 RES 8
R184 RES 8
R185 RES 12
R186 RES 12
R187 RES 12
R188 RES 18
R189 RES 18
R190 RES 35
R191 RES 9
R192 RES 12
R193 RES 12
R194 RES 12
R195 RES 18
R196 RES 8
R197 RES 8
R198 RES 9
R199 RES 9
R200 RES 18
R201 RES 18
R202 RES 20
R203 RES 19
R204 RES 20
R205 RES 20
R206 RES 5
R207 RES 8
R208 RES 8
R209 RES 12
R210 RES 20
R211 RES 20
R212 RES 20
R213 RES 22
R214 RES 20
R215 RES 8
R216 RES 12
R217 RES 12
R218 RES 20
R219 RES 20
R220 RES 20
R221 RES 19
R222 RES 20
R223 RES 19
R224 RES 20
R225 RES 8
R226 RES 8
R227 RES 8
R228 RES 19
R229 RES 19
R230 RES 12
R231 RES 20
R232 RES 20
R233 RES 20
R234 RES 19
R235 RES 20
R236 RES 19
R237 RES 20
R238 RES 9
R239 RES 10
R240 RES 19
R241 RES 5
R242 RES 10
R243 RES 10
R244 RES 14
R245 RES 19
R246 RES 19
R247 RES 19
R248 RES 19
R249 RES 19
R250 RES 9
R251 RES 21
R252 RES 10
R253 RES 19
R254 RES 19
R255 RES 21
R256 RES 19
R257 RES 19
R258 RES 19
R259 RES 19
R260 RES 19
R261 RES 19
R262 RES 19
R263 RES 19
R264 RES 14
R265 RES 19
R266 RES 19
R267 RES 34
R268 RES 21
R269 RES 19
R270 RES 19
R271 RES 19
R272 RES 19
R273 RES 19
R274 RES 19
R277 RES 14
R278 RES 14
R279 RES 21
R281 RES 14
R284 RES 21
R286 RES 26
R287 RES 15
R288 RES 34
R289 RES 34
R290 RES 34
R291 RES 14
R292 RES 34
R293 RES 25
R294 RES 19
R295 RES 25
R296 RES 33
R297 RES 34
R298 RES 33
R299 RES 21
R300 RES 33
R301 RES 34
R302 RES 34
R303 RES 34
R304 RES 34
R305 RES 34
R306 RES 19
R307 RES 19
R308 RES 33
R309 RES 33
R310 RES 33
R311 RES 19
R312 RES 34
R313 RES 34
R314 RES 34
R315 RES 34
R316 RES 19
R317 RES 22
R318 RES 34
R319 RES 27
R320 RES 22
R321 RES 34
R322 RES 34
R323 RES 34
R324 RES 34
R325 RES 34
R326 RES 34
R327 RES 34
R328 RES 34
R329 RES 34
R330 RES 34
R331 RES 34
R332 RES 19
R333 RES 27
R334 RES 27
R335 RES 27
R336 RES 34
R337 RES 34
R338 RES 9
R339 RES 19
R340 RES 19
R341 RES 19
R342 RES 22
R343 RES 27
R344 RES 27
R345 RES 27
R346 RES 27
R347 RES 27
R348 RES 17
R349 RES 34
R350 RES 33
R351 RES 19
R352 RES 19
R353 RES 27
R354 RES 27
R355 RES 27
R356 RES 34
R357 RES 9
R358 RES 31
R359 RES 32
R360 RES 32
R361 RES 27
R362 RES 27
R363 RES 31
R364 RES 31
R365 RES 31
R366 RES 34
R367 RES 33
R368 RES 33
R369 RES 33
R370 RES 27

R371	RES	27
R372	RES	27
R373	RES	17
R374	RES	31
R375	RES	31
R376	RES	34
R377	RES	33
R378	RES	33
R379	RES	32
R380	RES	27
R381	RES	27
R382	RES	27
R383	RES	31
R384	RES	34
R385	RES	34
R386	RES	9
R387	RES	9
R388	RES	19
R389	RES	19
R390	RES	19
R391	RES	22
R392	RES	32
R393	RES	27
R394	RES	31
R395	RES	31
R396	RES	31
R397	RES	34
R398	RES	34
R399	RES	15
R400	RES	22
R401	RES	32
R402	RES	32
R403	RES	27
R404	RES	27
R405	RES	25
R406	RES	27
R407	RES	34
R408	RES	34
R409	RES	9
R410	RES	19
R411	RES	24
R412	RES	32
R413	RES	27
R414	RES	31
R415	RES	34
R416	RES	19
R417	RES	35
R418	RES	35
R419	RES	35
R420	RES	35
R421	RES	35
R422	RES	35
R423	RES	35
R424	RES	35
R425	RES	35
R426	RES	32
R427	RES	27
R428	RES	27
R429	RES	34
R430	RES	19
R431	RES	33
R432	RES	32
R433	RES	32
R434	RES	34
R435	RES	27
R436	RES	28
R437	RES	28
R438	RES	27
R439	RES	9
R440	RES	11
R441	RES	24
R442	RES	24
R443	RES	32
R444	RES	28
R445	RES	28
R446	RES	28
R447	RES	28
R448	RES	34
R449	RES	11
R450	RES	35
R451	RES	19
R452	RES	24
R453	RES	29
R454	RES	31
R455	RES	35
R456	RES	33
R457	RES	33
R458	RES	24
R459	RES	28
R460	RES	31
R461	RES	35
R462	RES	33
R463	RES	33
R464	RES	28
R465	RES	27
R466	RES	31
R467	RES	33
R468	RES	32
R469	RES	28
R470	RES	28
R471	RES	28
R472	RES	29
R473	RES	31
R474	RES	31
R475	RES	30
R476	RES	30
R477	RES	33
R478	RES	28
R479	RES	35
R480	RES	35
R481	RES	33
R482	RES	33
R483	RES	32
R484	RES	28
R485	RES	28
R486	RES	28
R487	RES	31
R488	RES	31
R489	RES	31
R490	RES	31
R491	RES	30
R492	RES	30
R493	RES	35
R494	RES	28
R495	RES	28
R496	RES	28
R497	RES	31
R498	RES	31
R499	RES	31
R500	RES	9
R501	RES	30
R502	RES	30
R503	RES	30
R504	RES	30
R505	RES	30
R506	RES	33
R507	RES	33
R508	RES	32
R509	RES	28
R510	RES	28
R511	RES	31
R512	RES	31
R513	RES	30
R514	RES	33
R515	RES	33
R516	RES	28
R517	RES	30
R518	RES	30
R519	RES	33
R520	RES	33
R521	RES	32
R522	RES	28
R523	RES	33
R524	RES	28
R525	RES	28
R526	RES	31
R527	RES	25
R528	RES	33
R529	RES	33
R530	RES	26
R531	RES	26
R532	RES	23
R533	RES	23
R534	RES	23
R535	RES	30
R536	RES	30
R537	RES	25
R538	RES	33

R539	RES	33
R540	RES	26
R541	RES	32
R542	RES	31
R543	RES	31
R544	RES	30
R545	RES	26
R546	RES	28
R547	RES	28
R548	RES	31
R549	RES	31
R550	RES	23
R551	RES	26
R552	RES	23
R553	RES	25
R554	RES	26
R555	RES	28
R556	RES	28
R557	RES	28
R558	RES	31
R559	RES	31
R560	RES	31
R561	RES	31
R562	RES	30
R563	RES	28
R564	RES	28
R565	RES	31
R566	RES	31
R567	RES	31
R568	RES	23
R569	RES	30
R570	RES	31
R571	RES	31
R572	RES	30
R573	RES	30
R574	RES	28
R575	RES	28
R576	RES	28
R577	RES	28
R578	RES	31
R579	RES	31
R580	RES	31
R581	RES	23
R582	RES	23
R583	RES	30
R584	RES	30
R585	RES	30
R586	RES	26
R587	RES	23
R588	RES	31
R589	RES	33
R590	RES	26
R591	RES	26
R592	RES	30
R593	RES	30
R594	RES	30
R595	RES	30
R596	RES	30
R597	RES	30
R598	RES	23
R599	RES	31
R600	RES	26
R601	RES	24
R602	RES	24
R603	RES	24
R605	RES	23
R606	RES	23
R607	RES	35
R609	RES	14
R610	RES	35
R611	RES	35
R612	RES	24
R613	RES	24
R614	RES	14
R615	RES	23
R616	RES	35
R617	RES	23
R618	RES	23
R619	RES	23
R621	RES	13
R622	RES	14
R623	RES	25
R624	RES	13
R625	RES	14
R626	RES	13
R627	RES	35
R629	RES	13
R630	RES	13
R631	RES	14
R632	RES	14
R634	RES	14
R636	RES	14
R638	RES	14
R639	RES	8
R640	RES	8
R641	RES	8
R642	RES	8
R643	RES	8
R644	RES	8
R645	RES	8
R646	RES	8
R647	RES	8
R649	RES	22
R650	RES	22
R651	RES	8
R652	RES	8
R653	RES	8
R654	RES	8
R655	RES	22
R656	RES	14
R657	RES	8
R658	RES	8
R659	RES	8
R660	RES	8
R661	RES	22
R662	RES	22
R663	RES	22
R664	RES	8
R665	RES	8
R666	RES	8
R667	RES	8
R668	RES	8
R669	RES	8
R670	RES	22
R671	RES	22
R672	RES	35
R673	RES	8
R674	RES	8
R675	RES	8
R676	RES	8
R677	RES	8
R678	RES	8
R679	RES	25
R680	RES	22
R681	RES	22
R682	RES	14
R683	RES	8
R684	RES	8
R685	RES	8
R686	RES	22
R688	RES	22
R689	RES	25
R690	RES	22
R691	RES	22
R692	RES	25
R693	RES	5
R694	RES	22
R695	RES	25
R696	RES	22
R697	RES	33
R698	RES	14
R699	RES	14
R700	RES	22
R701	RES	14
R702	RES	5
R703	RES	22
R704	RES	22
R705	RES	22
R706	RES	22
R707	RES	14
R708	RES	14
R709	RES	35
R710	RES	25
R711	RES	19
R712	RES	35
R713	RES	25
R714	RES	22
R715	RES	35

R716	RES	25
R717	RES	25
R718	RES	22
R719	RES	25
R720	RES	14
R721	RES	21
R722	RES	21
R723	RES	25
R724	RES	22
R725	RES	25
R726	RES	25
R727	RES	35
R728	RES	21
R729	RES	21
R730	RES	24
R731	RES	33
R732	RES	34
R733	RES	27
R734	RES	31
R735	RES	27
R736	RES	29
R737	RES	29
R738	RES	31
R739	RES	31
R740	RES	28
R741	RES	29
R742	RES	31
R743	RES	29
R744	RES	31
R745	RES	24
R746	RES	31
R747	RES	31
R748	RES	31
R749	RES	31
R750	RES	17
R751	RES	29
R752	RES	29
R753	RES	17
R754	RES	31
R755	RES	31
R756	RES	17
R757	RES	17
R758	RES	26
R759	RES	28
R760	RES	28
R761	RES	28
R762	RES	17
R763	RES	31
R764	RES	17
R765	RES	30
R766	RES	17
R767	RES	17
R768	RES	30
R769	RES	30
R770	RES	23
R771	RES	23
R772	RES	23
R773	RES	23
R774	RES	31
R775	RES	28
R776	RES	23
R777	RES	23
R778	RES	30
R779	RES	29
R781	RES	28
R782	RES	30
R783	RES	26
R784	RES	26
R785	RES	30
R786	RES	30
R787	RES	30
R788	RES	30
R789	RES	26
R790	RES	26
R791	RES	26
R792	RES	26
R793	RES	26
R794	RES	26
R795	RES	26
R796	RES	26
R797	RES	35
R798	RES	35
R799	RES	35
R800	RES	35
R801	RES	35
R802	RES	35
R803	RES	35
R804	RES	19
R805	RES	34
R806	RES	34
R807	RES	34
R808	RES	34
R809	RES	34
R810	RES	35
R811	RES	25
R812	RES	25
R813	RES	25
R814	RES	25
RP1	RPAK4P	14
RP2	RPAK4P	24
RP3	RPAK4P	24
RP4	RPAK4P	24
RP5	RPAK4P	24
RP6	RPAK4P	14
RP7	RPAK4P	14
RP8	RPAK4P	14
RP9	RPAK4P	24
RP10	RPAK4P	24
RP11	RPAK4P	24
RP12	RPAK4P	13
RP13	RPAK4P	24
RP14	RPAK4P	13
RP15	RPAK4P	13
RP16	RPAK4P	13
RP17	RPAK4P	12
RP18	RPAK4P	12
RP19	RPAK4P	12
RP20	RPAK4P	12
RP21	RPAK4P	8
RP22	RPAK4P	12
RP23	RPAK4P	8
RP24	RPAK4P	8 14
RP25	RPAK4P	9
RP26	RPAK4P	9
RP27	RPAK2P	20
RP28	RPAK2P	20
RP29	RPAK4P	14
RP30	RPAK4P	9
RP31	RPAK4P	9
RP32	RPAK2P	20
RP33	RPAK4P	9
RP34	RPAK4P	9
RP35	RPAK4P	9
RP36	RPAK4P	9
RP37	RPAK4P	28
RP38	RPAK4P	28
RP39	RPAK10P2C	17
RP40	RPAK4P	30
RP41	RPAK4P	30
RP42	RPAK10P2C	23
RP43	RPAK10P2C	23
RP44	RPAK4P	25
RP45	RPAK4P	26
RP46	RPAK4P	14
RP47	RPAK4P	14
RP48	RPAK4P	14
RP49	RPAK4P	24
RP50	RPAK4P	24
RP51	RPAK4P	14
RP52	RPAK4P	23 26
RP53	RPAK4P	23
RP54	RPAK4P	26
RP55	RPAK4P	26
RP56	RPAK4P	14
RP57	RPAK2P	20
RP58	RPAK2P	20
RP59	RPAK2P	20
RP60	RPAK2P	20
RP61	RPAK2P	20
SH1	SHLD_3P_EMI	4
SP1	SPKR_CLIP_P84	4
SP2	SPKR_CLIP_P84	4
SP3	SPKR_CLIP_P84	4
SP4	SPKR_CLIP_P84	4
SP5	SPKR_CLIP_P84	4
SP6	SPKR_CLIP_P84	4
T1	XFR_ENET_1000BT	27
U1	SN74AUC1G04	7

U2	SN74AUC1G08	23
U3	ADT7460	25
U4	SN74AUC1G00	23
U5	SIL1162	20
U7	VREG_LT1962	14
U9	CBTV4020	10
U10	CBTV4020	10
U11	PI3B3257	34
U12	CBTV4020	10
U13	CBTV4020	10
U14	LTC3405	27
U15	COMPARATOR_LMC7211	31
U16	LTC1778	19
U17	FEPR_1MX8	9
U18	LTC1625	32
U19	PWR_CNTRL_TPS2211	17
U20	MAX1717	34
U21	COMPARATOR_LMC7211	32
U22	MAX1715	35
U23	AMP_MAX4172	31
U24	7432	22 30
U25	VREG_LP2951	32
U26	PCI1510GGU	17
U27	COMPARATOR_LMC7211	30
U28	LTC3707	33
U29	TSB81BA3A	28
U30	VREG_LP2951	32
U31	MAX1772	31
U32	EEPROM_16KX8_M2412BB	23
U33	M16C62	30
U34	VREG_LM2594	28
U35	MAX1915	23
U36	LTC1761	28
U37	VREG_LT1962	28
U38	COMPARATOR_LMC7211	31
U39	UPD720101_FBGA	26
U40	OPAMP_MAX4236EUT	23
U42	CLK_GEN_CY28512	14
U43	APOLLO_MPC7445_360	5 6
U44	RAGE_MBLTY_M10_CSP64_667	18 19 21
U45	INTREPID	8 9 12 13 14 15
U46	COMPARATOR_LMC7211	22
U47	CLK_GEN_CY25811	18
U49	TRANSCEIVER_88E1111	27
U50	OPAMP_LMC7111	31
U51	MAX6804	30
U52	FEPR_256KX8_ST72264_BGA	23
U54	VREG_MM1571J	21
U55	VREG_MM1571J	21
U56	741G32	22
U57	741G32	22
U58	LTC3412	35
XW1	SHORT	35
XW2	SHORT	19
XW3	SHORT	34
XW4	SHORT	32
XW5	SHORT	34
XW6	SHORT	35
XW7	SHORT	34
XW8	SHORT	33
XW9	SHORT	25
XW11	JUMPER	35
XW12	SHORT	22
XW13	SHORT	22
XW15	SHORT	34
XW19	SHORT	31
XW20	SHORT	19
XW21	SHORT	19
XW22	SHORT	19
XW23	SHORT	19
XW24	SHORT	19
XW27	SHORT	21
XW28	SHORT	21
XW29	SHORT	21
XW30	SHORT	21
XW31	SHORT	5
Y1	CRYSTAL	14
Y3	CRYSTAL	27
Y4	CRYSTAL	23
Y5	CRYSTAL	26
Y6	CRYSTAL	30
Y7	CRYSTAL_4PIN	30
ZT1	HOLE_VIA	4
ZT2	MTGHOLE	4
ZT3	HOLE_VIA	4
ZT4	MTGHOLE	4
ZT5	MTGHOLE	4
ZT6	MTGHOLE	4
ZT7	HOLE_VIA	4
ZT8	HOLE_VIA	4
ZT9	HOLE_VIA	4
ZT10	MTGHOLE	4
ZT11	MTGHOLE	4
ZT12	HOLE_VIA	4
ZT13	HOLE_VIA	4
ZT14	HOLE_VIA	4
ZT15	HOLE_VIA	4
ZT16	MTGHOLE	4
ZT17	HOLE_VIA	4
ZT18	HOLE_VIA	4
ZT19	HOLE_VIA	4
ZT20	HOLE_VIA	4
ZT21	HOLE_VIA	4
ZT22	HOLE_VIA	4
ZT23	HOLE_VIA	4
ZT24	HOLE_VIA	4
ZT25	HOLE_VIA	4
ZT26	HOLE_VIA	4
ZT27	HOLE_VIA	4
ZT28	HOLE_VIA	4
ZT29	HOLE_VIA	4
ZT30	HOLE_VIA	4
ZT31	HOLE_VIA	4
ZT32	HOLE_VIA	4
ZT33	HOLE_VIA	4
ZT34	HOLE_VIA	4
ZT35	HOLE_VIA	4
ZT36	HOLE_VIA	4
ZT37	HOLE_VIA	4
ZT38	HOLE_VIA	4
ZT39	HOLE_VIA	4
ZT40	HOLE_VIA	4
ZT41	HOLE_VIA	4
ZT42	HOLE_VIA	4
ZT43	HOLE_VIA	4
ZT44	HOLE_VIA	4
ZT45	HOLE_VIA	4
ZT46	HOLE_VIA	4
ZT47	HOLE_VIA	4
ZT48	HOLE_VIA	4
ZT49	HOLE_VIA	4
ZT50	HOLE_VIA	4
ZT51	HOLE_VIA	4
ZT52	HOLE_VIA	4
ZT53	HOLE_VIA	4
ZT54	HOLE_VIA	4
ZT55	HOLE_VIA	4
ZT56	HOLE_VIA	4
ZT57	HOLE_VIA	4
ZT58	HOLE_VIA	4
ZT59	HOLE_VIA	4
ZT60	HOLE_VIA	4
ZT61	HOLE_VIA	4
ZT62	HOLE_VIA	4
ZT63	HOLE_VIA	4
ZT64	HOLE_VIA	4
ZT65	HOLE_VIA	4
ZT66	HOLE_VIA	4
ZT67	HOLE_VIA	4
ZT68	HOLE_VIA	4
ZT69	HOLE_VIA	4
ZT70	HOLE_VIA	4
ZT71	HOLE_VIA	4
ZT72	HOLE_VIA	4
ZT73	HOLE_VIA	4
ZT74	HOLE_VIA	4
ZT75	HOLE_VIA	4
ZT76	HOLE_VIA	4
ZT77	HOLE_VIA	4
ZT78	HOLE_VIA	4
ZT79	HOLE_VIA	4
ZT80	HOLE_VIA	4
ZT81	HOLE_VIA	4
ZT82	HOLE_VIA	4
ZT83	MTGHOLE	4