Compal Confidential

KBL-U/R MB Schematic Document

Pantheon

LA-G741P

Rev: 1.0

2018.07.18

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: Cover Sheet			
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 1 of 54		

SHEET NO.	SHEET NAME	SHEET NO.	SHEET NAME	SHEET NO.	SHEET NAME
1	Cover Page	26	HP AMP DA7219-02VBA	51	CPU : CPU POWER (2/2)
2	TABLE OF CONTENTS	27	SPEAKER AMP MAX98357AEWL+T	52	PWR ROP
3	Block Diagram	28	eDP/Camera/Pen /Touch	53	Change list
4	Notes List	29	M.2 Conn.	54	Change list
5	Power Map	30	M.2 WLAN		
6	Power Sequence	31	DB1 USB TypeC/SD/BTN		
7	SKU Plan	32	USB TypeC ANX7447		
8	KBL-U(1/11)DDR CHA CHB	33	USB3.0 Type-C Conn.		
9	KBL-U(2/11)CLK/PCIE/USB	34	USB Type-A / LED		
10	KBL-U(3/11)DDI/EDP/CSI/EMMC	35	HIBERNATE WAKE SOURCE		
11	KBL-U(4/11)HDA/I2S/DMIC/SD	36	Trapckpad/Camera/Thermal		
12	KBL-U(5/11)SPI/SMB/I2C/UART	37	KB/KB Backlight/FAN/LID		
13	KBL-U(6/11)POWER MANAGEMENT	38	LID Sensor		
14	KBL-U(7/11)Power	39	INAs		
15	KBL-U(8/11)Power	40	LOAD SWITCHES		
16	KBL-U(9/11)Power,SVID	41	PCB/Screw/CLIP		
17	KBL-U(10/11)GND	42	PWR AC/DC CONN/OTP		
18	KBL-U(11/11)RSVD	43	PWR CHARGER(ISL9238)		
19	DDR4 CHA Memory Down I	44	PWR PMIC-TPS650830(1of2)		
20	DDR4 CHB Memory Down II	45	PWR PMIC-TPS650830(2of2)		
21	SPI EC ROM	46	PWR NVMe		
22	SERVO	47	PWR IMVP8(1of3)		
23	H1 SECURE	48	PWR IMVP8(2of3)		
24	EC NPCX586GA0BX	49	PWR IMVP8(3of3)		
25	EMMC/NVME	50	CPU : CPU POWER (1/2)		

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: TABLE OF CONTENTS			
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 2 of 54		

File Name : LA-G741PR01



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title	Block Diagram		
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 3 of 54		

Intel KBL-U Platform		KBL-U Chromebook (EQA04)		
HSIO Port	Capable	Port Allocation	PCIE CLK & CLKREQ	Note
1	USB3 #1 / OTG	USB3 Type-C port 0		
2	USB3 #2 / SSIC	USB3 Type-C port 1		
3	USB3 #3	USB3 Type-A port 0		
4	USB3 #4	USB3 to SD card reader		
5	PCIE #1 / USB3 #5			
6	PCIE #2 / USB3 #6			
7	PCIE #3 / LAN	NA		
8	PCIE #4 / LAN	WLAN + BT Intel 7265	PCIE CLK 1	M.2 key-E
9	PCIE #5 / LAN	SSD (PCIe x4/SATA)	PCIE CLK 3	M.2 key-E
10	PCIE #6			
11	SATA #0 / PCIE #7			
12	SATA #1 / PCIE #8			
13	PCIE #9 / LAN	On board NVMe	PCIE CLK 2	
14	PCIE #10 / LAN	On board NVMe	PCIE CLK 2	
15	PCIE #11			
16	PCIE #12			

Intel KBL-U Platform		KBL-U Chromebook (EQA04)	
USB Port	Capable	Port Allocation	Note
1	USB2 #1	USB3 Type-C port 0	
2	USB2 #2	USB3 Type-C port 1	
3	USB2 #3	USB3 Type-A port 0	
4	USB2 #4	USB3 to SD card	
5	USB2 #5	BLUETOOTH ON M.2	
6	USB2 #6	CAMERA 1	Rear
7	USB2 #7	CAMERA 2	Front
8	USB2 #8		
9	USB2 #9	M.2 key-E	
10	USB2 #10	NA	

Intel KBL-U Platform		KBL-U Chromebook (EQA04)	
DDI Port	Capable	Port Allocation	Note
1	DDI #1	Type-C port 1	
2	DDI #2	Type-C port 0	

SOC			
I2C Port	Voltage level	Device	Address(7 bit)
I2C_0	3.3V	Touch Screen	
I2C_1	3.3V	Trackpad	0011001
I2C_2	3.3V	Active pen	
I2C_3	1.8V	Headphone codec	0011010
I2C_4	3.3V	H1(Reserve)	

SOC	
GPIO group	Votagle level
A	1.8V
B	3.3V
C	3.3V
D	1.8V
E	3.3V
F	1.8V
G	3.3V

EC			
I2C Port	Power Rail	Device	Address(7 bit)
I2C_0	3.3V	BC1.2 Detecter (USB-C Port 0)	0100101
	3.3V	TCPC & Redrive-MUX (USB-C Port 0)	0001011
I2C0_1	3.3V	BC1.2 Detecter (USB-C Port 1)	0100101
		TCPC & Redrive-MUX (USB-C Port 1)	0101011
I2C_1	3.3V	Battery	0010110
I2C_2	3.3V	KB Back Light (LM3509)	0110110
	3.3V	PMIC	0110000
	3.3V	Battery Charger	0001001
I2C_3	3.3V	6-axis Accel & Gyro	1101000
		ALS	1000100
		G-sensor	0011000
		Thermal Sensor(F75303M_MSOP10)	1001100

	Location	Address	Channel	Test_Power_Net_Name	Test_Point		Remark
INA3221AIRGVR	U35	1000000	CH1	PPVAR_SYS_PMIC_V1	PR127	0.01_0603_1%	PP1000_A Source
			CH2	PPVAR_BL_PWR	F1	0.005_2010_1%	Panel backlight
			CH3	PPVAR_VCC	PR87	0.01_1206_1%	PPVAR_VCC Source
	U36	1000001	CH1	PP5000_A	PR160	0.005_1206_1%	
			CH2	PPVAR_SYS_PMIC_V5	PR159	0.01_0805_1%	PP5000_A Source
			CH3	PP1800_A	PR137	0_0603_5%	
	U37	1000010	CH1	PP1200_VDDQ	PR152	0.005_1206_1%	
			CH2	PP0600_DDRVTT	PR929	0.01_0603_1%	
			CH3	SYS_PPVAR_SYS_PMIC_V4	PR151	0_0603_5%	PP1200_VDDQ Source
	U38	1000011	CH1	VINVR2_650830	PR1236	0_0402_5%	PP1800_A Source
			CH2	PP1200_VDDQ_DDRVTTIN	PR931	0_0402_5%	PP0600_DDRVTT Source
			CH3	PPVAR_SYS_PMIC_V3	PR140	0.01_0805_1%	PP3300_DSW Source
INA219AIDCNRG4	U39	1000100	CH1	+8.4VB_VCC2_VIN	PR92	0.01_1206_1%	PPVAR_VCC Source
	U40	1000110	CH1	PP3300_DSW	PR138	0.005_1206_1%	
	U41	1001000	CH1	PPVAR_GT_VIN	PR97	0.01_1206_1%	PPVAR_GT Source
	U42	1000111	CH1	PPVAR_PWR_IN_BB	PR1	0.02_1206_1%	Charger
	U44	1000101	CH1	PPVAR_SA_VIN	PR99	0.01_1206_1%	PPVAR_SA Source
	U97	1001001	CH1	PP3300_S	R4920	0.01_0603_1%	
	U98	1001010	CH1	PP3300_DX_WLAN	R381	0.01_0805_1%	
	U99	1001011	CH1	PP1000_A	PR128	0.005_1206_1%	
	U100	1001100	CH1	PP3300_DX_EDP	R378	0.01_0603_1%	
	U101	1001101	CH1	PP3300_DSW_EC	R271	0.01_0402_1%	

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.	
Title	Notes List
Size: Custom	Document Number: LA-G741P
Rev	1.0
Date: Thursday, July 19, 2018	Sheet 4 of 54

EQA04/Nami Schematic: LA-G222PR02

PVAR_SYS



www.teknisi-indonesia.com

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: Power Map

Size: D | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 5 of 54



Security Classification	Compal Secret Data		Compal Electronics, Inc.
Issued Date	2018/03/02	Deciphered Date 2018/03/02	Title: Power Sequence
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.			Size: B, Document Number: LA-G741P, Rev: 1.0
			Date: Thursday, July 19, 2018, Sheet 8 of 58

M/B Sku #	RAM/SoC	Load BOM option (Stuff)	Load BOM option (DNS)
1	SAMSUNG_4G/Celeron	Celeron@/SAMSUNG_4G@/SANDISK_32G@/XDP@/EMI@/U22@/RF@/MP@/INA@/ESPI@/ESD@/EMMC@/DSX_S0IX@/DSX@/SDP@	@/@RF@/@EMI@
2	SAMSUNG_4G/Pentium	Pentium@/SAMSUNG_4G@/SANDISK_32G@/XDP@/EMI@/U22@/RF@/MP@/INA@/ESPI@/ESD@/EMMC@/DSX_S0IX@/DSX@/SDP@	@/@RF@/@EMI@
3	SAMSUNG_8G/U-i3	U_i3@/SAMSUNG_8G@/SAMSUNG_32G@/XDP@/EMI@/U22@/RF@/MP@/INA@/ESPI@/ESD@/EMMC@/DSX_S0IX@/DSX@/SDP@	@/@RF@/@EMI@
4	SAMSUNG_8G/R-i5	R_i5@/SAMSUNG_8G@/SAMSUNG_32G@/XDP@/EMI@/U42@/RF@/MP@/INA@/ESPI@/ESD@/EMMC@/DSX_S0IX@/DSX@/SDP@	@/@RF@/@EMI@
5	HYNIX_16G/R-i7	R_i7@/HYNIX_16G@/SANDISK_64G@/XDP@/EMI@/U42@/RF@/MP@/INA@/ESPI@/ESD@/EMMC@/DSX_S0IX@/DSX@/DDP@	@/@RF@/@EMI@
6	SAMSUNG_8G/R-i3	R_i3@/SAMSUNG_8G@/SAMSUNG_32G@/XDP@/EMI@/U42@/RF@/MP@/INA@/ESPI@/ESD@/EMMC@/DSX_S0IX@/DSX@/SDP@	@/@RF@/@EMI@
7	SAMSUNG_8G/U-i5	U_i5@/SAMSUNG_8G@/LONGSYS_128G@/XDP@/EMI@/U22@/RF@/MP@/INA@/ESPI@/ESD@/DSX_S0IX@/DSX@/SDP@/NVME@	@/@RF@/@EMI@

[PCB]

ZZZ

PCB 2DB LA-G741P REV0 M/B 2

DAA000HP010

SOC

UC1 — KBL-R I3-8130U
S IC F.895770282227 SR3W0 Y0 2.2G FCBGA
KBLR_I3@
SA0000BWN30

UC1 — KBL-R I5-8250U
S IC F.895770282221 SR3LA Y0 1.6G FCBGA
KBLR_I5@
SA0000AWB50

eMMC

U14 SDINADF4-32G-1001K SANDISK_32G@ SA00009W370	U14 H26M62002JPR HYNIX_32G@ SA0000ADH10	U14 KLM8G2-JETD-B041 SAMSUNG_32G@ SA0000AT400	U14 SDINADF4-32G-1001 SANDISK_32G_2@ SA00009W350	U14 SDINBDA4-32-1001V SANDISK_32G_3@ SA0000C0B00	U14 SDINBDA4-32-1001V (R3) SANDISK_32G_A@ SA0000C0B10
U14 KLMCG2KCTA-B041 SAMSUNG_64G@ SA0000BR900	U14 SDINADF4-64G-1001K SANDISK_64G@ SA00009L170	U14 H26M74002HMR HYNIX_64G@ SA0000A7100	U14 SDINBDA4-64-1001V SANDISK_64G_1@ SA0000B4R00	U14 SDINADF4-64G-1001K (R3) SANDISK_64G_A@ SA00009L180	U14 SDINBDA4-64-1001V (R3) SANDISK_64G_B@ SA0000B4R10
U14 KLMDG4UCTA-B041 SAMSUNG_128G@ SA0000BR800	U14 DINADF4-128-1001K SANDISK_128G@ SA00009ML60	U14 H26TB7001CMR HYNIX_128G@ SA0000BPX00	U14 SDINBDA4-128-1001V SANDISK_128G_1@ SA0000BPN00	U14 DINADF4-128-1001K (R3) SANDISK_128G_A@ SA00009ML70	U14 H26TB7001CMR (R3) HYNIX_128G_B@ SA0000BPX10	U14 SDINBDA4-128-1001V (R3) SANDISK_128G_C@ SA0000BPN10

RAM ID

Vendor	Vendor P/N	Memory	Channel	[3]	[2]	[1]	[0]	BOM structure	Die Package	Stuff component
MICRON	MT40A256M16GE-083E:B	4G	2	0	0	0	1	MICORN_4G@	SDP	R89,R90,R91,R92
SAMSUNG	K4A8G165WB-BCRC	8G	2	0	0	1	0		SDP	R88,R90,R91,R93
				0	0	1	1			R88,R89,R90,R91
HYNIX	H5ANAG6NAMR-UHC	16G	2	0	1	0	0		DDP	R87,R90,R92,R93
				0	1	0	1			R90,R87,R92,R89
				0	1	1	0			R87,R88,R90,R93
SAMSUNG	K4A4G165WE-BCRC	4G	2	0	1	1	1		SDP	R87,R88,R89,R90
SAMSUNG	K4A8G165WC-BCTD	8G	2	1	0	0	0	SAMSUNG_8G@	SDP	R86,R91,R92,R93
HYNIX	H5AN4G6NAFR-UHC	4G	2	1	0	0	1	HYNIX_4G_1@	SDP	R86,R91,R92,R89
				1	0	1	0			
				1	0	1	1			
SAMSUNG	K4AAG165WB-MCRC	16G	2	1	1	0	0		DDP	R86,R87,R92,R93
				1	1	0	1			
MICORN	MT40A512M16LY-075:E	8G	2	1	1	1	0	MICORN_8G@	SDP	R86,R87,R88,R93
HYNIX	H5AN8G6NCJR-VKC	8G	2	1	1	1	1	HYNIX_8G@	SDP	R86,R87,R88,R89

DDR

SAMSUNG_8G@	R86 10K_0201_1% SAMSUNG_8G@	R91 10K_0201_1% SAMSUNG_8G@
HYNIX_8G@	R86 10K_0201_1% HYNIX_8G@	R87 10K_0201_1% HYNIX_8G@
MICRON_8G@	R86 10K_0201_1% MICRON_8G@	R87 10K_0201_1% MICRON_8G@
MICRON_4G@	R89 10K_0201_1% MICRON_4G@	R90 10K_0201_1% MICRON_4G@
HYNIX_4G_1@	R86 10K_0201_1% HYNIX_4G_1@	R91 10K_0201_1% HYNIX_4G_1@

DDR	SDP	UD1 K4A8G165WC-BCTD SAMSUNG_8G@ SA0000B6F10	UD2 K4A8G165WC-BCTD SAMSUNG_8G@ SA0000B6F10	UD3 K4A8G165WC-BCTD SAMSUNG_8G@ SA0000B6F10
		UD4 K4A8G165WC-BCTD SAMSUNG_8G@ SA0000B6F10	UD5 K4A8G165WC-BCTD SAMSUNG_8G@ SA0000B6F10	UD6 K4A8G165WC-BCTD SAMSUNG_8G@ SA0000B6F10
		UD7 K4A8G165WC-BCTD SAMSUNG_8G@ SA0000B6F10	UD8 K4A8G165WC-BCTD SAMSUNG_8G@ SA0000B6F10	
	SDP	UD1 H5AN8G6NCJR-VKC HYNIX_8G@ SA00000BMN10	UD2 H5AN8G6NCJR-VKC HYNIX_8G@ SA00000BMN10	UD3 H5AN8G6NCJR-VKC HYNIX_8G@ SA00000BMN10
		UD4 H5AN8G6NCJR-VKC HYNIX_8G@ SA00000BMN10	UD5 H5AN8G6NCJR-VKC HYNIX_8G@ SA00000BMN10	UD6 H5AN8G6NCJR-VKC HYNIX_8G@ SA00000BMN10
		UD7 H5AN8G6NCJR-VKC HYNIX_8G@ SA00000BMN10	UD8 H5AN8G6NCJR-VKC HYNIX_8G@ SA00000BMN10	
	SDP	UD1 MT40A512M16LY-075:E MICRON_8G@ SA00000ARD30	UD2 MT40A512M16LY-075:E MICRON_8G@ SA00000ARD30	UD3 MT40A512M16LY-075:E MICRON_8G@ SA00000ARD30
		UD4 MT40A512M16LY-075:E MICRON_8G@ SA00000ARD30	UD5 MT40A512M16LY-075:E MICRON_8G@ SA00000ARD30	UD6 MT40A512M16LY-075:E MICRON_8G@ SA00000ARD30
		UD7 MT40A512M16LY-075:E MICRON_8G@ SA00000ARD30	UD8 MT40A512M16LY-075:E MICRON_8G@ SA00000ARD30	
	SDP	UD1 H5AN4G6NAFR-UHC HYNIX_4G_1@ SA00009U300	UD2 H5AN4G6NAFR-UHC HYNIX_4G_1@ SA00009U300	UD3 H5AN4G6NAFR-UHC HYNIX_4G_1@ SA00009U300
		UD4 H5AN4G6NAFR-UHC HYNIX_4G_1@ SA00009U300	UD5 H5AN4G6NAFR-UHC HYNIX_4G_1@ SA00009U300	UD6 H5AN4G6NAFR-UHC HYNIX_4G_1@ SA00009U300
		UD7 H5AN4G6NAFR-UHC HYNIX_4G_1@ SA00009U300	UD8 H5AN4G6NAFR-UHC HYNIX_4G_1@ SA00009U300	
	SDP	UD1 MT40A256M16GE-083E:B MICORN_4G@ SA00009NS00	UD2 MT40A256M16GE-083E:B MICORN_4G@ SA00009NS00	UD3 MT40A256M16GE-083E:B MICORN_4G@ SA00009NS00
		UD4 MT40A256M16GE-083E:B MICORN_4G@ SA00009NS00	UD5 MT40A256M16GE-083E:B MICORN_4G@ SA00009NS00	UD6 MT40A256M16GE-083E:B MICORN_4G@ SA00009NS00
		UD7 MT40A256M16GE-083E:B MICORN_4G@ SA00009NS00	UD8 MT40A256M16GE-083E:B MICORN_4G@ SA00009NS00	

Security Classification	Compal Secret Data		Compal Electronics, Inc.
Issued Date	2018/03/02	Deciphered Date 2019/03/02	Title: SKU PLAN
			Size: D — Document Number: LA-G741P — Rev: 1.0
			Date: Thursday, July 19, 2018 — Sheet 7 of 54

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title	KBL-U(1/11)DDI,MISC,XDP/EDP		
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 8 of 54		





teknisi-indonesia.com

Figure 4-16. KBL R DDR4 SODIMM V_{REF-CA} Overview







Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title	KBL-U(2/11)DDR4		
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 9 of 54		



I2C Bus	Functon	Bus Voltage	Module Voltage
I2C_0	Touch Screen	3.3V	3.3V
I2C_1	Track Pad	3.3V	3.3V
I2C_2	PEN	1.8V	1.8V
I2C_3	HP AMP	1.8V	1.8V
I2C_4	N/A	1.8V	N/A

PIN	FUNCTION	INTENT
GPP_B_23/SML1ALERTB#	IPD = EXI BOOT STALL BYPASS DISABLE PU = EXI BOOT STALL BYPASS ENABLED	DISABLE
GPP_B18/GSPI0_MOSI	IPD = DISABLE NO REBOOT MODE PU = ENABLE NO REBOOT MODE	DISABLE
GPP_C2/SMBALERT#	IPD = DISABLE TLS CONFIDENTIALITY PU = ENABLE TLS CONFIDENTIALITY	DISABLE
GPP_B22/GSPI1_MOSI	IPD = BOOT FROM SPI PU = BOOT FROM LPC	SPI
GPP_C5/SML0ALERT#	IPD = LPC IS SELECTED FOR EC PU = ESPI IS SELECTED FOR EC	ESPI

STRAPS ON THIS PAGE

PIN	FUNCTION	INTENT
GPP_E19/DDPB_CTRLDATA	IPD = DO NOT DETECT PORT B PU = DETECT PORT B	DETECT PORT B
GPP_E21/DDPC_CTRLDATA	IPD = DO NOT DETECT PORT C PU = DETECT PORT C	DETECT PORT C

STRAPS ON THIS PAGE

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.	
Title	KBL-U(3/11)SPI/eSPI/I2C/SMB
Size: Custom	Document Number: LA-G741P
Rev	1.0
Date: Thursday, July 19, 2018	Sheet 10 of 54



STRAPS ON THIS PAGE

PIN	FUNCTION	INTENT
PCH_BUZZER	IPD = DISABLE TOP SWAP OVERRIDE PU = ENABLE TOP SWAP OVERRIDE	DISABLE
HDA_SDO/I2S_TXD0	IPD = ENABLE DESCRIPTOR SECURITY PU = DISABLE DESCRIPTOR SECURITY	ENABLE



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: KBL-U(4/11)I2S/DMIC/eMMC

Size: Custom | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 11 of 54



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: KBL-U(5/11)CLK/GPIO			
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 12 of 54		



The 16 HSIO lanes on KBL R U PCH-LP supports the following configurations:

1. Up to 12 PCIe* lanes (multiplexed with USB 3.0 lanes, SATA lanes)
   - Only a maximum of 6 PCIe* Root Ports (or devices) can be enabled at any time
   - PCIe* Lanes 1-4, 5-8, and 9-12 each can be individually configured as 4x1, 2x2, 1x2+2x1, 2x1+1x2, or 1x4
2. Up to 3 SATA lanes (multiplexed with PCIe* lanes)
   - SATA lane 1 has the flexibility to be mapped to either PCIe* lane 8 or 11
3. Up to 6 USB 3.0 lanes (multiplexed with PCIe* lanes)
   - On-the-Go (OTG) capability is available on USB 3.0 lane 1
   - One SSIC x1 lane is multiplexed with USB 3.0 lane 2
4. One GbE device
   - GbE can be mapped into one of the PCIe* lanes 3-5 and 9-10
   - When GbE is enabled, there can be at most up to 5 PCIe* Root Ports (or devices) enabled
5. Up to 2 Intel® RST for PCIe* Storage Devices
   - Each device can be x2 or x4 and can be implemented on either PCIe* lanes 5-8 or 9 - 12
6. For unused SATA/PCIe* Combo Lanes, Flex I/O Lanes that can be configured as PCIe* or SATA, the lanes must be statically assigned to SATA or PCIe* via the SATA/PCIe Combo Port Soft Straps discussed in the SPI Programming Guide and through the Intel® Flash Image Tool (FIT) tool. These unused SATA/PCIe* Combo Lanes must not be assigned as polarity based.

Table 1-3. PCH HSIO Detail

SKU	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
Base-U / Base-U with iHDCP	USB 3.0/ OTG	USB 3.0/ SSIC	USB 3.0	USB 3.0	PCIe*	PCIe	PCIe/ LAN	PCIe/ LAN	PCIe/ LAN	PCIe	SATA	SATA	PCIe/ LAN	PCIe/ LAN	PCIe	PCIe
Premium-U / Premium-U with iHDCP	USB 3.0/ OTG	USB 3.0/ SSIC	USB 3.0	USB 3.0	PCIe* / USB 3.0	PCIe/ USB 3.0	PCIe/ LAN	PCIe/ LAN	PCIe/ LAN	PCIe	PCIe/ SATA	PCIe/ SATA	PCIe/ LAN	PCIe/ LAN	PCIe/ SATA	PCIe/ SATA
Premium-Y / Premium-Y with iHDCP	USB 3.0/ OTG	USB 3.0/ SSIC	USB 3.0	USB 3.0	PCIe* / USB 3.0	PCIe/ USB 3.0	PCIe/ LAN	PCIe/ LAN	PCIe/ LAN	PCIe	PCIe/ SATA	PCIe/ SATA	PCIe/ LAN	PCIe/ LAN	N/A	N/A



Follow 561280_KBL UY PDG Rev1_0.pdf & 561280_KBL UY PDG Schematic Checklist Rev1_0.docx

If OTG is not implemented on the platform, then USB2_ID and USB2_VBUSSENSE should both be connected to ground.

teknisi-indonesia.com

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2018/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title	KBL-U(6/11)PCIE,USB,SATA		
Size	Document Number		Rev
Custom	LA-G741P		1.0
Date: Thursday, July 19, 2018	Sheet 13 of 54		

PP1000_A TO PP1000_VCCSTU



PP1800_A TO PP1800_S

PP1000_A TO PP1000_STG / PP1000_VCCIO













PP1200_VDDQ_SOC : 10UF/6.3V/0603 *6
1UF/6.3V/0402 * 4





Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: KBL-U(7/11)Power

Size: Custom | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 14 of 54



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.	
Title	KBL-U(8/11)Power
Size: Custom	Document Number: LA-G741P
Rev	1.0
Date: Thursday, July 19, 2018	Sheet 15 of 54



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: KBL-U(9/11)Power,SVID

Size: Custom | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 16 of 54







www.teknisi-indonesia.com

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: KBL-U(10/11)GND

Size: Custom | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 17 of 54

Display Port Presence Strap	
CFG4	1 : Disabled; No Physical Display Port attached to Embedded Display Port 0 : Enabled; An external Display Port device is connected to the Embedded Display Port





Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title	KBL-U(11/11)RSVD		
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 18 of 54		

Memory down Channel A







DDR4 mapping	SDP	DDP
E9	VSS	UZQ
M9	VSS	BG1
T7	NC	VSS

SDP@ RD1 0_0402_1% SD034000080
SDP@ RD2 0_0402_1% SD034000080
SDP@ RD3 0_0402_1% SD034000080
SDP@ RD4 0_0402_1% SD034000080

DDR_A_BG1_R — RD16 1 DDP@ 2 0_0201_5% — DDR_A_BG1
RD17 1 SDP@ 2 0_0201_5%

PP0600_DDRVTT

DDR_A_MA0 RD19 1 2 36_0402_1%
DDR_A_MA1 RD21 1 2 36_0402_1%
DDR_A_MA2 RD23 1 2 36_0402_1%
DDR_A_MA3 RD24 1 2 36_0402_1%
DDR_A_MA4 RD26 1 2 36_0402_1%
DDR_A_MA5 RD27 1 2 36_0402_1%
DDR_A_MA6 RD29 1 2 36_0402_1%
DDR_A_MA7 RD31 1 2 36_0402_1%
DDR_A_MA8 RD33 1 2 36_0402_1%
DDR_A_MA9 RD35 1 2 36_0402_1%
DDR_A_MA10 RD37 1 2 36_0402_1%
DDR_A_MA11 RD39 1 2 36_0402_1%
DDR_A_MA12 RD41 1 2 36_0402_1%
DDR_A_MA13 RD43 1 2 36_0402_1%
DDR_A_MA14_WE# RD44 1 2 36_0402_1%
DDR_A_MA16_RAS# RD45 1 2 36_0402_1%
DDR_A_MA15_CAS# RD46 1 2 36_0402_1%

PP0600_DDRVTT

DDR_A_CLK0 RD20 1 2 36_0402_1%
DDR_A_CLK#0 RD22 1 2 36_0402_1%

PP0600_DDRVTT

DDR_A_CS#0 RD25 1 2 36_0402_1%
DDR_A_ODT0 RD28 1 2 36_0402_1%
DDR_A_CKE0 RD30 1 2 36_0402_1%
DDR_A_BA0 RD32 1 2 36_0402_1%
DDR_A_BA1 RD34 1 2 36_0402_1%
DDR_A_PAR RD36 1 2 36_0402_1%
DDR_A_BG0 RD38 1 2 36_0402_1%
DDR_A_BG1_R RD40 1 DDP@ 2 36_0402_1%
DDR_A_ACT# RD42 1 2 36_0402_1%

INTEL suggest used 50ohm(1%)
569217_KBL_RU_PDG_Rev2p0.pdf=>P.104
Follow sourcer change to 49.9

PP1200_VDDQ
DDR_A_ALERT# RD47 1 2 49.9_0402_1%

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: DDR4_CHA_Memory Down I

Size: Custom | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 19 of 54

Memory down Channel B







DDR4 mapping	SDP	DDP
E9	VSS	UZQ
M9	VSS	BG1
T7	NC	VSS

SDP@ RD48 0_0402_1% SD034000080
SDP@ RD49 0_0402_1% SD034000080
SDP@ RD50 0_0402_1% SD034000080
SDP@ RD51 0_0402_1% SD034000080



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: DDR4_CHA_Memory Down II

Size: Custom | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 20 of 54

PCH SPI FLASH



teknisi-indonesia.com

EC FLASH ROM



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: SPI EC ROM			
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 21 of 54		



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: SERVO			
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 22 of 54		



	I2C TPM	SPI TPM
H1_SLAVE_SPI_CLK	1M PU	PD
H1_SLAVE_SPI_CS_L	5K PD	PD
PCH_I2C_H1_TPM_SCL	PD	1M PU
PCH_I2C_H1_TPM_SDA	PD	1M PU

Security Classification	Compal Secret Data		Compal Electronics, Inc.
Issued Date	2018/03/02	Deciphered Date 2019/03/02	Title H1 SECURE
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.			Size Custom / Document Number LA-G741P / Rev 1.0
			Date: Thursday, July 19, 2018 / Sheet 23 of 54



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: EC NPCX586GA0BX			
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 24 of 54		



Startup config: For FORESEE PCIe Gen3 BGA SSD P900		
NVME_GPIO0	0 Normal Mode	1 Firmware safe mode
NVME_GPIO1	0 ENABLES eFUSE DISABLES JTAG/UART	1 ENABLES JTAG/UART
NVME_TEST_MODE	0 Normal Mode	1 Test Mode

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: eMMC / NVMe			
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 25 of 54		

Audio Codec



I2C ADDRESSES:
0X18
0X19
0X1A (DEFAULT)
0X1B

Changed R34,R37 to L9,L10. For EMI protect.
12.01.2017



Changed component to meet mechanical design.
12.01.2017

Added C54,C55. For EMI protect.
12.01.2017

LAYOUT NOTES

ROUTE SENSE SIGNALS CLOSE TO JACK CONNECTOR
ROUTE HP_RING2 AND HP_RING2_SENSE DIFFERENTIALLY
ROUTE HP_SLEEVE AND HP_SLEEVE_SENSE DIFFERENTIALLY

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: **HP AMP DA7219-02VBA**

Size	Document Number	Rev
Custom	LA-G741P	1.0

Date: Thursday, July 19, 2018 Sheet 26 of 54

SPEAKER AMP





SPEAKER CONNECTOR



LAYOUT NOTES

SPKL_P, SPKL_N & SPKR_P, SPKR_N SHOULD BE CONNECTED AS CLOSE TO THE SPEAKER CONNECTOR AS POSSIBLE

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: SPEAKER AMP			
Size: B	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 27 of 54		



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: eDP

Size: Custom | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 28 of 54

KEY E

BLANK

www.teknisi-indonesia.com

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: Blank			
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 29 of 54		

NGFF WiFi/BT (KEY E)



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: M.2 WLAN CONNECTOR

Size: Custom | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 30 of 54

TYPE-C 5V POWER SWITCH



Sub Board 1 (LS-G222)



USB-C BC1.2





Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: **USB TyecC DB**

Size: B | Document Number: **LA-G741P** | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 31 of 54

The DVDD_IO can be power supplied by 1.8V ~ 3.3V:
If AP or EC's IO type is 1.8V, select 1.8V power for DVDD_IO.
If AP or EC's IO type is 3.3V, select 3.3V power for DVDD_IO.

PP3300_USB_PD — FB21 BLM03AG241SN1D_2P — PP3300_USB_PD_ANX_AVDD
C4967 1U_0402_16V6K, C4968 0.1U_0201_10V6K, C4969 1000P_0201_25V7K
Closed Pin 13 and Pin 24.

PP3300_USB_PD_ANX_DVDD
C5008 @ 1U_0402_16V6K
PP3300_USB_PD_ANX_AVDD — R5067 1 @ 2 0_0402_5%
C4971 0.1U_0201_10V6K
Closed Pin 39.

U115 ANX3447QN-AC-R_QFN48_6X6

[8] SOC_DP1_P0 / [8] SOC_DP1_N0	SOC_DP1_P0 R5117 @MP@ 0_0201_5% SOC_DP1_P0_R	1	DP_LN_0P / DP_LN_0N
	SOC_DP1_N0 R5118 @MP@ 0_0201_5% SOC_DP1_N0_R	2	
[8] SOC_DP1_P1 / [8] SOC_DP1_N1	SOC_DP1_P1 R5119 @MP@ 0_0201_5% SOC_DP1_P1_R	7	DP_LN_1P / DP_LN_1N
	SOC_DP1_N1 R5120 @MP@ 0_0201_5% SOC_DP1_N1_R	8	
[8] SOC_DP1_P2 / [8] SOC_DP1_N2	SOC_DP1_P2 R5121 @MP@ 0_0201_5% SOC_DP1_P2_R	9	DP_LN_2P / DP_LN_2N
	SOC_DP1_N2 R5122 @MP@ 0_0201_5% SOC_DP1_N2_R	10	
[8] SOC_DP1_P3 / [8] SOC_DP1_N3	SOC_DP1_P3 R5123 @MP@ 0_0201_5% SOC_DP1_P3_R	3	DP_LN_3P / DP_LN_3N
	SOC_DP1_N3 R5124 @MP@ 0_0201_5% SOC_DP1_N3_R	4	
[8] SOC_DP1_AUXP / [8] SOC_DP1_AUXN	SOC_DP1_AUXP C4982 0.1U_0201_10V6K SOC_DP1_AUXP_C	16	AUXP / AUXN
	SOC_DP1_AUXN C4981 0.1U_0201_10V6K SOC_DP1_AUXN_C	17	
	USB_C0_DP_HPD R5048 1 @MP@ 0_0201_5% USB_C0_DP_HPD_R	36	HPD
[13] USB3_CTX_MRX_P2 / [13] USB3_CTX_MRX_N2	USB3_CTX_MRX_P2 R5129 @MP@ 0_0201_5% USB3_CTX_MRX_P2_R	12	SSTX_P / SSTX_N
	USB3_CTX_MRX_N2 R5130 @MP@ 0_0201_5% USB3_CTX_MRX_N2_R	11	
[13] USB3_CRX_MTX_P2 / [13] USB3_CRX_MTX_N2	USB3_CRX_MTX_P2 R5131 @MP@ 0_0201_5% USB3_CRX_MTX_P2_R	6	SSRX_P / SSRX_N
	USB3_CRX_MTX_N2 R5132 @MP@ 0_0201_5% USB3_CRX_MTX_N2_R	5	
[24] USB_C1_PD_RST_ODL	USB_C1_PD_RST_ODL R5140 @MP@ 0_0201_5% USB_C1_PD_RST_ODL_R	46	TEST_R
[24,33] EC_I2C0_1_SDA / [24,33] EC_I2C0_1_SCL	EC_I2C0_1_SDA	37	CFG_SDA / CFG_SCL
	EC_I2C0_1_SCL	38	
[24,33] EN_USB_C1_5V_OUT / [24,42] EN_USB_C1_CHARGE_EC	R5083 1 @ 2 0_0201_5% SINK_CTRL	43	SINK_CTRL / SOURCE_CTRL
	R4984 1 @ 2 0_0201_5% SOURCE_CTRL	44	
TP927 @	TEST_EN	45	TEST_EN
	VBUS_C1_DISCHG	35	DISCHARGE_CTRL
	ROLE_SELECT	28	ROLE_SELECT
	PD2_ADD0	48	I2C_ADR_0 / I2C_ADR_1
	PD2_ADD1	47	

	SSTXP1 / SSTXN1	25 / 26	USB3_DP1_1_MTX_DRX_P / USB3_DP1_1_MTX_DRX_N C49921 2 0.1U_0201_10V6K USB3_DP1_1_MTX_C_DRX_P1 / C49931 2 0.1U_0201_10V6K USB3_DP1_1_MTX_C_DRX_N1
	SSRXN2 / SSRXP2	33 / 34	USB3_DP1_2_MRX_DTX_N1 / USB3_DP1_2_MRX_DTX_P1
	SSTXP2 / SSTXN2	30 / 29	USB3_DP1_2_MTX_DRX_P / USB3_DP1_2_MTX_DRX_N C49961 2 0.1U_0201_10V6K USB3_DP1_2_MTX_C_DRX_N1
	SSRXN1 / SSRXP1	32 / 31	USB3_DP1_1_MRX_DTX_N1 / USB3_DP1_1_MRX_DTX_P1
	SBU1 / SBU2	19 / 18	DP1_AUXP_SBU1 / DP1_AUXN_SBU2
	CC1 / CC2	22 / 21	USB_C1_CC1 / USB_C1_CC2
	VCONN_POWER	23	C4991 4.7U_0402_6.3V6M; R5049 1M_0201_5%; R5050 1M_0201_5%; C4965 @EMI@ 1000P_0201_25V7K; C4966 @EMI@ 1000P_0201_25V7K
	FF0	41	
	FF1	42	
	INTP_OUT	40	USB_C1_PD_INT_ODL
	VBUS_SENSE	15	PPVAR_USB_C1_VBUS_SENSE R4983 1 2 348K_0201_1%
	VBUS_OCP	20	@ TP945
	NC / NC	14 / 27	
	VSS	49	

PP3300_USB_PD
R5068 1 2 100K_0201_1% SOC_DP1_AUXN_C
R5069 1 2 100K_0201_1% SOC_DP1_AUXP_C

PP3300_USB_PD_ANX_DVDD
R5051 1 2 1.8K_0201_1% EC_I2C0_1_SDA
R5052 1 2 1.8K_0201_1% EC_I2C0_1_SCL

PPVAR_USB_C1_VBUS_L
R5053 1.2K_0402_5%
Q77 PMZ370UNE_DFN1006-3
R5054 100K_0201_5% @
DISCHARGE_CTRL
Auto VBUS discharge pin.
Internal 100K pull down.

PP5000_A
R5049 1M_0201_5%, R5050 1M_0201_5%
C4965 @EMI@ 1000P_0201_25V7K, C4966 @EMI@ 1000P_0201_25V7K
C4991 4.7U_0402_6.3V6M

VCONN_POWER is the power source for VCONN:
1) VCONN Voltage range [3.6V, 5.5V]
2) Internal VCONN Switch:Iout Max 400mA,Rdson Max 1.2 ohm
2) VCONN Minimum power is 1W. If DP Alternate
Mode is supported, VCONN power is up to 1.5W.

PPVAR_USB_C1_VBUS_L
R5065 49.9K_0201_1%

PP3300_USB_PD_ANX_AVDD
R5055 1 2 4.7K_0201_5% ROLE_SELECT
R5058 1 @ 2 4.7K_0201_5%
ROLE_SELECT pin:
Logic 1: DRP Mode.
Logic 0: DFP Mode.
NC: UFP Mode.

[24] USB_C0_DP_HPD_EC — R4927 1 @ 2 0_0201_5% — USB_C0_DP_HPD
[8] USB_C0_DP_HPD_SOC — R4926 1 @MP@ 2 0_0201_5%
R28 100K_0201_1%

PP5000_A
D42 2 1 RB751S-40 CCD@
R5110 CCD@ 100K_0201_1%

R5155 1 @ 2 0_0201_1%
PMZ370UNE_DFN1006-3
DP1_AUXP_SBU1 — Q79 CCD@ — USB_C1_SBU1 [23,33]
C4993 @EMI@ 1000P_0201_25V7K
R5070 2M_0201_5%
To H1

CCD@ Q80
DP1_AUXN_SBU2 — PMZ370UNE_DFN1006-3 — USB_C1_SBU2 [23,33]
R5156 1 @ 2 0_0201_1%
C4992 @EMI@ 1000P_0201_25V7K
R5071 2M_0201_5%

PP3300_H1 — CCD@ PMZ370UNE_DFN1006-3 Q81
[23,24] CCD_MODE_ODL — CCD_MODE_ODL

Closed U115
Closed U11

PP3300_USB_PD_ANX_DVDD
R5056 1 2 4.7K_0201_5% PD2_ADD0 — R5057 1 @ 2 4.7K_0201_5%
R5059 1 2 4.7K_0201_5% PD2_ADD1 — R5060 1 @ 2 4.7K_0201_5%

I2C_ADR_1/I2C_ADR_0:
Input pin with internal 100k ohm pull-down

I2C_ADR_1	I2C_ADR_0	TCPC Address (Wakeup address)	SPI Address	EMTB Address	EMTB Address	Debug Address_1	Debug Address_2
0	0	0x58	0x7E	0x7A	0x84	0x72	0x70
0	1	0x56	0x6E	0x78	0x86	0x76	0x70
1	0	0x54	0x64	0x68	0x6C	0x5C	0x70
1	1	0x52	0x62	0x6A	0x74	0x82	0x70

	Stuff	Unstuff
CCD mode:	Q79, Q80, Q81, D42 and R5110	R5155 and R5156
Non CCD mode:	R5155 and R5156	Q79, Q80, Q81, D42 and R5110

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: USB TyecC LOAD SWITCH

Size: B | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 32 of 54

5V Current limit



USB TYPE-C Conn



Changed component to meet mechanical design.
12.01.2017

USB- C BC1.2









Remove USB3 choke for EMI request.
12.07.2017





Security Classification	Compal Secret Data		Compal Electronics, Inc.
Issued Date	2018/03/02	Deciphered Date 2019/03/02	Title: USB3.0 Type-C Conn.
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 33 of 54		

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Type A BC1.2



Device Control Pins				
Flow Line Condition	CTL1	CTL2	CTL3	ILIM_SEL
DCH (Discharge)	0	0	0	X
CDP	1	1	1	1
SDP2 (No Discharge from/to CDP)	1	1	1	0
SDP1 (Discharge from/to any charging state including CDP)	1	1	0	X
	0	1	0	X
DCP_SHORTED	1	0	0	X
DCP_DIVIDER	1	0	1	X
DCP_Auto	0	1	1	X
	0	0	1	X











LED Y/W



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: USB Type-A / LED

Size: Custom | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 34 of 54



Pin Configuration

Pin #	Pin Name	Type	Pin Description	Internal Resistor
1	VDD	PWR	Supply Voltage	--
2	ACOK_OD	Digital Input	Digital Input without Schmitt trigger	1MΩ pulldown
3	ROP_PMIC_PWRBTN	Digital Output	Open Drain NMOS 1X	floating
4	LID_SENSE_L	Digital Input	Digital Input without Schmitt trigger	100kΩ pullup
5	NC	--	Keep Floating or Connect to GND	--
6	EC_HIBERNATE	Digital Input	Digital Input without Schmitt trigger	1MΩ pulldown
7	GND	GND	Ground	--
8	EC_PWR_BTN_L	Digital Input	Digital Input without Schmitt trigger	100kΩ pullup
9	EC_PLATFORM_RST	Digital Input	Digital Input with Schmitt trigger	1MΩ pulldown
10	EC_RST_ODL	Bi-directional	Digital Input without Schmitt trigger / Push Pull 1X	100kΩ pullup
11	NC	--	Keep Floating or Connect to GND	--
12	ROP_PMIC_ENVR3	Digital Output	Open Drain NMOS 1X	floating

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: HIBERNATE WAKE SOURCE

Size: Custom | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 35 of 54



Rear Camera W/ DMIC





Thermal Sensor







Close SOC

Close POWER IC

TRACKPAD CONNECTOR



www.teknisi-indonesia.com

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.		
Title: Touch, Trapckpad, Pen		
Size:	Document Number: LA-G741P	Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 36 of 54	

KEYBOARD BACKLIGHT



ILED_MAX = 192×1.244V/RSET.
==>192 X 1.244/2.2K = 108 mA

CPU Fan Control Circuit



ODM TO CHOOSE CONNECTOR

KEYBOARD



For power key, stuff R424/R425, Non stuff R422/R423.
For lock key, Non stuff R424/R425, stuff R422/R423.

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: KB, KB Backlight, FAN			
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 37 of 54		







Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: **LID Sensor**

Size: Custom	Document Number: LA-G741P	Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 38 of 54	



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: INAs

Size: B | Document Number: LA-G741P | Rev: 1.0

Date: Thursday, July 19, 2018 | Sheet 39 of 54



Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: LOAD SWITCHES			
Size: Custom	Document Number: LA-G741P		Rev: 1.0
Date: Thursday, July 19, 2018	Sheet 40 of 54		



[CLIP]



[Screw Hole]



www.teknisi-indonesia.com

Security Classification	Compal Secret Data		
Issued Date	2018/03/02	Deciphered Date	2019/03/02

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title	PCB, Screw, CLIP		
Size	Custom	Document Number	LA-G741P
Rev	1.0		
Date:	Thursday, July 19, 2018	Sheet	41 of 54



Security Classification	Compal Secret Data		
Issued Date	2017/06/20	Deciphered Date	2018/06/20

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Title			
Size: Custom	Document Number		Rev: 0.1
Date: Thursday, July 19, 2018	Sheet 42 of 54		



TABLE 22. PROG PIN PROGRAMMING OPTIONS

PROG-GND RESISTANCE (kΩ)				DEFAULT SWITCHING FREQUENCY	Autonomous charging	DEFAULT ACLimit1 Reg(A)
MIN	TYP 1%	MAX	CELL #			
	0		1	733kHz	No	0.476
	8.45			733kHz	No	1.5
	14.7			1MHz	No	1.5
	21.0			1MHz	No	0.476
	28.0			733kHz	Yes	0.476
	35.7			733kHz	Yes	1.5
	43.2		2	733kHz	Yes	1.5
	52.3			733kHz	Yes	0.476
	61.9			1MHz	No	0.476
	71.5			1MHz	No	1.5
	82.5			733kHz	No	1.5
	93.1			733kHz	No	0.476
	105		3	733kHz	No	0.476
	118			733kHz	No	1.5
	133			1MHz	No	1.5
	147			1MHz	No	0.476
	162			733kHz	Yes	0.476
	178			733kHz	Yes	1.5
	196		4	733kHz	Yes	1.5
	215			733kHz	Yes	0.476
	237			1MHz	No	0.476
	261			1MHz	No	1.5
	287			733kHz	No	1.5
	316			733kHz	No	0.476
	348		1	733kHz	No	0.476

Security Classification	Compal Secret Data		
Issued Date	2016/05/02	Deciphered Date	2018/12/31

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: CHARGER ISL9238

Size: Custom | Document Number | Rev 0.1

Date: Thursday, July 19, 2018 | Sheet 43 of 54



Security Classification	Compal Secret Data		
Issued Date	2016/05/02	Deciphered Date	2018/12/31

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: PWR_PMIC-TPS650830(1of2)

Size: Custom | Document Number | Rev: 0.1

Date: Thursday, July 19, 2018 | Sheet 44 of 54



Security Classification	Compal Secret Data		
Issued Date	2016/05/02	Deciphered Date	2018/12/31

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: PWR_PMIC-TPS650830(2of2)

Size: Custom | Document Number | Rev: 0.1

Date: Thursday, July 19, 2018 | Sheet 45 of 54



Security Classification	Compal Secret Data		
Issued Date	2016/05/02	Deciphered Date	2018/12/31

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: PWR_NVMe

Size: Custom | Document Number | Rev: 0.1

Date: Thursday, July 19, 2018 | Sheet 46 of 54



Security Classification	Compal Secret Data		
Issued Date	2016/05/02	Deciphered Date	2018/12/31

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Title	Compal Electronics, Inc.
	PWR IMVP8(1of3)
Size	Document Number: Custom
Rev	0.1
Date:	Thursday, July 19, 2018
Sheet	47 of 54



Security Classification	Compal Secret Data		
Issued Date	2016/05/02	Deciphered Date	2018/12/31

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: PWR_IMVP8(2of3)			
Size: Custom	Document Number		Rev: 0.1
Date: Thursday, July 19, 2018	Sheet 48 of 54		



Security Classification	Compal Secret Data		
Issued Date	2016/05/02	Deciphered Date	2018/12/31

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.			
Title: PWR IMVP8(3of3)			
Size: Custom	Document Number		Rev: 0.1
Date: Thursday, July 19, 2018	Sheet 49 of 54		

+VCC_CORE
220U_R9 * 3 pcs
47U_0805 * 8 pcs
22U_0603 * 9 pcs
10U_0402 * 7 pcs
1U_0201 * 26 pcs

PPVAR_VCC



CAPS PLACE ON OPPOSITE SIDE OF SOC

www.teknisi-indonesia.com









Jumper Footprint: SOLDER_PREFORMS_0805

PPVAR_VCC PPVAR_GT_VCC

For KBL-R U42: PJCPU1
For KBL-U22: PJCPU2

PPVAR_VCC



Based on Intel PDG recommand

PPVAR_GT_VCC



Security Classification	Compal Secret Data		
Issued Date	2016/05/02	Deciphered Date	2018/12/31

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: CPU : CPU POWER (1/2)

Size: Custom | Document Number | Rev: 0.1

Date: Thursday, July 19, 2018 | Sheet 50 of 54

+VCC_GT
220U_R9 * 2 pcs
47U_0805 * 3 pcs
22U_0603 * 7 pcs
10U_0402 * 12 pcs
1U_0201 * 14 pcs

PPVAR_GT



+VCC_SA
10U_0402 * 13 pcs
1U_0201 * 7 pcs

PPVAR_SA



Security Classification	Compal Secret Data		
Issued Date	2016/05/02	Deciphered Date	2018/12/31

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: CPU : CPU POWER (2/2)

Size: Custom | Document Number | Rev: 0.1

Date: Thursday, July 19, 2018 | Sheet 51 of 54

Change PP2500_DRAM solution from G9661 to G5719 for Intel Deep S3 mode



Note:
When design Vin=5V, please stuff snubber to prevent Vin damage

Vout=0.6V* (1+Rup/Rdown)

Vout=2.544V



Security Classification	Compal Secret Data		
Issued Date	2016/05/02	Deciphered Date	2018/12/31

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.

Title: PWR 2.5VP

Size: Custom | Document Number | Rev: 0.1

Date: Thursday, July 19, 2018 | Sheet 52 of 54

Version change list

Item	Reason for change	PG#	Modify List	Date	Phase
1	Follow reference board design	43	Charger VDD/VDDP Cap down size portion. (Reserve PC1,PC2 and change PC28/PC29 from 1uF to 2.2uF)	4/19	FVT
2	Follow reference board design	44	Install PR105 pull 100K to PP1000_VCCST.	4/19	FVT
3	Follow reference board design	52	Modify PP3300_H1 IC solution from G922 to TPS62125 by Google request.	4/23	FVT
4	Follow reference board design	42	Change PR477 from 0 ohm to 1K ohm prevent abnormal contact. Add PRB01/PRB02 100 ohm on BATT I2C for Battery connector. Add PQ62 Resistor PRB03 prevent abnormal contact.	5/4	FVT
5	Follow reference board design	45	PR137 change to 0.01 ohm from 0 ohm for HW power consumption test	6/4	SIT
6	Follow reference board design	52	Add PR603 & PR607 for HW power consumption test	6/4	SIT
7	Follow reference board design	52	PL401 change to 2.2uH	7/10	SVT
8	Compal rule	43 44 45 47 48 49 52	PR5, PR10, PR13, PR14, PR16, PR17, PR20, PR112, PR119, PR122, PR126, PR943, PR129, PR130, PR131, PR132, PR134, PR139, PR141, PR142, PR144, PR146, PR147, PR148, PR153, PR154, PR155, PR157, PR161, PR162, PR165, PR931, PR1236, PR34, PR41, PR42, PR53, PR54, PR65, PR75, PR82, PR172, PR173, PR176, PR177, PR178, PR84, PR85, PR89, PR90, PR94, PR95, PR101, PR103, PR166, PR601, PR604 change to short pad.	7/10	SVT
9					
10					
11					
12					
13					
14					
15					
16					
17					

Security Classification	Compal Secret Data		
Issued Date	2016/03/21	Deciphered Date	2017/03/01

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.	
Title	PWR-PIR
Size: Custom	Document Number: LA-C423P
Rev	1.0
Date: Thursday, July 19, 2018	Sheet 53 of 54

Security Classification	Compal Secret Data		
Issued Date	2017/11/23	Deciphered Date	2018/11/23

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.	
Title	Change List
Size: Custom	Document Number
Rev	0.1
Date: Thursday, July 19, 2018	Sheet 53 of 54

Item	Page	Function/Signal/Parts	Change Descrption	Modified date
			Proto change list	
1	42	PJPB1	Change PJPB1 to 10pin connector.	2018/3/12
2	24	JTP1	Change JTP1 to 6pin connector.	2018/3/12
3	37	JKB1	Reverse JKB1 pin definition	2018/3/19
4	7	RAM ID	Update RAM ID and BOM structure	2018/3/19
5	24, 31	Power button LED	Add power button LED control signal PWRBTN_LED# from U89.A2 to R965.1 Net name EC_CHG_LED_W_R1 change to PWRBTN_LED_R#	2018/3/21
6	8	DDR select	RC230 un-stuff, RC231 stuff, and chane to 1k.	2018/3/21
7	40	PP3300_USB_PD	R385 un-stuff, R960 stuff	2018/3/22
8	40	Touch screen power	R5041 un-stuff, R5042 stuff	2018/3/22
9	12	VCCST_PWRGD	R95 stuff, PR105 un-stuff	2018/3/22
10	36	JTP1	Change JTP1 to 6pin pitch=0.5mm connector.	2018/3/23
11	14	VCCPLL_OC	Add CC118 for VCCPLL_OC by intel request	2018/3/23
12	22	R5087	Add PU 10k by google request	2018/3/26
13	33	0.1U 25V K X5R 0201	C24,C27 SE000001AA00 change to SE00001AAZ0	2018/3/26
14	14	0_0201_1%	RC27, RC30 change to 0_0201_5%	2018/3/26
15	15	C375	C375 change to 0.1U by RF request	2018/3/27
16	15	RC35	RC35 change to BLM18BG221SN1D_0603 by RF request	2018/3/27
17	9,12	ESD component	CC2, CC112, CC113, CC109, CC111, CC110, CC114, CC115 change to stuff by ESD request	2018/3/27
18	14	CC106	CC106 un-stuff by Intel request	2018/3/27
			EVT change list	
19	37	L1	PN change to SHX0000M200 to follow Nami design	2018/4/18
20	37	KB backlight	Add KBL@ for KB backlight BOM config	2018/4/18
21	15	CC77	Unstaff CC77 to meet intel sequence spec	2018/4/18
22	22	R5087/ WARM_RESETN	Add resistor 100K (R5087) PU to PP3300_A for WARM_RESETN	2018/4/18
23	20	R994/ DDR_B_ALERTN	Change R994 Compla PN(from SD000014400 to SD000007000)	2018/4/18
24	19, 20	RD18/RD65	Change RD18, RD65 Compal PN(from SD000015N80 to SD000012B80)	2018/4/18
25	12	C348/349	Change C348, C349 from 10P to 15P for crystal tuning	2018/4/18
26	23	R173	Unstaff R173 (EC don't control reset from H1)	2018/4/18
27	24	U103	Change U103.7 net form EC_WPW to PCH_WP for EEPROM	2018/4/18
28	25	RP1,RP2/ R5088-R5095	20k resister pack (SD300003000) change to 20k_0201 (SD000007G00)	2018/4/19
29	28	F1	1.1A fuse (SP040007U00) change to 1.5A fuse (SP040001G00)	2018/4/19
30	24	RP3,RP4/ R5096-R5103	4.7k resister pack (SD3094701B0) change to 4.7k_0201 (SD043470180)	2018/4/19
31	8	RPC1/ RC240-RC243	2.2k resistor pack (SD3092201B0) change to 2.2k_0201 (SD000012R80)	2018/4/19
32	13	RPC2/ RC235-RC238	10k resister pack (SD3091002B0) change to 10k_0201 (SD043100280)	2018/4/19
33	29, 30, 37	C381, C595, C4989	0.1u_0402 (SE095104K80) change to 0.1u_0201 (SE00000SW00)	2018/4/19
34	37	C596, C597	1u_0603 (SE000011W00) change to 1u_0402 (SE000010V00)	2018/4/19
35	19, 20	CD6, CD48, CD49, CD50, CD51, CD55, CD56, CD57, CD60, CD62	1u_0201 Compal PN SE00000YB00 change to SE00000UC00	2018/4/19
36	23	C369	1u_0402 (SE00000QL10) change to 1u_0201 (SE00000UC00)	2018/4/19
37	25, 28, 37	C72, C73, C237, C291, C4952	4.7u_0603 (SE00000MA00) change to 4.7u_0402 (SE00000ZY80)	2018/4/19
38	14, 15, 19, 20, 40	C579, CC4, CC5, CC9, CC14, CC16, CC19, CC27, CC29, CC30, CC37, CC38, CC39, CC40, CC41, CC42, CC51, CC54, CC55, CC56, CC60, CC61, CC62, CC63, CC64, CC65, CC66, CC67, CC69, CC70, CC73, CC74, CC78, CC79, CC106, CC116, CD2, CD3, CD4, CD5, CD9, CD10, CD11, CD12, CD13, CD14, CD15, CD16, CD18, CD19, CD20, CD23, CD24, CD28, CD29, CD30, CD31, CD32, CD33, CD34, CD35, CD38, CD39, CD42, CD43, CD45, CD46, CD53, CD54, CD58, CD59, CD63, CD64, CD65, CD70, CD71, CD74, CD75, CD76, CD77, CD78, CD79, CD80, CD81, CD84, CD85, CD88, CD89, CD91, CD92	1u_0402 (SE000000K80) change to 1u_0201 (SE00000UC00)	2018/4/19
39	43	PC1, PC2, PC28, PC29	Reserve PC1,PC2 and change PC28/PC29 from 1uF to 2.2uF	2018/4/22
40	44	PR105	Install PR105 pull 100K to PP1000_VCCST	2018/4/22
41	7	EMMC	Add SANDISK_64G_1@ SA0000B4R00	2018/4/22
42	7	RAM	Add MICRON4G@, HYNIX_4G_1@ RAM	2018/4/22
43	52	PD601	Modify PP3300_H1 IC solution from G922 to TPS62125 by Google request	2018/4/23
44	11, 15, 29, 30, 40	C263, C352, C353, C354, C355, C356, C578, C581, C4987, C4990, CC105	0.01u_0201 Compal PN SE172103K80 cahnge to SE00000YH00	2018/4/23
45	34	LED1	Changed LED pull up to PP3300_DSW_EC	2018/4/25
46	12	C3/C4	Change C3, C4 from 10P to 7P for crystal tuning	2018/4/25
47	21	Q78/R5104/R5105/R5017	Add circuit for EEPROM WP solution	2018/4/25
48	24	U103	Rename U103.7 netname to SKU_WP_R	2018/4/25
49	21	R5107	Rename R5107.2 to SKU_WP_R	2018/4/25
50	12	RC70/ CC97/CC98	Change RC70/ CC97/CC98 package to 0201	2018/4/25
51	32	Q79/Q80/Q81/R5110	Adding circuit to isolate the SBU signals from type-C connector to TCPC in order to support CCD	2018/4/25
52	29	JNGFF1	Del JNGFF1 and around circuit	2018/4/25
53	34	D35	D35 change to FUSB3FR4 (SCA00003W00) by ESD request	2018/4/26
54	34	D38	D38 change to AZC099-04S.R7G (SC300001G00) by ESD request	2018/4/26
55	24	R271, R5067	0.01_0402(SD00001UX00) change to 0_0402(SD028000080)	2018/4/27
56	34	R4998/R22	R4998 change to 1.2k ohm, R22 change to 200 ohm for LED brightness tuning.	2018/4/29
57	24, 35	R5111	Add R5111 between EC_RST_ODL and EC_WCC1_RST	2018/4/30
58	35	U91	U91 Compal PN change to SA0000BLL20 for FW update	2018/4/30
59	37	U88	Follow Nami U88 pin4&8 change to PP5000_A	2018/5/2
60	24	R4941/R4942	R4941, R4942 change to 2.2k	2018/5/2
61	42	PR477 PRB01/PRB02 PQ62/PRB03	Change PR477 from 0 ohm to 1K ohm prevent abnormal contact. Add PRB01/PRB02 100 ohm on BATT I2C for Battery connector. Add PQ62 Resistor PRB03 prevent abnormal contact.	2018/5/4
62	34	R22/R4998	Updated R22 to 1.2K-ohm (white color), R4998 to 200-ohm (amber) for tune brightness	2018/5/6
63	38	R4976/ R4977	Change R4976, R4977 to 3.3K and unstuff.	2018/5/6
64	32	C4973 - C4980 C4983 - C4986	Removed C4973 - C4980 for DP; C4983 - C4986 for USB3 (follow vendor reference schematic)	2018/5/6
65	37	C379	Change C379 power rail change to PP5000_A	2018/5/6
66	40	U53/R386/C319	Unstuff U53/R386/C319 for reserve path PP3300_USB_PD	2018/5/6
67	32	R5072/R5073 DP1_AUXP_SBU1; DP1_AUXN_SBU2	Removed R5072 and R5073 from DP1_AUXP_SBU1, DP1_AUXN_SBU2	2018/5/6
68	35	U91	Updated U91 reset IC Pin Configuration	2018/5/6
69	24	R5112	Add reserve R5112 100K PU to PP3300_H1 for TABLET_MODE	2018/5/6
70	34	LED1	Changed LED1 power rail to PP3300_DSW	2018/5/6
71	37	R829	Changed R829 from 2.2K to 8.06K for ILED max setting	2018/5/6
72	24	R5113-R5116	Add R5113-R5116 reseved circuit connect to EC_I2C_3	2018/5/6
73	10, 12, 15	C374/C375/C376	C374,C375,C376 change to 3.3p by RF request	2018/5/6
74	37	U88	U88 pin4 VIO change to PP3300_DSW_EC	2018/5/6
75	37	Keyboard	Reverse JKB1 pin define.	2018/5/9
76	12, 25	C4914, C4915, C348, C349, CC97, CC98	15p_0201_50V change to 15p_0201_25V for material shortage	2018/5/11
77	15	RC35	0ohm chane to bead BLM18BG221SN1D by RF request	2018/5/11
78	15	C374, C375	3.3p_0201_25V change to 2p_0201_25V for material shortage	2018/5/11
79	10	C376	3.3p_0402_50V change to 2p_0402_50V for material shortage	2018/5/11
			DVT change list	
80	24	U103	Rename EC_I2C_0_SCL_R>>HW_ID_I2C_SCL EC_I2C_0_SDA_R>>HW_ID_I2C_SDA to follow Nami's name	2018/6/1
81	13, 31	EMR_GARAGE_DET EMR_GARAGE_DET_GPP_E1 EMR_GARAGE_DET_GPP_E8	Rename EMR_GARAGE_DETH to EMR_GARAGE_DET for GME: EMR_GARAGE_DETH_GPP_E1 to EMR_GARAGE_DET_GPP_E1: EMR_GARAGE_DETH_GPP_E8 to EMR_GARAGE_DET_GPP_E8 (Switch is normal close)	2018/6/1
82	23	H1 SECURE	Add note for H1 strap	2018/6/1
83	37	R829	Follow test result change R829 to 8.2K for KB_BL ILED MAX	2018/6/1
84	32	PP3300_USB_PD PP3300_USB_PD_ANX_AVDD PP3300_USB_PD_ANX_DVDD ROLE_SELECT SOC_DP1_AUXP/N_C TEST_EN FF0/FF1	Changed power design: PP3300_USB_PD > PP3300_USB_PD_ANX_AVDD > PP3300_USB_PD_ANX_DVDD by vendor suggestion to make sure the AVDD33 power is no later than DVDD_IO. Changed ROLE_SELECT PU power rail to PP3300_USB_PD_ANX_AVDD by vendor suggestion. Change DP AUX PU/PD throught capacitor in MUX side. Remove TEST_EN, FF0 and FF1 testpoint by vendor suggestion to make them as NC.	2018/6/1
85	36	UT1 R5125/R5126	Remove UT1 I2C bus PU resistor RT1 and RT2. (Already PU on EC side) Change UT1 VCC to PP3300_DSW and reserve PP3300_S path.	2018/6/1
86	23	USB_C1_SBU1/USB_C1_SBU2 R5127/R5128 R797/R798	Add note for CCD mode Add R5127 and R5128 1M PD on H1 CC1/CC2 to prevent detecting Add if there isn't SuzyQ cable connected Change R797 and R798 to 0 ohm	2018/6/1
87	23	R841/R842	Stuff R841/R842 to enable SuzyQ	2018/6/1
88	13, 29, 30	R5136/R5137/R5138/R5139/C5004/C5005	Connect GPP_E4 for BT_OFFW to JWLN1.54, (JNGFF.54). Connect GPP_E2 for WLAN_OFFW to JWLAN1.56 (JNGFF1.56). Add 0 ohm for debugging and add cap for filtering.	2018/6/3
89	24, 32, 40	R5051/R5052/R877/R510/R5101/ R5056/R5059/R5135/C5008	Stuff R5051/R5052 and pull up to PP3300_USB_PD_ANX_DVDD. Pull up R5056/R5059/R877 to PP3300_USB_PD_ANX_DVDD. Unstuff R5100/R5101. Reserve R5135/C5008	2018/6/3
90	37	D14	Change D14 PCB FootPring to "ESD101-B1-02ELS_TSSLP-2-4-2"	2018/6/3
91	24, 32	R5140 TP927	Add 0 ohm resistor R5140 net to U115.46 & "SUB_C1_PD_RST_ODL" Add test point TP927 net to U115.45	2018/6/3
92	31, 33	R5141/R5143/U27/U33	Change U33.8 net to "PP3300_BC12_C1_VDDIO" ; add R5141 net to "PP3300_BC12_C1_VDDIO" change U27.8 net to "PP3300_BC12_C0_VDDIO" ; add R5143 net to "PP3300_BC12_C0_VDDIO"	2018/6/3
93	24	R5145/R5146/R4941/R4942	Add R5145 net to "EC_I2C_0_SCL"; R5146 net to "EC_I2C_0_SDA" Unstuff R4941/R4942	2018/6/3
94	24	R5147/R5148	Add reserve resistor R5148 net to "PP3300_DSW_EC" & U103.8 ; Add resistor R5147 net to "PP3300_USB_PD" & U103.8	2018/6/3
95	24, 32	R5151/R5152/R5153	Add reserve resistor R5151 net to "USB_C0_PD_INT_ODL" & "PP3300_DSW_EC"; Add reserve resistor R5152 net to "USB_C0_PD_RST_ODL" & "PP3300_DSW_EC"; Add reserve resistor R5153 net to "USB_C1_PD_RST_ODL" & GND	2018/6/3
96	33	DP1_AUXP_SBU1/DP1_AUXP_SBU2 USB_C1_SBU1/USB_C1_SBU1	change "DP1_AUXP_SBU1" to "USB_C1_SBU1" from JTYPEC1.A8 to D40.4/D40.7 change "DP1_AUXP_SBU2" to "USB_C1_SBU2" from JTYPEC1.B8 to D40.4/D40.7	2018/6/3
97	23	R841/R842	Change R841 and R842 BOM Structure to MP@	2018/6/3
98	28	R5085/R5086/C323/C324/C372/C371	Unstuff R5085/R5086/C323/C324/C372/C371	2018/6/3
99	28	F1	Change back 1.1A fuse (SP040007U00) to follow Nami	2018/6/3
100	33, 34	D20/ D38	D20, D38 change to AZC399-04S (SC300005Y00) by ESD request	2018/6/3
101	45	PR137	PR137 change to 0.01 ohm from 0 ohm for HW power consumption test.	2018/6/4
102	52	PR603/PR607	Add PR603 & PR607 for HW power consumption test.	2018/6/4
103	47, 52	PU2/PU601/PL601	Re-link PU2 & PU601 & PL501 for Compal Symbols released.	2018/6/4
104	32	R5117 ~ R5124, R5129 ~ R5132	Reserve R5129 ~ R5132 for USB3 by intel recommend. Add net USB3_CTX_MR_P/N2_R, USB3_CRX_MTX_P/N2_R for U115 USB3 port Reserve R5117 ~ R5124 for DP by intel recommend. Add net SOC_DP1_P/N[0:3]_R for U115 DP port	2018/6/5
105	31	JI02	Add R5149 and reserve R5150 for sub board PS8751 power	2018/6/5
106	12	R95	Unstuff R95 due to PR105 already pull-high.	2018/6/6
107	24	R5112	Stuff R5112	2018/6/7
108	23	R841/R842	Change R841 and R842 BOM Structure form MP@ to CCD@ for CCD mode enable	2018/6/7
109	35	U91	Update reset IC PN from FW005 to FW006(SA0000BLL30) and Pin Configuration table	2018/6/7
110	32	U115	Update U115 PN from ANX7447 to ANX3447(SA0000C9000)	2018/6/7
111	30	R5136/ R5137	Un-stuff R5136, R5137	2018/6/14
112	21	R5104	100k ohm change to 3.3k ohm	2018/6/14
113	30, 40	C260/C589	C260 change to 47U, C589 change to 22U for WLAN power rising time tuning	2018/6/19
114	11	L20/R4952	L20,R4952 unstuff for rear camera not support	2018/6/19
115	21	R5104/U103	Change R5104 from 3.3K to 1K for SKU_WP_R voltage level (depend on U103.7 internal PD)	2018/6/19
116	23, 32, 33	USB_C1_CC1/2 USB_C1_CC1_H1/2	Change netname USB_C1_CC1_H1/2 to USB_C1_CC1/2; USB_C0_CC1/2 to USB_C1_CC1_H1/2	2018/6/19
			FVT change list	
117	24, 36	R5154/R4918 USB2_ID_EC TP950	Change net USB2_ID_EC from GPI057 to GPI042 and add R5154 for OTG function. Unstuff R4918; Add Testpoint TP950 reserve for GPI057	2018/7/11
118	23	R797/R798/R5127/R5128	Change R797 and R798 from 0 ohm to 1K ohm; Unstuff R5127 and R5128.	2018/7/11
119	32	R5155/R5156 R5110/Q79/Q80/Q81/D42	Add reserve 0 ohm R5155 and R5156 for non-CCD mode Add note and BOM Structure for CCD mode option	2018/7/11
120	24	R5111	Unstuff R5111 for reset IC PW006	2018/7/11
121	37	R829	8.2K_0201_1% (SD00008B580) change to 8.2k_0201_5% (SD043E20180) by purchaser request.	2018/7/11
122	52	PL401	PL401 change to 2.2uH	2018/7/12
123	42-52	PR5, PR10, PR13, PR14, PR16, PR17, PR20, PR112, PR119, PR122, PR126, PR943, PR129, PR130, PR131, PR132, PR134, PR139, PR141, PR142, PR144, PR146, PR147, PR148, PR153, PR154, PR155, PR157, PR161, PR162, PR165, PR931, PR1236, PR94, PR41, PR42, PR53, PR54, PR85, PR75, PR82, PR172, PR173, PR176, PR177, PR178, PR84, PR85, PR89, PR90, PR94, PR95, PR101, PR103, PR166, PR601, PR604	0ohm change to short pad	2018/7/12
124		0201 R4917, R4916, RC6, R961, R962, R56, R4928, R929, R934, R4910, R105, R950, RC228, RC229, RC21, RC22, RC30, RC28, RC27, RC24, RC234, RC56, RC46, R5105, R136, R137, R138, R124, R125, R835, R834, R213, R214, R160, R190, R196, R176, R182, R188, R180, R202, R177, R196, R197, R194, R195, R171, R206, R837, R840, R966, R904, R968, R301, R5113, R5114, R965, R5006, R32, R5026, R5035, RC222, R4924, R332, R5143, R5117, R5118, R5119, R5120, R5121, R5122, R5123, R5124, R5129, R5130, R5131, R5132, R5140, R4926, R5042, R5141, R345, R4948, R970, R4919, R5126, R5042, R936, R953, R854, R855, R849, R848, R860, R853, R856, R862, R866, R47, R48, R46, R4989, R139, R5037 0402 RC110, RC25, RC33, RC51, R271, R5004, R5008, R5009, R5067, RC57,	0ohm change to short pad	2018/7/12
125	7	PCB Compal PN	PCB Compal part number change to K3 part number (DAA000HP010)	2018/7/13
126	7	U14	EMMC Compal part number change to K3 part number SA0000C9810 (Sandisk 32G), SA0000B4R10 (Sandisk 64G), SA0000BPX10 (Hynix 128G), SA0000BPN10 (Sandisk 128)	2018/7/13
127	7	UD1-UD8	DDR Compal part number change to K3 part number SA0000B6F10 (Samsung 8G), SA0000BMN10 (Hynix 8G), SA0000ARD30 Micorn 8G)	2018/7/13
128	31, 33	D59, D60	Reserved D59,D60 (SMF4L20A) TVS by Nami team request.	2018/7/17
129	21, 22, 30	D2, D4, D8, D9, D24	Change 2nd source RB520S30 (SC2S0000A200) to main source RB520SM (SC300006C00)by sourcer request	2018/7/18